



@server

iSeries

Install, upgrade, or delete
OS/400 and related software

Version 5 Release 3

SC41-5120-07





@server

iSeries

Install, upgrade, or delete
OS/400 and related software

Version 5 Release 3

SC41-5120-07

Note

Before using this information and the product it supports, be sure to read the information in "Notices," on page 213.

Eighth Edition (May 2004)

This edition applies to version 5, release 3, modification 0 of IBM Operating System/400 (product number 5722-SS1) and to all subsequent releases and modifications until otherwise indicated in new editions. This version does not run on all reduced instruction set computer (RISC) models nor does it run on CISC models.

This edition replaces SC41-5120-06.

This document may contain references to Licensed Internal Code. Licensed Internal Code is Machine Code and is licensed to you under the terms of the IBM License Agreement for Machine Code.

© **Copyright International Business Machines Corporation 1997, 2004. All rights reserved.**

US Government Users Restricted Rights – Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp.

Contents

Chapter 1. Install, upgrade, or delete OS/400 and related software 1

Chapter 2. What's new for V5R3 3

Chapter 3. Print this topic 5

Chapter 4. Fastpath for software installation, upgrade, and deletion tasks. 7

Chapter 5. Concepts for software installation 9

Software installation process	9
Types of software installation devices.	12
Contents of a software order.	13
Software licensing documents	14
Media distribution set	15
Individual product documentation.	16
Skipping a release	16
Mixed-release environment	17
Software upgrade or replacement	17
Supported releases for OS/400 upgrades	18
Installation and IBM-supplied objects.	19
Compressed objects and storage space	20
Globalization and software installation	20
Considerations for changing a primary language	21
Considerations for installing additional	
secondary languages	21
Object conversions	22

Chapter 6. Upgrading or replacing OS/400 and related software 25

Preparing to upgrade or replace software	25
Checklist: Software upgrade or replacement	
readiness	26
Verifying the contents of your software order	28
Identifying and reviewing information	
resources	28
Verifying the correct optical distribution media	29
Verifying license keys for keyed products	30
Preparing the server for software upgrade or	
replacement	30
Ensuring you have required software PTFs	
(fixes)	31
Required: Installing software agreement	
PTFs.	32
Installing optional PTF to choose disk	
configuration	33
Permanently applying program temporary	
fixes (PTFs)	33
Working with critical system values before	
you install software.	33

Recording and printing all system values	
before you install software	34
Changing certain system values	
(QSYSLIBL, QUSRLIBL, QALWOBJRST, or	
QVfyOJBjRST)	34
Creating a data area to specify the system	
time zone	36
Verifying the integrity of user-modified	
system objects	36
Verifying user profiles and checking	
cross-reference files	36
Checking the QSECOFR user profile	36
Ensuring that the IBM-supplied product	
libraries are in the system ASP	37
Removing any iSeries Access user-created	
subdirectories.	37
Ensuring two-phase commit integrity.	37
Minimizing software installation time	38
Gathering performance data for benchmark	38
Performing initial upgrade or replacement tasks	41
Choosing a software installation method and	
device	42
Preparing for globalization	42
Required: Creating a custom list of software to	
install	42
Preselecting the licensed programs to	
install	42
Adding additional licensed programs to the	
installation list	45
Required: Accepting software agreements	46
Ensuring the server meets disk storage	
requirements for upgrades	46
Determining storage space required	47
Cleaning up disk storage space.	49
Required: Allocating additional space for	
Licensed Internal Code	50
Choosing disk configuration.	51
Estimating upgrade or replacement time.	51
Preparing your console for software	
installation	51
Preparing the upgrade device and media	53
Scenario: Preparing to upgrade or replace	
software using an image catalog	53
Preparing to upgrade IBM Cryptographic	
Access Provider	55
Stopping the Integrated xSeries Server for	
iSeries and other application servers	55
Saving the server	55
Upgrading or replacing software using automatic	
installation	56
Before you begin automatic installation	56
Replacing software using the automatic	
installation method.	57
Verifying completion of automatic installation.	62
Upgrading or replacing software using manual	
installation	64

Before you begin manual installation	64
Replacing the Licensed Internal Code.	65
Replacing the operating system.	72
Replacing the licensed programs	77
Verifying completion of manual installation	80
Checklist: Completing the upgrade or replacement	81

Chapter 7. Installing OS/400 and related software on a new server or logical partition 87

Preparing to install the OS/400 release	87
Checklist: Software installation readiness	88
Verifying the contents of your software order	89
Identifying and reviewing information resources	89
Verifying the correct optical distribution media	90
Verifying license keys for keyed products	90
Performing initial installation tasks	90
Ensuring you have the latest information	91
Determining disk storage space required	91
Estimating installation time	91
Preparing your console for software installation	91
Preparing the installation device and media	93
Installing the OS/400 release	93
Installing Licensed Internal Code on a new logical partition	93
Before you begin to install Licensed Internal Code on a partition.	93
Installing Licensed Internal Code on the new logical partition	94
Installing software on a new server or logical partition (without OS/400 installed).	100
Before you begin to install software on a new server or logical partition	101
Installing OS/400 on a new server or logical partition	101
Installing software on a new server (with OS/400 installed)	109
Before you begin to install software on a new server	110
Performing the initial program load (IPL)	110
Installing additional licensed programs	114
Before you begin to install additional licensed programs	114
Using the Work with Licensed Programs menu to install IBM licensed programs	115
Using the Restore Licensed Programs command to install IBM or non-IBM licensed programs	120
Installing a secondary language	121
Before you begin to install a secondary language	121
Installing secondary languages for IBM licensed programs	121
Installing secondary languages for non-IBM licensed programs	124
Checklist: Completing the installation	125

Chapter 8. Changing the primary language of your server or logical partition. 131

Before you begin to change the primary language	131
Changing the primary language	132
Installing the licensed programs after changing the primary language	135

Chapter 9. Deleting software related to OS/400 139

Determining what unused parts of products to delete	139
Considerations for deleting licensed programs	141
Deleting licensed programs.	141

Chapter 10. Troubleshooting software installation problems 143

Where to begin recovery	144
Image catalog recovery	146
Starting point for automatic installation recovery	146
Licensed Internal Code recovery	147
Operating system recovery	149
Licensed programs, PTFs, and secondary language recovery	151
Starting the automatic installation process again	155
Starting the manual installation process again	156
Initialize System (INZSYS) recovery	157
Disk configuration warning and error messages	158
Starting from a power-off condition	160
Reference codes for software installation	160
Common reference codes for software installation	160
Installation recovery after using reference codes	164

Chapter 11. Software reference. 165

Licensed program releases and sizes.	166
Estimates for software installation time.	171
Common methods of estimating installation time	171
Conditions that affect installation time	172
Installation processes	172
Checklist: Estimating installation time	173
Times for installing the operating system	174
Times for installing licensed programs	174
Times for upgrade conversions	179
IBM Backup Recovery and Media Services for iSeries conversions	179
Data protection mechanisms	180
Installation devices and media.	180
Optical media	180
Image catalog for a virtual optical device	181
Tape or tape libraries.	181
Non-IBM tape device.	182
Alternate installation device	182
Overview: Alternate installation device.	182
Setting up an alternate installation device	183
Disabling an alternate installation device	186
Verifying and selecting an alternate installation device during a manual installation	187
OS/400 release interoperability	188
Installation notes about the OS/400 release	189
Media labels and their contents	189

Standard set products	191
Keyed set products	193
Feature codes for national language version	195
Blank displays	197
System password	197
Installed status values	197
Options on Prepare for Install menu.	199
Options on Work with Licensed Programs menu	201
Manual installation Option 1. Install all.	201
Automatic installation options.	202
Options for displaying, installing, deleting, and saving from a list	202
Option 10. Display installed licensed programs.	203
Option 11. Install licensed programs.	203
Option 12. Delete licensed programs	205
Option 13. Save licensed programs	205
Options for secondary languages	207

Option 20. Display secondary languages	207
Option 21. Install secondary languages	207
Option 22. Delete secondary languages	208
Completion status	208
Commands related to the Work with Licensed Programs menu	209

Chapter 12. Related information for software installation 211

Appendix. Notices 213

Trademarks	215
Terms and conditions for downloading and printing publications	216
Code disclaimer information	216

Index 217

Chapter 1. Install, upgrade, or delete OS/400 and related software

Use this information to install the OS/400® release, part of the OS/400 release, or licensed programs related to OS/400. If you are installing software as part of a hardware upgrade, first go to the topic Upgrades in the iSeries Information Center (**Migration > Upgrades**). If you are viewing this in printed copy, references to other topics such as this one in the information center are shown with a navigation path.

The following topics pertain to OS/400 software installation and upgrades:

Chapter 2, “What’s new for V5R3,” on page 3

Use this information to review changes in the upgrade, installation, and deletion information for OS/400 and related software. For example, several preparation steps are required before you upgrade to the new release. You must use the Prepare for install menu to accept software agreements and allocate additional space for Licensed Internal Code. An upgrade using automatic installation will stop if you do not do the required steps.

Chapter 3, “Print this topic,” on page 5

Print a PDF of all the information included in the Install, upgrade, or delete OS/400 and related software topic. Also view or download PDFs of related software topics.

Chapter 4, “Fastpath for software installation, upgrade, and deletion tasks,” on page 7

Use this information as a shortcut to help you determine the group of tasks you need to perform for your particular installation or upgrade.

Chapter 5, “Concepts for software installation,” on page 9

Find out the basics of installing OS/400 software: your software order, what to do when you skip a release, software installation scenarios, the types of devices used to install, globalization considerations, and how some conversions could affect your installation time.

Chapter 6, “Upgrading or replacing OS/400 and related software,” on page 25

Follow these procedures to upgrade or replace software, which include preparing for the upgrade or replacement, installing software using either automatic or manual installation, and completing the final checklist.

Chapter 7, “Installing OS/400 and related software on a new server or logical partition,” on page 87

Follow these procedures to plan and prepare to install the release, install software on a new server or logical partition, install additional licensed programs, or install a secondary language. The final checklist is also included.

Chapter 8, “Changing the primary language of your server or logical partition,” on page 131

Use this procedure to change the primary language of your server.

Chapter 9, “Deleting software related to OS/400,” on page 139

Use this information to help you determine if you need to delete an unwanted part of a licensed program and to delete a part of a (or an entire) licensed program.

Chapter 10, “Troubleshooting software installation problems,” on page 143

This information describes common problem scenarios, recovery methods, and ways to get help if you encounter a problem during software installation.

Chapter 11, “Software reference,” on page 165

This reference information contains a collection of supporting information about the concepts and tasks described in the category. Topics include licensed programs releases and sizes, OS/400 interoperability, and other licensed program reference information.

Chapter 12, “Related information for software installation,” on page 211

Related sources of information for software installation or upgrades are listed here.

Note: Read “Code disclaimer information” on page 216 for important legal information.

Chapter 2. What's new for V5R3

This topic highlights changes in the upgrade, installation, and deletion information for OS/400 and related software.

Licensed programs require the acceptance of their software agreements before you install

For IBM® licensed programs that have an online software agreement for V5R3, you will need to accept the agreement through the Prepare for Install menu before you can upgrade the programs. You must install a PTF (steps to do this are included in the topic “Required: Installing software agreement PTFs” on page 32) to be able to accept the software agreements for Licensed Internal Code and the OS/400 operating system. You will not be allowed to continue the OS/400 upgrade if you do not accept these software agreements.

If you do not accept the agreements for any other licensed program, these licensed programs will not be installed automatically during the upgrade. You can also accept new licensed programs before an upgrade. “Required: Accepting software agreements” on page 46 describes how to accept the agreements for an upgrade.

The topic Maintain and manage OS/400 and related software in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software**) describes how to use, manage, and generate software agreements.

Additional requirements before you install Licensed Internal Code

To be able to install the Licensed Internal Code for V5R3, your server or logical partition requires an additional .42 GB of storage on the load source than in previous releases. This means that the load-source disk unit will take approximately 1.42 GB for V5R3 Licensed Internal Code installation. Your upgrade will stop during the installation of Licensed Internal Code if you do not use the Prepare for Install option to allocate the additional space. This step is included in “Required: Allocating additional space for Licensed Internal Code” on page 50.

Cumulative PTF package is not included in software orders

The cumulative PTF package does not come with your software order. About a week or two before you upgrade, order the most recent cumulative PTF package and also order PTF groups that pertain to your environment. These tasks are discussed in “Ensuring you have required software PTFs (fixes)” on page 31.

Console mode value

Because the console mode value is honored for V5R3 installations, you need to check that it is set correctly before you upgrade. A value of zero means that the console mode has not been set and might interfere with the automatic installation process. Steps for verifying the console mode value are included in the upgrade and installation tasks.

Server firmware

On IBM @server^(R) 5xx models, the level of the server firmware needs to be managed. *Server firmware* is the code that resides in system flash memory, and includes a number of subcomponents, including power control code and the logical partition firmware that is loaded into AIX or Linux logical partitions. The server firmware is installed on your system as part of the Licensed Internal Code. If your system is defined as the service partition and your server is not managed by a Hardware Management Console for eServer^(TM), the level of the server firmware that is on the service partition is used. A *service partition* is one partition on a server that must be set up to report hardware status and software errors to IBM. Installing a new level of the Licensed Internal Code might change the level of the server firmware and require a server IPL to be performed. A *server IPL* is an initial program load where all logical partitions on a server are shut down and restarted at the same time.

If your system is managed by a Hardware Management Console (HMC), the level of the server firmware that is part of the Licensed Internal Code on the service partition is not used. The level of the server firmware is managed by the HMC. For more information about using the HMC, see the Hardware Management Console topic in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).

Software keys available online

You can view, print, or download the software license keys. For instructions on how to access your online software license keys, refer to the Customer Notice that is included with your software order.

Multiple primary languages can be ordered

For V5R3, you can order multiple primary languages (feature code 80xx) and receive the standard set and keyed set for each of those languages. Secondary languages, if ordered, come on separate optical media.

Printed version of this PDF

This online PDF is available online through the Chapter 3, "Print this topic," on page 5 information. For V5R3, the printed version of this PDF, *Install, upgrade, or delete OS/400 and related software*, SC41-5120-07, is available through feature code 8004. When you order OS/400, the default is to receive this feature code with your order.

To find other information about what's new or changed this release, see the Memo

to Users  in the information center.

Chapter 3. Print this topic


To view or download the PDF version of this topic, select Install, upgrade, or delete OS/400 and related software (about 2497 KB). A printed version of this PDF (SC41-5120; feature code 8004) can be ordered with OS/400 software upgrade orders or new hardware orders.

The “Checklist: Software upgrade or replacement readiness” on page 26 or the “Checklist: Software installation readiness” on page 88 within this topic contain summaries of the major task categories that you need to do before you begin to upgrade or install your software. You can print these checklists by using the print function of your browser.

You can view or download these related topics in the information center:

- Basic system operations (about 230 KB) contains information on iSeries™ basic operations and OS/400 concepts.
- The Maintain and manage OS/400 software (about 224 KB) topic in the information center indicates how you can manage and maintain fixes and licensed programs in your network.
- The Distribute software topic (about 334 KB) in the information center includes tasks on how to distribute software to other systems or logical partitions.
- The print these topics for Backup and recovery contains several PDFs on how to plan a backup and recovery strategy, how to set up disk protection for your data, how to back up your system, and how to control your system shutdown in the event of a failure. It also includes information about the Backup, Recovery, and Media Services plug-in to iSeries Navigator.

The related manual to the Backup and recovery topic, Backup and Recovery

Guide , provides general information about recovery and availability options for the iSeries server. It describes the options available on the system, compares and contrasts them, and tells where to find more information about them.

Saving PDF files

To save a PDF on your workstation for viewing or printing:

1. Right-click the PDF in your browser (right-click the link above).
2. Click **Save Target As...** if you are using Internet Explorer. Click **Save Link As...** if you are using Netscape Communicator.
3. Navigate to the directory in which you would like to save the PDF.
4. Click **Save**.

Downloading Adobe Acrobat Reader


You need Adobe Acrobat Reader to view or print these PDFs. You can download a copy from the Adobe Web site (www.adobe.com/products/acrobat/readstep.html)



Chapter 4. Fastpath for software installation, upgrade, and deletion tasks

Use the following information to determine which set of subtasks you need from the Install, upgrade, or delete OS/400 and related software topic.

Task	Steps
Upgrading or replacing a release on a server or logical partition	<ol style="list-style-type: none"> 1. "Preparing to upgrade or replace software" on page 25 2. Use one of the following methods to upgrade or replace an OS/400 release: <ul style="list-style-type: none"> • "Upgrading or replacing software using automatic installation" on page 56 • "Upgrading or replacing software using manual installation" on page 64 3. "Installing additional licensed programs" on page 114 4. "Installing a secondary language" on page 121 5. Review "Checklist: Completing the upgrade or replacement" on page 81
Installing the OS/400 release on a new server or logical partition	<ol style="list-style-type: none"> 1. "Preparing to install the OS/400 release" on page 87 2. Perform the following based on your situation: <ul style="list-style-type: none"> • "Installing Licensed Internal Code on a new logical partition" on page 93 • "Installing software on a new server or logical partition (without OS/400 installed)" on page 100 • "Installing software on a new server (with OS/400 installed)" on page 109 3. "Using the Work with Licensed Programs menu to install IBM licensed programs" on page 115 4. "Installing a secondary language" on page 121 5. Review "Checklist: Completing the installation" on page 125
Installing licensed programs	<ol style="list-style-type: none"> 1. "Installing additional licensed programs" on page 114 2. Review "Checklist: Completing the installation" on page 125 (certain steps apply)
Installing a secondary language	<ol style="list-style-type: none"> 1. Review "Globalization and software installation" on page 20 2. "Installing a secondary language" on page 121 3. Review "Checklist: Completing the installation" on page 125 (certain steps apply)
Changing the primary language using either primary or secondary language media on the same release.	<ol style="list-style-type: none"> 1. Arrange your media in the order shown in "Media labels and their contents" on page 189 2. Chapter 8, "Changing the primary language of your server or logical partition," on page 131 3. Review "Checklist: Completing the installation" on page 125
Changing your primary language and upgrading a release using primary language media	<ol style="list-style-type: none"> 1. "Preparing to upgrade or replace software" on page 25 2. Use one of the following methods to upgrade or replace an OS/400 release: <ul style="list-style-type: none"> • "Upgrading or replacing software using automatic installation" on page 56 • "Upgrading or replacing software using manual installation" on page 64 3. "Installing additional licensed programs" on page 114 4. "Installing a secondary language" on page 121 5. Review "Checklist: Completing the upgrade or replacement" on page 81

Task	Steps
Selecting the primary language or changing your primary language and installing software on a new server.	<ol style="list-style-type: none"> 1. "Preparing to install the OS/400 release" on page 87 2. Perform the following based on your situation: <ul style="list-style-type: none"> • "Installing Licensed Internal Code on a new logical partition" on page 93 • "Installing software on a new server or logical partition (without OS/400 installed)" on page 100 • Chapter 8, "Changing the primary language of your server or logical partition," on page 131 3. "Using the Work with Licensed Programs menu to install IBM licensed programs" on page 115 4. "Installing a secondary language" on page 121 5. Review "Checklist: Completing the installation" on page 125
Adding a new disk unit to an existing server before upgrading or replacing a release	<p>If you are currently using mirrored protection, device parity protection, or auxiliary storage pools, refer to the information on working with auxiliary storage pools in the Backup and Recovery  manual before you begin these tasks.</p> <ol style="list-style-type: none"> 1. "Preparing to upgrade or replace software" on page 25 2. "Upgrading or replacing software using manual installation" on page 64 3. "Installing additional licensed programs" on page 114 4. "Installing a secondary language" on page 121 5. Review "Checklist: Completing the upgrade or replacement" on page 81
Installing a cumulative program temporary fix (PTF) package	<ol style="list-style-type: none"> 1. Go to the IBM eServer iSeries Support Web site (http://www.servers/eserver/series/support) for Internet downloads or PSP information. 2. Review the iSeries PTF Shipping Information Letter that you received for instructions on how to install a cumulative PTF package. 3. (Optional) Review concept information about how to use and install fixes (OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Fixes concepts and terms) in the iSeries Information Center.
Installing a hardware upgrade	<p>For IBM eServer 5xx models, perform the tasks in the Upgrades topic in the IBM eServer Hardware Information Center (Migrating or upgrading your server > iSeries systems > Upgrades). For iSeries 8xx and earlier models, see the Upgrades topic in the iSeries Information Center (Migration > Upgrades).</p>
Deleting software	<p>Use either of the following methods:</p> <ul style="list-style-type: none"> • "Preselecting the licensed programs to install" on page 42. If you have licensed programs that are no longer supported, these can be deleted when you perform other upgrade preparation tasks in this topic. • Chapter 9, "Deleting software related to OS/400," on page 139.

Chapter 5. Concepts for software installation

You and IBM together manage the use, documentation, and transfer of licensed programs. Following is a conceptual look at OS/400 software installation.

“Software installation process”

Use this information to understand the various processes that are included within software installation and upgrades.

“Types of software installation devices” on page 12

Understand the different devices used to upgrade or install the new release on the server.

“Contents of a software order” on page 13

When you order software from IBM, you receive the CD-ROM media distribution set. The software license keys and software entitlements created for your licensed programs are available online.

“Skipping a release” on page 16

If you plan to skip a release, such as performing an upgrade from V5R1 to V5R3 and skipping V5R2, you need to be aware of changes from the skipped release that could affect your programs and system operations.

“Mixed-release environment” on page 17

Licensed programs or their options do not always have the same release as the OS/400 operating system. Use this information to understand the various levels of products that work with OS/400.

“Software upgrade or replacement” on page 17

Use this information to understand basic considerations of the server during upgrade or replacement processes.

“Globalization and software installation” on page 20

Find out about the installation of national languages on your iSeries server.

“Object conversions” on page 22

When you install the operating system, you need to plan time for certain object conversions from previous releases. The amount of time that is required could be significant depending on the number and size of the object types that you have on your server.

Software installation process

The software installation process has three phases:

1. Preinstallation activities:

You can do these activities days or even a few weeks in advance. To plan and prepare your server before you install your software, use the planning and preparation topics “Preparing to upgrade or replace software” on page 25 or “Preparing to install the OS/400 release” on page 87 to guide you through the activities that you need to do. Some of these activities include verifying your order, checking the amount of available disk space, backing up your server, and cleaning your media device. Two of the tasks (accepting software agreements

and allocating additional space for Licensed Internal Code) are required. If you do not perform these tasks, you will be forced to restart the installation.

2. **The installation process:**

The installation process begins when you start performing the instructions in one of the procedural topics. For example, to upgrade to the new release, you might have chosen automatic installation. The automatic installation process installs the Licensed Internal Code, the operating system (OS/400), and licensed programs. You would have minimal interaction with the system, except to load the optical distribution media and to monitor the system.

Your only installation activity might be changing the primary language or installing additional licensed programs. Or, perhaps you want to perform these activities after an automatic or manual installation.

3. **Postinstallation activities:**

The last step of each procedure directs you to use a completion checklist. You might be directed to additional steps, such as saving your system and performing installation activities on workstations for IBM @server iSeries Access Family products. Other activities could include customizing your system, or setting usage limits for user-based priced products. Before you begin production work on your system, be sure to adequately protect your system from unauthorized use.

The following figure shows an example of one type of software installation. (Your particular installation might not include all of the topics that are shown in this figure.)




Figure 1. Overview of the installation process

The procedure that you use for software installation depends on what you plan to install.

Install software on a new server

If you just received a new server, the operating system and other licensed programs might or might not be installed already.

Upgrade or replace existing software

If you are upgrading or replacing your existing OS/400 software, use either the automatic installation method or the manual installation method.

Automatic installation replaces your existing release with minimal user interaction. The language feature code on the distribution media is installed as the primary language on the server. The automatic installation process keeps the current environment and system values. The process can add all nonconfigured disk units to the system auxiliary storage pool (ASP) and retain the ASP configuration of previously configured disk units. The automatic installation process is recommended for use with most servers.

Manual installation interactively replaces your existing release by using the Work with Licensed Programs menu. Displays that require responses appear on the console. During a manual installation, you can change installation options. Use the manual installation process if you are doing any of the following installation procedures:

- Adding a disk device using mirrored protection, device parity protection, or user auxiliary storage pools.
- Changing the environment (OS/400 or System/36™), system values, language feature code, or configuration values.
- Planning to use an alternate installation device when you upgrade.
- Creating logical partitions during the installation process.
- Using tapes created with the Save System (SAVSYS) command. (The SAVSYS command creates tapes that are meant for recovery.)

Add licensed programs

When you add additional licensed programs (in addition to those done already in the methods mentioned above) or optional parts of licensed programs, you use the method done through option 11 (Install licensed programs) of the Work with Licensed Programs (LICPGM) menu. Typically you use option 11 when you need to install a new licensed program or to replace a single licensed program.

Add or change globalization support

When you add a secondary language, you add additional language objects for the licensed programs that are installed on your system.

When you change the primary language, you replace the existing language objects. Depending on the procedure that you use, you can also replace program objects.

If a failure occurs during the installation process, Chapter 10, “Troubleshooting software installation problems,” on page 143 contains information that can help you determine the problem and the necessary recovery steps.

Types of software installation devices

Following are the different devices that you can use to install software:

- **Optical devices**

The software distribution media that is shipped to customers is optical media (CD-ROM). This CD-ROM media can be used in CD-ROM, DVD-ROM, or DVD-RAM devices.

- **Virtual optical devices**

You can use an image catalog to perform a software upgrade, to install PTFs (fixes), or to install single licensed programs that you receive on media. Installing with an image catalog has significant advantages when you want to do the following tasks:

- Validate your optical media before you install the release.
- Eliminate the handling of individual media during the installation (unattended installations).
- Upgrade software from an installation image delivered from a network or generated from IBM-supplied CD-ROM media.

- **Tape devices**

There could be times when tape media is used for installation. Examples include distribution media creation or certain backup and recovery scenarios.

- **Alternate installation devices**

You can perform installation and recovery procedures by using the primary installation device along with an alternate installation device that you define. The alternate installation device can be a tape device or an optical device. Some servers, typically with faster devices attached, might see a performance improvement when using an alternate installation device.

The following table shows the naming conventions for a device that can be used for the alternate IPL (a Type D IPL). The optical drive is the installation device for software distribution media. Examples here use OPT01 for the optical device (optical media class). This is the OS/400 normal naming convention. Your system could be set up to use the System/36 naming convention. Use the following table to select the correct device name for your server’s installation device or use the name that you have selected.

Table 1. Naming conventions for devices

Media type	System/36 names	OS/400 Normal names
Optical media (CD, DVD, or virtual images)	OPTxx	OPTxx
Cartridge	TC	TAPxx
Reel	T1	TAPxx
Media library device created through automatic configuration		TAPMLBxx

“Preparing the upgrade device and media” on page 53 contains further information on what you need to do with your media before you install a release.

Contents of a software order

This information describes what you can expect to receive with your software orders and how the materials are to be used.

“Software licensing documents” on page 14

This information describes the documents that you receive with your software release order. These can be either printed or online.

“Media distribution set” on page 15

This information describes the different media sets for the software products that you receive for the release.

“Individual product documentation” on page 16

You might have received material that contains information unique to the installation of a certain product on your server.

Software licensing documents

This information describes the documents that you receive with your software release order. These documents contain important information concerning the use, management, and transfer of licensed programs. The licensing documents for IBM licensed programs that you receive could be either printed or online on the server. The Customer Notice that is included in your software order describes how to access the online documents.

To automatically install IBM licensed programs that have the online International Program License Agreement (IPLA), you need to accept the agreement through the Prepare for Install menu before you can install the programs. An upgrade of the Licensed Internal Code and the OS/400 operating system will stop if the agreements have not been preaccepted. The topic “Required: Accepting software agreements” on page 46 describes how to accept the agreements.

Ensure that you read and understand all software license agreements and documents before you use the programs.

Store the printed agreements and documents in a secure location. Both printed and online agreements need to be passed to the new owner when you transfer a program.

Proof of Entitlement

The Proof of Entitlement (POE) serves as transferable evidence of product licensure with use restrictions noted either on the POE or on the original invoice (depending on the country or region). The POE is evidence of the owner’s authorization to use the program and is the official record on entitlement. It is evidence of eligibility for any version or release updates under software subscription, warranty services, future upgrade program prices (if announced), and potential special or promotional opportunities. A POE is created for new customer orders or when additional entitlement is purchased. A POE is not provided for a software release upgrade.

The International Program License Agreement

The International Program License Agreement (IPLA) provides a nonexclusive license to use a software product that has a warranty.

International License Agreement for Non-Warranted Programs

This agreement is similar to the IPLA but is used for IBM licensed programs that have no warranty.

Licensed Information Document

The Licensed Information Document (LID) contains specific license information and additional restrictions for a product.

International License Agreement for Evaluation of Programs

The Evaluation of Programs provides a nonexclusive, nontransferable license to use a program only for internal evaluation, testing, or demonstration purposes, on a trial or “try-and-buy” basis.

Software license keys

For each keyed IBM product or keyed IBM product option that you order, a software license key is created. This applies to both new and upgraded software. You can view, print, or download the software license keys. For instructions on how to access your online software license keys, refer to the Customer Notice that is included with your software order. In addition to the online license keys, your software order might also contain printed software license key sheets.

For a general description of how software license keys are used, see the topic [Work with software agreements and licenses in the iSeries Information Center \(OS/400 and related software > Maintain and manage OS/400 and related software > Work with software agreements and licenses\)](#). For unique licensing applications regarding logical partitions on iSeries 8xx or earlier models, see the topic [Software licensing and licensed programs for logical partitions in the iSeries Information Center \(Systems management > Logical partitions > Partitioning with iSeries Navigator > Concepts > Software and licensed programs for logical partitions\)](#). For IBM @server^(R) 5xx models, see [Considerations for license agreements in the IBM eServer^{\(TM\)} Hardware Information Center \(Partitioning the server > Partitioning for OS/400 > Concepts for OS/400 partitions > Considerations for OS/400 license agreements\)](#).

Media distribution set

Following is a description of the media distribution set that you receive with your OS/400 software order.

The licensed programs on the standard set and keyed set come in your primary language. If you order additional primary languages (feature code 80xx), you will receive the standard set and keyed set for those languages. Secondary languages, if ordered, come on separate optical media.

Other licensed programs, which are in addition to the standard set and keyed set, come on their own separate media when ordered. In this case, all supported languages, not just one secondary language, come on this same media.

Standard set

The standard set of products comes with every server software or upgrade order. It contains the hardware and software components to install on your server. This includes Licensed Internal Code, OS/400, its no-charge options, and no-charge licensed programs and options. The OS/400 operating system has all the applications necessary for the basic operations of your server. In addition, it could contain more programs than you want. You can choose not to install some of these programs.

Keyed set

The keyed set of products comes with the standard set. It contains keyed products and program options. You can evaluate these programs for a 70-day trial period. Within 70 days, you must apply license keys to keep the programs operational. Once you purchase the use of a licensed program and load the license key, the licensed program will remain in operation for continual use.

Single products (if ordered)

When specifically ordered, licensed programs that are not part of the standard set and keyed set arrive on separate media with your software

order. You might install these licensed programs using the automatic installation procedure. Some of these licensed programs might come with their own installation instructions, and some might have limited language support.

Secondary languages (if ordered)

You can order secondary languages separately from the primary language. Each language comes on separate optical media or as a set of optical media. You specify the secondary language during the installation procedure.

Informational set

IBM provides technical and setup information on optical media with your software order. This information includes the iSeries Information Center and the PDF versions of iSeries manuals.

Individual product documentation

You might have received additional letters to users for individual products. Such material could contain information unique for that product that could affect its installation. Be sure to check these additional sources. When you install a product for the first time, you might need to customize the product or complete additional actions before the product will work. Look for this type of information in your product order.

Skipping a release

If you are skipping a release level of OS/400, you should review the *Memo to Users* for the release that you are skipping. This will ensure that you are aware of software changes that occurred in the skipped release that could also affect your programs and system operations.

Object conversions

Conversions that occur when you install a new release provide improved performance, reliability, and support. The number and type of conversions that occur, however, can have a significant effect on your installation time and storage requirements.

More conversions occur if you are skipping a release. Consider both the conversions in the release that you are skipping and the new release. "Object conversions" on page 22 contains more information on the V5R3 impacts to your server.

Performance data collection

With any software release, the support for new functions can cause an incremental change (increase or decrease) in performance for some workloads. IBM makes a significant effort to minimize negative effects, and in most cases a change in performance is not observed. However, in a skip-release upgrade, there is a higher potential that the compound effect of incremental performance differences will be observed.

To understand the performance characteristics of an upgrade, collect performance data both before and after the upgrade is complete. Following are two recommended performance collections:

- Collect general performance data for one or more days by using Collection Services. “Gathering performance data for benchmark” on page 38 contains information on ways to start Collection Services.
- Collect specific profile data for approximately an hour by running the following program in a batch job during a period of high activity on the server. To call this program, enter the command CALL SYSPROF PARM(PEXDTAVxRy) where *x* and *y* indicate the OS/400 version and release numbers.

Note: You cannot store PEX data from two different releases into the same library.

```

SYSPROF: PGM PARM(&LIB)
DCL VAR(&LIB) TYPE(*CHAR) LEN(10) /* Library to store the data */

/* Create a PEX definition to collect profile data. */
ADDPDFN DFN(SYSPROF) TYPE(*TRACE) JOB((*ALL)) +
        TASK(*ALL) MAXSTG(1000000) INTERVAL(5) +
        TRCTYPE(*PRFDTA)

/* If the definition already exists, assume it is ok. */
MONMSG MSGID(CPFAF10)

STRPEX SSNID(SYSPROFILE) DFN(SYSPROF)
DLYJOB 3600
ENDPEX SSNID(SYSPROFILE) DTALIB(&LIB)
ENDPGM

```

Save this data from both collections for future reference.

Mixed-release environment

Licensed programs do not need to have the same release as the OS/400 operating system. Also, licensed programs can be packaged so that the product’s options are not at the same release as its base. This is referred to as a mixed-release environment. For these reasons, your V5R3 media might contain licensed programs and options that are at different releases than V5R3. Products that do not have any new function for this release are not repackaged, and therefore could have a release previous to V5R3. “Licensed program releases and sizes” on page 166 contains information on the version, release, and modification level of the standard and keyed set products. You can also look at the product information to determine OS/400 releases that are supported.

Software upgrade or replacement

This topic provides an overview of special considerations for software installation when you upgrade or replace a release.

“Supported releases for OS/400 upgrades” on page 18

Upgrades to current releases require that you be at a certain level of software. This information shows the supported combinations for source and current target releases.

“Installation and IBM-supplied objects” on page 19

When you replace your software with the new release, the server keeps changes that you made to some IBM-supplied objects.

“Compressed objects and storage space” on page 20

All of the licensed programs and some objects of the operating system ship in

a compressed form. This requires less storage space on your server. The server decompresses objects according to certain criteria, which could affect the performance of the server.

Files that the server deletes during installation

If you have created logical files over IBM-supplied physical files in QSYS, the logical files will be deleted during the installation process

Supported releases for OS/400 upgrades

To be able to upgrade to or replace the V5R3 OS/400 release, your current version of the operating system must be either at V5R1, V5R2, or V5R3. If your target release is V5R2 or V5R1, use the OS/400 software installation information for the the version of OS/400 that is your target release.

If you plan to use logical partitions and want to understand about supported releases on logical partitions, see Software and licensed programs for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Concepts > Software and licensed programs for logical partitions**) for iSeries 8xx and earlier models. For IBM eServer 5xx models, see Shared processor pool considerations for OS/400 licensed agreements in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Concepts for OS/400 logical partitions > Shared processor pool considerations for OS/400 licensed agreements**).

Table 2 shows the currently supported combinations for source and target releases. Some of the target releases shown in this table might not be available. If your currently installed release is earlier than those listed here, you must first upgrade your server to either V5R1 or V5R2 before you can upgrade to V5R3.


Table 2. Supported releases for OS/400 upgrades

Currently installed (source) release	Valid target releases
V5R3	V5R3
V5R2	V5R3 V5R2
V5R1	V5R3 V5R2 V5R1

You will not be able to install V5R3 on the following iSeries models:

Table 3. Nonsupported models for OS/400 upgrades

150	53S	50S	650	S40
400	500	600	S10	SB1
40S	510	620	S20	
436	530	640	S30	

For information on planning for system hardware upgrades, see **iSeries Upgrade Planning** 

(<http://www.ibm.com/servers/eserver/series/support/planning/nav.html>).

Installation and IBM-supplied objects

When you replace your software with the new release, by default the system keeps the changes that you made to some IBM-supplied objects. Certain job descriptions and subsystem descriptions are restored during the installation process. The installation process creates these libraries (if they do not already exist):

- QINSYS
- QINMEDIA
- QINPRIOR

The system copies your current customized descriptions from library QSYS to library QINSYS. The descriptions are installed from the installation media into library QSYS. The system compares those values with the descriptions in QINSYS. If there are any differences, the system uses your customized value from QINSYS to update the QSYS version. If there are conflicts in certain values, the system uses the value from the installation media, and the conflicting value remains in QINSYS. QINMEDIA holds the description from the installation media. QINPRIOR holds the descriptions from the prior release level so that you can compare the current and previous release descriptions.

Use the PRTSYSINF command before you upgrade to have a copy of the IBM-supplied objects. After the upgrade you can change these objects back to the previous customization.

IBM-supplied objects that retain customized information

If you have made changes to any of the IBM-supplied descriptions shown in the following table, the system optionally keeps your changes.

Job descriptions	Subsystem descriptions
QCTL (Controlling subsystem job description)	QBASE (Basic controlling)
QCTLIJBD (Controlling subsystem ICG job description)	QBATCH (Batch)
QESAUTON (Automatic problem notification)	QCMN (Communications)
QFSIOPWK (File server I/O processor)	QCTL (Controlling subsystem)
QMSF (Used by QPGMF job)	QINTER (Interactive)
QPDAUTOPAR (Used for automatic problem analysis)	QPGMR (Programmer)
QQQTEMPS (DB2 [®] UDB for iSeries job description used by QSYSWRK)	QSNADS (Systems Network Architecture (SNA) Distribution)
QSPLERROR (Spooling error)	QSPL (Spooling subsystem)
QSTRUPJD (Auto start)	QSYSWRK (System subsystem)
QSYSWRK (System subsystem job description)	QUSRWRK (User subsystem)
QTMSNMP (Simple Network Management Protocol (SNMP) job description)	
QZMFEJBD (QSYSWRK autostart job entry)	

Compressed objects and storage space

All of the licensed programs and some objects of the operating system ship in a compressed form, which requires less storage space on your system. System jobs (QDCPOBJ x , where x is a number) automatically decompress these objects during the installation process if your system has sufficient unused disk storage. If enough storage space is not available, the system decompresses the objects when you use them, which could affect the performance of the system.

The server decompresses objects according to the following criteria:

- Greater than 750 MB available storage
The system submits jobs to decompress all system objects just installed.
- 250-750 MB available storage
The server decompresses only frequently used objects automatically. Object-usage information (the number of days an object has been used and the last-used date) is used to identify frequently used objects. The server decompresses any object that was used at least five times when the last use was within the last 14 days. The server leaves the remaining low-use objects in compressed form.
 - This does not include decompression of objects that are shipped in the operating system and in library QSYS. The system resets usage information for those objects during the installation process. For all other licensed programs, the object usage information is kept during the installation process.
 - A call to a system program does not update its usage information; the system does not automatically decompress programs in constrained storage mode. However, high-use programs ship in decompressed form and are not considered able to be compressed.
- Less than 250 MB available storage
The system does not submit the decompression jobs and instead decompresses the objects as they are used.

Note: The QDCPOBJ x system jobs might run for some time after the installation process completes. More information about compressing and decompressing

objects is available in CL Programming .

Globalization and software installation

The **primary language** is the national language that is installed on the system as the default language used to display and print information. The primary language is also used to service the system.

If you are planning to change your primary language only and not upgrade at the same time, use the manual installation process. To determine which installation process will work best for your situation, compare reasons in “Software installation process” on page 9.

If the primary language is uppercase English (2938 or 2950), you need to type uppercase characters when you respond to system messages.

Secondary languages are one or more additional national languages that can be installed on the system to display and print information.

The iSeries Information Center topic OS/400 Globalization (**Programming > Globalization**) contains more information about planning for and using national languages on your iSeries server.

Feature codes for your primary or secondary languages are listed in the topic, “Feature codes for national language version” on page 195.

The following topics pertain to primary languages and secondary languages:

- “Considerations for changing a primary language”
- “Considerations for installing additional secondary languages”

Considerations for changing a primary language

You can change the primary language of your system in these two ways:

- By using secondary language media to replace the language objects.
- While replacing a release using the manual installation process.

You cannot change your primary language to a language you currently have installed as a secondary language on your system. You must delete the secondary language before you can change it to your primary language. Use Option 22 from the Work with Licensed Programs menu to delete a secondary language.

If you perform the tasks in Chapter 8, “Changing the primary language of your server or logical partition,” on page 131, the release and modification of your system must be the same as the release and modification of your secondary language media. You need both the media that contains OS/400 (B29xx_01) and the media that contains the secondary language (N29xx).

When changing your primary language from a single-byte character set (SBCS) to a double-byte character set (DBCS) or from a DBCS to SBCS, refer to the topic OS/400 globalization in the iSeries Information Center. If you change the character set of your primary language as part of a release upgrade, your installation time could be longer.

Make sure that you configure your console device to support the default code page of the primary language you are going to install. If you plan on using 5250 emulation on the Hardware Management Console for eServer, not all languages are supported. Change the console device to one that supports the code page of the new primary language before you install a new release.

Considerations for installing additional secondary languages

The process to add a secondary language installs only one secondary language at a time. If you need to add more than one secondary language, you need to perform the procedure to install a secondary language multiple times. “Installing a secondary language” on page 121 contains the following two procedures to install secondary languages:

- “Installing secondary languages for IBM licensed programs” on page 121 shows how to install secondary language objects for OS/400 and installed licensed programs. Use this procedure when you are installing a secondary language after installing the new release or when you are adding additional secondary languages to the system.
- “Installing secondary languages for non-IBM licensed programs” on page 124 shows how to restore a secondary language for only one licensed program or optional part. Use this procedure when you want to restore a secondary

Concepts

language for only one licensed program and when you are installing secondary language objects for licensed programs that you installed using the RSTLICPGM command.

Only the secondary language objects for the installed licensed programs are installed. If you add a licensed program or an optional part after the secondary language is installed, you will not have the secondary language objects for licensed programs you add later. To get the new language objects, install the secondary language for the added licensed program.

When you plan to install a secondary language, consider the following:

- To save storage space, delete secondary languages you no longer need. If you want to delete a secondary language for all of the licensed programs installed on your system, use option 22 on the Work with Licensed Program menu. If you want to delete a secondary language for only one licensed program, use the Delete Licensed Program (DLTLICPGM) command.
- The QSECOFR user profile cannot have a secondary language library at a previous release in its library list when you install a new release. If you have an initial program for the QSECOFR user profile, be sure it does not add a secondary language library to the system library list. (the task, Checking the QSECOFR user profile, ensures that you do this.)
- If you added a secondary language library (QSYS29xx) to the system values QSYSLIBL or QUSRLIBL, use the WRKSYSVAL command to remove the library from the library list before you install a new release. (Performing the steps in the topic, “Changing certain system values (QSYSLIBL, QUSRLIBL, QALWOBJRST, or QVFOBJRST)” on page 34, ensures that you do this.) OS/400 globalization also contains more information about secondary language libraries in user profiles.

Object conversions

Object conversions that occur when you install a new release provide improved performance, reliability, and support. The number and type of conversions that occur can have a significant effect on your installation time and storage requirements. Before you install a new release, you might need to gather information about specific object types on your server.

More conversions occur if you are skipping a release. Consider both the conversions in the release that you are skipping and the new release.

More information on how conversions can affect your installation time is in “Times for upgrade conversions” on page 179.

Integrated file system conversions

As of V5R1, the “root” (/), QOpenSys, and user-defined file systems (UDFS) in the integrated file system support the *TYPE2 directory format. The *TYPE2 directory format is an enhancement of the original *TYPE1 directory format. *TYPE2 directories have a different internal structure than *TYPE1 directories and provide improved performance and reliability. In releases V5R1 and V5R2, you could optionally convert to the *TYPE2 directory format using the appropriate conversion utility. Additionally, if the server was preloaded with V5R2, the directory format was *TYPE2.

Shortly after V5R3 is installed, the conversion to *TYPE2 directories automatically begins for any of the file systems that have not yet been converted to support *TYPE2 directories. This conversion runs in the background during normal operations and should not significantly impact your system activity. For more information on integrated file system directory conversions, see [Convert directories from *TYPE1 to *TYPE2](#) in the iSeries Information Center (**Files and file systems > Integrated file system > Convert directories from *TYPE1 to *TYPE2**).

Chapter 6. Upgrading or replacing OS/400 and related software

This information contains task-oriented instructions to upgrade or replace OS/400 and its related software on a system that uses optical or tape distribution media. You must have either V5R1 or V5R2 currently installed on your server to be able to upgrade to V5R3.

The following tasks pertain to software upgrades or replacement:

“Preparing to upgrade or replace software”

Here are the critical preparation tasks. Included are the required tasks, accepting software agreements and allocating additional space for Licensed Internal Code, that you need to perform before you upgrade or replace your software.

“Upgrading or replacing software using automatic installation” on page 56

An automatic installation replaces your existing release with minimal user interaction. These instructions replace the Licensed Internal Code, Operating System/400®, and licensed programs currently installed on your server with the V5R3 release.

“Upgrading or replacing software using manual installation” on page 64

A manual installation interactively replaces your existing release by using the Work with Licensed Programs menu. Displays that require responses appear on the console and you can change installation options. These instructions, like the automatic installation method, replace the Licensed Internal Code, Operating System/400, and licensed programs currently installed on your server with the V5R3 release.

“Checklist: Completing the upgrade or replacement” on page 81

Use these instructions to complete the upgrade or replacement process.

Preparing to upgrade or replace software

Careful, complete, and early preparation saves a considerable amount of time and can help make your software release upgrade on your system run smoothly.

Perform these preparatory tasks, some of which are mandatory, before you schedule your installation. To do the tasks in this topic, you will need to sign on as security officer (QSECOFR user profile). Allow ample time (a few weeks or days before the installation) to complete these tasks before you perform the actual installation tasks.

If you are setting up logical partitions, you need to plan in advance of your installation and have a basic understanding of logical partitions plus your software and hardware requirements. For iSeries 8xx or earlier models, refer to Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, refer to Plan for OS/400 logical partitions in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 logical partitions**). You can

Preparing to upgrade or replace software

also have different release levels on different partitions. For directions on how to do these correctly, see Manage logical partitions in the iSeries Information Center (**Systems management > Partitioning with iSeries Navigator > Manage logical partitions**) for iSeries 8xx or earlier models. For IBM eServer 5xx models, see Managing OS/400 partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Managing OS/400 partitions**).

The following topics pertain to the preparation tasks for software upgrades or replacement:

“Checklist: Software upgrade or replacement readiness”

Use this checklist to help consolidate and verify that you have completed all the preparation tasks for a software upgrade.

“Verifying the contents of your software order” on page 28

Verify that the contents of your order is correct before you begin your upgrade or replacement.

“Preparing the server for software upgrade or replacement” on page 30

Review and perform the tasks that pertain to your server.

“Performing initial upgrade or replacement tasks” on page 41

Before you save the server, complete these initial installation tasks.


“Saving the server” on page 55

Ensure that you have a current backup of your server.

Checklist: Software upgrade or replacement readiness

Following is a summary of the major task categories that you need to do before you begin to upgrade or replace your software.

Before you begin

- Verify that your server model meets the requirements to support the new release. This information is found in the IBM @server iSeries System Handbook  at the following Web site: <http://publib-b.boulder.ibm.com/cgi-bin/searchsite.cgi?query=iSeries+AND+handbook>. Use this Web page to search for the correct version.
- Know your current strategy for connecting a console to your server or logical partition. Your current connection strategy influences your planning activities. For information about twinaxial consoles and Operations Console, refer to the Connecting to iSeries topic in the iSeries Information Center. For information about managing your systems with Hardware Management Console for eServer, refer to the topic Hardware Management Console in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).
- If you are using an IBM eServer 5xx model, plan for extra time after the upgrade to perform a server IPL. This is one of the tasks described in the “Checklist: Completing the upgrade or replacement” on page 81.
- Understand server administration tasks (basic system operations). To perform software installation tasks, you need to be able to restart your server, sign on and off, use the command interface, install fixes, change the system operation mode and initial program load (IPL) source on the system unit control panel, and analyze server problems.
- Understand the different “Types of software installation devices” on page 12. The installation tasks are different based on the device type and media type that you use.

From the following checklist, perform the tasks that are appropriate for your server. Required steps are noted. If you are viewing this in printed copy, use this checklist as a guide for the steps on the pages that follow.

Software preupgrade or replacement tasks

- “Verifying the contents of your software order” on page 28
 - “Identifying and reviewing information resources” on page 28
 - “Verifying the correct optical distribution media” on page 29
 - “Verifying license keys for keyed products” on page 30

- “Preparing the server for software upgrade or replacement” on page 30
 - “Ensuring you have required software PTFs (fixes)” on page 31
 - **“Required: Installing software agreement PTFs” on page 32**
 - “Installing optional PTF to choose disk configuration” on page 33
 - “Permanently applying program temporary fixes (PTFs)” on page 33

 - “Working with critical system values before you install software” on page 33
 - “Recording and printing all system values before you install software” on page 34
 - “Changing certain system values (QSYSLIBL, QUSRLIBL, QALWOBJRST, or QVIFYOBJRST)” on page 34
 - “Creating a data area to specify the system time zone” on page 36

 - “Verifying the integrity of user-modified system objects” on page 36
 - “Verifying user profiles and checking cross-reference files” on page 36
 - “Checking the QSECOFR user profile” on page 36
 - “Ensuring that the IBM-supplied product libraries are in the system ASP” on page 37

 - “Removing any iSeries Access user-created subdirectories” on page 37
 - “Ensuring two-phase commit integrity” on page 37
 - “Minimizing software installation time” on page 38
 - “Gathering performance data for benchmark” on page 38

- “Performing initial upgrade or replacement tasks” on page 41
 - “Choosing a software installation method and device” on page 42
 - “Preparing for globalization” on page 42
 - **“Required: Creating a custom list of software to install” on page 42**
 - “Preselecting the licensed programs to install” on page 42
 - “Adding additional licensed programs to the installation list” on page 45

 - **“Required: Accepting software agreements” on page 46**
 - “Ensuring the server meets disk storage requirements for upgrades” on page 46
 - “Determining storage space required” on page 47
 - “Cleaning up disk storage space” on page 49
 - **“Required: Allocating additional space for Licensed Internal Code” on page 50**

 - “Choosing disk configuration” on page 51
 - “Estimating upgrade or replacement time” on page 51
 - “Preparing your console for software installation” on page 51
 - “Preparing the upgrade device and media” on page 53
 - “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53

 - “Preparing to upgrade IBM Cryptographic Access Provider” on page 55
 - “Stopping the Integrated xSeries Server for iSeries and other application servers” on page 55

- “Saving the server” on page 55

Preparing to upgrade or replace software

After the tasks in the preceding checklist and your upgrade have been completed, consider the following tasks.

After you finish

- Develop a strategy for managing and maintaining your software. For information about software fixes (or program temporary fixes, PTFs), and software licenses and license keys, go to the Maintain and manage OS/400 and related software (**OS/400 and related software > Maintain and manage OS/400 and related software**) topic in the iSeries Information Center.
- For information about software distribution of supported products, go to the Distribute software (**OS/400 and related software > Distribute software**) topic.

Verifying the contents of your software order

To save you time and avoid frustration, verify that the contents of your software order are correct before you start installation.

“Identifying and reviewing information resources”

Become familiar with the important resources pertaining to the installation of your new software. Use these documents to plan your installation process.

“Verifying the correct optical distribution media” on page 29

If you are planning for a complete software release upgrade, ensure you have the correct media for your upcoming tasks.

“Verifying license keys for keyed products” on page 30


Review the software license keys for keyed IBM products or keyed IBM product options that you have ordered.

Identifying and reviewing information resources

The following resources pertain to the installation of your new software. Many of these resources are shipped with the distribution media in your software order. You need to use these documents to plan parts of your installation process. Read the material that applies to your server.

- **Memo to Users**  (in the iSeries Information Center)



The *Memo to Users* describes significant changes in the new release that could potentially affect your programs or system operations. Use the *Memo to Users* to prepare for changes on the release and to use the new release. Be sure to read each section that pertains to licensed programs that you currently have installed or plan to install on your server.

In addition to the Memo to Users in the iSeries Information Center, you can access the Memo to Users from the IBM @server iSeries Support  Web site (www.ibm.com/eserver/series/support).

On the Web site, follow this path:

1. Search technical databases
2. Preventive Service Planning - PSP
3. All Preventive Service Planning Documents by Release
4. R530
5. SF98086: iSeries Memorandum to Users

The *Memo to Users* is also available to customers who use electronic customer support. You can order this document for V5R3 by using the Send PTF Order (SNDPTFORD) command and specifying program temporary fix (PTF) number SF98086.

If you are skipping a release level of OS/400, you should also review the Memo to Users for the release that you are skipping. This ensures that you are aware of changes that occurred in the skipped release that could also affect your programs and system operations. The command to order the PTF version of the V5R2 Memorandum to Users is SNDPTFORD SF98076. The same version is also available on the @server V5R2 iSeries Information Center  (www.ibm.com/eserver/iseres/infocenter) and through the preventive service planning information at the IBM @server iSeries Support  Web site (www.ibm.com/eserver/iseres/support).

- **Setup and Operations CD-ROM**

With every order that includes Operations Console, you receive *iSeries Setup and Operations*, SK3T-4098. This CD-ROM contains IBM @server iSeries Access for Windows[®] and the EZ-Setup wizard.

- **iSeries Information Center CD-ROM**

This CD-ROM, *iSeries Information Center*, SK3T-4091, ships with your IBM Operating System/400 software upgrade order.

- **PSP information**

To keep informed of the latest information about conditions that could impede your software installation, you need the most recent edition of the preventive service planning information (PSP). For information on preventive service planning, see preventive service planning information in the iSeries Information Center (**Maintain and manage OS/400 and related software > Use software fixes > Where to find information about fixes > Preventive service planning (PSP) information**).

- **iSeries PTF shipping information letter**

This letter contains the instructions for installing the cumulative program temporary fix (PTF) package. IBM recommends that you order the cumulative PTF package about a week or two before your OS/400 installation and then install the package as part of your completion tasks. For information about the most recent cumulative package, refer to the Order fixes topic in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Order fixes**).

Verifying the correct optical distribution media

If you are planning for a complete software release upgrade, do the following to ensure you have the correct media for your upcoming tasks.

1. Locate the software distribution media. Verify that the optical media for Licensed Internal Code and OS/400 are for V5R3.

When you receive software for a new release, you should receive optical media for at least Licensed Internal Code, OS/400, and licensed programs. You could also receive optical media for secondary languages and other types of software products, such as Programming Requests for Price Quotation (PRPQs) and licensed program offerings (LPOs).

The product tables (Standard set products, Keyed set products, and Licensed program releases and sizes) in Chapter 11, "Software reference," on page 165 list the names and product identifiers of licensed programs that you ordered.

Preparing to upgrade or replace software

2. Verify that the media you received is in the correct primary and secondary languages. Do the following to determine the feature number for the national language version (NLV) for your system's primary language and any installed secondary languages:
 - a. From the Work with Licensed Programs command menu (type G0 LICPGM and press Enter). Select option 20 (Display secondary languages).
 - b. The Display Installed Secondary Languages display appears. This display identifies the primary language of the system and any installed secondary languages.

Compare the OS/400 media label with the primary language of your system. If the system uses secondary languages, compare the secondary language media that you have received with the secondary languages listed on your system.
 - c. Press the F3 (Exit) key twice.

Note: If the logical partitions on your server have different primary languages, make sure you have media for each primary language.

Verifying license keys for keyed products

For the keyed IBM products or keyed IBM product options that you have ordered, review the software license keys created for your server online. Refer to the Customer Notice that is included with your software order for information on how to access your software license keys. The online access requires that you do the following:

- Register with IBM.
- Use the customer packing list from your software order to obtain the following numbers:
 - Customer number that was used for your order.
 - Software order number that was used to process your order.

After completing these steps, you can view, print, or download your software license keys to your server. If you have further questions, refer to the information on the Customer Notice for details on how to contact the IBM Software License Key Center.

For general information on licensed keys, refer to the topic Software license keys in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Work with software agreements and licenses > Concepts > Software license keys**).

For a list of products, see "Licensed program releases and sizes" on page 166.

Preparing the server for software upgrade or replacement

To prepare the iSeries server for software installation, review and perform the tasks that pertain to your server:

"Ensuring you have required software PTFs (fixes)" on page 31

Before you begin the installation process, make sure that your server is ready by ensuring you have the required program temporary fixes (PTFs). For this release, a PTF for accepting online software agreements for Licensed Internal Code and the OS/400 operating system is required to be temporarily applied before you upgrade.

“Working with critical system values before you install software” on page 33

Record and print system values. Check the QSYSLIBL, QUSRLIBL, QALWOBJRST, and QVFYOBJRST system values.

“Verifying the integrity of user-modified system objects” on page 36

When you replace your software with the new release, the system changes you made to some IBM-supplied objects. Check these system objects before you begin the software installation process.

“Removing any iSeries Access user-created subdirectories” on page 37

Ensure that your system does not have any user-created subdirectories if you are migrating to a newer iSeries Access package or you plan to delete or replace iSeries Access products.

“Ensuring two-phase commit integrity” on page 37

Complete or cancel all pending resynchronizations of commitment control definitions before you replace your software.

“Minimizing software installation time” on page 38

Minimize the time required to install your software.

“Gathering performance data for benchmark” on page 38

Establish system benchmarks before installing a new version of OS/400 or making a major system configuration change, such as adding a new software application.

Ensuring you have required software PTFs (fixes)

Before you begin the installation process, make sure that your server is ready by performing the following tasks relating to program temporary fixes (PTFs).

- **Finding the latest available PSP information**

Keep informed on the most recent information about conditions that could impede your software installation process. If you are using image catalogs to upgrade from V5R1 to V5R3, for example, a certain PTF is required. Review the most recent edition of preventive service planning information (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Fixes concepts and terms > Where to find information about fixes > Preventive service planning (PSP) information**).

- **Identifying required software fixes**

“Required: Installing software agreement PTFs” on page 32 describes the steps you need to do to apply the Software Agreement PTFs for V5R1 and V5R2.

A fix cross-reference summary list (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Fixes concepts and terms**) allows you to analyze the program temporary fixes (PTFs) and Licensed Internal Code fixes you currently have installed on your system. With this information, you can determine which fixes you need to order to maintain the same or higher PTF and Licensed Internal Code fix level as you update to the new level of software. These summaries are updated each working day with the latest information as new PTFs and Licensed Internal Code fixes are released.

- **Ordering current cumulative PTF packages and required group fixes**

About a week or two before you upgrade, order the most recent cumulative PTF package and also order PTF groups that pertain to your environment. The cumulative PTF package does not come with your software order. The topics

Preparing to upgrade or replace software

under Use software fixes (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes**) describe how to order fixes.

- **Installing optional PTF to use the image catalog (virtual optical device) support for installation**

If you are using an image catalog to upgrade from V5R1 to V5R3, load and apply PTF SI10553. The PTF cover letter contains information about upgrading from V5R1 to V5R3. This PTF contains specific instructions for using image catalogs and the virtual optical device.

If you are using an image catalog to upgrade from V5R2 to V5R3, do the following steps:

1. Load and apply the required V5R2 PTF SI10563.
2. Perform the setup steps in “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53. Perform step 6 on page 54 in “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53 at least a day before you do the actual installation. This ensures that your installation media are ready to use.

- **“Installing optional PTF to choose disk configuration” on page 33**

If you will be using automatic installation to upgrade and do not want nonconfigured disk units added, PTFs are available that allow you to set your disk configuration option.

- **“Permanently applying program temporary fixes (PTFs)” on page 33**

Make sure your system is ready by permanently applying fixes that were previously temporarily applied.

Required: Installing software agreement PTFs: Occasionally, situations arise that require specific program temporary fixes (PTFs) before you can install a new release. Before you can install V5R3, you must temporarily apply a PTF from the *Software Agreement PTFs for V5R1 and V5R2*, SK3T-8163-00, CD-ROM to be able to accept online software agreements for V5R3 licensed programs.

Important: You need to accept the licensed agreements for Licensed Internal Code and OS/400 before you can upgrade. If you do not accept the agreements, the installation of Licensed Internal Code will not be allowed to continue.

The *Software Agreement PTFs for V5R1 and V5R2* CD-ROM is included with your V5R3 software media. You need to temporarily apply the appropriate PTF to the current release before you upgrade.

To install the Software Agreement PTFs for V5R1 and V5R2, follow these steps:

1. Locate the CD-ROM labeled *Software Agreement PTFs for V5R1 and V5R2*.
2. Load the CD-ROM in the optical device.
3. Type G0 PTF and press Enter.
4. Select option 8 (Install program temporary fix package) and press Enter. The Install Options for Program Temporary Fixes display appears.
5. Specify the following and press Enter:
 - Device: OPT01
 - Automatic IPL: N
 - PTF type: 1
 - Other options: N

For V5R1, the server applies 5722999 PTF MF29250, 5722SS1 PTF SI06069, and the associated PTFs for the installed national languages for your current release. For V5R2, the server applies PTFs 5722SS1 SI10284 and SI08995.

Steps for using the functions of the PTF are included in the preparation process under “Required: Accepting software agreements” on page 46.

Installing optional PTF to choose disk configuration: Today, as part of the automatic installation process, all nonconfigured disk units are added to the system auxiliary storage pool (ASP). If you are using automatic installation to upgrade and do not want nonconfigured disk units added, PTFs are available that allow you to set your disk configuration option. If you are upgrading from V5R2, an additional IPL is required for this to occur. No IPL is required if you are upgrading from V5R1.

If you want to change your current disk configuration, follow the instructions to download and apply one of these PTFs:

- PTF SI08937 if you are upgrading from V5R1
- PTF SI08897 if you are upgrading from V5R2

Prerequisite PTFs for Licensed Internal Code are included. The instructions also include how to change the disk configuration. You must be signed on as security officer (QSECOFR user profile) to use these PTFs to change the disk configuration option.


If you are currently on a V5R3 system, have already installed either of the disk configuration PTFs before you upgraded to V5R3, and are replacing the OS/400 operating system, follow the instructions in “Choosing disk configuration” on page 51.

Permanently applying program temporary fixes (PTFs): Temporarily applied PTFs require a considerable amount of disk storage space. Do this only for products and temporarily applied PTFs that you have verified on your system.

When a new release is installed, the installation process overwrites the PTFs applied to the previous release. The PTFs for the previous release are no longer applied, but there might be associated objects that remain on the system and take up disk storage space. When you use Operational Assistant and choose to clean up system journals and system logs, PTF save files from previous releases are deleted from your system. However, for systems that have the System Manager for iSeries licensed program installed, the PTF save files are not deleted.

Note:

- Apply fixes in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Install fixes > Advanced fix installation procedures > Apply fixes**) contains information on applying immediate PTFs temporarily or permanently.
- If you have System Manager for iSeries licensed program (57xx-SM1) installed on your system, use the instructions in the book System

Manager Use  for managing PTFs on your system.

Working with critical system values before you install software

System values are IBM-supplied objects that can be modified from their shipped value to tailor certain aspects of the OS/400 operating system to your

Preparing to upgrade or replace software

environment. The software installation program will overlay these objects on your system with values that are supplied on the installation media.

To prevent this, IBM recommends that you do the following tasks:

- **“Recording and printing all system values before you install software”**
IBM recommends that you record or print your system values prior to the upgrade.
- **“Changing certain system values (QSYSLIBL, QUSRLIBL, QALWOBJRST, or QVfyOBJRST)”**
To ensure that your installation runs smoothly, check the system library list (QSYSLIBL), user library list (QUSRLIBL), allow restore of security sensitive objects (QALWOBJRST), or verify object signatures during restore (QVfyOBJRST) system values.

IBM recommends that you also create a data area to specify your system time zone before you upgrade to V5R3. This data area is used when you upgrade to set the time zone system value. By doing this, the time zone used on the system is set immediately.

Recording and printing all system values before you install software: IBM recommends that you record or print out your system values prior to the upgrade. To do this, use the Work with System Value command. On the command line, type `WRKSYSVAL OUTPUT(*PRINT)`. This helps to ensure that the upgrade process will not fail due to a previous modification of any system value. This also helps to make sure you will be able to reset the values after you complete the upgrade.

Changing certain system values (QSYSLIBL, QUSRLIBL, QALWOBJRST, or QVfyOBJRST): To ensure that your installation runs smoothly, do the following to check these system values:

- System library list (QSYSLIBL)
- User library list (QUSRLIBL)
- Allow restore of security sensitive objects (QALWOBJRST)
- Verify object signatures during restore (QVfyOBJRST)

1. Type the Work with System Values command, `WRKSYSVAL`, and press Enter. The Work with System Values display appears.
2. Type 2 (Change) in the *Option* column next to the system value you want and press Enter. The Change System Value display appears.
3. Check the system values as described in table that follows.
4. Write down the current values of QALWOBJRST and QVfyOBJRST plus any library names that are shown for QSYSLIBL and QUSRLIBL.

Preparing to upgrade or replace software

System value	Action to take
System library list (QSYSLIBL) ¹ Current libraries: _____ _____ _____ _____ User library list (QUSRLIBL) ¹ Current libraries: _____ _____ _____ _____	If you have any of the following libraries, use the spacebar to delete the library from the library list. <ul style="list-style-type: none"> • Remove any licensed program libraries. • Remove any secondary language libraries (QSYS29xx). Note: Do not remove QSYS, QGPL, QUSRSYS, QTEMP, or QSYS2.
Allow restore of security sensitive objects (QALWOBJRST) ² Current value: _____	Change the value to *ALL before installing OS/400 or licensed programs.
Verify object signatures during restore (QVFYOBJRST) ³ Current value: _____	If this system value is set to either 4 or 5, change this value to 3 before you install the new release. If you have previously locked this system value, go to SST and unlock it before you upgrade. Lock and unlock security-related system values (Systems management > System values > Manage system values > Lock and unlock security-related system value) describes how to do this.
Notes: <ol style="list-style-type: none"> 1. Having licensed program libraries or secondary language libraries in these library lists can cause errors when you install or delete software. 2. The Allow restore of security sensitive objects (QALWOBJRST) system value specifies whether or not objects with security-sensitive attributes can be restored. It is important to set the value to *ALL before performing the following system activities: <ul style="list-style-type: none"> • Installing a new release of OS/400. • Installing new licensed programs • Applying program temporary fixes (PTFs). • Recovering your system. These activities can fail if the value of QALWOBJRST is not set to *ALL. To ensure system security, return the QALWOBJRST value to your normal setting after completing the system activity. 3. After you have upgraded the OS/400 operating system and option 34, you can return the QVFYOBJRST system value to either 4 or 5. 	

Note that if you want the same values after the installation process is completed, you need to reset the system values. This step is included in the final checklist after you upgrade.

You can also use iSeries Navigator to set your system values. For more information, see system values in the iSeries Information Center (**Systems management > System values**) to find out how to use and access the system values from iSeries Navigator.

Preparing to upgrade or replace software

Creating a data area to specify the system time zone: Time management allows you to manage time on your server. Within the time management component of iSeries Navigator, you can work with the time zone and time adjustment functions. You can set the time zone on your system either before you upgrade, during an attended IPL, or after an IPL. IBM recommends that you specify the system time zone before you upgrade to the new release. This ensures that your system time is set properly as soon as the upgrade is complete. The iSeries Information Center topic *Setting the time zone before upgrading (Systems management > Time management > Set up time management > Set the time zone (QTIMZON) system value > Set the time zone before upgrading)* includes instructions for creating the data area before you upgrade.

Verifying the integrity of user-modified system objects

When you replace your software with the new release, the system keeps changes you made to some IBM-supplied objects.

To ensure a successful installation of all licensed programs and to take advantage of certain new functions, perform these tasks that relate to system objects before you begin:

“Verifying user profiles and checking cross-reference files”

The installation process requires that the QSECOFR and QLPINSTALL user profiles exist in the system distribution directory. The process also requires that all database cross-reference files are not in error before the installation process begins.

“Checking the QSECOFR user profile”

The QSECOFR user profile cannot contain secondary language libraries or alternate initial menus.

“Ensuring that the IBM-supplied product libraries are in the system ASP” on page 37

If you have moved IBM-supplied product libraries to user auxiliary storage pools (user ASPs), the installation procedures will not update the libraries.

Verifying user profiles and checking cross-reference files: The following procedure adds the QSECOFR and QLPINSTALL user profiles if you have deleted them from the system distribution directory. It also checks for errors in database cross-reference files on your system.

1. Type `G0 LICPGM` at the command line and press Enter. The Work with Licensed Programs menu appears.
2. Type 5 (Prepare for Install) and press Enter. The Prepare for Install display appears.
3. Select the option to verify system objects and press Enter. The system verifies the system directory entries and adds the QSECOFR and QLPINSTALL user profiles if necessary. Database cross-reference files are checked for errors.
4. If the database cross-reference files are in error, you see message CPI3DA3. Follow the instructions of this message to resolve the errors before you continue.
5. If the database cross-reference files are not in error, you see a completion message at the bottom of the display. Press F3 (Exit) to return to the Work with Licensed Programs menu.

Checking the QSECOFR user profile: The QSECOFR user profile cannot have a secondary language library (QSYS29xx) at a previous release in its library list when

you install a new release. If you have an initial program for the QSECOFR user program, be sure that it does not add a secondary language library to the system library list.

Ensuring that the IBM-supplied product libraries are in the system ASP: If you have moved IBM-supplied product libraries to user auxiliary storage pools (user ASPs), the installation procedures will not update the libraries. To prevent this problem, ensure that IBM-supplied product libraries are in the system ASP before you start the installation procedures. The product libraries should remain in the system ASP. PTFs are not applied to product libraries that are not in the system ASP.

If you have duplicate IBM-supplied product libraries, delete the duplicate libraries before you start the upgrade procedures. The upgrade process fails and the new release does not install until duplicate IBM-supplied libraries are deleted.

Removing any iSeries Access user-created subdirectories

If you are migrating to a newer iSeries Access package, or you plan to delete or replace iSeries Access products, ensure that your system does not have any user-created subdirectories. Examples include any of your own directories that were created through the /QIBM/ProdData/CA400/Express or /QIBM/ProdData/Access paths.

If any user-created subdirectories exist, the install or delete operation can fail. You can use the WRKLNK command to remove all user-created subdirectories for these products.

Ensuring two-phase commit integrity

Before you replace your software, you must either complete or cancel all pending resynchronizations of commitment control definitions.

You need to perform this task only if both of the following are true:

- Your server is connected in a network.
- Your system runs applications that use two-phase commit support.

Two-phase commit support is used when an application updates database files on more than one system. Two-phase commit support ensures that the databases remained synchronized. If you are not sure whether your system uses two-phase commit support, perform steps 1 and 2 on page 38. You might need to continue with the rest of the procedure.

Remember that any actions you take with respect to a pending resynchronization affect the other systems that are participating in the logical unit of work (transaction) with your system. Therefore, you or someone else will also need to handle pending resynchronizations on the connected systems before you begin your upgrade procedure.

If you perform this procedure 1 or 2 days before you install the new release, you should recheck for resynchronizations before starting the installation.

To work with pending resynchronizations on your source system, do the following:

1. To display all commitment definitions that might require resynchronization, type the following Work with Commitment Definitions (WRKCMTDFN) command:

```
WRKCMTDFN JOB(*ALL) STATUS(*RESYNC)
```

Preparing to upgrade or replace software

2. If you see the message, No commitment definitions are active, you can skip the rest of this procedure.
3. On the Work with Commitment Definitions display, type 19 (Cancel Resync) in the Option column for each commitment definition. You see the Cancel Resync display.
4. If the value in the column *Resync Required* is Yes for any remote location listed, then do the following for that location:
 - a. Attempt an action, such as restarting communications, and allow the resynchronization to complete.
 - b. If you cannot allow the resynchronization to complete, specify option 1 (Select) to cancel resynchronization to that remote location.

You could receive message CPF83E4, which indicates that the logical unit of work is in an undecided state. You will have to make an educated decision to force either a commit operation or a rollback operation before you can successfully cancel resynchronization. These options are available from the Work with Commitment Definitions display.

By canceling resynchronization, you could cause the databases between the two systems to be in an inconsistent state. You must then take the responsibility for determining the action taken by all the other locations that participated in this Logical Unit of Work (LUW), and resynchronize the database changes.

5. Refresh the display periodically. When resynchronization for a commitment definition completes or cancels successfully, the value in the *Resync in Progress* column will be No.

The resynchronization or a cancellation of resynchronization might not take place immediately. They are dependent on the state of the other systems that are participating in the logical unit of work.

For more information on commitment control and resynchronization, see the iSeries Information Center topic, Troubleshoot transactions and commitment control (**Database > Commitment control > Troubleshoot transactions and commitment control > When to force commits and rollbacks and when to cancel resynchronization**).

Minimizing software installation time

The following actions can minimize the time required to install your system:

- Use the automatic installation process rather than performing a manual installation process. “Software installation process” on page 9 has information on both methods.
- If you are not using the automatic installation process, be sure to set the QSYSOPR message queue in *BREAK mode before you start the installation process.
- Perform the licensed program installation with all subsystems ended (ENDSBS *ALL). If you are performing an automatic installation, you are operating in the preferred environment. This environment provides maximum system resources to the installation process and eliminates certain functions.
- If you have a large number of spooled files on your system, set the compress job tables IPL attribute to none. To do this, use the Change IPL Attributes command: CHGIPLA CPRJOBTL(*NONE).

Gathering performance data for benchmark

You should establish system benchmarks before installing a new version of OS/400 or making a major system configuration change, such as adding a new application.


Accurate system benchmarks allow you to compare system performance before and after the upgrade. A valid comparison allows you to accurately assess any performance improvement as well as isolate any changes to the system that can prevent optimal performance.

Collection Services can collect sample data for a wide range of system resources. Collection Services stores sample performance data in a collection object (*MGTCOL) on your system. Minimally, benchmarks should include data from current and representative collection objects. This can require that Collection Services run long enough to collect representative data. Representative data should include all periods of activity (both peak and off-peak hours), all applications, and all normal activities performed on a system. Additionally, you might require more detailed benchmark information to identify how critical applications, transactions, and jobs are affected by the system configuration change.

Several tools are available for collecting detailed information about application performance. However, these tools can require specialized skills and could adversely affect system performance. For details about collecting different types of performance data, refer to research a performance problem (**Systems management > Performance > Manage iSeries performance > Research a performance problem**) in the iSeries Information Center.

Gathering performance data with Collection Services

If you are not running Collection Services, or your collection objects are not current, start Collection Services in any of the following ways:

- Use the Collection Services function that is available in iSeries Navigator. Specific information on Collection Services is in the iSeries Information Center at **Systems management > Performance > Applications for performance management > Collection Services**.
- Use either the Start Collector (QYPSSTRC) API or the Start Performance Collection (STRPFRCOL) command. If you do not use the Management Central function in iSeries Navigator, you can manage your collections with either of the following methods:
 - Performance Management APIs in the iSeries Information Center (**Programming > APIs > APIs by category > Performance Management**). These APIs start, end, and cycle collections, and change and retrieve system parameters for the data collected.
 - Performance collection commands: STRPFRCOL, End Performance Collection (ENDPFRCOL), Configure Performance Collection (CFGPFRCOL), and Check Performance Collection (CHKPFRCOL). These commands start, end, and cycle collections for the data collected.
- If you have the Performance Tools licensed program (PT1) installed, use Option 2 from the Performance Tools main menu. Refer to Performance Tools for iSeries  for additional information on collecting performance data with this option.
- Activate IBM Performance Management for @server iSeries, which automates the start of Collection Services and then creates the database files during collection.

Ensure that Collection Services has been configured to collect the data you require, and that it runs long enough to accurately represent your operating environment.

The following example uses the Collector APIs.

Preparing to upgrade or replace software

1. Run Collection Services for at least one or two days, and make sure that peak and off-peak workloads are represented. Type this command:

```
CALL PGM(QYPSSTRC) PARM('*PFR      ' '*STANDARDP' X'00000000')
```

This command starts Collection Services and uses the **Standard plus protocol** for the collection profile. Once you start Collection Services with this command, it will collect performance data and store it in the collection object until you either explicitly stop it or restart the system. (If collection was run for more than one day, more than one collection object will be produced.) This profile collects all the data categories typically needed by the tools in Performance Tools for iSeries, including communications protocol data. The default configuration also starts a batch job CRTPFRTA, which creates the performance database files.

2. Collection Services stores the data in an object type of *MGTCOL. You can convert this object into performance database files for later analysis. To retain the object for future use, you can save the objects to tape or to a save file (SAVF). Collection Services can delete collection objects from the server at any time after the retention period has expired. The default retention period is 24 hours. If you do not want Collection Services to delete your collection objects for you, change your retention period to permanent (set a retention period of *PERM) as shown in the example that follows.

Note: The command example below shows the shipped default values with the exception of the retention period value. A retention period of *PERM requires a value of 0. Furthermore, you must make this change before or during the data collection. The change does not affect any collection objects that are already cycled.

To change the retention period by using the Change Collection Services Attributes API, type the following command:

Note: Read “Code disclaimer information” on page 216 for important legal information.

```
CALL PGM(QYPSSCSA) PARM('*PFR      ' /* collection */
                        X'00000384' /* interval 900 sec */
                        'QPFRDATA ' /* library      */
                        X'00000000' /* retention period is permanent */
                        X'00000000' /* cycle time 00:00:00 */
                        X'00000018' /* cycle interval 24Hrs */
                        X'00000001' /* start CRTPFRTA */
                        '*STANDARDP' /* default profile */
                        X'00000000') /* return code */
```

3. If you want to explicitly stop the collector after the desired data is obtained, type this command:

```
CALL PGM(QYPSSEND) PARM('*PFR      ' X'00000000')
```

Analyzing performance data

To analyze the performance data, you must either export collection object data into the performance database files (if Collection Services has not already done so) or convert the database files created from the prior release to the current release format. For more information, refer to **Create database files from a collection object** in the iSeries Information Center (**Systems management > Performance > Applications for performance management > Collection Services > Create**

database files from a collection object) and also the step regarding converting the performance data in “Checklist: Completing the upgrade or replacement” on page 81.

There are several tools you can use to analyze the data from Collection Services. For more information, refer to Applications for performance management in the iSeries Information Center (**Systems management > Performance > Applications for performance management**). In particular, the Performance Tools for iSeries licensed program summarizes this data into several reports you can use for detailed analysis.

Performing initial upgrade or replacement tasks

Complete these initial installation tasks, which include saving the server. Note that several of these tasks are required for a successful software upgrade.

“Choosing a software installation method and device” on page 42

Decide which installation method (manual or automatic) and which kind of device (optical media, image catalog, tape, or alternate installation device) you will use to install the new release.

“Preparing for globalization” on page 42

If appropriate, prepare to change the primary language on your server or install additional secondary languages.

“Required: Creating a custom list of software to install” on page 42

Use the Prepare for install option to create a customized installation list and preselect the licensed programs that you want to install.

“Required: Accepting software agreements” on page 46

As a continuation of using the Prepare for install option, you must accept the software agreements for licensed programs before they can be installed.

“Ensuring the server meets disk storage requirements for upgrades” on page 46

Ensure that you have adequate disk storage.

“Required: Allocating additional space for Licensed Internal Code” on page 50

The Licensed Internal Code requires .42 GB of extra space for V5R3.

“Choosing disk configuration” on page 51

If you do not want to add all nonconfigured disk units to the configuration during the upgrade, follow these steps to apply a PTF that calls a program to change the disk configuration.

“Estimating upgrade or replacement time” on page 51

Estimate the time that is needed to upgrade or replace this release of software on your server.

“Preparing your console for software installation” on page 51

Get your console ready for the software installation process.

“Preparing the upgrade device and media” on page 53

Prepare to install software from optical media, an image catalog, tape devices or tape libraries, or alternate installation devices.

Preparing to upgrade or replace software

“Preparing to upgrade IBM Cryptographic Access Provider” on page 55
Find out how to install the correct version of this licensed program for V5R3.

“Stopping the Integrated xSeries Server for iSeries and other application servers” on page 55
Vary off the Integrated Netfinity® Server before you begin the software installation process.

Choosing a software installation method and device

If you are upgrading OS/400 and your licensed programs to the new release, you need to decide which installation method (manual or automatic) to use. For a general view of the installation methods, see “Software installation process” on page 9.

To help you determine which device you will use, refer to “Types of software installation devices” on page 12. “Installation devices and media” on page 180 contains more detailed information on the devices and media available.

Preparing for globalization

If you plan to change the primary language on your server or install additional secondary languages, review the information in “Globalization and software installation” on page 20.

Required: Creating a custom list of software to install

This topic describes how to use the Prepare for install option to create a customized installation list and preselect the licensed programs that you want to install. Before you do these tasks, you must perform the steps in the topic, “Required: Installing software agreement PTFs” on page 32.

The Prepare for install option compares the programs that are installed on your server with the programs on the media. It then generates a list. This list contains preselected programs that are replaced during the installation. To customize this list, select or deselect programs from this installation list, depending on which programs you want to install or replace. You must verify that what you ordered can be replaced. You must verify that you have all of the necessary upgrades on your installation media to complete the automatic installation. You need to accept the software agreements for these licensed programs later in these preparation tasks.

Some single licensed programs might not appear on this installation list. If a previous release is currently installed on the server, the new release of these licensed programs is installed during the upgrade. If these licensed programs are new (being installed for the first time), they cannot be added to this customized list. However, you can install them by using the method in “Installing additional licensed programs” on page 114 or by following these steps.

“Preselecting the licensed programs to install”

Create and customize an installation list from your distribution media.

“Adding additional licensed programs to the installation list” on page 45

After you have created an installation list, add any additional licensed programs to the list.

Preselecting the licensed programs to install: Use the following process to create and customize an installation list from your distribution media:

1. Arrange the optical media for Licensed Internal Code, OS/400, and licensed programs in the order that is shown in the table “Media labels and their

contents” on page 189. The order is important. More specifically, include only the I_BASE_01, B29xx_nn, B29MM_nn, D29xx_nn, L29xx_nn, and F29xx_nn optical media. Do not include any other optical media when creating the installation list at this time.

2. Sign on as security officer (QSECOFR user profile).

Note: If you are using image catalogs, you must first allocate additional space for the Licensed Internal Code (see “Required: Allocating additional space for Licensed Internal Code” on page 50). After completing that task, go to “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53 and complete steps 1 on page 53 through 5 on page 54. Then return to this topic. Ignore the following steps that refer to loading volumes.

3. Type CHGMSGQ QSYSOPR *BREAK SEV(95) to put your message queue in the break mode.
4. A message display could appear. Press Enter.
5. Type GO LICPGM and press Enter.
6. Select option 5 (Prepare for install) from the Work with Licensed Programs (LICPGM) menu and press Enter. The Prepare for Install display appears.
7. Select the option to Work with Licensed Programs for Target Release and press Enter. The Work with Licensed Programs for Target Release display appears.
8. Do the following:
 - a. Load the first optical media in the optical device.
 - b. Specify 1 (Distribution media), for the *Generate list from* prompt.
 - c. Specify a value for the optical device or virtual optical device.
 - d. Specify the target release.
 - e. Press Enter.
9. When the Display Messages display appears, load the next media volume. Type G and press Enter.

Notes:

1. After you load each volume, type G and press Enter.
 2. If there are no more volumes to load or if you want to end the loading process, type X and press Enter.
10. Continue to load the optical media in order (as in the step above) until the server has read all of the volumes.

If the display contains the message, Problem occurred loading volume into device, or if it states that a product was not found on the media, one of these situations occurred:

 - You left the same media in the drive and the server read it again.
 - The server had problems reading in the new volume that you placed into the drive.
 11. After the server reads all the optical media and the message, Load next volume in optical device (X G), appears, type an X and press Enter. The Work with Licensed Programs for Target Release display appears.

The list you see contains the licensed programs that are on the optical distribution media and are installed on your server. Preselected licensed programs indicate that the product on the distribution media can replace a product that is installed on the server. (Preselected means a 1 appears in the option column.)

Preparing to upgrade or replace software

Verify that you received all of the licensed programs and priced features that you ordered.

Note:

- Use the F11 key to see alternative views that display information about licensed programs in greater detail. Press F11 to toggle through these views:
 - a. Display additional storage
 - b. Display expected release
 - c. Display expected action
 - d. Display product option
 - Use option 5 (Display release-to-release mapping) to see what, if any, currently installed product will be replaced by the selected product. You might need to specify option 2 (Merge with additional distribution media) on the Work with Licensed Programs for Target Release display to merge your existing list with information about licensed programs on additional optical media. This task is described later. Continue with the next step.
12. Select additional licensed programs or optional parts of licensed programs to add to your customized list. Type a 1 in the *Option* column to select a licensed program to install. To remove a selected product from the list, blank out or remove the 1 in the *Option* column. When you complete your selections, press Enter. A message at the bottom of the display will prompt you to enter more changes, or press Enter to confirm the changes. The Confirm Target Release Licensed Programs display appears.
 13. Press Enter to confirm the list. The Prepare for Install display appears.
 14. Select the option to List Licensed Programs Not Found on Media and press Enter. The Licensed Programs Not Found On Media display appears.
 15. If no products are listed, you have all the media needed to replace your existing software. Press Enter to return to the Work with Licensed Programs menu. Go to the next step (step 16 on page 45) to create a printed list of the licensed programs you selected.

If there are any products listed, do the following:

- a. Delete the licensed programs that are no longer supported.
- b. You might need to obtain the others before you begin installing software. Do the following:
 - 1) Check to see whether you accidentally omitted an optical disc when you performed step 8 on page 43.
 - 2) Compare your media labels to the product tables (“Standard set products” on page 191, “Keyed set products” on page 193, and “Licensed program releases and sizes” on page 166) to see if the product was shipped. If you did not receive a licensed program that you expected, contact your software provider.
 - 3) When you receive the product or locate the media, use the distribution media and product tables (“Media labels and their contents” on page 189 “Standard set products” on page 191, “Keyed set products” on page 193, and “Licensed program releases and sizes” on page 166) to add its contents to the installation list. Use the procedure “Adding additional licensed programs to the installation list” on page 45 to create a printed list of the programs that you selected to install.

- 4) If you want to modify the installation list, type 3 (Modify previously generated list) on the Work with Licensed Programs for Target Release display.
16. (If you do not need to add any additional licensed programs to the installation list, do this step now. Otherwise, skip to the next step to add additional licensed programs.) From the Prepare for Install display, select the option to Display Licensed Programs for the Target Release and press Enter. Specify *PRINT for output on the Display Licensed Programs for Target Release display and press Enter. This creates a spooled file that you can print and use as a reference while performing the installation.
You should see the message, Task to prepare for install successfully completed, appear at the bottom of the display.
17. Press F3 to exit.

Adding additional licensed programs to the installation list: Perform this task only when you have already created a custom list of software to install and only when you have additional licensed programs to add to the list.

These additional programs could be a single product on media that came with your order or that were independently shipped. The order in which you load the additional optical media is not important.

Not all products will be included in this list. Among those are Programming Request for Price Quotations (PRPQs), licensed program offerings (LPOs), and single licensed programs. “Installing additional licensed programs” on page 114 describes how to install these products after you have completed your upgrade to the new release.

To add licensed programs from additional optical media to the installation list, follow these steps:

1. Load the installation media that contains the additional licensed programs. Wait for the In Use indicator to go out.
2. Starting from the Work with Licensed Programs (LICPGM) menu, select option 5 (Prepare for install), and press Enter. The Prepare for Install display appears.
3. Select the option to Work with licensed programs for the target release, and press Enter. The Work with Licensed Programs for Target Release display appears.
4. Select option 2 (Merge with additional distribution media) for the *Generate list from* prompt so that optical media contents can be added to the list. The target release value of the existing list appears.
5. Specify a name for the optical device and press Enter.
6. When the Display Messages display appears, load the next media volume.
Type G and press Enter.
After you load each volume, type G and press Enter. If there are no more volumes to load or if you want to end the loading process, type X and press Enter. A list of licensed programs appears.
7. Type 1 next to the additional licensed programs or optional parts that you want to select, and press Enter. The Confirm Licensed Programs for Target Release display appears. Press Enter to confirm the list.
8. You see the Prepare for Install display. Select the option to Display Licensed Programs for the Target Release, and press Enter.

Preparing to upgrade or replace software

9. Specify *PRINT for output on the Display Licensed Programs for Target Release display, and press Enter. This creates a spooled file that you can print and use as a reference while performing the installation.

Required: Accepting software agreements

It is a system requirement that you accept the online software agreements for the Licensed Internal Code and the OS/400 operating system through the Prepare for Install menu before you upgrade to V5R3. If these software agreements are not accepted, you will not be allowed to continue with the upgrade of Licensed Internal Code. Any other licensed programs that have software agreements must also be accepted before they are upgraded to V5R3.

To accept the software agreements for the licensed programs that you plan to upgrade, follow these steps:

1. Ensure that you have performed the steps in the topics “Required: Installing software agreement PTFs” on page 32 and “Required: Creating a custom list of software to install” on page 42. To be able to upgrade, the custom list must include, at a minimum, the Licensed Internal Code and the OS/400 operating system.
2. Type GO LICPGM and press Enter. The Work with Licensed Programs display appears.
3. From the Work with Licensed Programs (LICPGM) menu, select option 5 (Prepare for install) and press Enter. The Prepare for Install display appears.
4. Select the option to work with software agreements. Press Enter.

On the Work with Software Agreements display that appears, you see all IBM licensed programs that require software agreement acceptance and whether the agreement has been accepted. Only licensed programs that are not yet installed appear on this display. If you have non-IBM licensed programs on CD-ROM that were not inserted when you used the option to work with licensed programs for target release (step 7 on page 43 under “Preselecting the licensed programs to install” on page 42), press F22 to add these licensed programs to the Work with Software Agreements display.

5. Select to display the software agreements for licensed programs that you want to accept and press Enter. Press F14 (Accept) to accept the terms of the software agreement. Press F15 (Accept all) to display a list of all licensed programs that share the same set of terms as the software agreement you are currently reading. Press Enter to accept the software agreements for all of the listed licensed programs.

Ensuring the server meets disk storage requirements for upgrades

You must ensure that you will have adequate disk storage before you start to install or replace software. To make more efficient use of your storage, clear your system of items that you no longer require before you estimate how much storage you will need.

“Determining storage space required” on page 47

Before you schedule a time to install this release, determine the available storage space and the storage space that is required.

“Cleaning up disk storage space” on page 49

Cleaning up your system before you begin to install a new release makes more storage space available for the installation process.

Determining storage space required: Before you schedule a time to install this release, determine the available storage space and the storage space that is required for this release.

Note:


1. Load-source disk unit requirements:
You must have a load-source disk unit of 4 GB or larger on each server or logical partition. (This unit is disk unit number 1 in auxiliary storage pool (ASP) number 1.)
2. The procedures in this topic might not include all requirements for storage that you have on your server.

To determine if you have enough storage space for the new release, perform the following steps:

1. Type G0 LICPGM. The Work with Licensed Programs display appears.
2. Choose option 5 (Prepare for Install).
3. Type 1 next to Estimated storage requirements for system ASP. The Estimated Storage Requirements for System ASP display appears.

Enter the total storage that is needed for additional applications. Include storage for single licensed programs that were not included on your customized installation list, and storage for Programming Request for Price Quotations (PRPQs), licensed program offerings (LPOs), or third-party software.

Round up to the nearest whole number. Refer to the product documentation to determine how much additional storage is required. The system uses this number to calculate the disk storage that is required to install the target release. Include third-party software only when you intend to store it in the system

ASP. Refer to the Backup and Recovery  manual or Backup and recovery in the iSeries Information Center for more information about system ASPs.

4. Press Enter to continue to the next display. The second Estimated Storage Requirements for System ASP display appears.
This display shows you information that you will need to determine whether enough disk storage is available to complete the installation.
5. Compare the value for *Storage required to install target release* with the value for *Current supported system capacity*. If the value for *Current supported system capacity* is greater than the value for *Storage required to install target release*, you can continue with the installation process. If the system capacity is less than the storage required, you might need to add additional disk units or install fewer optional programs.
6. Press Enter to return to the Prepare for Install display.

Repeat this process whenever you make any changes to your system that affect the available disk storage space.

Storage considerations for image catalog installation

Image catalog installation requires additional storage space to contain the installation images. The amount of system disk-unit storage that you need varies based on what you are installing. The IBM-supplied media set uses the following storage:

Preparing to upgrade or replace software

Table 4. Storage sizes for IBM-supplied media

Media	Allocated size (in megabytes)
I_Base_01	472
B29xx_01	533
B29xx_02	456
B29MM_03	678
B29MM_04	397
D29xx_01	424
D29xx_02	522
D29xx_03	489
D29xx_04	421
D29xx_05	309
L29xx_01	411
L29xx_02	516
Total	5628

To calculate the size of any media not listed in this table, load your media into an optical device and enter the Work with Optical Volumes (WRKOPTVOL) command. Select option 5 and use the value for *Volume capacity (bytes)* and add 1 MB to get the approximate size allocated for that optical media.

To understand how the system decompresses objects, see “Compressed objects and storage space” on page 20.

Free space in the load-source disk unit for an image catalog

Image catalog installation requires at least 1074 MB of free space on the load-source disk unit of your server. If you are using an image catalog to install software, perform the following steps to verify how much free space you have available:

Use the Work with Disk Status (WRKDSKSTS) command to determine if your load-source disk unit (unit 1) has at least 1074 MB of free space. If you do not have 1074 MB of free space and are upgrading from V5R1, follow the instructions provided in PTF SI10553, Optical Support, to free the load-source disk unit space.

If you are upgrading from V5R2, it is required to have PTF SI10563 loaded and applied. Continue with the following steps:

1. Use the Start ASP Balance (STRASPBAL) command to end the allocation for storage in the load-source disk unit:
STRASPBAL TYPE(*ENDALC) UNIT(1)
2. Use the Check ASP Balance (CHKASPBAL) command to view the previous end allocations and see these messages:
 - Unit 1 is selected for end allocation.
 - ASP balancing is not active for ASP 1.
3. Use the STRASPBAL command to move data off of the load-source disk unit:
STRASPBAL TYPE(*MOVDTA) TIMLMT(60)

4. Use the WRKDSKSTS command to monitor when the disk unit has 1074 MB of free space. The CHKASPBAL command can be used to determine if the move data function is still active.

When you perform a system IPL during the upgrade, the allocations for the load-source disk unit storage are resumed.

Cleaning up disk storage space: Cleaning up your server before you begin to install a new release makes more storage space available for the installation process. To keep your server running smoothly, see the topic Basic system operations in the iSeries Information Center (**Systems management > Basic system operations**).

Consider the following tasks that you can do to clean up your system and make more disk space available:

- Use the automatic cleanup option in Operational Assistant to keep your system free of unnecessary clutter.
- Permanently apply program temporary fixes (PTFs) that are temporarily applied on your system if you have not already done so.
- Delete PTF save files and cover letters that are no longer needed.
- Delete any software applications that you installed from software sampler CD-ROMs.
- Perform the steps in “Deleting licensed programs during cleanup” for licensed programs or optional parts that you no longer use. Read the topics on deleting licensed programs in Chapter 9, “Deleting software related to OS/400,” on page 139 for additional information.
- Have each user perform the tasks in “Cleaning up user profiles” on page 50. Delete any user profiles that you no longer need.

Deleting licensed programs during cleanup: Cleaning up your system before installing a new release of software can include deleting products. You might no longer need some licensed programs, or you might plan to not replace them. Occasionally, the system can require that you delete an obsolete product before you install a new release. The Work with Licensed Programs (LICPGM) menu option, Prepare for install, provides an easy way for you to identify and delete licensed programs when you are preparing to install a new release of software. Do the following:

1. Select option 5 (Prepare for install) from the Work with Licensed Programs display and press Enter. The Prepare for Install display appears.
2. Ensure that you have a customized installation list of software. If you do not have one, go to “Required: Creating a custom list of software to install” on page 42; then return to this step.

Select the option *Work with Licensed Programs to Delete* and press Enter. The Work with Licensed Programs to Delete display appears.

The display shows a list of installed products that should be deleted from the system. Licensed programs can appear in this list for the following reasons:

- The licensed program should not remain on the system because it is not supported in the target release.
- The licensed program is installed, but no replacement product was found on the optical distribution media.
- A preselected licensed program was removed from the installation list so its associated installed product appears on this display. If the installed product remains on the system, it will be replaced by the licensed program that is on the distribution media.

Preparing to upgrade or replace software

Press F11 (Display reasons), then press the Help key to display the reason each product is included in the list for deletion. Carefully review the reason for deletion before you take any action.

3. When you are sure of which products to delete, save a copy of the products, using option 1 (Save) in case you might need them again. Then use option 4 (Delete) to delete the products before you install the target release of software. Option 4 immediately deletes the product from your system.

Cleaning up user profiles: Before you upgrade to a new release, you should clean up user profiles and the objects that are owned by user profiles.

Attention: Do not delete any IBM-supplied user profiles (profiles that start with the letter Q). Have each user sign on and do the following:

1. On the command line, type WRK0BJOWN. The Work with Objects by Owner display is shown. It lists all of the objects that are owned by the user. Use option 4 (Delete) to delete objects that are no longer needed.
2. Type WRKSPLF to list all of the spooled files that are owned by the user. Delete spooled files that are no longer needed.

If the users cannot do this, you can do it as follows:

1. Sign on as security officer (QSECOFR user profile).
2. From the Work with Licensed programs menu (type G0 LICPGM), select option 5 (Prepare for install).
3. Select the option to work with user profiles from the Prepare for Install display. The Work with User Profiles display appears.
4. Use option 12 (Work with objects by owner) to display the objects that are owned by a user profile. First, use the F21 key (F21=Select Assistance level) to change your assistance level to Intermediate. Do the following:
 - For each user profile, delete objects that are no longer needed.
 - Use the WRKSPLF SELECT(*ALL) command to delete spooled files that are no longer needed.
5. Delete the user profiles that you no longer need.

Required: Allocating additional space for Licensed Internal Code

The V5R3 Licensed Internal Code requires .42 GB more storage space than in previous releases. All server models with V5R2 or earlier installed require the additional reserved storage before V5R3 can be installed. If you do not add this additional space, the upgrade will stop during the installation of the Licensed Internal Code.

To allocate the additional storage, do the following steps:

1. Type G0 LICPGM and press Enter.
2. From the Work with Licensed Programs (LICPGM) menu, select option 5 (Prepare for install). Press Enter. The Prepare for Install display appears.
3. Select the option to allocate additional space for Licensed Internal Code.
4. On the Allocate Additional Space for Licensed Internal Code display, type *YES and press Enter.

A message appears at the bottom of the display that indicates the Licensed Internal Code will allocate additional disk space at the next IPL. This additional IPL must occur before you power down the server or logical partition to upgrade to the new release. A step for this IPL is included in "Upgrading or replacing software using automatic installation" on page 56 and "Upgrading or replacing software using manual installation" on page 64.

If additional space for Licensed Internal Code has already been allocated, the message, *Additional space has already been allocated*, shows at the bottom of the Prepare for Install menu.

Choosing disk configuration

If you are using automatic installation to upgrade and do not want nonconfigured disk units added, PTFs are available that enable you to set your disk configuration option.

If you are upgrading from either V5R1 or V5R2 to V5R3 and want to change your disk configuration, refer to the instructions in the topic “Installing optional PTF to choose disk configuration” on page 33.

If you are currently on a V5R3 system and are replacing the OS/400 operating system, do the following to keep your current disk configuration:

1. Type G0 LICPGM and press Enter.
2. From the Work with Licensed Programs (LICPGM) menu, select option 5 (Prepare for install) and press Enter. The Prepare for Install display appears.
3. Select the option to keep the disk configuration and press Enter. The Keep Disk Configuration display appears.
4. At the Keep Disk Configuration prompt, type *YES and Press Enter.

Estimating upgrade or replacement time

If you want to estimate the time it will take to upgrade software on your server, use the information in “Estimates for software installation time” on page 171.

Preparing your console for software installation

Although you can use twinaxial console on most servers, IBM recommends for V5R3 that you use either Operations Console or Hardware Management Console for eServer. For requirements on twinaxial console, Operations Console, and PCs, refer to the category, *Connecting to iSeries* in the iSeries Information Center. If you are moving from twinaxial console to Operations Console, use the *iSeries Setup and Operations CD-ROM*, SK3T-4098-02, to install Operations Console before you install the new release.

If you are using twinaxial console, the software installation process expects the system console device to be attached at port 0 and address 0 of the first workstation controller. In most cases, your hardware should be defined in this way. You should verify that the console is attached at port 0 address 0.

If you are planning on migrating your Operations Console, do so either before or after you upgrade. If you are planning on migrating your Hardware Management Console (HMC), do so only after you have completely installed your system. For more information about using the HMC as your OS/400 console, see *Hardware Management Console* in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).

For all servers, verify that the console mode value is set correctly for your console. To verify the console mode value, follow these steps:

1. Access Dedicated Service Tools (DST).
2. Select **Work with DST environment**.
3. Select **System Devices**.
4. Select **Console mode**. The value of the current console mode is present in the input field. Verify that this is the correct setting. A value of zero means that the console mode has not been set and can interfere with the automatic installation

Preparing to upgrade or replace software

process. The console mode value must be one of the following values:

1	Twinaxial console
2	Operations Console (directly attached)
3	Operations Console (LAN attached)
4	Hardware Management Console (HMC)

During an installation or upgrade to V5R3, the console type specified by this value is used.

If you use Operations Console, do the following before you install V5R3 on your server:


- Review the Operations Console topic in the iSeries Information Center (**Connecting to iSeries > Operations Console**). To view the most recent information on Operations Console, go to the Operations Console Web site  (http://www.ibm.com/servers/eserver/series/clientaccess/qnaopcons.htm)
- IBM recommends that you update IBM @server iSeries Access for Windows to V5R3 before you upgrade the OS/400 operating system. For more information, see Install and set up in the iSeries Information Center (**Connecting to iSeries > iSeries Access for Windows > Install and set up**).
- If you use the Operations Console configuration, Local console directly attached to the server, the adapter used for the cable connection must be in a specific position. The adapter can be a 2721, 2742, 2745, 2771, or 2793. The position is based on the server model shown in the following table:

Table 5. Card position

Server model	Operations Console asynchronous card position for the cable
170 or 250	C08
270	C07
520	C03
570	C02
720	C09
730 or 740	See cabling information
800 or 810	C07
820	C06
825	C06
830 or SB2	C02
840 or SB3	C02
870 or 890	C02

- When you receive the OS/400 release upgrade, the shipped service tools user IDs (except 1111111) are expired. For all upgrades and installations, you need to establish a connection between the server and Operations Console PC by using the service tools user ID of 1111111 (eight 1's). This ensures a successful authentication of the subsequent connection of the client to the server. This is especially important for automatic installations.

Failure to comply with the above actions can prevent the console from working correctly during the upgrade or installation.

Preparing the upgrade device and media

If you are not sure which installation device to use for your software upgrade, refer to “Types of software installation devices” on page 12. The topic “Installation devices and media” on page 180 contains more detailed information on the devices and media available.

To use an image catalog for your software upgrade or replacement, follow the steps in “Scenario: Preparing to upgrade or replace software using an image catalog.”

Scenario: Preparing to upgrade or replace software using an image catalog: You can use an image catalog to perform a software upgrade, to install PTFs (fixes), or to install single licensed programs that you receive on media. “Image catalog for a virtual optical device” on page 181 further describes the requirements for using image catalogs.

The following is a scenario of how you create an image catalog and an image catalog entry, add an image catalog entry, and load the image catalog in preparation of performing a software upgrade.

If you want to upgrade from V5R1 to V5R3, you must load and apply V5R1 PTF SI10553 and then follow the instructions in the V5R1 PTF cover letter.

To perform a V5R2-to-V5R3 software upgrade from an image catalog, load and apply V5R2 PTF SI10563 and then do the following steps.

Note: The following steps also apply when replacing V5R3 with V5R3. If you already performed steps 1 through 5 on page 54, which are part of the tasks in “Preselecting the licensed programs to install” on page 42, skip to step 6 on page 54.

1. Create a virtual optical device

To create a device description, enter the following:

```
CRTDEVOPT DEVD(virtual-device-name) RSRNAME(*VRT)
  ONLINE(*YES) TEXT(text-description)
```

2. Vary on the virtual optical device

Note: You can have only one image catalog active at a time.

Enter the following:

```
VRYCFG CFGOBJ(virtual-device-name) CFGTYPE(*DEV) STATUS(*ON)
```

3. Create an image catalog

Create an image catalog for the licensed programs that you want to install. The Create Image Catalog (CRTIMGCLG) command associates an image catalog with a target directory where the optical image files are loaded.

```
CRTIMGCLG IMGCLG(catalog-name) DIR(catalog-path)
  CRTDIR(*YES) TEXT(text-description)
```

4. Add an image catalog entry

Add an image catalog entry for each physical media that you have. You need to repeat this step for each volume of media. You should add the images in the same order as if you were going to install from them. Start with the first media in the list and continue until all the media are loaded.

You can add the entries from either an optical device or from an existing optical image file. Select one of the following ways:

From an image file:

Preparing to upgrade or replace software

- (This is the fastest way.) To add an image entry to an image catalog from an integrated-file-system file that is already in the image catalog directory, enter the following:

```
ADDIMGCLGE IMGCLG(catalog-name) FROMFILE(file-name)
TOFILE(*fromfile) TEXT(text-description)
```

- To add an image catalog entry to an image catalog from an existing integrated-file-system optical image file from a directory other than the image catalog directory, enter the following:

```
ADDIMGCLGE IMGCLG(catalog-name)
FROMFILE(/directory-name/directory-name/file-name)
TOFILE(file-name) TEXT(text-description)
```

From a physical file:

- To add an image catalog entry to an image catalog from a physical optical media device named OPT01, enter the following:

```
ADDIMGCLGE IMGCLG(catalog-name) FROMDEV(OPT01)
TOFILE(file-name) TEXT(text-description)
```

Note: To generate a name for the TOFILE parameter, specify *GEN. To generate a text description from the media, specify *GEN.

5. Load the image catalog

This step associates the virtual optical device to the image catalog. Only one image catalog at a time can be associated with a specific virtual optical device. To load the image catalog, type the following command:

```
LODIMGCLG IMGCLG(catalog-name)
DEV(virtual-device-name) OPTION(*LOAD)
```

6. Verify that the images are in the correct order

If you are preparing for an upgrade, you need to verify that the required media for an upgrade exist and are sorted in the correct sequence.

Note: If you are here because you are performing the steps in “Preselecting the licensed programs to install” on page 42, do not perform this step at this time. You are directed to perform this step later.

Enter the following command:

```
VFYIMGCLG IMGCLG(catalog-name) TYPE(*UPGRADE) SORT(*YES)
```

An additional method would be to enter the following:

```
WRKIMGCLGE IMGCLG(catalog-name)
```

Then press PF7 to prompt for the VFYIMGCLG command. Enter *UPGRADE for the type and *YES for the sort field.

Note: Three possible values for the verification TYPE parameter are *UPGRADE (used for upgrading), *PTF (used for PTFs), and *OTHER (used for individual licensed programs).

The server puts the images in the correct order. By default, the volume with the lowest index is mounted. Then all the other volumes are loaded. To see the order of the images, use the Work with Image Catalog Entries (WRKIMGCLGE) command:

```
WRKIMGCLGE IMGCLG(catalog-name)
```

After completing these steps, your image catalog is ready for use.

Preparing to upgrade IBM Cryptographic Access Provider

The server does not automatically remove the previous version of Cryptographic Access Provider when you upgrade. If you are upgrading to IBM Cryptographic Access Provider 128-bit for iSeries, 5722-AC3, and you currently have either 5769-AC1 (Cryptographic Access Provider 40-bit for AS/400®) or 5722-AC2 (Cryptographic Access Provider 56-bit for AS/400) on your server, you need to remove the previous version of the product before you can install 5722-AC3. Any of these versions of the licensed program can be used for V5R3. Only one can be installed on the server at a time.

Stopping the Integrated xSeries Server for iSeries and other application servers

Before you begin the installation process, you must vary off the Integrated xSeries® Server. If your server has an active Integrated xSeries Server for iSeries (formally called Integrated Netfinity Server), it can cause the installation process to fail. Stopping the server also stops the operating system and any applications that are running on the server.

As a precaution, record the associated resources for your hardware. For these instructions, refer to the topic Upgrade the IBM iSeries Integration for Windows Server licensed program in the iSeries Information Center (**Integrated operating environments > Windows environment on iSeries > Install and configure > Upgrade the IBM iSeries Integration for Windows Server licensed program**).

Notify users before you stop the Integrated xSeries Server. The “Checklist: Completing the upgrade or replacement” on page 81 contains instructions on starting the server after you have completed your installation.

To stop the Integrated xSeries Server, use the Network Server Administration menu:

1. Type GO NWSADM on an OS/400 command line. The Network Server Administration display appears.
2. Select option 3 (Stop a network server).

Other application servers, such as Lotus® Domino™ Enterprise Server for AS/400 (5769-LNT), should be stopped before upgrading your software.

Saving the server

Before you upgrade to a new release, you should have a current backup copy of your server. You do not need to save your server when you have a current backup copy that can be used to recover if a failure occurs. Be sure to keep this backup copy until you save your entire server again. In the iSeries Information Center, the topic Back up your server (**Systems management > Backup and recovery > Back up your server**) contains information on how to perform your save strategy and also the steps to automatically save your entire server.

1. Before you begin the process for saving the server for a recovery procedure, determine the optical or tape device for the alternate IPL.
2. Save your server by using the alternate IPL device.

Tapes that are created with the Save System (SAVSYS) command cannot be used with the automatic installation process. These tapes also do not provide a complete backup.

Note: After you begin to upgrade the Licensed Internal Code to the next release, the upgrade process must be completed. If you do not complete the upgrade

Preparing to upgrade or replace software

and you want to return to the previous release of the operating system, you need to initialize the disks and reload the server by using the backup tapes that were created by the GO SAVE command (Option 21) just before you began the upgrade.

Upgrading or replacing software using automatic installation

Using the instructions in this topic, you will replace the Licensed Internal Code, Operating System/400, and licensed programs currently installed on your system with the V5R3 release.

The following topics pertain to the tasks for performing a software upgrade using automatic installation:

1. "Before you begin automatic installation"
2. "Replacing software using the automatic installation method" on page 57
3. "Verifying completion of automatic installation" on page 62

Before you begin automatic installation

Before you upgrade to a new OS/400 release, verify the following points.

Should you use this topic? Refer to "Supported releases for OS/400 upgrades" on page 18 to determine which releases are supported for upgrades to V5R3. Be familiar with the sequence of the steps you use to upgrade or replace a release on a server or logical partition as shown in Chapter 6, "Upgrading or replacing OS/400 and related software," on page 25.

Complete the preparation tasks in "Preparing to upgrade or replace software" on page 25 before you upgrade. It is required that you use the Prepare for Install options to accept online software agreements for the Licensed Internal Code and the OS/400 operating system for the upgrade to occur.

Also before upgrading to V5R3, you must use the Prepare for Install options to allocate additional space for the Licensed Internal Code.

If you are changing a primary language, you must be aware of additional considerations before you begin the installation. Be sure to read the topic "Globalization and software installation" on page 20. You cannot change your primary language to a language you currently have installed as a secondary language on your system. You must delete the secondary language first before you can change it to your primary language.

Verify your console information in the topic "Preparing your console for software installation" on page 51. You must verify that your console mode value is set correctly before you can upgrade to V5R3.

Do you plan to use an alternate installation device? If you are using an alternate installation device, ensure that the alternate installation device is enabled. See "Alternate installation device" on page 182 for information on setting up an alternate installation device. If you are not planning on using an alternate installation device and currently have one configured, you must clear the alternate installation device configuration information from the system before you install the new release.

If you plan to use an alternate IPL device within a logical partition on IBM @server^(R) 5xx models, refer to the Manage OS/400 logical partitions topic in the

IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 logical partitions**). For iSeries 8xx or earlier models, refer to the Manage logical partitions topic in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions**).

Do you plan to use or are you using logical partitions? For IBM eServer 5xx models, read the topic Plan for OS/400 partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 partitions**). For iSeries 8xx and earlier models, see Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**).

If you are installing software on a logical partition, the reference codes are viewable under the primary partition or the Hardware Management Console for eServer. For IBM eServer 5xx models, refer to Manage OS/400 partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 partitions**) for more information. For iSeries 8xx or earlier models, refer to Manage logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions**).

Do you plan to use an image catalog (virtual optical device) to install? Read the topic “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53 to create a device, an image catalog, and an image catalog entry.

Note: Information about upgrading from V5R1 to V5R3 is available through V5R1 PTF SI10553, Optical Support. This PTF contains specific instructions for using image catalogs and the virtual optical device.

To upgrade from V5R2 to V5R3 using an image catalog, do the following steps:

1. Load and apply the required V5R2 PTF SI10563.
2. Perform the setup steps in “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53. Perform step 6 on page 54 at least a day before you do the actual installation. This ensures that your installation media are ready to use.

Replacing software using the automatic installation method

The automatic installation process replaces all of the products that are currently installed and have been refreshed. To add new products, either use the Work with Licensed Programs menu (type G0 LICPGM) option 5 (Prepare for Install) before you perform these automatic installation procedures or use LICPGM menu option 11 (Install Licensed Programs) after the automatic installation. You might need to delete some products that you do not want after the installation has finished.

As you perform these steps, reference codes (also known as system reference codes or SRCs) appear on the data display of the control panel or virtual control panel of the primary partition or HMC. When the system attention light is on and a reference code starting with A6 appears, the system is waiting for you respond to a message or make a device ready. When this information lists a reference code with xx (such as A6xx 6001), it means that any combination of characters can occur where the xx appears. The console can also display reference codes during the installation of Licensed Internal Code. For more details about reference codes, refer to “Reference codes for software installation” on page 160.

Automatic installation

Before you upgrade, it is required that you use the Prepare for Install options to accept online software agreements for those licensed programs (including Licensed Internal Code and the OS/400 operating system) that you plan to install. You must also allocate additional space for Licensed Internal Code. These tasks are described in “Required: Accepting software agreements” on page 46 and “Required: Allocating additional space for Licensed Internal Code” on page 50. If these steps are not completed, the upgrade will not be completed.

1. Arrange the installation media that you plan to install in the following order (you might not have all of these):
 - a. I_BASE_01 Licensed Internal Code for OS/400
 - b. B29xx_01 Operating System/400
 - c. B29xx_02 OS/400 no-charge options
 - d. B29MM_03 OS/400 no-charge options
 - e. B29MM_04 OS/400 no-charge options
 - f. D29xx_01 OS/400 no-charge options
 - g. D29xx_02 OS/400 no-charge options
 - h. D29xx_03 OS/400 no-charge options
 - i. D29xx_04 OS/400 no-charge options
 - j. D29xx_05 OS/400 no-charge licensed programs
 - k. L29xx_01 priced licensed programs
 - l. L29xx_02 priced licensed programs
 - m. F29xx_01 single licensed programs

Keep the following installation media available for later use:

- a. N29xx_01 Secondary Language Media
- b. Cydddvrn_01 Cumulative PTF Package (if ordered)
- c. SK3T-4091 iSeries Information Center

For descriptions of the optical media, refer to “Media labels and their contents” on page 189.

2. If you are using an image catalog (virtual optical device) to install, perform this step at least a day before you do the actual installation.

Verify the status of the images in the image catalog. Type the following:

```
VFYIMGCLG IMGCLG(catalog-name) SORT(*YES)
```

A status message is shown. If this command fails, use the Work with Image Catalog Entries (WRKIMGCLGE) command to review the status of the images.

Note: Installations done by using an image catalog require a command line to initiate the installation.

3. Verify that your system unit is powered on. If your system unit is powered off, go to “Starting from a power-off condition” on page 160 and perform the procedure there. That procedure tells you when to return here.
4. On your console, ensure that you have a connection to the server.
5. Load the first volume of installation media that contains Licensed Internal Code into the installation device that is defined for the server. (If you are using IBM-supplied media, this volume is labeled I_BASE_01.) Throughout these procedures, load the next volume when prompted by the server. Wait for the In Use indicator to go out.
 - a. If you are using a tape device instead of an optical device, verify that the tape unit is varied on and allocated to your system.
 - b. If you are using a device that is enabled as an alternate installation device, you need to load the Licensed Internal Code media in your primary device and your installation media in your alternate installation device. Your

installation will fail if both media do not contain the same release level of Licensed Internal Code. For more information, see “Alternate installation device” on page 182.

6. Use the control panel to set the mode to **Normal**.

For logical partitions only
<p>Use the virtual control panel (Work with Partition Status display on your primary partition or partition status on systems with HMC) to set the mode to Normal. Also, make sure that you have already selected the alternate IPL device before performing the initial program load (IPL) in step 8.</p> <p>Notes:</p> <ol style="list-style-type: none"> 1. If you have not already set up an alternate IPL device for a logical partition, refer to online help information in IBM iSeries Navigator. 2. If you are using another method to select an alternate IPL device in a logical partition, refer to the topic “Overview: Alternate installation device” on page 182.

7. If you have not previously performed an IPL either to perform the tasks to allocate additional storage for the V5R3 Licensed Internal Code (required) or to change the disk configuration (optional), you must do this IPL now before you power down the server or logical partition.

Note: If you are not sure that additional space for the Licensed Internal Code has been allocated, follow the steps in “Required: Allocating additional space for Licensed Internal Code” on page 50. If additional space has been allocated, you will receive a message that the Licensed Internal Code has allocated the space on a previous IPL.

If you are using an image catalog to perform your upgrade and you performed the IPL in this step, you need to perform step 5 on page 54 and return here to the next step.

8. Power down the server or logical partition:
 - If you are upgrading from V5R1 to V5R3 and you are using an image catalog (virtual optical device) to install, use V5R1 PTF SI10553, Optical Support, and follow the instructions on the cover letter to perform the upgrade steps.
 - If you are upgrading from V5R2 to V5R3 and you are using a virtual optical device to install, ensure you have loaded and applied PTF SI10563. Then type the following:


```
PWRDWSYS OPTION(*IMMED) RESTART(*YES) IPLSRC(*IMGCLG)
IMGCLG(catalog-name)
```
 - If you are performing any other upgrade, type the following:


```
PWRDWSYS OPTION(*IMMED) RESTART(*YES) IPLSRC(D)
```

Note: If you have nonconfigured disk units present, performing this step configures disk units automatically by default. If you do not want nonconfigured disk units added, follow the directions in the topic “Installing optional PTF to choose disk configuration” on page 33.

Press Enter. Powering down could take approximately 15 minutes or more for this step. The data display area of the control panel continues to display reference codes.

Automatic installation

9. If you did not do the required preparation tasks for accepting software agreements or allocating additional space for Licensed Internal Code, you will see error messages. You need to follow the instructions on the display and then begin the installation again.
10. If the system attention light appears and one of the reference codes listed in “Reference codes for software installation” on page 160 appears in the data display on the control panel, complete the instructions for that reference code. If you have logical partitions, the reference codes appear in the primary partition or HMC.
11. If the Alternate Installation Device Failed display appears, there is an alternate installation device on the system that is enabled. Either it was not disabled before starting the installation, or the device is otherwise not ready. Do one of the following:
 - To continue the installation with optical media, press Enter.
 - To use the alternate installation device, make a note of the message at the bottom of the display.
Press F12 (Cancel). Reference code B608 1105 appears on the control panel. Use the “Common reference codes for software installation” on page 160 to determine how to continue.
12. If you are using optical media or tape for the upgrade, the Licensed Internal Code - Status display appears on your console. After 100% complete is reached, the console can appear blank for approximately 5 minutes and the IPL in Progress display might appear. You do not need to respond to these displays.

```
Install Licensed Internal Code - Status
Install of the Licensed Internal Code in progress.

Percent  +-----+
complete |                XX %                |
         +-----+

Elapsed time in minutes . . . . . :   x.x

Please wait.
```

If you are using an image catalog (virtual optical device) for the upgrade, you will see status messages that indicate the progress of the Licensed Internal Code installation:

- a. C6xx41DC is a status reference code that indicates the progress of the Licensed Internal Code decompression. The xx indicates the percent that is decompressed. No action is required.
 - b. C6xx41CC is a status reference code that indicates the progress of the Licensed Internal Code installation. The xx indicates the percent of the Licensed Internal Code that is installed. No action is required.
13. If you are using optical media or tape for the upgrade and an error occurs, you might see a display that requires a response. Perform the action necessary as prompted by the display.

If you are using an image catalog for the upgrade and an error occurs, see “Image catalog recovery” on page 146 for the recovery actions.

After a period of time (when the installation process starts to install the operating system), some displays appear on the console. One of the displays is called Licensed Internal Code IPL in Progress. Some of the IPL steps could

take a long time (up to two hours or longer), depending on how much data recovery is required for your system. The last message shown on the IPL in Progress display should be Start the Operating System.

- Load the next volume in sequence when the system prompts you for another volume.

Note: If the system does not prompt you or if you receive a Media command failed message, remove the I_BASE_01 volume and insert the B29xx_01 volume. Select option 1 (Attempt to install the operating system again) to continue with the installation.

You can be prompted for the next volume several times during the installation process.

- Status displays appear during the installation process. The installation status display shown here indicates how much of the installation is complete as well as how many stages remain. You do not need to respond to this status screen. The display is blank for a time between stage 4 and stage 5.

```

Message ID. . . : CPI2070                      OS/400 Installation Status

Stage 2  |-----+
          |                XX %                |
          |-----+

Installation
Stage          Completed      Objects
Restored

  1 Creating needed profiles and libraries . . . . . : X
>> 2 Restoring programs to library QSYS . . . . . :      XXXX
  3 Restoring language objects to library QSYS . . .
  4 Updating program table . . . . .
  5 Installing database files. . . . .
  6 Completing OS/400 installation . . . . .
    
```

If you are installing from tape and you receive a message Device QINDEV not ready, first make the device ready. Refer to step 5a on page 58. Then press Enter to continue.

- Status displays might appear. These displays show the status of the licensed programs and language objects as they install on the system. You do not need to respond to these status displays.

```

Installing Licensed Programs                      System: XXXX

Licensed programs processed . . . . . :      0 of XXX

Licensed program install in progress
    
```

The following display is an example of the display that appears during the installation process.

```

Installing Licensed Programs                      System: XXXX
Licensed programs processed . . . . . :      X of XXX

Licensed
Program  Option  Description                                     Type
5722SS1   2      OS/400 - Online Information                       2924
    
```

Automatic installation

This display shows which licensed programs and optional parts of licensed programs are being processed. After the *PGM objects and *LNG objects are processed, the display shows the total number of licensed programs processed.

17. The following message might appear when the server is ready for the next media volume that contains licensed programs. When you are installing from optical media, wait for the In Use indicator to go out before you respond to the message.

```
Display Messages
System: XXXX
Queue . . . . . : QSYSOPR      Program . . . . . : *DSPMSG
Library . . . . . : QSYS       Library . . . . . :
Severity . . . . . : 95        Delivery . . . . . : *BREAK

Type reply (if required), press Enter.
Load a valid volume containing licensed programs in optical device OPT01 (X G).
Reply . . . . G
```

Load the next media volume that contains licensed programs and continue the installation. Occasionally, you will be prompted to load the next volume after a short time has passed. This event usually happens when the licensed programs on the media are at the same level as the licensed programs already installed on your machine.

Type G and press Enter. After you load each volume, type G and press Enter. If there are no more volumes to load that contain licensed programs, or if you want to end the loading process, type X and press Enter.

18. The media has been read, and now the licensed programs are going through the installation process. Even though it might take a long time, wait for the Sign On display to appear. When the installation is successfully completed, the Sign On display appears. (There is no message that indicates automatic installation completed successfully. The Sign On display acts as the confirmation.)

If you receive the message Automatic installation not complete, sign on using QSECOFR for your user ID and go to Chapter 10, "Troubleshooting software installation problems," on page 143 to determine the problem.

Continue with Verifying completion of automatic installation.

Verifying completion of automatic installation

1. The Sign On display appears on the console after the installation has completed.

```
Sign On
System. . . . . : XXXX
Subsystem . . . . : XXXX
Display . . . . . : XXXXXXXX

User. . . . . : QSECOFR
Password . . . . . : _____
Program/procedure . . . . . : _____
Menu . . . . . : _____
Current library . . . . . : _____
```

Type the following and press Enter:

User: QSECOFR

Password: (Enter password, if required.)

2. The OS/400 Main Menu (or the menu you chose as your initial menu) appears on the console.
Type GO LICPGM and press Enter.
3. The Work with Licensed Programs display appears. Use the page down or roll up key to see the third display of the Work with Licensed Programs menu. The OS/400 Main Menu (or the menu you chose as your initial menu) appears on your console
Type 50 and press Enter.
4. The Display Install History display appears. The XX's indicate default values.

```

                Display Install History
Type choices, press enter.
Start date . . . . . XX/XX/XX  MM/DD/YY
Start time . . . . . XX:XX:XX  HH:MM:SS
Output . . . . . * _____ *, *PRINT
```

Press Enter.

5. Look at the messages that appear on the Display History Log Contents display.
 - If you had an installed licensed program that was not renewed by IBM, it might not be replaced. Refer to “Mixed-release environment” on page 17 for more information.
 - If any of the messages on the display indicate a failure or a licensed program that is partially installed, go to Chapter 10, “Troubleshooting software installation problems,” on page 143 to determine the problem.

Otherwise, press F3 (Exit).

6. Verify the installed status values of your licensed programs and check for compatibility. It is important to make sure all of your licensed programs are compatible with the operating system. You can determine a licensed program's compatibility by checking the installed status value.

Use LICPGM menu option 10 (Display licensed programs) to see the release and installed status values of the installed licensed programs. If the installed status value of a licensed program is *COMPATIBLE, it is ready for use. If the installed status value of a licensed program is *BACKLEVEL, the licensed program is installed, but its version, release, and modification is not compatible with the currently installed level of the OS/400 operating system.

Check the topic “Licensed program releases and sizes” on page 166 to verify the current version, release, and modification of the licensed program. “Installed status values” on page 197 lists the possible installed status value descriptions.

You have completed this task.

1. Do you need to install additional licensed programs?
 - **No.** Go to the next step.
 - **Yes.** Go to “Installing additional licensed programs” on page 114 and complete the instructions.
2. Do you need to install a secondary language?
 - **No.** Go to the next step.
 - **Yes.** Go to “Installing a secondary language” on page 121 and complete the instructions.

Automatic installation

3. You must complete the installation process before you put your system into operation. Go to “Checklist: Completing the upgrade or replacement” on page 81 and complete the instructions.

Upgrading or replacing software using manual installation

The instructions in this topic replace the Licensed Internal Code, Operating System/400, and licensed programs currently installed on your system with the V5R3 level.

You can also change the primary language on your system.

The following topics pertain to the tasks for performing a software upgrade using manual installation:

1. “Before you begin manual installation”
2. “Replacing the Licensed Internal Code” on page 65
3. “Replacing the operating system” on page 72
4. “Replacing the licensed programs” on page 77
5. “Verifying completion of manual installation” on page 80

Before you begin manual installation

Before you upgrade to a new OS/400 release, verify the following points.

Should you use this topic? Refer to “Supported releases for OS/400 upgrades” on page 18 to determine which releases are supported for upgrades to V5R3. Be familiar with the sequence of the steps you use to upgrade or replace a release on a server or logical partition as shown in Chapter 6, “Upgrading or replacing OS/400 and related software,” on page 25.

Complete the preparation tasks in “Preparing to upgrade or replace software” on page 25 before you upgrade. It is required that you use the Prepare for Install options to accept online software agreements for the Licensed Internal Code and the OS/400 operating system for the upgrade to occur.

Also before upgrading to V5R3, you must use the Prepare for Install options to allocate additional space for the Licensed Internal Code.

If you are changing a primary language, you must be aware of additional considerations before you begin the installation. Be sure to read the topic “Globalization and software installation” on page 20. You cannot change your primary language to a language you currently have installed as a secondary language on your system. You must delete the secondary language first before you can change it to your primary language.

Verify your console information in the topic “Preparing your console for software installation” on page 51. You must verify that your console mode value is set correctly before you can upgrade to V5R3.

Do you plan to use an alternate installation device? If you are using an alternate installation device, ensure that the alternate installation device is enabled. See “Alternate installation device” on page 182 for information on setting up an alternate installation device.

If you plan to use an alternate IPL device within a logical partition on IBM eServer^(R) 5xx models, refer to the Manage OS/400 logical partitions topic in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 logical partitions**). For iSeries 8xx or earlier models, refer to the Manage logical partitions topic in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions**).

Do you plan to use or are you using logical partitions? For IBM eServer 5xx models, read the topic Plan for OS/400 partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 partitions**). For iSeries 8xx and earlier models, see Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**).

If you are installing software on a logical partition, the reference codes are viewable under the primary partition or the Hardware Management Console for eServer. For IBM eServer 5xx models, refer to Manage OS/400 partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 partitions**) for more information. For iSeries 8xx or earlier models, refer to Manage logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions**).

Do you plan to use an image catalog (virtual optical device) to install? Read the topic, “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53 to create a device, image catalog, and an image catalog entry.

Note: Information about upgrading from V5R1 to V5R3 is available through V5R1 PTF SI10553, Optical Support. This PTF contains specific instructions for using image catalogs and the virtual optical device.

To upgrade from V5R2 to V5R3 using an image catalog, do the following steps:

1. Load and apply the required V5R2 PTF SI10563.
2. Perform the setup steps in “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53. Perform step 6 on page 54 at least a day before you do the actual installation. This ensures that your installation media are ready to use.

Replacing the Licensed Internal Code

As you perform these steps, reference codes appear on the data display of the control panel or the virtual control panel on the primary partition or Hardware Management Console (HMC). When the system attention light is on and a reference code starting with A6 appears, the system is waiting for you to respond to a message or make a device ready. When this information lists a reference code with xx (such as A6xx 6001), it means that any combination of characters can occur where the xx appears. The console can also display reference codes during the installation of Licensed Internal Code. For more details about reference codes, refer to “Reference codes for software installation” on page 160.

1. Arrange the installation media that you plan to install in the following order (you might not have all of these):
 - a. I_BASE_01 Licensed Internal Code for OS/400
 - b. B29xx_01 Operating System/400
 - c. B29xx_02 OS/400 no-charge options
 - d. B29MM_03 OS/400 no-charge options

Manual installation

- e. B29MM_04 OS/400 no-charge options
- f. D29xx_01 OS/400 no-charge options
- g. D29xx_02 OS/400 no-charge options
- h. D29xx_03 OS/400 no-charge options
- i. D29xx_04 OS/400 no-charge options
- j. D29xx_05 OS/400 no-charge licensed programs
- k. L29xx_01 priced licensed programs
- l. L29xx_02 priced licensed programs
- m. F29xx_01 single licensed programs

Keep the following installation media available for later use:

- a. N29xx_01 Secondary Language Media
- b. Cydddvrn_01 Cumulative PTF Package (if ordered)
- c. SK3T-4091 iSeries Information Center

For descriptions of the optical media, refer to “Media labels and their contents” on page 189.

2. If you are using an image catalog (virtual optical device) to install, perform this step at least a day before you do the actual installation. Verify the status of the images in the image catalog. Type the following:

```
VFYIMGCLG IMGCLG(catalog-name) SORT(*YES)
```

A status message is shown. If this command fails, use the Work with Image Catalog Entries (WRKIMGCLGE) command to review the status of the images.

Note: Installations done by using an image catalog require a command line to initiate the installation.

3. If you have not previously performed an IPL either to perform the tasks to allocate additional storage for the V5R3 Licensed Internal Code (required) or to change the disk configuration (optional), you must do this IPL now before you power down the server or logical partition.

Note: If you are not sure that additional space for the Licensed Internal Code has been allocated, follow the steps in “Required: Allocating additional space for Licensed Internal Code” on page 50. If additional space has been allocated, you receive a message that the Licensed Internal Code has allocated the space on a previous IPL.

If you are using an image catalog to perform your upgrade and you performed the IPL in this step, you need to perform step 5 on page 54 and return here to the next step.

4. Verify that your system unit is powered on. If your system unit is not powered on, go to “Starting from a power-off condition” on page 160 and perform the procedure there. That procedure tells you when to return here.
5. On your console, ensure that you have a connection to the server. If you are working on a logical partition, ensure that power is on for the console of that logical partition.
6. If you are upgrading a logical partition, verify that this partition has an alternate initial program load (IPL) resource assigned. For most cases, this is the optical device that supports the optical media class.

For more information, use the following sources to locate and select the alternate IPL resource:

- For IBM eServer 5xx models, Managing OS/400 logical partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Managing OS/400 logical partitions**).
 - For iSeries 8xx and earlier models, Manage logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions**).
7. Load the first volume of installation media that contains Licensed Internal Code into the installation device that is defined for the server. (If you are using IBM-supplied media, this volume is labeled I_BASE_01.) Throughout these procedures, load the next volume when prompted by the server. Wait for the In Use indicator to go out.
 - a. If you are using a tape device instead of an optical device, verify that the tape unit is varied on and allocated to your system.
 - b. If you are using a device that is enabled as an alternate installation device, you need to load the Licensed Internal Code media in your primary device and your installation media in your alternate installation device. Your installation will fail if both media do not contain the same release level of Licensed Internal Code. For more information, see “Alternate installation device” on page 182.
 8. Use the control panel to set the mode selection to **Manual**. If you are upgrading a logical partition, use the virtual control panel function of your primary partition or HMC. Also make sure that you have already selected the alternate IPL device before you perform the initial program load (IPL) in the next step.
 9. Power down the server or logical partition:
 - If you are upgrading from V5R1 to V5R3 and you are using an image catalog (virtual optical device) to do the upgrade, use V5R1 PTF SI10553, Optical Support, and follow the instructions on the cover letter to perform the upgrade steps.
 - If you are upgrading from V5R2 to V5R3 and you are using a virtual optical device to do the upgrade, ensure you have loaded and applied PTF SI10563. Then type the following and press Enter:


```
PWRDWN SYS OPTION(*IMMED) RESTART(*YES) IPLSRC(*IMGCLG)
  IMGCLG(catalog-name)
```
 - If you are performing any other upgrade, type the following and press Enter:



```
PWRDWN SYS OPTION(*IMMED) RESTART(*YES) IPLSRC(D)
```

Powering down could take approximately 15 minutes or more for this step. The data display area of the control panel continues to display reference codes.

10. If the system attention light appears and a reference code listed in the topic “Reference codes for software installation” on page 160 appears in the data display on the control panel, complete the instructions for that reference code. If you are upgrading a logical partition, the system attention light will not appear. You must monitor the logical partition reference codes from the primary partition or the HMC. When the State changes to Failed, that is the equivalent of having the attention light on for the primary partition.
11. If you are using an image catalog (virtual optical device) to install, go to step 19 on page 71.
12. The Select a Language Group display shows the primary language that is currently installed on the system.

Manual installation

Note: The installation media for Licensed Internal Code is now language-independent. It is important that you complete this step carefully.



To keep the same primary language, verify that the displayed language feature matches the feature that is printed on the media that contains the operating system. The operating system media are labeled B29xx_nn, where 29xx indicates the feature for the primary language.


Note: The language you select and the language of the OS/400 must match. If they do not match, do not continue with the upgrade. Stop and call your software provider. Get the correct language feature before continuing.

Refer to “Feature codes for national language version” on page 195 for a list of the language feature codes.

To change the primary language, type the language feature that appears on the media that contains the operating system.


Press Enter.

13. After you enter the language feature, the Confirm Language Group display appears.



Press Enter.

14. The Install Licensed Internal Code display appears.



Either select the option to install Licensed Internal Code or the option to define an alternate installation device:

- If you are not using an alternate installation device, type 1 (Install Licensed Internal Code). (The alternate installation device function supports installation from optical or tape media that you have created. “Overview: Alternate installation device” on page 182 describes when you can use an alternate installation device.)
- If you have an alternate installation device attached to the system, type 3 to verify its address and determine whether it is enabled or disabled. Continue with the Verifying Alternate Installation Device Subtask in step 16. If you have an alternate installation device configured and do not want to use it, type 3 to clear the alternate installation device configuration information. If you are not using an alternate installation device, go on to step 18 on page 70.

Press Enter.

15. If you did not do the required preparation tasks for accepting software agreements or allocating additional space for Licensed Internal Code, you will see error messages. You need to follow the instructions on the display and then begin the installation again.
16. **Verifying and selecting alternate installation device subtask:** The Select Alternate Installation Device Bus display appears.

Select Alternate Installation Device Bus			System: XXXX
Type Option, press Enter.			
1=Select			
Option	Bus Number	Selected	
-	1		
-	2		
<u>1</u>	3	*	
-	4		
-	5		
-	6		
-	7		
-	8		
-	9		
-	A		
-	B		
-	C		
-	D		
F2=Deselect Device F3=Exit F12=Cancel			More.....

- a. Verify that the selected device is on the correct system bus. Type 1 in the Options field next to the selected bus, and press Enter to view information about the device that is attached to the bus. This might take several minutes. If you see the message No alternate installation device configured, wait one minute and refresh the display.
- b. When the Select Media Type display appears, select 1 for tape or 2 for optical media. Press Enter.
- c. The Select Alternate Installation Device display appears. Use this display to verify the resource name, type, model, and serial number for the device. The following display shows an example of a tape device.

Manual installation

```

                                Select Alternate Installation Device
                                System:  SYSTEMA

Additional devices may be available for use.  Press F5 to see
if any additional devices have been detected.

Type option, press Enter.
1=Select  5=Display details

   Bus      Resource
Option  Number  Name      Type  Model  Serial      Selected
-      -      -
   1      1      TAP08    6386  001    00-11111
   3      3      TAP19    3570  B11    13-22222      *

F2=Deselect device  F3=Exit  F5=Refresh  F12=Cancel

```

- d. Type 1 to select the device and make any needed corrections to select, enable, or disable the device. Press Enter to confirm the changes.
- e. The message Alternate installation device selected appears. Press F3 to return to the Install Licensed Internal Code display.
- f. Type 1 and press Enter to install the Licensed Internal Code.

This completes the subtask for verifying and selecting alternate installation device.

- 17. If there is an alternate installation device defined and enabled, the Confirm Alternate Installation Device display appears.
 - To install from the alternate installation device, press Enter.
 - To install from optical media, press F12 to Cancel. You see the Licensed Internal Code display. Perform step 14 on page 68 and select option 3 (Define alternate installation device). Perform step 16 on page 69 and disable the alternate installation device.
- 18. The Install Licensed Internal Code (LIC) display appears on your console.

```

                                Install Licensed Internal Code (LIC)

Disk selected to write the Licensed Internal Code to:
Serial Number  Type  Model  I/O Bus  Controller  Device
xx-xxxxxxx    xxxx  xxx    x        x          x

Select one of the following:

1. Restore Licensed Internal Code
2. Install Licensed Internal Code and Initialize system
3. Install Licensed Internal Code and Recover Configuration
4. Install Licensed Internal Code and Restore Disk Unit Data
5. Install Licensed Internal Code and Upgrade Load Source


```

Attention: Be sure to select option 1. Some options on this display remove all data from your system.

Type 1 (Restore Licensed Internal Code) and press Enter.


If you did not previously accept the software agreement for the Licensed Internal Code or did not allocate additional space for the Licensed Internal Code, error messages are shown. Follow the instructions in the error messages. More information is in the topics “Required: Allocating additional space for Licensed Internal Code” on page 50 and “Required: Accepting software agreements” on page 46.

19. The Install Licensed Internal Code - Status display appears on your console. You do not need to respond to this display. It remains on your console for up to 30 minutes.



If you are using an image catalog (virtual optical device) for the upgrade, you will see status messages that indicate the progress of the Licensed Internal Code installation:

- a. C6xx41DC is a status reference code that indicates the progress of the Licensed Internal Code decompression. The xx indicates the percent that is decompressed. No action is required.
 - b. C6xx41CC is a status reference code that indicates the progress of the Licensed Internal Code installation. The xx indicates the percent of the Licensed Internal Code that is installed. No action is required.
20. If you are using optical media or tape for the upgrade and an error occurs, you might see a display that requires a response. Perform the action necessary as prompted by the display. If you are using an image catalog for the upgrade and an error occurs, see “Image catalog recovery” on page 146 for the recovery actions.
 21. The Disk Configuration Attention Report display might appear. If it does, display the detailed report for each problem shown on the display. Press the Help key from the Disk Configuration Attention Report display for more information about your choices. You can also refer to the topic “Disk configuration warning and error messages” on page 158.



If the problem Disk unit not formatted for optimal performance appears on this display, do the following:

- Type 5, and press Enter to display the detailed report.

Manual installation

- Write down the information displayed. After the upgrade is completed, you will need this information to format these disk units to gain optimal performance.
 - Press F12 to cancel and return to the Disk Unit Attention Report.
 - Press F10 to accept the problems and continue the IPL.
22. If the console mode value is zero, the Accept Console display appears. If this display appears, follow these steps:
 - a. Press F10 to accept the current console type. The Accept and Set New Console Type on this IPL display appears. The old value (zero) and the new value to be set (your current console type) are shown.
 - b. Press Enter to set the new value and continue with these instructions.
 23. If your system processor configuration has changed, you could see other displays at this point. After you supply the requested information, the installation continues and the IPL or Install the System display appears. Refer to “System password” on page 197 for more information.
 24. After approximately 10 minutes, the IPL or Install the System display appears. The Licensed Internal Code is now installed. Do not remove the distribution media at this time.
 25. If the Accept Console display in step 22 did not appear, set the console mode for this partition:
 - a. At the IPL or Install the system display, select option 3 to access Dedicated Service Tools (DST).
 - b. Sign on as security officer (QSECOFR user profile / QSECOFR password). When prompted, change the password to what you want to use for this partition.
 - c. Select option 5 (Work with DST environment).
 - d. Select option 2 (System devices).
 - e. Select option 6 (Console mode).
 - f. Select the valid console that you have for this partition. Press Enter and then press F3 to return to the DST main menu.

Note: If you are using Operations Console (LAN) as your console type, press Enter on the verify window. You can also press F11 to review your network configuration.
 - g. Press F3 to exit DST and return to the IPL or Install the System display.

Continue with “Replacing the operating system.”

Replacing the operating system

1. The IPL or Install the System menu appears on your console.

```
                                IPL or Install the System
                                System: XXXX


Select one of the following:

    1. Perform an IPL
    2. Install the operating system
    3. Use Dedicated Service Tools (DST)
    4. Perform automatic installation of the operating system
    5. Save Licensed Internal Code
```


Load the first volume of installation media that contains OS/400. (If you are using IBM-supplied media, this volume is labeled B29xx_01, where 29xx is the

identifier for the primary language.) Throughout these procedures, load the next volume when prompted by the server. When you are installing from optical media, wait until the In Use indicator goes out before you continue.

After you install the new release over your previous release (V5R1 or V5R2), passwords for all service tools user profiles that still use the default password expire automatically. When you try to log on or access service tools using those profiles, you receive a message that the password has expired and must be changed. Follow the prompts or press the appropriate key (F9) to change the password for that user profile. For more information on service tools user


profiles, see [Tips and Tools for Securing Your iSeries](#) .

2. Type 2 (Install the operating system) and press Enter. The Install Device Type Selection display appears.



Type the number that corresponds to your device type and press Enter.


3. The Select a Language Group display appears, which shows the primary language currently installed on the system. The primary language value should match the language feature number that is printed on the installation media. To find the appropriate feature code for your language, refer to “Feature codes for national language version” on page 195.



If you need to change the feature, type the numbers of the feature code for the language you want.

Press Enter.


4. The Confirm Install of OS/400 display is shown on your console. Press Enter.
5. If the Add All Disk Units to the System menu does not appear, go to step 7 on page 76.
6. **Adding disk units subtask:**
 - a. If any nonconfigured disk units that are capable of being protected by device parity are currently unprotected, the Add All Disk Units to the System display is shown. If the following display is not shown, continue with step 6b on page 74.



It is much faster to start device parity protection on the disk units at DST before the disk units are added to the auxiliary storage pool configuration.


To start device parity on the eligible disk units, do the following tasks from the Add All Disk Units to the System display:

- 1) Select option 2 to perform disk configuration at DST.
 - 2) Sign on at the Dedicated Service Tools Sign-on prompt and return to the Use Dedicated Service Tools (DST) menu.
 - 3) Select the option Work with disk units.
 - 4) Select the option Work with disk configuration.
 - 5) Section the option Work with device parity protection.
 - 6) Select the option Start device parity protection.
 - 7) A list of parity sets that are capable of running device parity protection are shown. Type 1 on each option line for each parity set.
 - 8) You might see a Confirm Continuation display that indicates that the server must perform a directory recovery. Press Enter to continue.
 - 9) The Confirm Starting Device Parity Protection display is shown. This shows the list of disk units that will have device parity protection. Press Enter to continue.
 - 10) An in-progress display that indicates the status of the function is shown.
 - 11) Return to the IPL or Install the System display.
- b. If the Add All Disk Units to the System menu appears, it could look like the following example.



If you do not want device parity protection, mirrored protection, or user ASPs, select option 3 (Add all disk units to the system auxiliary storage pool). By adding disk units before you install the operating system, you improve your overall system performance because the operating system is distributed across all of your disk units.

For logical partitions only

If you will be creating logical partitions later, you do not want to configure all units now. Refer to the validated output from the Logical Partition Validation Tool (LVT) supplied by IBM for the configuration selection. To access the tool, go to the Logical Partitioning Web site  (<http://www.ibm.com/eserver/series/lpar>).

Note: If either the Disk Configuration Error Report display or the Disk Configuration Warning Report display appears, go to “Disk configuration warning and error messages” on page 158 to determine the appropriate action.

- c. You could see the following display if your disk configuration has changed. Type 5 next to the problem and press Enter to display the detailed report.

Problem Report

Note: Some action for the problems listed below may need to be taken. Please select a problem to display more detailed information about the problem and to see what possible action may be taken to correct the problem.

Type option, press Enter.
5=Display Detailed Report

OPT	Problem
-	_____
-	_____

- d. If the following display appears, a disk unit that you selected to add to your disk configuration could already have data on it. If you choose to continue, any data that is on the disk units listed will be removed. Be certain that you want to configure the disk before you continue. Follow the instructions on the display. Press Enter to return to the Problem Report display. Press F10 to continue the Add Disk Unit subtask.

Possibly Configured Units

Problem: These non-configured units appear to be configured units of some other disk configuration and may contain valid data. This option will clear the data from these units and destroy the other disk configuration.

Press Enter to continue
Press F12=Cancel to return and change your choices.

Serial Number	Type	Model	Resource Name	Other System Serial Number
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____
_____	_____	_____	_____	_____

More..

F3=Exit F12=Cancel

- e. The following display shows the percentage of disk units added. This display does not require a response.

Manual installation

```

                                Function Status
You selected to add units.

                                ___ % Complete
  
```

- f. When the process completes, continue the manual installation process with the next step.

This completes the subtask for adding disk units.

- 7. Status displays are displayed on the console. You do not need to respond to these status displays. Some of the IPL steps might take a long time. The time varies depending on how much data recovery is required for your system.
- 8. The Install the Operating System display appears when the IPL for the Licensed Internal Code completes. The XX's in the following display indicate default date and time values.

```

                                Install the Operating System
Type options, press Enter.

Install
option . . . . . 1           1=Take defaults (No other
                                options are displayed)
                                2=Change install options

Date:
Year . . . . . XX           00-99
Month . . . . . XX          01-12
Day . . . . . XX           01-31

Time:
Hour . . . . . XX           00-23
Minute . . . . . XX         00-59
Second . . . . . XX         00-59
  
```

Type the following and press Enter:

- Install option 1
- Date: (Use the current year, month, and day.)
- Time: (Use the current time, 24-hour clock.)

- 9. Status messages are displayed during the installation process. You do not need to respond to these displays. The following is an example of a status display. This display might be present for 2 hours or more. The display is blank for a time between stage 4 and stage 5.

```

Message ID. . . . : CPI2070           OS/400 Installation Status

Stage 2  +-----+
          |                XX %                |
          +-----+

Installation
Stage           Completed      Objects
Restored

  1 Creating needed profiles and libraries . . . . : X
>> 2 Restoring programs to library QSYS . . . . . :      XXXXX
  3 Restoring language objects to library QSYS . . :
  4 Updating program table . . . . . :
  5 Installing database files. . . . . :
  6 Completing OS/400 installation . . . . . :
  
```

- After the operating system has been replaced, the Sign On display appears on your console.

Continue with Replacing the licensed programs.

Replacing the licensed programs

- Begin this task at the Sign On display.

```

Sign On
System. . . . . : XXXX
Subsystem . . . . : XXXX
Display . . . . . : XXXXXXXX

User. . . . . QSECOFR
Password . . . . .
Program/procedure . . . . .
Menu . . . . .
Current library . . . . .
    
```

Type the following and press Enter:

User: QSECOFR

Password: (Enter password, if required.)

- The IPL Options display appears.

```

IPL Options

Type choices, press Enter.

System date . . . . . XX / XX / XX      MM / DD / YY
System time . . . . . XX : XX : XX      HH : MM : SS
System time zone . . . . . Q0000UTC      F4 for list
Clear job queues. . . . . N              Y=Yes, N=No
Clear output queues . . . . . N          Y=Yes, N=No
Clear incomplete job logs . . . . . N    Y=Yes, N=No
Start print writers . . . . . Y          Y=Yes, N=No
Start system to restricted state . . . . N  Y=Yes, N=No

Set major system options. . . . . N      Y=Yes, N=No
Define or change system at IPL. . . . . N  Y=Yes, N=No

Last power-down operation was ABNORMAL
    
```

Notes:

- Ignore the message on the bottom of the IPL Options display.
- If you need to change system values, you can do so now. One example of a system value that you might change is the value for the security level (QSECURITY) system value.

Another example is the scan control (QSCANFCTL) system value. Consider specifying *NOPOSTRST for the QSCANFCTL system value to minimize future scanning of some objects that are restored during the installation of licensed programs in the following steps. For more information on scanning and the system value settings, see the topic Scanning support in the iSeries Information Center (**Files and file systems > Integrated file system > Concepts > Scanning support**).

Type Y for the *Define or change the system at IPL* prompt. Follow the instructions on the displays.

Type the following and press Enter:

System date: (Use the current date.)

Manual installation

System time: (Use the current time, 24-hour clock.)

System time zone: (Verify that it is correct or press F4 to select a time zone.)

Set major system options: N

3. The Edit Rebuild of Access Paths display could be shown. If it is, press Enter to continue.

4. Additional display messages could be shown.

Press Enter after each message to continue.

5. The OS/400 Main Menu (or the menu you chose as an initial menu) appears on your console.

Do the following to put the system in a restricted state and filter the messages that appear:

a. Type CHGMSGQ QSYSOPR *BREAK SEV(60) and press Enter.

b. A message display could appear. Press Enter.

c. Type ENDSBS *ALL *IMMED and press Enter.

d. When the following message appears, press Enter to continue:

```
ENDSBS SBS(*ALL) command being processed
```

e. The message System ended to restricted condition appears. Press Enter to continue.

f. Type CHGMSGQ QSYSOPR SEV(95) and press Enter.

g. A message display could appear. Press Enter.

6. The OS/400 Main Menu (or the menu you chose as an initial menu) appears on your console.

Type GO LICPGM and press Enter.

7. The Work with Licensed Programs display appears.

```
LICPGM                      Work with Licensed Programs                System:  XXXX
Select one of the following:
Manual Install
  1. Install all
```

Type 1, and press Enter.

8. The Manual Install display appears.

```
Manual Install                      System:  XXXX
Type choices, press Enter.
Install option . . .  1           1=Installed products
                                   2=All products
                                   3=New products
Installation device  OPT01       Name
Replace if current   N           Y=Yes
                                   N=No
Nonaccepted agreement 2         1=Do not install licensed program
                                   2=Display software agreement
Automatic IPL . . .  N           Y=Yes
                                   N=No
```

Type the following and press Enter:

Install option: 1

Installation device: OPT01 (See notes that follow.)
 Replace if current: N
 Nonaccepted agreement: 2 (See note that follows.)
 Automatic IPL: N

Note:

- If you created a customized installation list, select install option 4 (Installed and additionally selected products). This option only appears if you used the LICPGM menu option to Prepare for Install, which is described in “Required: Creating a custom list of software to install” on page 42.
- In this example, the installation device is OPT01. If you are using a different naming convention, use the name you have assigned to the installation device.
- If you are using your own distribution media, select 2 for the *Install option* field. For the *Replace if current* field, type Y.
- If you have not previously accepted software agreements for licensed programs that you plan to install, option 2 displays the software agreements for acceptance as each licensed program is installed. This will increase the length of your installation time. If you want to accept the software agreements now, go to step 5 on page 116 and then return here.

9. Status displays might appear. These displays show the status of the licensed programs and language objects as they install on the system. You do not need to respond to these status displays.

```

                Installing Licensed Programs
                                     System: XXXX

Licensed programs processed . . . . . :    0 of XXX

                Licensed program install in progress
```

The following display is an example of the display that appears during the installation process.

```

                Installing Licensed Programs
                                     System: XXXX

Licensed programs processed . . . . . :    X of XXX

Licensed
Program  Option  Description
5722SS1    2    OS/400 - Online Information
                                     Type
                                     2924
```

This display shows which licensed programs and optional parts of licensed programs are being processed. After the *PGM objects and *LNG objects are processed, the display shows the total number of licensed programs processed.

10. If a message similar to the following appears, load the next media volume that contains licensed program products, and continue the installation. When you are installing from optical media, wait for the In Use indicator to go out before you respond to the message.

Manual installation

```
Display Messages
System: XXXX
Queue . . . . . : QSYSOPR      Program . . . . . : *DSPMSG
Library . . . . . : QSYS        Library . . . . . :
Severity . . . . . : 95         Delivery . . . . . : *BREAK

Type reply (if required), press Enter.
Load the next volume in optical device OPT01 (X G)
Reply . . . . . G
```

Type G and press Enter.

After you load each volume, type G and press Enter. If there are no more volumes to load that contain licensed programs, or if you want to end the loading process, type X and press Enter.

11. If a licensed program requires acceptance of a software agreement, the Software Agreements display appears. Do either of the following:
 - Press F14 to accept the agreement and allow the licensed program to continue installing.
 - Press F16 to decline the agreement and end the installation of that licensed program.
12. The Work with Licensed Programs display appears on your console when the installation process is completed. One of the following messages appears on the bottom of the Work with Licensed Programs display:
 - Work with licensed programs function has completed.
 - Work with licensed programs function not complete.

For either message, continue with Verifying completion of manual installation.

Verifying completion of manual installation

1. The Work with Licensed Programs display appears. Use the page down or roll up key to see the third display of the Work with Licensed Programs menu. Type 50 and press Enter.
2. The Display Install History display appears. The XX's indicate default values.

```
Display Install History
Type choices, press enter.
Start date . . . . . XX/XX/XX MM/DD/YY
Start time . . . . . XX:XX:XX HH:MM:SS
Output . . . . . * _____ *, *PRINT
```

Press Enter.

3. Look at the messages that appear on the Display History Log Contents display.
 - If you had an installed licensed program that was not renewed by IBM, it might not be replaced. Refer to “Mixed-release environment” on page 17 for more information.
 - If any of the messages on the display indicate a failure or a licensed program that is partially installed, go to Chapter 10, “Troubleshooting software installation problems,” on page 143 to determine the problem.

Otherwise, press F3 (Exit).

4. Verify the installed status values of your licensed programs and check for compatibility. It is important to make sure that all of your licensed programs are compatible with the operating system.

Use LICPGM menu option 10 (Display licensed programs) to see the release and installed status values of the installed licensed programs. If the installed status value of a licensed program is *COMPATIBLE, it is ready for use. If the installed status value of a licensed program is *BACKLEVEL, the licensed program is installed, but its version, release, and modification is not compatible with the currently installed level of the OS/400 operating system. Check the topic “Licensed program releases and sizes” on page 166 to verify the current version, release, and modification of the licensed program. “Installed status values” on page 197 lists the possible installed status value descriptions.

You have completed this task.

1. Do you need to install additional licensed programs?
 - **No.** Go to the next step.
 - **Yes.** Go to “Installing additional licensed programs” on page 114 and complete the instructions.
2. Do you need to install a secondary language?
 - **No.** Go to the next step.
 - **Yes.** Go to “Installing a secondary language” on page 121 and complete the instructions.
3. You must complete the installation process before you put your system into operation. Go to “Checklist: Completing the upgrade or replacement” and complete the instructions.

Checklist: Completing the upgrade or replacement

Use this checklist to complete any of the OS/400 upgrade or replacement processes.

- ___ 1. If you still have default passwords for your service tools user IDs, you need to change them now. For information on service tools user IDs, see Change service tools user IDs and passwords in the iSeries Information Center (**Security > Service tools user IDs and passwords > Manage service tools > Manage service tools user IDs > Change service tools user IDs and passwords**).
- ___ 2. Remove the media volume when the installation is complete. If your media is tape, wait for the tape to rewind completely.
- ___ 3. If you have any IBM or non-IBM products with special installation instructions, install these products now. Check the product’s documentation, and follow the special instructions there. Otherwise, continue with the next step.
- ___ 4.

For logical partitions only

<p>Attention: Do not perform this step to install the cumulative PTF package until after you are aware of the unique PTF installation considerations involved on a server with logical partitions. You could potentially lose data. Refer to the topic Install fixes on systems with logical partitions in the iSeries Information Center (OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Install fixes > Step 3: Choose your fix installation scenario > Install fixes on systems with logical partitions) to understand how to install the cumulative PTF package on a system with logical partitions.</p>

Checklist: Completing the upgrade or replacement

Install the most current cumulative PTF package. (This package should have been ordered a week or two before your installation.) Use the instructions in the *PTF Shipping Information Letter*. Then return here and continue with the next step.

Note: If you do not install the cumulative PTF package now, you need to perform an IPL and let the Initialize System (INZSYS) process complete. Before you do, set the IPL type to **B** (or the IPL type you use for everyday operation) and then set the mode selection to **Normal**. “Initialize System (INZSYS) recovery” on page 157 has more information on INZSYS.

- 5. Apply any PTF groups that you have ordered. For more information on PTF groups, refer to “Ensuring you have required software PTFs (fixes)” on page 31. To apply PTF groups, refer to the cover letter and instructions for the program temporary fix (PTF). For general information on applying PTFs, go to Advanced procedures for fix installation in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Install fixes > Advanced procedures for fix installation**).
- 6. If your system is operating as a service partition and your server is not being managed by a Hardware Management Console for @server^(R), you might be required to perform a server IPL. A *server IPL* is an IPL whereby all logical partitions on the server are shut down at the same time. This allows, for example, a new level of the server firmware to be activated on the server.

You might be required to perform a server IPL after you apply or remove a PTF on the service partition if that PTF affects the server firmware portion of the Licensed Internal Code. You also might be required to perform a server IPL after you upgrade or install a new level of the Licensed Internal Code on the service partition.

To find out if you need to do a server IPL, type DSPPTF 5722999 on the command line and press Enter. If a server IPL is required, message CPD35F8 Server IPL required is shown at the bottom of the display.

To find out if your system is operating as a service partition, type DSPPTF 5729999 on the command line and press Enter. If your system is operating as a service partition, the IPL Source field indicates the copy of the server firmware that was used on the previous server IPL.

- 7. Look for messages in the install history log that indicate the status of the Initialize System (INZSYS) process:
 - a. Type G0 LICPGM and press Enter.
 - b. Type 50 (Display log) on the Work with Licensed Programs display, and press Enter.
 - c. The Display Install History display appears. Press Enter.

The Display History Log Contents display appears. If you do not see either of the following messages on the display, wait a few minutes and select option 50 again. Find the message Initialize System (INZSYS) started. After this message appears, wait for a period of time and look for the Initialize System (INZSYS) processing completed successfully message (CPC37A9). If you do not see message CPC37A9 on the display, go to “Initialize System (INZSYS) recovery” on page 157 to determine the problem.

Checklist: Completing the upgrade or replacement

- ___ 8. If you used image catalogs to perform your installation, you might want to remove all installation images from your server. To delete the catalog and all the optical images (image files), type the following:

```
DLTIMGCLG IMGCLG(mycatalog) KEEP(*NO)
```
- ___ 9. Install software license keys for your OS/400 and keyed products. Use the Work with License Information (WRKLICINF) command to display the installed keyed products to add license key data. For specific instructions, go to Add license key information in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Work with software agreements and licenses > Manage software agreements and license keys > Display and change software license information > Add license key information**).
After updating the license key information, return here and continue with the next step.
- ___ 10. After you complete the installation process and before you make a server or partition available to all users, you must set the usage limit for the software-license managed products. These products are listed on the Proof of Entitlement (POE), invoice, or other documents that you have received with your software order. For products that have a usage limit, you set the usage limit with the Work with License Information (WRKLICINF) command.
To set your usage limit, do the following:
 - ___ a. Type WRKLICINF and press Enter.
 - ___ b. On the Work with License Information display, press F11 (Display Usage Information). The usage limit number on each product that is listed on the POE, invoice, or other documents must match the usage limit number on the Work with License Information display for the associated product.
 - ___ c. If the usage limit is to be updated, move the cursor to the line that contains the product name whose usage limit is to be updated.
 - ___ d. Type 2 (Change) and press Enter.
 - ___ e. When the Change License Information display is shown, update the usage limit prompt with the usage limit shown on the POE. In addition, update the threshold prompt with either *CALC or *USGLMT. Do not leave the threshold set to zero.


Note: If message CPA9E1B [Usage limit increase must be authorized. Press help before replying (C G).] is sent, respond by typing G.
 - ___ f. If the POE lists more products than the Work with License Information display, set the usage limits after you install those products.
- ___ 11. If you deleted any licensed program libraries or secondary language libraries from either of the library list system values [system library list (QSYSLIBL) or user library list (QUSRLIBL)], you can change system values QSYSLIBL or QUSRLIBL to add the libraries back in the library list now.
- ___ 12. If you changed the verify object signatures during restore (QVFYOBJRST) system value from 4 or 5 to 3 before your upgrade, you now can change this back to either 4 or 5. If you changed the allow restore of security sensitive objects (QALWOBJRST) system value to *ALL or had unlocked it before the upgrade, you now can return the value to its normal locked setting.

Checklist: Completing the upgrade or replacement

- ___ 13. If you changed the scan control (QSCANFSCCTL) system value to minimize future scanning of some objects that are restored before you installed your licensed programs, you can now remove the *NOPOSTRST specification from this system value.
- ___ 14. If you changed any other system value such as security level (QSECURITY) during your upgrade, you can change it back now.
- ___ 15. Some of the tasks in this topic require that you change the QSYSOPR severity code filter to 95. If you do not want to continue with this level or you want to change the delivery notification, type CHGMSGQ QSYSOPR DLVRY(xx) SEV(yy) where *xx* indicates the delivery notification and *yy* indicates the severity code that you want to use. The system defaults are DLVRY(*HOLD) SEV(0).
- ___ 16. If you have iSeries Integration for Windows Server, 5722-WSV, currently installed and you want to upgrade it to the current iSeries release, vary the server on and determine if an upgrade to the latest iSeries release is necessary. Refer to the information center topic, *Install and configure Windows environment on iSeries* (**Integrated operating environments > Windows environment on iSeries > Install and configure Windows environment on iSeries**).
- ___ 17. If you have installed the product 5722-VI1, Content Manager, you can use the product. However, you must perform post-installation commands. For more information, refer to the Post Installation section in the product document *IBM ImagePlus® VisualInfo™ for AS/400: Planning and Installation Guide*, GC34-4585 (V4R5 or earlier).
- ___ 18. If you have not already verified the compatibility of your licensed programs with the OS/400, then do this now. Use LICPGM menu option 10, Display installed licensed programs. If *COMPATIBLE is not listed next to a licensed program, then go to “Installed status values” on page 197 and determine how to proceed.
- ___ 19. Save your system using your normal save procedures. Refer to the instructions in the Back up your server topic in the iSeries Information Center (**Systems management > Backup and recovery > Back up your server**). Make sure that the Initialize System (INZSYS) process is complete before you save your system.

Note: Before you start a save operation, use the Work with Active Jobs (WRKACTJOB) command to check the status of QDCPOBJx jobs. These jobs decompress objects. There could be more than one QDCPOBJx job. You can start your save operation if these jobs are in an inactive state. If you put the system in a restricted state by ending subsystems, the QDCPOBJx jobs become inactive. The jobs will restart when the system is not in a restricted state. For more information about decompressing objects, see “Compressed objects and storage space” on page 20.
- ___ 20. If you plan to install and use the iSeries Information Center either from a workstation or the server, refer to the CD-ROMs that come with your IBM Operating System/400 order: *iSeries Information Center*, SK3T-4091. This package also includes the PDF versions of iSeries manuals. For the installation instructions, see the readme.txt file.
- ___ 21. If you have installed IBM @server iSeries Access Family products, you might have other tasks that you need to complete. You can find further information about installing iSeries Access Family products in the following sources:

Checklist: Completing the upgrade or replacement

- iSeries Access for Windows in the iSeries Information Center (**Connecting to iSeries > iSeries Access > iSeries Access for Windows**).
 - The IBM @server iSeries Access Family Web site  (<http://www.ibm.com/eserver/iseries/access>).
- ___ 22. You might have installed licensed programs that require additional installation steps on PCs. Or, you might have programs that should be installed on PCs through an iSeries Access Family function. If you have products such as these, complete your PC installation by using the instructions for the product.
- ___ 23. If you have an Integrated xSeries Server that you stopped before you began the installation process, restart it now.
- a. Type GO NWSADM on an OS/400 command line. The Network Server Administration display appears.
 - b. Select option 2 (Start a network server).
- ___ 24. If you installed 5722-TC1, TCP/IP Utilities, go to the topic TCP/IP setup in the iSeries Information Center (**Networking > TCP/IP setup**) for advanced configuration and setup information.
- ___ 25. If you installed 5722-JV1, IBM Developer Kit for Java, verify that the program is installed and is working correctly. Type java Hello on a command line, and press Enter. You should see the message Hello World. Java program completed.
- IBM Developer Kit for Java™ in the iSeries Information Center (**Programming > Java > IBM Developer Kit for Java**) contains additional information about the licensed program.
- ___ 26. If you have customized an IBM-supplied program (for example, QSTRUP in library QSYS) in a previous release, make sure that you re-create this program to run correctly in the new release.
- ___ 27. If you have duplicated any IBM-supplied objects, you might want to make new duplicates after you install the release. This enables you to take advantage of functions added in the new release. Examples of objects that you might duplicate include the following:
- Message text descriptions
 - Commands
 - Command defaults
- ___ 28. If you use IBM Performance Management for @server iSeries, function, the Collection Services tool, or the Performance Tools for iSeries licensed program and you collected data prior to installing your new release, you need to perform an action to enable the collecting of performance data to continue.

You have the following choices regarding how to handle your performance data from the prior release:

- Convert the data.
Use the Convert Performance Data (CVTPFRDTA) command to convert the data in the collection library.

- Use the automatic data collection support

If you do not convert your performance database files and if Collection Services is started and you specified the option to create database files automatically, a performance library for the prior release files is created. The performance database files are moved to that library. This action allows new files to be created and preserves the existing data files from the previous release. You should be aware of the following items:

Checklist: Completing the upgrade or replacement

- The library name that is created is QPFRDvrmmn, where vrm is the current version, release, and modification and nn is a unique sequence number starting with 01, for example, QPFRD52001.
- The library is created with *EXCLUDE public authority. The library is owned by the QSYS user profile, and the owner of the original library is given *ALL authority.
- All QAPMxxxx files are moved.
- If you do not want to keep the data from the previous release, you can delete the QPFRDvrmmn library with the Delete Library (DLTLIB) command (DLTLIB qpfrdvrmmn)
- Delete the QAPMxxxx files
If you do not convert your performance database files and do not run Collection Services, you can delete the QAPMxxxx files with the Delete File (DLTF) command (DLTF library/QAPM*).

You have completed upgrading to the new release on your server.

Chapter 7. Installing OS/400 and related software on a new server or logical partition

This software installation process includes installing the Licensed Internal Code, OS/400 operating system, and other software for the first time. If you are upgrading software that you currently have installed, go to Chapter 6, “Upgrading or replacing OS/400 and related software,” on page 25. If you want to install a new primary language from either a secondary language media set or a primary language media set, go to Chapter 8, “Changing the primary language of your server or logical partition,” on page 131.

“Preparing to install the OS/400 release”

Perform these preparatory tasks before you schedule your software installation.

“Installing the OS/400 release” on page 93

Install the OS/400 release or perform an IPL for the first time.

“Installing additional licensed programs” on page 114

Install licensed programs that were not previously installed or upgraded.

“Installing a secondary language” on page 121

Install a new secondary language on a server or logical partition.

“Checklist: Completing the installation” on page 125

Use this checklist to complete any of the installation processes in this installation information.

Preparing to install the OS/400 release

Careful, complete, and early preparation saves a considerable amount of time and can help make your software installation on your new server or logical partition run smoothly.

Perform these preparatory tasks before you schedule your installation. Allow ample time (a few weeks or days before the installation) to complete these tasks before you perform the actual installation tasks.

If you are setting up logical partitions, you will need to plan in advance of your installation and have a basic understanding of logical partitions, your software requirements, and your hardware requirements. For iSeries 8xx and earlier models, refer to the topic **Plan for logical partitions** in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, see the topic **Plan for OS/400 partitions** in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 logical partitions**). You can also have different release levels on different partitions. For directions on how to do these correctly for iSeries 8xx and earlier models, see the topic **Manage logical partitions** in the iSeries Information Center (**Systems management > Partitioning with iSeries Navigator > Manage logical partitions**). For IBM eServer 5xx models, see the topic **Manage OS/400 partitions** in the IBM

Preparing to install the OS/400 release

eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 logical partitions**).

The following topics pertain to the preparation tasks for software installation.

“Checklist: Software installation readiness”

Use this checklist to help consolidate and verify that you have completed all the preparation tasks for a software installation.

“Verifying the contents of your software order” on page 89

Verify that the contents of your order are correct before you begin your installation.


“Performing initial installation tasks” on page 90

Complete these initial installation tasks.

Checklist: Software installation readiness

Following is a summary of the major task categories that you need to do before you begin to install your software.

Before you begin

- Verify that your server model meets the requirements to support the new release. This information is found in the IBM eServer iSeries System Handbook  at the following Web site: <http://publib-b.boulder.ibm.com/cgi-bin/searchsite.cgi?query=iSeries+AND+handbook>. Use this Web page to search for the correct version.
- Know your current strategy for connecting a console to your server or logical partition. Your current connection strategy influences your planning activities. For information about twinaxial consoles and Operations Console, refer to the Connecting to iSeries topic in the iSeries Information Center. For information about managing your systems with Hardware Management Console for eServer, refer to the topic Hardware Management Console in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).
- Understand server administration tasks (basic system operations). To perform software installation tasks, you need to be able to restart your server, sign on and off, use the command interface, install fixes, change the system operation mode and initial program load (IPL) source on the system unit control panel, and analyze server problems.
- Understand the different “Types of software installation devices” on page 12. The installation tasks are different based on the optical media that you use.

Perform the following tasks that are appropriate for your server.

Software preinstallation tasks

- “Verifying the contents of your software order” on page 89
 - “Identifying and reviewing information resources” on page 89
 - “Verifying the correct optical distribution media” on page 90
 - “Verifying license keys for keyed products” on page 90
- “Performing initial installation tasks” on page 90
 - “Ensuring you have the latest information” on page 91
 - “Determining disk storage space required” on page 91
 - “Estimating installation time” on page 91
 - “Preparing your console for software installation” on page 91
 - “Preparing the installation device and media” on page 93

After the tasks in the preceding checklist and your installation have been completed, consider the following tasks.

After you finish

- Develop a strategy for managing and maintaining your software. For information about software fixes (also known as program temporary fixes or PTFs), software licenses, and license keys, go to the topic **Maintain and manage OS/400 and related software** in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software**).
- For information about software distribution of supported products, go to the **Distribute software** in the iSeries Information Center (**OS/400 and related software > Distribute software**) topic.

Verifying the contents of your software order

To save you time and avoid frustration, verify that the contents of your software order are correct before you start installation.

“Identifying and reviewing information resources”

Become familiar with the important resources pertaining to the installation of your new software. Use these documents to plan your installation process.

“Verifying the correct optical distribution media” on page 90

Ensure that you have the correct media for your upcoming tasks.

“Verifying license keys for keyed products” on page 90

Review the software license keys for keyed IBM products or keyed IBM product options that you have ordered.

Identifying and reviewing information resources

The following resources pertain to the installation of your new software. Many of these resources are shipped with the distribution media in your software order. You need to use these documents to plan parts of your installation process. Read the material that applies to your server.

Setup and Operations CD-ROM

With every software order that includes Operations Console, you receive *iSeries Setup and Operations*, SK3T-4098. This CD-ROM contains IBM @server iSeries Access for Windows and the EZ-Setup wizard.

iSeries Information Center CD-ROM

This *iSeries Information Center*, SK3T-4091-04 CD-ROM comes with your IBM Operating System/400 software order.

PSP information

To keep informed of the latest information about conditions that could impede your software installation, you need the most recent edition of the preventive service planning information (PSP). For information on preventive service planning, see preventive service planning information in the iSeries Information Center (**Maintain and manage OS/400 and related software > Use software fixes > Where to find information about fixes > Preventive service planning (PSP) information**).

iSeries PTF shipping information letter

Preparing to install the OS/400 release

This letter contains the instructions for installing the cumulative program temporary fix (PTF) package. The letter comes with the package. IBM highly recommends that you order the cumulative PTF package about a week or two before your OS/400 installation and then install the package as part of your completion tasks. For information about the most recent cumulative package, refer to the Order fixes topic in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 > Use software fixes > Order fixes**).

Verifying the correct optical distribution media

Do the following to ensure that you have the correct media for your upcoming tasks.

1. Verify that the optical media for Licensed Internal Code and OS/400 are for V5R3.
2. Verify that the media you received are in the correct primary and secondary languages.

Verifying license keys for keyed products

For the keyed IBM products or keyed IBM product options that you have ordered, review the software license keys created for your server online. Refer to the Customer Notice that is included with your software order for information on how to access your software license keys. The online access requires that you do the following:

- Register with IBM.
- Use the customer packing list from your software order to obtain the following numbers:
 - Customer number that was used for your order.
 - Software order number that was used to process your order.

After completing these steps, you can view, print, or download your software license keys to your server. If you have further questions, refer to the information on the Customer Notice for details on how to contact the IBM Software License Key Center.

For general information on licensed keys, refer to the topic Software license keys in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Work with software agreements and licenses > Concepts > Software license keys**).

For a list of products, see “Licensed program releases and sizes” on page 166.

Performing initial installation tasks

Before you install new software on your server, complete these initial installation tasks:

“Ensuring you have the latest information” on page 91

Before you begin the installation process, make sure that your server is ready by ensuring you have the latest information.

“Determining disk storage space required” on page 91

Ensure that you have adequate disk storage before you install.

“Estimating installation time” on page 91

Estimate the time that is needed to install this release of software on your server.

“Preparing your console for software installation”

Get your console ready for the software installation process.

“Preparing the installation device and media” on page 93

Prepare to install software from optical media, tape devices or tape libraries, or alternate installation devices.

Ensuring you have the latest information

Before you begin the installation process, make sure that your server is ready by performing the following tasks relating to having the latest sources:

- **Find the latest available PSP information**

Keep informed on the most recent information about conditions that could impede your software installation process. Review the most recent edition of the preventive service planning information (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Fixes concepts and terms > Where to find information about fixes > Preventive service planning (PSP) information**).

- **Order current cumulative PTF packages and required group fixes**

The cumulative PTF package does not come with your software order. About a week or two before your installation, order the most recent cumulative PTF package and also order PTF groups that pertain to your environment.

Determining disk storage space required

Before you schedule a time to install this release, determine the available storage space and the storage space that is required for this release.

Load-source disk unit requirements: You must have a load-source disk unit of 4 GB or larger on each server or logical partition. (This unit is disk unit number 1 in auxiliary storage pool (ASP) number 1.)

To understand how the system decompresses objects, see “Compressed objects and storage space” on page 20.

Estimating installation time

If you want to estimate the time it will take to install software on your new server or logical partition, see the information in “Estimates for software installation time” on page 171. Ignore the tasks that refer to upgrades.

Preparing your console for software installation

Although you can use twinaxial console on most servers, IBM recommends for V5R3 that you use either Operations Console or Hardware Management Console for eServer. For requirements on twinaxial console, Operations Console, and PCs, refer to the category, Connecting to iSeries in the iSeries Information Center. If you are moving from twinaxial console to Operations Console, use the *iSeries Setup and Operations CD-ROM*, SK3T-4098-02, to install Operations Console before you install the new release.

If you are using twinaxial console, the software installation process expects the system console device to be attached at port 0 and address 0 of the first workstation controller. In most cases, your hardware should be defined in this way. You should verify that the console is attached at port 0 address 0.

If you are planning on migrating your Operations Console, do so either before or after you upgrade. If you are planning on migrating your Hardware Management Console (HMC), do so only after you have completely installed your system. For

Preparing to install the OS/400 release

more information about using the HMC as your OS/400 console, see Hardware Management Console in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).

For all servers, verify that the console mode value is set correctly for your console. To verify the console mode value, follow these steps:

1. Access Dedicated Service Tools (DST).
2. Select **Work with DST environment**.
3. Select **System Devices**.
4. Select **Console mode**. The value of the current console mode is present in the input field. Verify that this is the correct setting. A value of zero means that the console mode has not been set and can interfere with the automatic installation process. The console mode value must be one of the following values:

1	Twinaxial console
2	Operations Console (directly attached)
3	Operations Console (LAN attached)
4	Hardware Management Console (HMC)

During an installation or upgrade to V5R3, the console type specified by this value is used.

If you use Operations Console, do the following before you install V5R3 on your server:


- Review the Operations Console topic in the iSeries Information Center (**Connecting to iSeries > Operations Console**). To view the most recent information on Operations Console, go to the Operations Console Web site  (<http://www.ibm.com/servers/eserver/series/clientaccess/qnaopcons.htm>)
- IBM recommends that you update IBM @server iSeries Access for Windows to V5R3 before you upgrade the OS/400 operating system. For more information, see Install and set up in the iSeries Information Center (**Connecting to iSeries > iSeries Access for Windows > Install and set up**).
- If you use the Operations Console configuration, Local console directly attached to the server, the adapter used for the cable connection must be in a specific position. The adapter can be a 2721, 2742, 2745, 2771, or 2793. The position is based on the server model shown in the following table:

Table 6. Card position

Server model	Operations Console asynchronous card position for the cable
170 or 250	C08
270	C07
520	C03
570	C02
720	C09
730 or 740	See cabling information
800 or 810	C07
820	C06
825	C06
830 or SB2	C02

Table 6. Card position (continued)

Server model	Operations Console asynchronous card position for the cable
840 or SB3	C02
870 or 890	C02

- When you receive the OS/400 release upgrade, the shipped service tools user IDs (except 1111111) are expired. For all upgrades and installations, you need to establish a connection between the server and Operations Console PC by using the service tools user ID of 1111111 (eight 1's). This ensures a successful authentication of the subsequent connection of the client to the server. This is especially important for automatic installations.

Failure to comply with the above actions can prevent the console from working correctly during the upgrade or installation.

Preparing the installation device and media

If you are not sure which installation device to use, refer to “Types of software installation devices” on page 12. “Installation devices and media” on page 180 contains more detailed information on the devices and media available.

Installing the OS/400 release

This topic contains instructions to install Licensed Internal Code, the operating system, or licensed programs on a new server or logical partition. It also includes tasks to change the primary language of your server. Perform any of the following tasks if you are installing software on a new system.

“Installing Licensed Internal Code on a new logical partition”

Perform these tasks to install Licensed Internal Code on a new logical partition with twinaxial console or Operations Console installed.

“Installing software on a new server or logical partition (without OS/400 installed)” on page 100

Follow these instructions to install the operating system and licensed programs on your new server or logical partition or to change the primary language when you are installing the operating system.

“Installing software on a new server (with OS/400 installed)” on page 109

Use these procedures if you already have OS/400 on your new server and want to install other licensed programs.

Installing Licensed Internal Code on a new logical partition

Use the instructions in this topic to install the Licensed Internal Code on a new secondary logical partition. If you are using the Hardware Management Console for @server^(R) to install Licensed Internal Code, review the Hardware Management Console topic in the IBM eServer^(TM) Hardware Information Center (**Managing your server > Hardware Management Console**).

After you perform the instructions in this topic, follow the instructions in “Installing software on a new server or logical partition (without OS/400 installed)” on page 100 to install the Operating System/400 and licensed programs.

Before you begin to install Licensed Internal Code on a partition
Should you use this topic? The release supported in this topic is V5R3.

Installing Licensed Internal Code on a new logical partition

If you have not already done so, complete the tasks in the iSeries Information Center topic “Preparing to install the OS/400 release” on page 87.

Do you need to use the manual installation process? Yes, you must use the manual installation process for this procedure.

Verify your console information in the topic “Preparing your console for software installation” on page 91. You must verify that your console mode value is set correctly before you can upgrade to V5R3.

Have you completed the planning and creating tasks for your logical partition? If you have not already done so, review the topics for iSeries 8xx or earlier models in Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, review the topic Plan for OS/400 partitions in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 partitions**).

Attention:
This procedure causes existing data on the disk units assigned to this logical partition to be lost! Make sure you really want to perform this procedure.

During the installation in a logical partition, reference codes appear either on the primary partition or the Hardware Management Console for eServer.

Note:

- In this information, when a reference code appears with the characters xx (such as B2xx xxxx), xx pertains to the partition identifier and xxxx pertains to a variety of other characters.
- The term *system* refers to the logical partition on which you are performing the installation.
- When installing on logical partitions, the *control panel* can be found either on the primary partition or the HMC.
- For more information, refer to the appropriate logical partition topics:
 - For iSeries 8xx and earlier models, Manage logical partitions by using iSeries Navigator, DST, and SST in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions > Manage logical partitions by using iSeries Navigator, DST, and SST**).
 - For IBM eServer 5xx models, Manage OS/400 logical partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Managing OS/400 logical partitions**).
- Until you have completed the installation of Licensed Internal Code, the information shown about the configuration of logical partitions will be incorrect. Devices attached to the buses of logical partitions are not listed until the installation is complete. Therefore, if you have logical partitions and look at your configuration from the primary partition or HMC before you complete the installation, you might see only buses and IOPs, but not the IOA and device details.

Installing Licensed Internal Code on the new logical partition

1. Load the first volume of installation media that contains Licensed Internal Code into the installation device that is defined for the server. (If you are using

Installing Licensed Internal Code on a new logical partition

IBM-supplied media, this volume is labeled I_BASE_01.) Throughout these procedures, load the next volume when prompted by the server. Wait for the In Use indicator to go out.

Note: The optical media that you will need later for the operating system and other licensed programs are listed in step 2 on page 101 of “Installing OS/400 on a new server or logical partition” on page 101.

2. Make sure you can access either the primary partition or the Hardware Management Console (HMC) to control your new logical partition.
If power is not on, go to the following sources for more information and return here when done.
 - For IBM eServer 5xx models, Restarting and shutting down an OS/400 logical partition in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Manage OS/400 logical partitions > Restarting and shutting down an OS/400 logical partition**).
 - For iSeries 8xx and earlier models, Restart and power down a system with logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions > Restart and power down a system with logical partitions**).
3. Ensure the following for the new logical partition:
 - If you are using a twinaxial console, the device for the new logical partition needs to be powered on.
 - If you are using Operations Console, you need a valid connection configuration for the logical partition after you have run the Operations Console wizard. The console for the logical partition needs to be at **Connecting console**. (To view the status in Operations Console, click the IBM @server iSeries Access for Windows icon and double-click **iSeries Operations Console**.)
4. Verify that this logical partition has an alternate IPL resource (the resource for loading) assigned. For more information on alternate IPL resources, see the following sources:
 - For IBM eServer 5xx models, Concepts for OS/400 logical partitions in the IBM eServer Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Logical partitions > Concepts for OS/400 logical partitions**).
 - For iSeries 8xx and earlier models, Logical partition concepts in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Concepts**).
5. Load the installation media volume that contains Licensed Internal Code (I_BASE_01) into the installation resource defined for this logical partition. Before you go to the next step, be sure that no conditions exist that require your attention.

Note: If you are using a tape device instead of the optical device that is optimized for optical media, verify that the tape unit is loaded and that the tape drive is ready.
6. Use the control panel to verify or to set the mode selection to **Manual** and the IPL source to **D**. These settings indicate that you are controlling the logical partition from the primary partition or HMC, but the installation is done on the logical partition.
7. Use the control panel to power on this logical partition.

Installing Licensed Internal Code on a new logical partition

- Wait for the OS/400 display to appear that has the language feature to select. (This could take several minutes, but you can monitor the status.)

Note: If you are using Operations Console and receive a **Service Device Sign-On** window when doing this step, sign on by using the appropriate data. It is strongly recommended that you use the userid/password of 11111111/11111111 for this connection. If you do not receive the **Service Device Sign-On** window, the data is supplied by the personal computer from previously entered data.

The installation media for Licensed Internal Code is now language-independent. It is important that you complete this step carefully.

The languages on your media for the Licensed Internal Code and OS/400 must match. If they do not match, do not continue with the installation. Stop and call your software provider. Get the correct language feature before continuing.

Refer to “Feature codes for national language version” on page 195 to locate the appropriate feature code for your language.

```
000000      SSSSS // 44      00000      00000
00 00 SS SS // 444      00 00 00 00
00 00 SS // 4444      00 00 00 00
00 00 SS // 44 44      00 00 00 00
00 00 SSS // 44 44      00 00 00 00
00 00 SSS // 44 44      00 00 00 00
00 00 SS // 44 44      00 00 00 00
00 00 SS // 4444444444      00 00 00 00
00 00 SS SS // 44      00 00 00 00
000000      SSSSS // 44      00000      00000

LANGUAGE FEATURE ==> 2924
```

The language feature 2924 (English) is the default for this display. If you are installing a language other than 2924, type the correct primary language feature code in place of 2924. The language feature is shown on the label of your OS/400 installation media as B29xx_nn, where 29xx indicates the feature for the primary language.

Press Enter.

- After you enter the language feature, the Confirm Language Group display appears.

```
Confirm Language Group


Language feature . . . . . : 2924

Press Enter to confirm your choice for language feature.
Press F12 to change your choice for language feature.
```

Press Enter.

- The Install Licensed Internal Code display appears.

Installing Licensed Internal Code on a new logical partition



Attention: Tape devices attached by a Fibre Channel interface will need to be set up as alternate installation devices.

If you use an alternate installation device, you need to ensure that you set up the device and that you enable the device. You also need to have the CD-ROM, DVD-RAM, or tape media that contains the Licensed Internal Code and your save media.


Either select the option to install Licensed Internal Code or the option to define an alternate installation device:

- Type 1 (Install Licensed Internal Code) if you are not using an alternate installation device. (The alternate installation device function supports installation from tape media that you have created. “Overview: Alternate installation device” on page 182 describes when you can use an alternate installation device.)
- If you have an alternate installation device attached to the system, type 3 to verify its address and determine whether it is enabled or disabled. Continue with the Verifying Alternate Installation Device Subtask in step 11. If you have an alternate installation device configured and do not want to use it, type 3 to clear the alternate installation device configuration information. If you are not using an alternate installation device, go on to step 13 on page 98.

Press Enter. This step could take some time.

11. Verifying and selecting alternate installation device subtask:

The Select Alternate Installation Device Bus display appears.



- a. Verify that the selected device is on the correct system bus. Type 1 in the Options field next to the selected bus and press Enter to view information about the device that is attached to the bus. This might take several minutes. If you see the message No alternate installation device configured, wait one minute and refresh the display.

Installing Licensed Internal Code on a new logical partition

- b. When the Select Media Type display appears, select 1 for tape or 2 for optical media. Press Enter.
- c. The Select Alternate Installation Device display appears. Use this display to verify the resource name, type, model, and serial number for the device. The following display shows an example of a tape device.

```

Select Alternate Installation Device
System:  SYSTEMA

Additional devices may be available for use. Press F5 to see
if any additional devices have been detected.

Type option, press Enter.
1=Select  5=Display details

Option  Bus  Resource
Number  Name   Type  Model  Serial  Selected
-       -     -     -     -     -
  1     1    TAP08  6386  001    00-11111
  3     3    TAP19  3570  B11    13-22222  *

F2=Deselect device  F3=Exit  F5=Refresh  F12=Cancel
    
```

- d. Type 1 to select the device and make any needed corrections to select, enable, or disable the device. Press Enter to confirm the changes.
- e. The message Alternate installation device selected appears. Press F3 to return to the Install Licensed Internal Code display.
- f. Type 1 and press Enter to install the Licensed Internal Code.

End of verifying and selecting alternate installation device subtask.

12. If there is an alternate installation device defined and enabled, the Confirm Alternate Installation Device display appears.
 - To install from the alternate installation device, press Enter.
 - To install from optical media, press F12 to Cancel. You see the Licensed Internal Code display. Perform step 10 on page 96 and select option 3 (Define alternate installation device). Perform step 11 on page 97 and disable the alternate installation device.
13. The Install Licensed Internal Code (LIC) display appears on your console.

```

Install Licensed Internal Code (LIC)

Disk selected to write the Licensed Internal Code to:
Serial Number  Type  Model  I/O Bus  Controller  Device
xx-xxxxxxx    xxxx  xxx    x        x          x

Select one of the following:

1. Restore Licensed Internal Code
2. Install Licensed Internal Code and Initialize system
3. Install Licensed Internal Code and Recover Configuration
4. Install Licensed Internal Code and Restore Disk Unit Data
5. Install Licensed Internal Code and Upgrade Load Source
    
```

Type 2 (Install Licensed Internal Code and Initialize system) and press Enter.

14. Read the attention notice and reply to the Confirmation display.

Attention: This procedure causes existing data on the disk units assigned to this logical partition to be lost! Make sure you really want to perform this procedure.

Installing Licensed Internal Code on a new logical partition

18. If the console mode value is zero, the Accept Console display appears. If this display appears, follow these steps:
 - a. Press F10 to accept the current console type. The Accept and Set New Console Type on this IPL display appears. The old value (zero) and the new value to be set (your current console type) is shown.
 - b. Press Enter to set the new value and continue with these instructions.
19. After approximately 10 minutes, the IPL or Install the System display appears. The Licensed Internal Code is now installed. Do not remove the distribution media at this time.
20. If the Accept Console display in step 18 did not appear, set the console mode for this partition:
 - a. At the IPL or Install the system display, select option 3 to access Dedicated Service Tools (DST).
 - b. Sign on as security officer (QSECOFR *user profile* / QSECOFR *password*). When prompted, change the password to what you want to use for this partition.
 - c. Select option 5 (Work with DST environment).
 - d. Select option 2 (System devices).
 - e. Select option 6 (Console mode).
 - f. Select the valid console that you have for this partition. Press Enter and then press F3 to return to the DST main menu.

Note: If you are using Operations Console (LAN) as your console type, press Enter on the verify window. You can also press F11 to review your network configuration.
 - g. Press F3 to exit DST and return to the IPL or Install the System display.

You have completed the installation of Licensed Internal Code on a new logical partition. The optical media that you will need for the operating system and other licensed programs are listed in step 2 on page 101 of “Installing OS/400 on a new server or logical partition” on page 101. Continue with step 10 on page 103.

Installing software on a new server or logical partition (without OS/400 installed)

This topic contains instructions to install the operating system and licensed programs on your new server or logical partition. It explains how to change the primary language when you are installing the operating system if you need to change it at this time. Refer to the OS/400 globalization topic in the iSeries Information Center (**Programming > Globalization**) for any special considerations you might need to know about other languages.

Notes:

1. If you are installing software on a server, these instructions assume that the V5R3 release of the Licensed Internal Code is installed and the server is powered off. If you do not know what level of Licensed Internal Code is on your system, sign on to DST. Select option 7 (Start a Service Tool) and then select option 4 (Hardware Service Manager). The release at the top of the display should be V5R3M0.
2. If you are installing software on a new logical partition, you need to complete the steps in “Installing Licensed Internal Code on a new logical partition” on page 93 first and then continue with step 10 on page 103 in this topic.

Installing software on a new server or logical partition (without the operating system installed)


The following topics pertain to the tasks for installing software on a new server or logical partition:

1. "Before you begin to install software on a new server or logical partition"
2. "Installing OS/400 on a new server or logical partition"

Before you begin to install software on a new server or logical partition

Should you use this topic? The release supported in this topic is V5R3.

If you have not already done so, complete the tasks in the iSeries Information Center topic "Preparing to install the OS/400 release" on page 87.

Do you plan to use logical partitions? For iSeries 8xx and earlier models, read the topic Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, read the topic Plan for OS/400 logical partitions in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 logical partitions**). Additionally, refer to the Logical Partitioning Web site  (<http://www.ibm.com/eserver/series/lpar>).

For logical partitions only

If you perform these actions on a system with logical partitions, the instructions pertain only to that partition. If that partition is a primary partition, these instructions will change the power status and perform an IPL on the entire system. There is no effect if you are on a system managed by Hardware Management Console for @server^(R).

Attention: If you are installing on a primary partition, you must shut down all partitions before performing these instructions. Otherwise, you could lose data or damage system software objects. You must perform these instructions for each partition with which you will do the related work. Also, references to the control panel refer either to the virtual control panel (Work with Partition Status display) on your primary partition.

Installing OS/400 on a new server or logical partition

1. Ensure that the server is powered off before you begin.
2. Arrange the installation media that you plan to install in the following order (you might not have all of these):
 - a. B29xx_01 Operating System/400
 - b. B29xx_02 OS/400 no-charge options
 - c. B29MM_03 OS/400 no-charge options
 - d. B29MM_04 OS/400 no-charge options
 - e. D29xx_01 OS/400 no-charge options
 - f. D29xx_02 OS/400 no-charge options
 - g. D29xx_03 OS/400 no-charge options
 - h. D29xx_04 OS/400 no-charge options
 - i. D29xx_05 OS/400 no-charge licensed programs
 - j. L29xx_01 priced licensed programs
 - k. L29xx_02 priced licensed programs
 - l. F29xx_01 single licensed programs

Keep the following installation media available for later use:

- a. N29xx_01 Secondary Language Media

Installing software on a new server or logical partition (without the operating system installed)


- b. Cydddvrn_01 Cumulative PTF Package (if ordered)
- c. SK3T-4091 iSeries Information Center

For descriptions of the optical media, see “Media labels and their contents” on page 189.

3. Ensure the following for the server:
 - If you are using a twinaxial console, the console for the server needs to be powered on.
 - If you are using Operations Console, you need a valid connection configuration for the server after you have run the Operations Console wizard. The console for the server needs to be at **Connecting console**. (To view the status in Operations Console, click the IBM @server iSeries Access for Windows icon and double-click **iSeries Operations Console**.)
4. If the installation device has a separate power switch, set it to the On position.
5. Use the control panel to set the IPL type to **A** and set the mode to **Manual**.
6. Press the Enter button on the control panel.
7. Turn the power on for the server by pressing the power button.

Note: If either the Disk Configuration Error Report display or the Disk Configuration Warning Report display appears, go to “Disk configuration warning and error messages” on page 158 to determine the appropriate action.

8. The IPL or Install the System menu appears on your console.




If you have not already done so, set the console mode for your server:

- a. At the IPL or Install the system display, select option 3 to access Dedicated Service Tools (DST).
- b. Sign on as security officer (*QSECOFR user profile / QSECOFR password*). When prompted, change the password to what you want to use for this partition.
- c. Select option 5 (Work with DST environment).
- d. Select option 2 (System devices).
- e. Select option 6 (Console mode).
- f. Select the valid console that you have for this partition. Press Enter and then press F3 to return to the DST main menu.


Note: If you are using Operations Console (LAN) as your console type, press Enter on the verify window. You can also press F11 to review your network configuration.

- g. Press F3 to exit DST and return to the IPL or Install the System display.

Installing software on a new server or logical partition (without the operating system installed)




9. Load the first volume of installation media that contains OS/400. (If you are using IBM-supplied media, the first volume is labeled B29xx_01, where 29xx is the identifier for the primary language.) Throughout these procedures, load the next volume when prompted by the server. When you are installing from optical media, wait until the In Use indicator goes out before you continue.
10. On the IPL or Install the System display, type 2 and press Enter. The Install Device Type Selection display appears.



Type the number that corresponds to the correct device type and press Enter.

11. The Confirm Install of OS/400 display is shown on your console. Press Enter.
12. The Select a Language Group display, which shows the primary language currently on the system, appears. This value should match the language feature number that is printed on the installation media. Refer to “Feature codes for national language version” on page 195 for a list of language feature codes.




Verify that the displayed value is correct, or type the numbers of the feature code for the language you want. Press Enter.

13. After you enter the language feature, the Confirm Language Feature Selection display appears on your console. Press Enter.
14. If the Add All Disk Units to the System menu is not shown, go to the IPL Step in Progress display in step 16 on page 106.

Note: If you are installing on a single disk unit, ensure that you have enough storage. The minimum requirements for each server or logical partition are listed in “Determining disk storage space required” on page 91.

15. **Adding disk units subtask:**
 - a. If any nonconfigured disk units that are capable of being protected by device parity are currently unprotected, the Add All Disk Units to the System display is shown. If the following display is not shown, go to step 15b on page 104.


Installing software on a new server or logical partition (without the operating system installed)



It is much faster to start device parity protection on the disk units at DST before the disk units are added to the auxiliary storage pool configuration.


To start device parity on the eligible disk units, do the following tasks from the Add All Disk Units to the System display:

- 1) Select option 2 to perform disk configuration at DST.
 - 2) Sign on at the Dedicated Service Tools Sign-on prompt and return to the Use Dedicated Service Tools (DST) menu.
 - 3) Select the option, Work with disk units.
 - 4) Select the option, Work with disk configuration.
 - 5) Section the option, Work with device parity protection.
 - 6) Select the option, Start device parity protection.
 - 7) A list of parity sets that are capable of running device parity protection are shown. Type 1 on each option line for each parity set.
 - 8) You might see a Confirm Continuation display that indicates that the server must perform a directory recovery. Press Enter to continue.
 - 9) The Confirm Starting Device Parity Protection display is shown. This shows the list of disk units that will have device parity protection. Press Enter to continue. An in-progress display that indicates the status of the function is shown.
 - 10) Return to the IPL or Install the System display.
- b. If you see the following display, continue with this step.



If you do not want device parity protection, mirrored protection, or user ASPs, select option 3 (Add all disk units to the system auxiliary storage pool). By adding disk units before you install the operating system, you improve your overall system performance because the operating system is distributed across all of your disk units.


Installing software on a new server or logical partition (without the operating system installed)



- f. When the process is completed, continue the software installation process with the next step.

This completes the subtask for adding disk units.


16. Status displays appear on the console. You do not need to respond to any of these displays. The following is an example of a status display:



The following list shows some of the IPL steps that are shown on the IPL Step in Progress display.

- Authority Recovery
- Journal Recovery
- Database Recovery
- Journal Synchronization
- Start the Operating System

17. The Install the Operating System display appears.



Type the following and press Enter:

Install option: 1
 Date (Use the current year, month, and day.)
 Time (Use the current time, 24-hour clock.)

18. Status messages appear during the installation process. You do not need to respond to any of these status displays. The following is an example of a status display. The display is blank for a time between stage 4 and stage 5.

Installing software on a new server or logical partition (without the operating system installed)

```

Message ID. . . . : CPI2070                OS/400 Installation Status

Stage 2  +-----+
          |                XX %                |
          +-----+

Installation
Stage                                Completed      Objects
                                           Restored

  1 Creating needed profiles and libraries . . . . : X
>> 2 Restoring programs to library QSYS . . . . . :          XXXXX
  3 Restoring language objects to library QSYS . . :
  4 Updating program table . . . . . :
  5 Installing database files. . . . . :
  6 Completing OS/400 installation . . . . . :
    
```

19. Messages similar to the following might appear:

```

                                Display Messages
Queue . . . . . : QSYSOPR                System:  XXXX
Library . . . . : QSYS                    Program . . . . : *DSPMSG
Severity . . . . : 10                     Library . . . . :
                                           Delivery . . . . : *BREAK

Press Enter to continue.
System operator message queue QSYSOPR created again.
Console values lost.
    
```

Press Enter.

20. The Sign On display is shown.

```

                                Sign On
System. . . . . : XXX
Subsystem . . . : XXXXX
Display . . . . : XXXXXXXX

User. . . . . : QSECOFR
Program/procedure . . . . . : _____
Menu. . . . . : _____
Current library . . . . . : _____
    
```

Type QSECOFR for the *User* prompt. Press Enter.

21. Several Display Messages displays could be shown. To continue, press Enter for each message display.

The following display is an example of a message that could be shown:

```

                                Display Messages
Queue . . . . . : QSYSOPR                System:  XXXX
Library . . . . : QSYS                    Program . . . . : *DSPMSG
Severity . . . . : 60                     Library . . . . :
                                           Delivery . . . . : *BREAK

Press Enter to continue.
System object QWCSCPF created again during IPL.
    
```

22. The IPL Options display appears.

Installing software on a new server or logical partition (without the operating system installed)

```

                                IPL Options

Type choices, press Enter.

System date . . . . . XX / XX / XX      MM / DD / YY
System time . . . . . XX : XX : XX      HH : MM : SS
System time zone . . . . . Q0000UTC      F4 for list
Clear job queues. . . . . N              Y=Yes, N=No
Clear output queues . . . . . N          Y=Yes, N=No
Clear incomplete job logs . . . . . N    Y=Yes, N=No
Start print writers . . . . . Y          Y=Yes, N=No
Start system to restricted state . . . . . Y
                                                Y=Yes, N=No

Set major system options. . . . . Y      Y=Yes, N=No
Define or change system at IPL. . . . . N Y=Yes, N=No

Last power-down operation was ABNORMAL

```

Note:

- Ignore the message on the bottom of the IPL Options display.
- If you need to change system values, you can do so now. One example of a system value that you might change is the value for the security level (QSECURITY) system value.

Another example is the scan control (QSCANFSCCTL) system value. Consider specifying *NOPOSTRST for the QSCANFSCCTL system value to minimize future scanning of some objects that are restored during the installation of licensed programs in the following steps. For more information on scanning and the system value settings, see the topic [Scanning support in the iSeries Information Center \(Files and file systems > Integrated file system > Concepts > Scanning support\)](#).

Type Y for the *Define or change the system at IPL* prompt. Follow the instructions on the displays.

Type the following and press Enter.

- System date (Use the current date.)
- System time (Use the current time, 24-hour clock.)
- System time zone (Verify that it is correct or press F4 to select a time zone.)
- Start system to restricted state Y
- Set major system options Y

23. Additional display messages could be shown. Press Enter after each message to continue.
24. The Set Major System Options display appears.

```

                                Set Major System Options

Type choices, press Enter.

Enable automatic configuration . . . . . Y      Y=Yes, N=No
Device configuration naming . . . . . *NORMAL *NORMAL, *S36,
                                                *DEVADR
Default special environment. . . . . *NONE     *NONE, *S36

```

Respond to the prompts on the Set Major System Options display.

- Enable automatic configuration

Installing software on a new server or logical partition (without the operating system installed)

The value Y (Yes) automatically configures local devices. N (No) indicates no automatic configuration.

- Device configuration naming

Specify *NORMAL to use a naming convention unique to the iSeries server. The value *S36 uses a naming convention similar to System/36. Refer to the book *Local Device Configuration*, SC41-5121-00, for information about device configuration naming and *DEVADR.

- Default special environment

The default value *NONE indicates no special environment. *S36 sets up the System/36 environment. Refer to the book, *System/36 Environment Programming*, SC41-4730 (V4R5 or earlier), for more information about working in the System/36 environment on the iSeries server.

Press Enter.

25. The Edit Rebuild of Access Paths display could be shown. If it is, press Enter to continue.
26. A message Your password has expired might appear. Press Enter. The Change Password display appears. Change the password from QSECOFR to your own choice. First enter the old password, QSECOFR. Then enter the new password of your choice. Enter the new password again as verification.
27. Several Display Messages displays are shown. To continue, press Enter for each message display.

The following display is an example of a message that could be shown:

```
Display Messages
System:      XXXX
Queue . . . : QSYSOPR      Program . . . : *DSPMSG
Library . . . : QSYS       Library . . . :
Severity . . . : 10        Delivery . . . : *BREAK

Press Enter to continue.
Library QHLPYSYS in SYSVAL QSYSLIBL not found.
```

28. The Work with Software Agreements display appears. Select to display the software agreements for the Licensed Internal Code (5722999) and the OS/400 operating system (5722SS1). Read and accept these agreements. If the software agreements are declined, you are given the choice to either power down the server or return and accept the agreements. Press Enter.
29. When the OS/400 Main Menu appears on your console, you have completed the task of installing the OS/400 operating system.

You have completed this task.

To install additional licensed programs, continue with the tasks in “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115.

Installing software on a new server (with OS/400 installed)

The following instructions assume that V5R3 of the Licensed Internal Code and the operating system are installed, the primary language is correct, the console mode value is correct, and the server is powered off.

If you are not sure whether the operating system is already installed, contact your authorized service provider.

The following topics pertain to the tasks for installing software on a new server:

Installing software on a new server (with OS/400 installed)

1. "Before you begin to install software on a new server"
2. "Performing the initial program load (IPL)"

Before you begin to install software on a new server

If you have not already done so, complete the tasks in the iSeries Information Center topic "Preparing to install the OS/400 release" on page 87.

Note: If you have added a new disk unit to your server, you should load the operating system again to use that disk unit. This will improve the performance of your server by distributing the operating system across all of your disk units. Complete "Installing software on a new server or logical partition (without OS/400 installed)" on page 100 if you are adding disk units. If you are planning to use device parity protection, auxiliary storage pools, or mirrored protection, refer to the book *Backup and Recovery*, SC41-5304-07, before you begin.

Do you plan to use logical partitions? For iSeries 8xx and earlier models, read the topic Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, read the topic Plan for OS/400 logical partitions in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 logical partitions**). Additionally, refer to the Logical Partitioning Web site:

<http://www.ibm.com/eserver/iseres/lpar>

For logical partitions only

If you perform these actions on a system with logical partitions, the instructions pertain only to that partition. If that partition is a primary partition, these instructions will change the power status and perform an IPL on the entire system. There is no effect if you are on a system managed by Hardware Management Console for @server^(R).

Attention: If you are installing on a primary partition, you must shut down all partitions before performing these instructions. Otherwise, you could lose data or damage system software objects. You must perform these instructions for each partition with which you will do the related work. Also, references to the control panel refer either to the virtual control panel (Work with Partition Status display) on your primary partition.

Performing the initial program load (IPL)

Note: If you already have the OS/400 Main Menu on your console, go to "Using the Work with Licensed Programs menu to install IBM licensed programs" on page 115 to install additional licensed programs.

1. Ensure that the system is powered off before you begin.
2. On your console, establish a connection to the server.
3. If the installation device has separate on and off switches, verify that the switch is in the On position.
4. Use the control panel to set the IPL type to **A** and to set the mode to **Manual**.
5. Press the Enter button on the control panel.
6. Turn the system power on by pressing the power button.
7. After some time, the IPL or Install the System display appears.

Installing software on a new server (with OS/400 installed)

```
IPL or Install the System
System: XXXX

Select one of the following:

1. Perform an IPL
2. Install the operating system
3. Use Dedicated Service Tools (DST)
4. Perform automatic installation of the operating system
5. Save Licensed Internal Code
```

Type 1 and press Enter.

8. Status displays are shown on the console. You do not need to respond to any of these displays. The following is an example of a status display:

```
Licensed Internal Code IPL in Progress

IPL:
Type . . . . . Attended
Start date and time . xx/xx/xx xx:xx:xx
Previous system end . Normal

IPL step . . . . . : Storage Management Recovery
```

The following list shows some of the IPL steps that are shown on the IPL Step in Progress display.

- Authority Recovery
- Journal Recovery
- Database Recovery
- Journal Synchronization
- Start the Operating System

Some of the IPL steps could take a long time.

9. Several messages might appear on the console. The following is an example of a message that might appear:

```
Display Messages
Queue . . . . . : QSYSOPR          System. . . . . : XXXX
Library . . . . . : QSYS           Program . . . . . : *DSPMSG
Severity . . . . . : 10            Library . . . . . :
Delivery . . . . . : *BREAK

Press Enter to continue.
System object xxxxx created again during IPL.
```

To continue, press Enter after each message that you receive.

10. The Sign On display appears.

```
Sign On
System. . . . . : XXX
Subsystem . . . : XXXXX
Display . . . . : XXXXXXXX

User. . . . . : QSEC0FR
Password. . . . .
Program/procedure . . . . . _____
Menu. . . . . : _____
Current library . . . . . _____
```

Type QSEC0FR for the *User* prompt, and type your password, if required. Press Enter.

Installing software on a new server (with OS/400 installed)

Note: If you need to change the password for the QSECOFR user profile, record the new password now. Store it in a safe location.

11. The OS/400 IPL in Progress display appears.
12. If the Select Products to Work with PTFs display appears, press F3 (Exit).
13. The IPL Options display appears.

```
IPL Options

Type choices, press Enter.

System date . . . . . XX / XX / XX   MM / DD / YY
System time . . . . . XX : XX : XX   HH : MM : SS
System time zone . . . . . Q0000UTC   F4 for list
Clear job queues. . . . . N         Y=Yes, N=No
Clear output queues . . . . . N       Y=Yes, N=No
Clear incomplete job logs . . . . . N   Y=Yes, N=No
Start print writers . . . . . Y       Y=Yes, N=No
Start system to restricted state . . . . . Y   Y=Yes, N=No

Set major system options. . . . . Y       Y=Yes, N=No
Define or change system at IPL. . . . . N       Y=Yes, N=No

Last power-down operation was ABNORMAL
```

Note:

- Ignore the message on the bottom of the IPL Options display.
- If you need to change system values, you can do so now. One example of a system value that you might change is the value for the security level (QSECURITY) system value.

Another example is the scan control (QSCANFSCCTL) system value. Consider specifying *NOPOSTRST for the QSCANFSCCTL system value to minimize future scanning of some objects that are restored during the installation of licensed programs in the following steps. For more information on scanning and the system value settings, see the topic Scanning support in the iSeries Information Center (**Files and file systems > Integrated file system > Concepts > Scanning support**).

Type Y for the *Define or change the system at IPL* prompt. Follow the instructions on the displays.

Type the following and press Enter.

- System date (Use the current date.)
- System time (Use the current time, 24-hour clock.)
- System time zone (Verify that it is correct or press F4 to select a time zone.)
- Start system to restricted state Y
- Set major system options Y

14. Additional display messages could be shown.
Press Enter after each message to continue.
15. The Set Major System Options display appears.

Installing software on a new server (with OS/400 installed)

```
Set Major System Options

Type choices, press Enter.

Enable automatic configuration . . . . . Y           Y=Yes, N=No
Device configuration naming . . . . . *NORMAL       *NORMAL, *S36,
                                                    *DEVADR
Default special environment. . . . . *NONE         *NONE, *S36
```

Respond to the prompts on the Set Major System Options display.

- Enable automatic configuration
The value Y (Yes) automatically configures local devices. N (No) indicates no automatic configuration.
- Device configuration naming
Specify *NORMAL to use a naming convention unique to the iSeries server. The value *S36 uses a naming convention similar to System/36. Refer to the book *Local Device Configuration*, SC41-5121-00, for information about device configuration naming and *DEVADR.
- Default special environment
The default value *NONE indicates no special environment. *S36 sets up the System/36 environment. Refer to the book, *System/36 Environment Programming*, SC41-4730 (V4R5 or earlier), for more information about working in the System/36 environment on the iSeries server.

Press Enter.

16. The Edit Rebuild of Access Paths display could be shown. If it is, press Enter to continue.
17. The Work with Software Agreements display appears. Select to display the software agreements for the Licensed Internal Code (5722999) and the OS/400 operating system (5722SS1). Read and accept these agreements. If the software agreements are declined, you are given the choice to either power down the server or return and accept the agreements.
18. Several blank displays and Display Messages displays appear. To continue, press Enter for each message display. Do not respond to blank displays.

The following display is an example of a message that appears:

```
Display Messages

Queue . . . . . : QSYSOPR           System. . . . . : XXXX
Library . . . . : QSYS              Program . . . . : *DSPMSG
Severity . . . . : 10               Library . . . . :
Delivery . . . . :                   *BREAK

Press Enter to continue.
All jobs in system lost. Job and output queues cleared.
```

19. The OS/400 Main Menu appears on your console.

You have completed this task.

To install additional licensed programs, continue with the tasks in “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115.

Installing additional licensed programs

Use this topic to install additional licensed programs or optional parts of licensed programs on your server or logical partition. (Separately ordered features are installed as a licensed program.) You can use these procedures to install most software products. However, if you received any other special installation instructions with your order, make sure that you verify these instructions before you install the software product.

The following topics pertain to the tasks for installing additional licensed programs:

- “Before you begin to install additional licensed programs”
- “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115
- “Using the Restore Licensed Programs command to install IBM or non-IBM licensed programs” on page 120

Before you begin to install additional licensed programs

Use this information to add additional licensed programs either as part of a software release upgrade or independently of one.

If you have not already done so, complete the tasks in the iSeries Information Center topic “Preparing to install the OS/400 release” on page 87.

If you install an additional licensed program independently of a software release upgrade, check the following:

- Ensure that you have a recent copy of the cumulative PTF package (SF99530). When you order the cumulative PTF package, you also get the latest PTF HIPER Group CD-ROM (SF99529) and the Database Group CD-ROM (SF99503).
- Use the preventive service planning (PSP) information to determine if any prerequisite PTFs will need to be installed or if any special instructions are included for installing the licensed program.

The PTFs for licensed programs are on a separate media. Use the *iSeries PTF Shipping Information Letter* to install the cumulative PTF package after adding additional licensed programs.

If you add additional licensed programs and you have a secondary language installed on your system, you must install the secondary language after you install the licensed programs. Otherwise, the added licensed program will not have secondary language support.

Restricted state required: The system must be in a restricted state to install the following libraries and options of OS/400.

- OS/400 libraries QGPL and QUSRSYS
- OS/400 option 3 - Extended Base Directory Support
- OS/400 option 12 - Host Servers

Some licensed programs and libraries require a restricted state, while others only require a partially restricted system. However, put the system in a restricted state to avoid installation failures and to get the best performance during your upgrade.

Other licensed programs might require special actions before saving, restoring, or installing a new copy of the product. For example, IBM WebSphere MQ for iSeries, V5.3 requires its own specific procedure to restrict the product.

If you want to install other licensed programs while the system is not in a restricted state, you can skip steps 3a through 3e of “Using the Work with Licensed Programs menu to install IBM licensed programs.”

If you are selecting more than one licensed program and want to ensure that the products you select install as fast as possible, review the information in “Installation processes” on page 172. The topic, “Required: Accepting software agreements” on page 46 describes how to accept the software agreements for licensed programs before an upgrade to take advantage of multiprocess installation.

Do you plan to use or are you using logical partitions? For iSeries 8xx and earlier models, read the topic Plan for logical partitions in the iSeries Information Center (**Systems management > Logical partitions > Partitioning with iSeries Navigator > Plan for logical partitions**). For IBM @server^(R) 5xx models, read the topic Plan for OS/400 logical partitions in the IBM eServer^(TM) Hardware Information Center (**Partitioning the server > Partitioning for OS/400 > Plan for OS/400 logical partitions**).

Do you plan to use an image catalog (virtual optical device) to install? Read the topic “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53 to create a device, image catalog, and an image catalog entry. Information about upgrading

Using the Work with Licensed Programs menu to install IBM licensed programs

If you have logical partitions, you must perform this procedure on each partition to which you want to install the licensed programs.

1. If you are not already signed on to the server as the security officer (QSECOFR user profile), do so now.

Note: The OS/400 Main Menu (or the menu you chose as your initial menu) appears on the console.

2. If you are installing from an image catalog (virtual optical device), the setup instructions are in the topic “Scenario: Preparing to upgrade or replace software using an image catalog” on page 53.

If you are installing from optical media, insert the volume of the licensed program that you want to install into the installation device. If this is a new installation, start with OS/400 media volume B29xx_02. To install keyed products, load the volumes labeled L29xx_01 and L29xx_02. If you have priced features of OS/400 or single licensed programs, load the volume labeled F29xx_01. For more information on the optical media you received with your order, see “Media labels and their contents” on page 189. Wait until the In Use indicator goes out before you continue.

3. Do the following to put the system in a restricted state and filter the messages that appear:
 - a. Type CHGMSGQ QSYSOPR *BREAK SEV(60) and press Enter.
 - b. A message display could appear. Press Enter.

Installing additional licensed programs

- c. Type ENDSBS *ALL *IMMED and press Enter.
 - d. When the following message appears, press Enter to continue:
ENDSBS SBS(*ALL) command being processed
 - e. The message System ended to restricted condition appears. Press Enter to continue.
 - f. Type CHGMSGQ QSYSOPR SEV(95) and press Enter.
 - g. A message display could appear. Press Enter.
4. Type GO LICPGM and press Enter.
 5. The Work with Licensed Programs display appears.

```
LICPGM                Work with Licensed Programs                System:  XXXX
Select one of the following:

Manual Install
  1. Install all

Preparation
  5. Prepare for install

Licensed Programs
  10. Display installed licensed programs
  11. Install licensed programs
  12. Delete licensed programs
  13. Save licensed programs
```

If you want to accept software agreements for your licensed programs individually, continue with step 6.

If you have many licensed programs to install, accepting them together is faster than accepting them individually through manual installation. If you want to preaccept your licensed program agreements all at one time, select option 5 (Prepare for install).

- a. Select the option to work with software agreements. If a licensed program that you want to install does not appear on the Work with Software Agreements display, use F22 (Restore software agreements). Otherwise, continue with the next step.
 - b. Type 5 to display the licensed programs that you want to install and press Enter. Press F14 to accept the software agreements and then return to the Work with Licensed Programs display.
6. On the Work with Licensed Programs display, either type 1 (Install all) or type 11 (Install licensed programs). Read the following note to help you decide.

Note: If you want to install all licensed programs that are on the distribution media, use Manual Install option 1, Install all. This will save time for the installation. If you want most of the licensed programs on the media, then Manual Install option 1 is also the preferred choice. You will have to delete the extra unwanted licensed programs. The Manual Install display appears after selecting Manual Install option 1.

Type the following on this display:

```
Install option: 2 (2=all products)
Installation device: OPT01
Replace if current: N
Nonaccepted agreement: 2 (2=Display software agreement)
Automatic IPL: N
```

Installing additional licensed programs

In this example, OPT01 is used for the installation device. If you use a different naming convention, type the name that you have assigned to the installation device.

For more information about using option 1, refer to “Manual installation Option 1. Install all” on page 201.

Press Enter. If you typed 1, continue with step 10 on page 118 of these instructions.

7. If you typed 11, the Install Licensed Programs display appears.

Page through the display to find the licensed programs you want. Type a 1 in the Option column next to the licensed programs to be installed.

Install Licensed Programs

System: XXXX

Type options, press Enter.
1=Install

Option	Licensed Program	Product Option	Description
-	5722SS1		OS/400 - Library QGPL
-	5722SS1		OS/400 - Library QUSRSYS
-	5722SS1	1	OS/400 - Extended Base Support
-	5722SS1	2	OS/400 - Online Information
-	5722SS1	3	OS/400 - Extended Base Directory Support
-	5722SS1	5	OS/400 - System/36 Environment
-	5722SS1	6	OS/400 - System/38 Environment
-	5722SS1	7	OS/400 - Example Tools Library
-	5722SS1	8	OS/400 - AFP Compatibility Fonts
-	5722SS1	9	OS/400 - *PRV CL Compiler Support
-	5722SS1	12	OS/400 - Host Servers
-	5722SS1	13	OS/400 - System Includes

More...

F3=Exit F11=Display status/release F12=Cancel F19=Display trademarks

Note:

- The libraries QGPL and QUSRSYS, and Extended Base Support (option 1) and Extended Base Directory Support (option 3) are preselected if you are installing licensed programs as part of a new system installation. If you are adding additional (new) licensed programs or optional parts, these items would be preselected only if they are in an error state.
- A licensed program you want to install might not be listed on the Install Licensed Programs display. If a licensed program is not listed, it can be added to the list by entering information into the blank fields at the top of the list. After you press Enter, this product then appears on the list with the other products.
 - Type 1 in the Option column.
 - Type the product identifier in the Licensed Program column.
 - Type the product option value in the Product Option column.
 - Press Enter.

When you are typing the product option, the system accepts only the following three values: *BASE, option number, or *ALL.

- A value of *BASE installs only the base product of the associated product identifier.
- The product option number installs only the particular option of the associated product identifier. To be able to install options, you must install the base product (*BASE).

Installing additional licensed programs

- A value of *ALL installs the base product and all options of the associated product identifier that are found on the media.

Keep in mind that licensed programs that you add will appear on the list with only the product identifier and will not give a descriptive name of the product. Also, you should check the documentation that came with the product to see whether there are any special instructions.

If you get a message that the product already appears in the list, scroll down to the product. Make sure that there is a 1 in the Option column. Make sure that it is selected for installation.

Press Enter.

8. The Confirm Install of Licensed Programs display appears on the console. Press Enter to confirm your choices.
9. The Install Options display appears.

```

                                Install Options
                                System:  XXXX
Type choices, press Enter.
Installation device . . . . OPT01   Name
Objects to install . . . . 1       1=Programs and language objects
                                   2=Programs
                                   3=Language objects
Nonaccepted agreement. . . . 2     1=Do not install licensed program
                                   2=Display software agreement
Automatic IPL . . . . . N         Y=Yes
                                   N=No
```

Type the following on this display:

Installation device: OPT01 (In this example, OPT01 is used for the installation device. If you use a different naming convention, type the name that you have assigned to the installation device.)
Objects to install: 1
Nonaccepted agreement: 2
Automatic IPL: N

10. One or both of the following displays show the status of the licensed programs and language objects as they are being installed on the system. You do not need to respond to these status displays.

```

                                Installing Licensed Programs
                                System:  XXXX
Licensed programs processed . . . . . :    0 of XXX
                                Licensed program install in progress
```

The following display is an example of the display that appears during the installation process.

Installing additional licensed programs

```
Installing Licensed Programs                               System: XXXX
Licensed programs processed . . . . . : X of XXX
Licensed
Program Option Description                               Type
5722SS1  12   OS/400 - Host Servers                               2924
```

Note: This display shows which licensed programs and optional parts of licensed programs are being installed. After the *PGM objects and *LNG objects for each licensed program or optional part have been installed, the licensed program identifier disappears from the display and the number in the licensed programs processed field changes to show how many are processed.

11. You might see the Display Messages display. If you have another media volume that contains licensed programs to load, you can load it at this time. If you are installing from optical media, wait for the In Use indicator to go out before responding to the message.

```
Display Messages                                       System: XXXX
Queue . . . . . : QSYSOPR                               Program . . . . . : *DSPMSG
Library . . . . . : QSYS                               Library . . . . . :
Severity . . . . . : 95                               Delivery . . . . . : *BREAK

Type reply (if required), press Enter.
Load the next volume in optical device OPT01 (X G)
Reply . . . . G
```

Type G and press Enter. After you load each volume, type G and press Enter. If there are no more volumes to load that contain licensed programs, or if you want to end the loading process, type X and press Enter.

12. If a licensed program requires acceptance of a software agreement, the Software Agreements display appears. Do either of the following:
 - Press F14 to accept the agreement and allow the licensed program to continue installing.
 - Press F16 to decline the agreement and end the installation of that licensed program.
13. The Work with Licensed Programs display appears on your console when the installation process is completed. One of the following messages appears on the bottom of the Work with Licensed Programs display:

Work with licensed programs function not complete. Go to the topic Chapter 10, "Troubleshooting software installation problems," on page 143 to determine the problem.

Work with licensed programs function has completed. Continue with the next step.
14. Verify the installed status values of your licensed programs and check for compatibility. It is important to make sure all of your licensed programs are compatible with the operating system.

Use LICPGM menu option 10 (Display licensed programs) to see the release and installed status values of the installed licensed programs. If the installed status value of a licensed program is *COMPATIBLE, it is ready for use. If the installed status value of a licensed program is *BACKLEVEL, the licensed program is installed, but its version, release, and modification is not compatible with the currently installed level of the OS/400 operating system.

Installing additional licensed programs

Check the topic, “Licensed program releases and sizes” on page 166, to verify the current version, release, and modification of the licensed program. “Installed status values” on page 197 lists the possible installed status value descriptions.

You have completed this task.

1. Do you have more licensed programs or optional parts to install, but they did not appear in the list displayed in step 7 on page 117 (or could not be added to the list)?
 - **No.** Go to the next step (step 2).
 - **Yes.** Go to “Using the Restore Licensed Programs command to install IBM or non-IBM licensed programs” to install these licensed programs or optional parts.
2. Do you need to install a secondary language?
 - **No.** Go to the next step (step 3).
 - **Yes.** Go to “Installing a secondary language” on page 121 and complete the instructions.
3. You must complete the installation process before you put your system into operation. Go to “Checklist: Completing the installation” on page 125 and complete the instructions.

Using the Restore Licensed Programs command to install IBM or non-IBM licensed programs

You might be instructed to use the RSTLICPGM command to install non-IBM licensed programs. All IBM-supplied licensed programs, including Programming Request for Price Quotations (PRPQs), licensed program offerings (LPOs), and single-set licensed programs, should have been installed already by using the LICPGM menu options 1 or 11, or during automatic installation.

Note: If you do not have non-IBM licensed programs, you can skip this task. If you need to install a secondary language, go to “Installing a secondary language” on page 121 and complete the instructions. Otherwise, you must complete the installation process and then go to “Checklist: Completing the installation” on page 125 and complete the instructions.

1. You might have received special installation instructions with these products. If you did, you should use those instructions.
2. Load the media containing the licensed program or optional part in the installation device.
3. If you have non-IBM software agreements to accept, you can either preaccept all your licensed program agreements at one time, such as when you install products in a batch process, or you can accept them individually later. To accept all your software agreements now, type GO LICPGM. Select option 5 (Prepare for install).
 - a. Select the option to work with software agreements. On the Work with Software Agreements display, use F22 (Restore software agreements).
 - b. Type 5 to accept the licensed programs that you want to install and press Enter. Follow the directions to accept the software agreements and then return to the Work with Licensed Programs display.
4. In the following steps, OPT01 is used for the installation device. If you are using a different naming convention, use the name you have assigned to the installation device.

To install a new licensed program, type the command:

Installing additional licensed programs

```
RSTLICPGM LICPGM(xxxxxxx) DEV(OPT01) OPTION(*BASE)
```

where *xxxxxxx* is the product identifier for the licensed program you are installing.

Press Enter. You might see an online software agreement. If you accept the software agreement, you can continue to install and use the program.

5. To install a new optional part, type the command:

```
RSTLICPGM LICPGM(xxxxxxx) DEV(OPT01) OPTION(n)
```

where *xxxxxxx* is the product identifier for the licensed program you are installing and *n* is the option number.

Press Enter. You might see an online software agreement. If you accept the software agreement, you can continue to install and use the option.

6. Repeat steps 4 and 5 until you have installed all of the new licensed programs and optional parts that could not be installed in “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115.

You have completed this task.

1. Do you need to install other licensed programs such as Lotus Domino for iSeries, TCP/IP, or WebSphere® to allow your company to participate over the Internet with other e-businesses?
 - **No.** Go to the next step.
 - **Yes.** Go to the iSeries Information Center e-business and Web serving category.
2. Do you need to install a secondary language?
 - **No.** Go to the next step.
 - **Yes.** Go to “Installing a secondary language” and complete the instructions.
3. You must complete the installation process before you put your system into operation. Go to “Checklist: Completing the installation” on page 125 and complete the instructions.

Installing a secondary language

This topic contains instructions for installing a secondary language on your system or logical partition.

- “Before you begin to install a secondary language”
- “Installing secondary languages for IBM licensed programs”
- “Installing secondary languages for non-IBM licensed programs” on page 124

Before you begin to install a secondary language

Complete the tasks in the iSeries Information Center topic: “Preparing to install the OS/400 release” on page 87. Pay particular attention to the “Globalization and software installation” on page 20 topic for more information about installing and using secondary languages.

Installing secondary languages for IBM licensed programs

1. You must sign on to the system as QSECOFR. If you are not, sign off and then sign on again using QSECOFR.

Installing a secondary language

2. Write down the national language version identifier on the secondary language media. You will need this in step 8. _____
Secondary language media is identified by the N29xx on the label. The identifier is in the form 29xx, where xx is a unique number for each language. To find the appropriate feature code for your language, refer to "Feature codes for national language version" on page 195.
3. Load the secondary language media volume in the installation device.
4. Type the following command on any command line and press Enter:
CHGMSGQ QSYSOPR *BREAK SEV(95)
5. A message display could appear. Press F3 (Exit).

Note: Ignore the messages that are shown.

6. Type GO LICPGM on any command line and press Enter:
7. The Work with Licensed Programs menu appears. Use the page down or rollout key to see the second display of the Work with Licensed Programs menu.

```

LICPGM                Work with Licensed Programs                System: XXXX
Select one of the following:

Secondary Languages
 20. Display installed secondary languages
 21. Install secondary languages
 22. Delete secondary languages
  
```

Type 21 and press Enter.

8. The Install Secondary Languages display appears.

```

                Install Secondary Languages                System: XXXX
Primary language . . . . . : 2924
Description . . . . . : English

Type options, press Enter.
 1=Install

Option Language Description Library Installed
-      2902 Estonian      QSYS2902 Release
-      2903 Lithuanian   QSYS2903
-      2904 Latvian      QSYS2904
-      2905 Vietnamese   QSYS2905
-      2906 Lao          QSYS2906
-      2909 Belgian English QSYS2909
 1     2911 Slovenian    QSYS2911
-      2912 Croatian     QSYS2912
  
```

Use the Page Down key until you see the language that you want to install. Type 1 in the option column next to the language you want to install. You can install only one language at a time. Press Enter.

9. After the language feature is entered, the Confirm Install of Secondary Languages display is shown.

```

                Confirm Install of Secondary Languages        System: XXX
Press Enter to confirm your choices for 1=Install.
Press F12 to return to change your choices.

Option Language Description Library Installed
 1     2911 Slovenian    QSYS2911 Release
  
```

Press Enter.

10. The Install Option for Secondary Languages appears.

```

      Install Option for Secondary Languages                System:  XXX
Type choice, press Enter.

Installation device . . . . . OPT01          Name
Replace if Current . . . . .  N             Y=Yes
                                           N=No
    
```

Type the following and press Enter:

Installation device: OPT01 (See note.)
 Replace if Current: N

Note: OPT01 is used for the installation device in this example. If you are using a different naming convention, type the name you have assigned to the installation device.

One or both of the following displays show the status of the language objects as they are installed on the system.

```

      Installing Licensed Programs                        System:  XXXX

Licensed programs processed . . . . . :      0 of XXX

      Licensed program install in progress
    
```

The following display is an example of the display that appears during the installation process.

```

      Installing Licensed Programs                        System:  XXXX

Licensed programs processed . . . . . :      X of XXX

Licensed
Program  Option  Description                                Type
5722WDS  *BASE   WebSphere Development Studio                2911
    
```

11. If you see the following message, load the next volume of the secondary language media and continue the installation.

Note: Be certain that the label on the next volume is for the same secondary language.

```

      Display Messages                                  System:  XXXX

Queue . . . . . :  QSYSOPR          Program . . . . . :  *DSPMSG
Library . . . . . :  QSYS           Library . . . . . :
Severity . . . . . :    95          Delivery . . . . . :  *BREAK

Type reply (if required), press Enter.
Load the next volume in optical device OPT01 (X G)
Reply . . . . . G
    
```

Type G and press Enter. After you load each volume, type G and press Enter. If there are no more volumes to load that contain licensed programs, or if you want to end the loading process, type X and press Enter.

Installing a secondary language

12. The Work with Licensed Programs display appears on your console when the installation process is completed. One of the following messages appears on the bottom of the Work with Licensed Programs display:

Work with licensed programs function not complete. Go to the topic Chapter 10, "Troubleshooting software installation problems," on page 143 to determine the problem.

Work with licensed programs function has completed. Continue with the next step.

Note: Some licensed program options do not have language objects or are not supported for secondary languages. For example, options 6, 7, and 9 of the operating system are not supported. Option 8 of the operating system does not have any language objects. You can use LICPGM menu option 20 to see the products that have secondary languages installed.

You have completed this task.

1. Do you have more secondary languages to install?
 - **No.** Go to the next step.
 - **Yes.** Go back to step 2 at the beginning of this topic.
2. Do you need to install secondary languages for licensed programs that are not shown in the list using option 11 of the Work with Licensed Programs menu?
 - **No.** Go to the next step.
 - **Yes.** Go to "Installing secondary languages for non-IBM licensed programs" to install secondary languages for these licensed programs.
3. You must complete the installation process before you put your system into operation. Go to "Checklist: Completing the installation" on page 125 and complete the instructions.

Installing secondary languages for non-IBM licensed programs

You might be instructed to use the Restore Licensed Program (RSTLICPGM) command to install secondary languages for non-IBM licensed programs. All IBM-supplied licensed programs, including Programming Request for Price Quotations (PRPQs), licensed program offerings (LPOs), and single-set licensed programs, should have had secondary languages installed already by using the LICPGM menu option 21.

Note: If you do not have non-IBM licensed programs, you can skip this task. However, you must complete the installation process. Go to "Checklist: Completing the installation" on page 125 and complete the instructions.

1. You might have received special installation instructions with independently shipped licensed programs (those that are not on the same media as the software release). If you did, you should use those instructions.
2. Load the media volume containing the secondary language that you want to install.

In the following steps, OPT01 is used for the installation device. If you are using a different naming convention, use the name you have assigned to the installation device.

3. To install a secondary language for a licensed program, type this command and press Enter:

```
RSTLICPGM LICPGM(xxxxxxx) DEV(OPT01)
OPTION(*BASE) RSTOBJ(*LNG) LNG(29xx)
```

where *xxxxxxx* is the product identifier for the licensed program and *29xx* is the national language version feature code.

4. To install secondary language for an optional part of a licensed program, type this command and press Enter:

```
RSTLICPGM LICPGM(xxxxxxx) DEV(OPT01)
OPTION(n) RSTOBJ(*LNG) LNG(29xx)
```

where *xxxxxxx* is the product identifier for the licensed program, *n* is the option number, and *29xx* is the national language version feature code.

5. Repeat steps 3 and 4 until you have installed all of the secondary languages for the licensed programs and optional parts that were independently installed.

You have completed this task.

You must complete the installation process before you put your system into operation. Go to “Checklist: Completing the installation” and complete the instructions.

Checklist: Completing the installation

Use this checklist to complete any of the installation processes in this topic.

- ___ 1. If you still have default passwords for your service tools user IDs, change them now. For information on service tools user IDs, see Change service tools user IDs and passwords in the iSeries Information Center (**Security > Service tools user IDs and passwords > Manage service tools > Manage service tools user IDs > Change service tools user IDs and passwords**).
- ___ 2. Remove the media volume when the installation is complete. If your media is tape, wait for the tape to rewind completely.
- ___ 3.

For logical partitions only

<p>Attention: Do not perform this step to install the cumulative PTF package until after you are aware of the unique PTF installation considerations involved on a server with logical partitions. You could potentially lose data. Refer to the topic Install fixes on systems with logical partitions in the iSeries Information Center (OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Install fixes > Step 3: Choose your fix installation scenario > Install fixes on systems with logical partitions) to understand how to install the cumulative PTF package on a system with logical partitions.</p>

Install the most current cumulative PTF package. (This package should have been ordered a week or two before your installation.) Use the instructions in the *PTF Shipping Information Letter*. Then return here and continue with the next step.

Note: If you do not install the cumulative PTF package now, you need to perform an IPL and let the Initialize System (INZSYS) process complete. Before you do, set the IPL type to **B** (or the IPL type you use for everyday operation) and then set the mode selection to **Normal**. “Initialize System (INZSYS) recovery” on page 157 has more information on INZSYS.

- ___ 4. Apply any PTF groups that you have ordered. For more information on PTF groups, refer to “Ensuring you have the latest information” on page 91. To apply PTF groups, refer to the cover letter and instructions for the program temporary fix (PTF). For general information on applying PTFs,

Checklist: Completing the installation

go to Advanced procedures for fix installation in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes > Install fixes > Advanced procedures for fix installation**).

- 5. If your system is operating as a service partition and your server is not being managed by a Hardware Management Console for @server^(R), you might be required to perform a server IPL. A *server IPL* is an IPL whereby all logical partitions on the server are shut down at the same time. This allows, for example, a new level of the server firmware to be activated on the server.

You might be required to perform a server IPL after you apply or remove a PTF on the service partition if that PTF affects the server firmware portion of the Licensed Internal Code. You also might be required to perform a server IPL after you upgrade or install a new level of the Licensed Internal Code on the service partition.

To find out if you need to do a server IPL, type DSPPTF 5722999 on the command line and press Enter. If a server IPL is required, message CPD35F8 Server IPL required is shown at the bottom of the display.

To find out if your system is operating as a service partition, type DSPPTF 5729999 on the command line and press Enter. If your system is operating as a service partition, the IPL Source field indicates the copy of the server firmware that was used on the previous server IPL.

- 6. Look for messages in the install history log that indicate the status of the Initialize System (INZSYS) process:
 - a. Type G0 LICPGM and press Enter.
 - b. Type 50 (Display log) on the Work with Licensed Programs display, and press Enter.
 - c. The Display Install History display appears. Press Enter.

The Display History Log Contents display appears. If you do not see either of the following messages on the display, wait a few minutes and select option 50 again. Find the message Initialize System (INZSYS) started. After this message appears, wait for a period of time and look for the Initialize System (INZSYS) processing completed successfully message (CPC37A9). If you do not see message CPC37A9 on the display, go to “Initialize System (INZSYS) recovery” on page 157 to determine the problem.

- 7. If you used image catalogs to perform your installation, you might want to remove all installation images from your server. To delete the catalog and all the optical images (image files), type the following:

```
DLTIMGCLG IMGCLG(mycatalog) KEEP(*NO)
```

- 8. Install software license keys for your OS/400 and keyed products. Use the Work with License Information (WRKLICINF) command to display the installed keyed products to add license key data. For specific instructions, go to Add license key information in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Work with software agreements and licenses > Manage software agreements and license keys > Display and change software license information > Add license key information**).

After updating the license key information, return here and continue with the next step.

- 9. After you complete the installation process and before you make the server available to all users, you must set the usage limit for the software-license

Checklist: Completing the installation

managed products. These products are listed on the Proof of Entitlement (POE), invoice, or other documents that you have received with your software order. For products that have a usage limit, you set the usage limit with the Work with License Information (WRKLICINF) command.


To set your usage limit, do the following:

- ___ a. Type WRKLICINF and press Enter.
 - ___ b. On the Work with License Information display, press F11 (Display Usage Information). The usage limit number on each product that is listed on the POE, invoice, or other documents must match the usage limit number on the Work with License Information display for the associated product.
 - ___ c. Move the cursor to the line that contains the product name whose usage limit is to be updated.
 - ___ d. Type 2 (Change) and press Enter.
 - ___ e. When the Change License Information display is shown, update the usage limit prompt with the usage limit shown on the POE. In addition, update the threshold prompt with either *CALC or *USGLMT. Do not leave the threshold set to zero.

Note: If message CPA9E1B [Usage limit increase must be authorized. Press help before replying (C G).] is sent, respond by typing G.
 - ___ f. If the POE lists more products than the Work with License Information display, set the usage limits after you install those products.
- ___ 10. If you have installed the product 5722-VI1, Content Manager, you can use the product. However, you must perform post-installation commands. For more information, refer to the Post Installation section in the product document *IBM ImagePlus VisualInfo for AS/400: Planning and Installation Guide*, GC34-4585 (V4R5 or earlier).
 - ___ 11. If you have not already verified the compatibility of your licensed programs with the OS/400, then do this now. Use LICPGM menu option 10, Display installed licensed programs. If *COMPATIBLE is not listed next to a licensed program, then go to "Installed status values" on page 197 and determine how to proceed.
 - ___ 12. If you changed the scan control (QSCANFSCCTL) system value to minimize future scanning of some objects that are restored before you installed your licensed programs, you can now remove the *NOPOSTRST specification from this system value.
 - ___ 13. If you changed any other system value such as for example security level (QSECURITY) during your installation, you can change it back now.
 - ___ 14. Some of the tasks in this topic require that you change the QSYSOPR severity code filter to 95. If you do not want to continue with this level or you want to change the delivery notification, type CHGMSGQ QSYSOPR DLVRY(xx) SEV(yy) where *xx* indicates the delivery notification and *yy* indicates the severity code that you want to use. The system defaults are DLVRY(*HOLD) SEV(0).
 - ___ 15. Save your system using your normal save procedures. Refer to the instructions in the Back up your server topic in the iSeries Information Center (**Systems management > Backup and recovery > Back up your server**). Make sure that the Initialize System (INZSYS) process is complete before you save your system.

Checklist: Completing the installation

Note: Before you start a save operation, use the Work with Active Jobs (WRKACTJOB) command to check the status of QDCPOBJx jobs. These jobs decompress objects. There could be more than one QDCPOBJx job. You can start your save operation if these jobs are in an inactive state. If you put the system in a restricted state by ending subsystems, the QDCPOBJx jobs become inactive. The jobs will restart when the system is not in a restricted state. For more information about decompressing objects, see “Compressed objects and storage space” on page 20.

- ___ 16. If you plan to install and use the iSeries Information Center either from a workstation or the iSeries, refer to the CD-ROMs that come with your IBM Operating System/400 order: *iSeries Information Center*, SK3T-4091. This package also includes the PDF versions of iSeries manuals. For the installation instructions, see the readme.txt file.
- ___ 17. If you have installed IBM @server iSeries Access Family products, you might have other tasks that you need to complete. You can find further information about installing iSeries Access Family products in the following sources:
 - iSeries Access for Windows in the iSeries Information Center (**Connecting to iSeries > iSeries Access > iSeries Access for Windows**).
 - The IBM @server iSeries Access Family Web site  (<http://www.ibm.com/eserver/series/access>).
- ___ 18. You might have installed licensed programs that require additional installation steps on PCs. Or, you might have programs that install on PCs through an iSeries Access Family function. If you have products such as this, complete your PC installation by using the instructions for the product.
- ___ 19. If you have an Integrated xSeries Server that you stopped before you began the installation process, restart it now.
 - a. Type GO NWSADM on the iSeries command line. The Network Server Administration display appears.
 - b. Select option 2, Start a network server.
- ___ 20. If you installed 5722-TC1, TCP/IP Utilities, go to the topic TCP/IP setup in the iSeries Information Center (**Networking > TCP/IP setup**) for advanced configuration and setup information.
- ___ 21. If you installed 5722-JV1, IBM Developer Kit for Java, verify that the program is installed and is working correctly. Type java Hello on a command line, and press Enter. You should see the message Hello World. Java program completed.

IBM Developer Kit for Java in the iSeries Information Center (**Programming > Java > IBM Developer Kit for Java**) contains additional information about the licensed program.
- ___ 22. If you have customized an IBM-supplied program (for example, QSTRUP in library QSYS) in a previous release, make sure that you re-create this program to run correctly in the new release.
- ___ 23. If you have duplicated any IBM-supplied objects, you might want to make new duplicates after you install the release. This allows you to take advantage of functions added in the new release. Examples of objects that you might duplicate include the following:
 - Message text descriptions
 - Commands
 - Command defaults

Checklist: Completing the installation

You have completed your installation.

Checklist: Completing the installation

Chapter 8. Changing the primary language of your server or logical partition

This topic contains the instructions to install a primary language from either a secondary language media set or a primary language media set. Please follow the directions closely because you will use different options based on the type of media.

Notes:

1. If you have logical partitions, you must perform these instructions for each partition to which you change the primary language.
2. Image catalogs (virtual optical devices) do not support the procedures in this topic.

The following topics pertain to the tasks for changing the primary language:

1. "Before you begin to change the primary language"
2. "Changing the primary language" on page 132
3. "Installing the licensed programs after changing the primary language" on page 135

Before you begin to change the primary language

Before you begin to change the primary language, read the topic, "Globalization and software installation" on page 20.

Obtain either of the following media:

- A complete set of the primary language media, which includes the Operating System/400 (5722-SS1). The media labels include the characters B29xx_01, for example, where 29xx is the language feature code for the primary language that you want to install. Use either the steps in this topic collection ("Changing the primary language" on page 132) or, if you want to change your primary language as part of a release upgrade, then refer to "Upgrading or replacing software using automatic installation" on page 56 or "Upgrading or replacing software using manual installation" on page 64.
- Secondary language media. You need to ensure that the media label includes the characters N29xx and the name of the language. The character N indicates that the media contains only language objects, and 29xx is the language feature code of the secondary language. You will also need the B29xx_01 media from your system's primary language media set. Follow the instructions for using secondary language media in "Changing the primary language" on page 132.

Note: If the label on the secondary language media does not match this description, do not continue with the instructions in this part. If the letter B precedes the language feature code, go to "Installing software on a new server or logical partition (without OS/400 installed)" on page 100 and use those instructions to change your primary language.

The release and modification of your system must be the same as the release and modification of your secondary language media.

If you have not already done so, complete the tasks in "Preparing to install the OS/400 release" on page 87.

Changing the primary language

Attention: You cannot change your primary language to a language you currently have installed as a secondary language on your system. You must delete the secondary language first before you can change it to your primary language. Go to “Option 22. Delete secondary languages” on page 208 for more information about deleting secondary languages.

If you have secondary logical partitions, you must perform these instructions for each partition to which you change the primary language.

To change the primary language on the server or logical partition, do the following:

1. Begin at the OS/400 Main Menu (or the menu you chose as your initial menu).

Load the first volume of the media that contains the operating system (5722-SS1). This volume is labeled B29xx_01.

Note: Do not load your secondary language media at this time.

2. Use the control panel to switch the mode to **Manual**.
3. Type `PWRDWN SYS OPTION(*IMMED) RESTART(*YES)` and press Enter.
4. Wait for the IPL or Install the System display to appear on your console.

```
                                IPL or Install the System
                                System: XXXX

Select one of the following:

    1. Perform an IPL
    2. Install the operating system
    3. Use Dedicated Service Tools (DST)
    4. Perform automatic installation of the operating system
    5. Save Licensed Internal Code
```

Type 2 (Install the operating system) and press Enter.

```
                                Install Device Type Selection
                                System: XXXX

Select the installation device type:

    1. Tape
    2. Optical
    3. Virtual optical - preselected image catalog
```

Type 2 (Optical) and press Enter.

5. The Confirm Install of OS/400 display is shown on your console. Press Enter.
6. The Select a Language Group display shows the primary language currently installed on the system. Change the primary language of your system by specifying the language feature code of the secondary language media on this display.

For example, assume the primary language is English (2924) and you are using secondary language media to change it to Portuguese (2922). This display would appear showing 2924. You would type 2922.

Changing the primary language

```
                Select a Language Group
                System: XXXX
Note: The language feature shown is the language feature
installed on the system.
Type choice, press Enter.
Language feature . . . . . 2924
```

Type the numbers of the feature code for the language you want and press Enter.

7. After the language feature code is entered, the Confirm Language Feature Selection display appears on your console. Press Enter.
8. Some status displays appear on the console. You do not need to respond to any of these status displays. The following is an example of a status display:

```
                Licensed Internal Code IPL in Progress
IPL:
Type . . . . . Attended
Start date and time . xx/xx/xx xx:xx:xx
Previous system end . Normal
IPL step . . . . . : Storage Management Recovery
```

The following list shows some of the IPL steps that are shown on the IPL Step in Progress display.

- Authority Recovery
- Journal Recovery
- Database Recovery
- Journal Synchronization
- Start the Operating System

Some of the IPL steps could take a long time.

9. The Install the Operating System display appears when the IPL is complete.

```
                Install the Operating System
Type options, press Enter.
Install
option . . . . . 2          1=Take defaults (No other
                             options are displayed)
                             2=Change install options
Date:
Year . . . . . —          00-99
Month . . . . . —         01-12
Day . . . . . —           01-31
Time:
Hour . . . . . —          00-23
Minute . . . . . —        00-59
Second . . . . . —        00-59
```

Type the following and press Enter.

- Install option: 2
- Date (Use the current year, month, and day.)
- Time (Use the current time, 24-hour clock.)

10. The Installation Status display appears. You do not need to respond to this display.

Changing the primary language

11. The Specify Install Options display appears.

```
Specify Install Options
Type options, press Enter.
Restore option . . . . . 4      1=Restore programs and language objects
                                from the current media set
                                2=Do not restore programs or
                                language objects
                                3=Restore only language objects
                                from current media set
                                4=Restore only language objects
                                from a different media set using the
                                current install device.
Job and output
queues option . . . . . 2      1=Clear, 2=Keep
Distribute OS/400 on
available disk units . . . . 2  1=Yes, 2=No
```

- a. Type either of the following for the restore option:
 - 1) 3 (Restore only language objects from current media set) if you are installing from the primary language media.
 - 2) 4 (Restore only language objects from a different media set using the current install device) if you are installing from the secondary language media.
 - b. Type 2 for the Job and output queues option and press Enter.
12. Based on the type of media you are using, perform either of the following steps:

- If you are using secondary language media, the Installation Status display appears. You do not need to respond to this display. When the following message appears, load the volume that contains secondary language media, which is labeled N29xx. The value 29xx is the feature code of the secondary language.

```
Message
Message ID . . . . . : CPA2057      Type . . . . . : Inquiry
From program . . . . . : XXXXXXXX   Severity . . . . : 99
Language ID . . . . . : 2922
Message . . . . . : The installation media containing language objects
                    for the system language is needed to continue the installation
                    process.
Recovery . . . . . : Load the installation media containing language objects
                    for the specified language.
Type choice, press Enter.
Reply . . . . . 1      1=Continue, 2=End installing
```

Type 1 and press Enter.

The system searches through the media and loads the necessary language information. The Installation Status display appears, indicating that the language is being changed (in stage 3). The installation continues through the remaining stages. This display does not require a response.

- If you are using primary language media, insert the correct media when you are prompted.
13. After the base part of the operating system has been changed to the new primary language, the Sign On display appears on your console. Continue with the steps to change the language objects for the licensed programs in Installing the licensed programs after changing the primary language.

Installing the licensed programs after changing the primary language

If you have secondary logical partitions, you must perform this procedure on each partition to which you want to install the licensed programs.

1. Begin at the Sign On display.

```

                                Sign On
                                System. . . . : XXX
                                Subsystem . . . : XXXXX
                                Display . . . . : XXXXXXXX

User. . . . . QSECOFR
Password. . . . .
Program/procedure . . . . .
Menu. . . . .
Current library . . . . .
    
```

Type QSECOFR for the *User* prompt, and type your password, if required. Press Enter.

2. Several display messages appear. To continue, press Enter on each display. The following is an example of a message that might appear:

```

                                Display Messages
                                System: XXXX

Queue . . . . . : QSYSOPR          Program . . . . . : *DSPMSG
Library . . . . . : QSYS           Library . . . . . :
Severity . . . . . : 10           Delivery . . . . . : *BREAK

Press enter to continue.
System object QWCSCPF created again during IPL.
    
```

3. The IPL Options display appears.

```

                                IPL Options

Type choices, press Enter.

System date . . . . . XX / XX / XX   MM / DD / YY
System time . . . . . XX : XX : XX   HH : MM : SS
System time zone . . . . . Q0000UTC   F4 for list
Clear job queues. . . . . N         Y=Yes, N=No
Clear output queues . . . . . N       Y=Yes, N=No
Clear incomplete job logs . . . . . N   Y=Yes, N=No
Start print writers . . . . . Y       Y=Yes, N=No
Start system to restricted state . . . . . Y   Y=Yes, N=No

Set major system options. . . . . Y       Y=Yes, N=No
Define or change system at IPL. . . . . N       Y=Yes, N=No

Last power-down operation was ABNORMAL
    
```

Changing the primary language

Note: Ignore the message on the bottom of the IPL Options display.

Type the following and press Enter.

System date (Use the current date.)

System time (Use the current time, 24-hour clock.)

System time zone (Verify that it is correct or press F4 to select a time zone.)

Start system to restricted state Y

Set major system options N

4. Additional display messages could be shown.
Press Enter after each message to continue.
5. The OS/400 Main Menu (or the menu you chose as your initial menu) appears on your console.
Type CHGMSGQ QSYSOPR *BREAK SEV(95) and press Enter.
6. A message display could appear. Press Enter.
7. The OS/400 Main Menu (or the menu you chose as your initial menu) appears again.
Type GO LICPGM and press Enter.
8. The Work with Licensed Programs display appears.

```
LICPGM                Work with Licensed Programs                System:  XXXX
Select one of the following:

Manual Install
  1. Install all

Preparation
  5. Prepare for install

Licensed Programs
  10. Display installed licensed programs
  11. Install licensed programs
  12. Delete licensed programs
  13. Save licensed programs
```

If you are using primary language media, type 11, press Enter, and go to step 9.

If you are using secondary language media, type 1, press Enter and go to step 12 on page 137.

9. The Install Licensed Programs display appears. Type 1 in the option column next to the IBM products and options that have *COMPATIBLE or *INSTALLED as the installed status value and which exist on the media you will use for the installation. Press Enter.
10. The Confirm Install of Licensed Programs display appears. Press Enter to confirm your choices or press F12 to return to the Install Licensed Programs display and change your choices.
11. The Install Options display appears.

Changing the primary language

```
Install Options
System: XXXX
Type choices, press Enter.
Installation device . . . OPT01      Name
Objects to install . . . . 3          1=Programs and language objects
                                   2=Programs
                                   3=Language objects
Nonaccepted agreement. . . 2          1=Do not install licensed program
                                   2=Display software agreement
Automatic IPL . . . . . N           Y=Yes
                                   N=No
```

Type the following on this display:

Installation device: OPT01 (In this example, OPT01 is used for the installation device. If you use a different naming convention, type the name that you have assigned to the installation device.)

Objects to install: 3

Nonaccepted agreement: 2

12. One or both of the following displays show the status of the licensed programs and language objects as they are being installed on the system. You do not need to respond to these status displays.

```
Installing Licensed Programs
System: XXXX
Licensed programs processed . . . . . : 0 of XXX
Licensed program install in progress
```

The following display is an example of the display that appears during the installation process.

```
Installing Licensed Programs
System: XXXX
Licensed programs processed . . . . . : X
Licensed
Program Option Description Type
5722SS1 OS/400 - Library QUSRSYS 2922
```

13. If you see the following message, load the next volume of the language media and continue the installation.

Note: Be certain that the label on the next volume is for the same language.

```
Display Messages
System: XXXX
Queue . . . . . : QSYSOPR      Program . . . . . : *DSPMSG
Library . . . . : QSYS         Library . . . . . :
Severity . . . . : 95          Delivery . . . . . : *BREAK
Type reply (if required), press Enter.
Load the next volume in optical device OPT01 (X G)
Reply . . . . G
```

Type G and press Enter. After you load each volume, type G and press Enter. If there are no more volumes to load that contain licensed programs, or if you want to end the loading process, type X and press Enter.

Changing the primary language

14. The Work with Licensed Programs display appears on your console when the language objects for all of the licensed programs are installed. One of the following messages appears on the bottom of the Work with Licensed Programs display:

Work with licensed programs function has completed. Press F3 (Exit) to return to the OS/400 Main Menu.

Work with licensed programs function not complete. Go to Chapter 10, "Troubleshooting software installation problems," on page 143 to determine the problem.

You have completed this task.

To complete your installation, go to "Checklist: Completing the installation" on page 125 and follow the instructions there.

Chapter 9. Deleting software related to OS/400

Use the following information to help you determine if you should delete an unwanted part of a licensed program. For example, some licensed programs have requirements that certain parts of OS/400 be installed. These requirements are not always apparent. You can use the procedures in this topic to delete the parts of licensed programs you have determined you do not need.

“Determining what unused parts of products to delete”

You might be able to delete some optional parts of licensed programs to give you more storage.

“Considerations for deleting licensed programs” on page 141

Review these notes to determine unique situations that can occur when deleting some licensed programs.

“Deleting licensed programs” on page 141

Follow these instructions to delete a licensed program.

Determining what unused parts of products to delete

Depending on your business needs, you might be able to delete some of the optional parts of the licensed programs that are shown in Table 8 on page 140. (Table 8 shows V5R3 product identifiers, but the information in the table applies to deleting unwanted parts either before or after installing the new release of software.) For example, you can delete the licensed programs for any iSeries Access Family clients that you do not use. Deleting unwanted licensed programs or optional parts will give you more storage for your business needs.

Before deleting anything, read the following:

- If you do not have the original or a current copy of OS/400 software distribution media, make sure that you first save the affected licensed program. Type GO LICPGM on the command line and select option 13 (Save licensed programs). You will need extra tapes for this save operation. To save these licensed programs to tape can take several hours. At a later time, if you need any of the licensed programs or deleted optional parts, you can install them from these tapes. To install them, use GO LICPGM and select option 11 (Install licensed programs).
- System backup tapes come with some systems. These backup tapes are not the same as software distribution media. While you can use software distribution media to reinstall individual licensed programs or optional parts, you cannot use system backup tapes. If you cannot locate or your system did not come with the original installation media, you must save the licensed programs and optional parts before you delete them. You will need the saved copy, if you need to restore the licensed programs or optional parts at a future time.

Use Table 8 on page 140, the Chapter 11, “Software reference,” on page 165 topics (**Installation notes about the OS/400 release** and **Installation notes about other licensed programs**), and the keys in the following table to help you determine which programs or optional parts you might want to delete.

Deleting software related to OS/400

Table 7. Keys for deleting unwanted licensed programs table

Key	Description
a	You cannot delete the entire OS/400 operating system. You can delete optional parts, but you cannot delete OS/400 option 1 or option 3.
b	IBM recommends that you do not delete this part.
c	Delete this optional part if you are running only iSeries applications.
d	This optional part is needed only by software developers.
e	Do not delete this optional part if you are using the Print Services Facility/400.
f	Delete this part if you do not need to compile CL programs for a previous release.
g	This option is a separately orderable feature.
h	This optional part is needed if you use Unicode applications.
i	Do not delete if you are using IBM @server iSeries Access Family products.
j	If you are not using this specific client, you can delete the complete licensed program for that client.
k	If you delete this optional part, you must first remove QHLPSYS from the system library list. Refer to note 141 for more information.
l	You can delete these if you are not using them.
m	To prevent the problem of not getting Application Program Driver (Application Program Driver) converted for use with PowerPC® technology and redoing all Application Program Driver work, IBM strongly advises you to configure Application Program Driver to disable the Simplified Sign-on Panel. Perform the following steps to disable the Simplified Sign-on Panel and enable the Standard Sign-on Panel. Sign on with a user ID that has authority identical to QSECOFR and enter STRAPD: <ol style="list-style-type: none"> 1. Select 1. Application Program Driver 2. Select 2. Install and Delete Applications 3. Select 6. Install the Standard Sign-on Panel After following these steps, the Standard Sign-on Panel will be active. You can save your data and begin the migration.

Table 8. Deleting unwanted licensed programs and optional parts after the installation is complete

Keys	Licensed program and optionally installable product part	Number for product option
a	5722-SS1 OS/400	
a	Extended Base Support	1
k	OS/400 Online Information (Online help information)	2
a	Extended Base Directory Support	3
c	OS/400 System/36 and System/38™ Environment	5 and 6
d	OS/400 Example Tools Library	7
e	OS/400 AFP™ Compatibility Fonts	8
f	OS/400 *PRV CL Compiler Support	9
b, i	OS/400 Host Servers	12
d	OS/400 System Openness Includes	13
l	OS/400 GDDM®	14

Table 8. Deleting unwanted licensed programs and optional parts after the installation is complete (continued)

Keys	Licensed program and optionally installable product part	Number for product option
g	OS/400 - Media and Storage Extensions	18
l	OS/400 optional parts 21, 22, 25, 30, 31, 33, 34, 35, and 43.	21 - 43
h	OS/400 - International Components for Unicode	39
i	5722-XW1 IBM @server iSeries Access Family	Base
i	5722-XW1 iSeries Access Enablement Support	1
j	5722-XE1 IBM @server iSeries Access for Windows	Base
j	5722-XH2 IBM @server iSeries Access for Web	Base
m	5722-PD1 IBM Application Program Driver for AS/400	Base

Considerations for deleting licensed programs

Do not attempt to use the Delete Library (DLTLIB) command to remove a licensed program or optional part of a licensed program from the system. Some licensed programs copy objects into other libraries; the DLTLIB command will not delete the duplicated objects. Using the DLTLIB command to delete a licensed program or optional part could leave the licensed program in a partially installed condition. For a list of IBM-supplied libraries that are organized by licensed program, see the book *CL Programming*, SC41-5721-06.

If you are unable to delete a licensed program, it might be because the library for the licensed program exists in one of the library lists. Do the following:

1. Use the WRKSYSVAL command to check both the system library and the user library lists.
2. When the Work with System Values display appears, type a 5 next to the QSYSLIBL and QUSRLIBL system values to display the associated libraries.
3. If the library for the licensed program is listed on this display, press Enter to return to the Work with System Values display.
4. Type a 2 to change the system value.
5. When the Change System Value display appears, use the spacebar to remove that licensed program library from the library list.

You will be able to delete your licensed program after your next IPL.

Deleting licensed programs

To delete licensed programs, do the following steps:

1. Type G0 LICPGM and press Enter. The Work with Licensed Programs menu appears.
2. Select option 12 (Delete licensed programs). The Delete Licensed Programs display appears.
3. Type 4 (Delete) in the Option column in front of each licensed program that you want to delete. Page down to display additional licensed programs.
4. Press Enter. You are shown the Confirm Delete of Licensed Programs display.
5. Press Enter if your selections are correct. Press F12 to make corrections.
6. You receive confirmation messages from the system when the licensed programs are deleted.

Deleting software related to OS/400

7. Press F12 to return to the Work with Licensed Programs menu.

If you have difficulty deleting a licensed program following these steps, type ENDSBS *IMMED and press Enter. Then proceed with step 1 on page 141 again.

Chapter 10. Troubleshooting software installation problems

This information describes common problem scenarios, recovery methods, and ways to get help if you encounter a problem during software installation.

Error messages and reference codes (also known as system reference codes or SRCs) let you know that an error occurred during the installation process. Use the error messages or reference codes to determine which part of the process failed.

“Where to begin recovery” on page 144

First you need to determine the type of software installation failure.

“Image catalog recovery” on page 146

If you used an image catalog to install, follow these procedures to determine where the failure occurred and the appropriate recovery action.

“Starting point for automatic installation recovery” on page 146

If you used the automatic installation process, use the following information to determine where the failure occurred and the appropriate recovery action.

“Licensed Internal Code recovery” on page 147

Use this procedure if an error occurred when you installed the Licensed Internal Code.

“Operating system recovery” on page 149

Use this procedure if an error occurred when you installed the OS/400 operating system.

“Licensed programs, PTFs, and secondary language recovery” on page 151

Use this procedure if an error occurred when you installed a licensed program, PTF, or secondary language.

“Starting the automatic installation process again” on page 155

Use one of three methods if you want to start the automatic installation process again.

“Starting the manual installation process again” on page 156

Use one of these methods if you want to start the manual installation process again when recovering from an error while installing licensed programs, PTFs, or secondary languages.

“Initialize System (INZSYS) recovery” on page 157

In a software upgrade, the installation is complete when the licensed program portion of the installation process is completed and the INZSYS process successfully is completed. Use this information if the INZSYS process did not complete.

“Disk configuration warning and error messages” on page 158

Perform the actions necessary if you see a disk configuration warning or an error report.

Troubleshooting

“Starting from a power-off condition” on page 160

Perform the steps necessary to power on the server and begin normal installation.


“Reference codes for software installation” on page 160

If a reference code appeared during the automatic or manual installation, use these procedures.

Where to begin recovery

When you determine that you have an installation error, first you need to determine what your first step to recovery should be:

Type of installation failure	
When failure occurred	What to do
Saving server before installation	If a problem occurs while you are saving the system, review your job log to determine what caused the failure. Correct the error and complete your system save procedure. Do not continue to replace the new release until you have a complete backup copy of your system. If you cannot complete installing the new release, you will need this backup copy to restore the system to the previous release.
Installing new release or licensed program	Use the next table on this page to direct you to the recovery information that you need to find the problem, determine what caused it, correct the problem, and then complete installing this release.
Power failure during an installation process	If you have a power failure anytime during the installation process, go to the next table on this page to determine where to start the installation again. You should be able to start with the task where you were when the failure occurred. For example, if you had completed installing the operating system when the power failed, and are now installing licensed programs, start with the task to install licensed programs. If you are using the automatic process, start at the beginning. The system can determine which tasks have not been completed and will resume at the appropriate task.

If the installation process fails and you cannot continue the current installation, use the book Backup and Recovery  and your server's backup copy to restore the previous release.

In the farthest left column of the following table, locate the installation section you were using when the failure occurred. In the second column, locate which task you were performing in that section. Locate the first task that failed during your installation and then use the information in the last column to determine your recovery starting point.

Where to start recovery		
Installation procedure in use	Task number in use at time of failure	Where to start
Using image catalogs to install		“Image catalog recovery” on page 146

Where to start recovery		
Installation procedure in use	Task number in use at time of failure	Where to start
Replacing a release using automatic installation	Task 1. Using automatic installation	“Starting point for automatic installation recovery” on page 146
Replacing a release using manual installation	Task 1. Replacing the Licensed Internal Code	“Licensed Internal Code recovery” on page 147
	Task 2. Replacing the operating system	“Operating system recovery” on page 149
	Task 3. Replacing the licensed programs	“Licensed programs, PTFs, and secondary language recovery” on page 151
Installing software on a new iSeries server (with the operating system already installed)	Task 1. Doing the initial program load (IPL)	“Operating system recovery” on page 149
Installing software on a new iSeries server (without the operating system installed)	Task 1. Installing the operating system	“Operating system recovery” on page 149
Changing your primary language	Task 1. Changing the primary language	“Operating system recovery” on page 149
	Task 2. Installing the licensed programs	“Licensed programs, PTFs, and secondary language recovery” on page 151
Installing additional licensed programs	Task 1. Installing IBM licensed programs	“Licensed programs, PTFs, and secondary language recovery” on page 151
	Task 2. Installing non-IBM licensed programs	Look at the messages for the command
Installing a secondary language	Task 1. Using the Work with Licensed Programs Menu	“Licensed programs, PTFs, and secondary language recovery” on page 151
	Task 2. Using the Restore Licensed Program command	Look at the messages for the command

Image catalog recovery

The following table lists the error messages that could occur if you are using an image catalog to install.

Table 9. Image Catalog Verification Recovery

Message	Description
CPF9897 CPDBD1E	<p>Cause (Reason code 01): The load-source disk unit must have at least 1074 MB of free storage space to be able to install from an image catalog (virtual optical device).</p> <p>Recovery: Perform the procedure for freeing up space on the load-source disk unit and try your request again. The topic, "Cleaning up disk storage space" on page 49, contains the procedure.</p> <p>Cause (Reason code 02): Installation of the release requires additional allocation of space for License Internal Code.</p> <p>Recovery: Follow the directions in the error message. More information is in the topic, "Required: Allocating additional space for Licensed Internal Code" on page 50.</p> <p>Cause (Reason code 03): The Licensed Internal Code media is not supported for installation over the current version, release, and modification that is installed.</p> <p>Recovery: Try your request again with a supported release.</p> <p>Cause: PTF 5722SS1-SI06069 V5R1M0 and requisite PTFs are required to upgrade to OS/400 V5R3.</p> <p>Recovery: Apply the PTFs and retry the request.</p>
CPF3DE5	<p>Cause: The Licensed Internal Code and Operating System/400 software agreements have not been accepted.</p> <p>Recovery: Perform the steps "Required: Accepting software agreements" on page 46.</p>

Starting point for automatic installation recovery

If you used the automatic installation process (replacing a release using automatic installation), use the following information to determine where the failure occurred and the appropriate recovery action. After you have the problem corrected, go to "Starting the automatic installation process again" on page 155.

- To use automatic installation recovery, you must use the same version, release, and modification distribution media that caused the failure.
- If you have a failure during the automatic installation process and sign on to do problem analysis, your system will be running under the QSYSSBSD controlling subsystem. When your system completes an IPL after the installation has completed successfully, your controlling subsystem is active again.

Where to start recovery for the automatic installation process	
Finding the problem (symptom)	Where to start
Reference code B608 1105	"Licensed Internal Code recovery" on page 147

Where to start recovery for the automatic installation process	
Finding the problem (symptom)	Where to start
Reference codes other than B900 xxxx	"Licensed Internal Code recovery"
Reference codes starting with B900 xxxx	"Operating system recovery" on page 149
Messages starting with CPZ20xx	"Operating system recovery" on page 149
Message that indicates the load source disk unit needs additional space for Licensed Internal Code.	"Licensed Internal Code recovery"
Message that indicates the Licensed Internal Code and Operating System/400 software agreements have not been accepted.	"Licensed Internal Code recovery"
Message that indicates automatic installation is not complete.	"Licensed programs, PTFs, and secondary language recovery" on page 151

Licensed Internal Code recovery

Use this procedure if an error occurred when you installed the Licensed Internal Code.

1. Use the following table to determine the action to take if the Install Licensed Internal Code - Error display shows the following message:
An unrecoverable error occurred. The error reason code is listed below. This install cannot be completed. Give the reason code to your authorized service provider. Do not re-IPL the system until your authorized service provider can retrieve any needed information.

Return code for Licensed Internal Code - Error display	
Reason code	Action
51 52 53 54	If you are using optical media, clean the media. If you are using tape, clean the tape device. Then retry the installation.
All others	Retry the installation. If the installation fails again with the same reason code, retry the installation with another set of media. If the same failure occurs, contact your authorized service provider.

2. If you received a message that indicates the load source disk unit needs additional space for Licensed Internal Code, follow the directions in the error message. Ensure that you have adequate disk storage before you allocate the additional space for the Licensed Internal Code. The tasks for this are described in the topic "Ensuring the server meets disk storage requirements for upgrades" on page 46. The tasks for allocating additional space are in the topic, "Required: Allocating additional space for Licensed Internal Code" on page 50.
3. If you received a message that indicates the Licensed Internal Code and Operating System/400 software agreements have not been accepted, perform the steps "Required: Accepting software agreements" on page 46.
4. For Licensed Internal Code reference codes, go to one of the following sources:
 - If the reference code is of the form A6xx 6xxx, refer to the appendix on Licensed Internal Code reference codes in the book Backup and Recovery



Troubleshooting

- If any reference code other than an A6xx 6xxx appears, go to Analyze server and system problems in the iSeries Information Center (**Service, support, and troubleshooting > Get started with troubleshooting > Analyze server and system problems**) and follow the instructions.
5. Find the reference code that is shown on the control panel display and take the appropriate recovery action. If the reference code indicates that you have a media error, thoroughly clean the installation device. If you are using optical media, clean the media. If you are using tape, clean the tape head and tape path thoroughly. Then continue with the next step. If you receive another error message that indicates a media error on the same media, get another set of media to complete the installation process.
 6. You are trying to do one of the following:
 - Install from optical media when an alternate installation device is enabled.
 - Use an alternate installation device which is not enabled.

Go to “Setting up an alternate installation device” on page 183 or “Disabling an alternate installation device” on page 186 and perform the appropriate procedure.

If you cannot find the address information or the configuration has changed and the address is wrong, you must determine the address by physical inspection. This inspection can be difficult and could vary depending on your system model and the specific configuration of your IO buses. For this reason, IBM recommends that you call your next support level for help in determining the addresses for the alternate installation device. A service agreement might be required for this type of assistance.

7. Start the installation process again.

If you were using the automatic installation process, go to “Starting the automatic installation process again” on page 155 to start the installation process again. You must load the first volume in the installation device to start the automatic recovery installation process.

If you were using the manual installation process, go to “Starting the manual installation process again” on page 156 to start the installation process again.

The following table lists error messages that could occur during the installation of Licensed Internal Code when using image catalogs.

Error messages	
Message	Description
B60041FD	<p>Cause: This reference code occurs when the decompression of Licensed Internal Code fails when performing an installation using image catalogs. A main storage dump occurs. This should be copied to the auxiliary storage pool (ASP) or media. Words 12 and 13 of the reference code contain reason codes that indicate why the failure occurred. If you plan to contact your authorized service provider, write down the 8 numbers from word 13.</p> <p>Recovery: No Licensed Internal Code has been installed yet. You can either restart the server by using the currently installed Licensed Internal Code (perform a B-side IPL) or by using the physical media to install.</p>

Error messages	
Message	Description
B60041FC	<p>Cause: This reference code occurs when the Licensed Internal Code installation fails when performing an installation using image catalogs. Words 12 and 13 of the reference code contain reason codes that indicate why the failure occurred. If you plan to contact your authorized service provider, write down the 8 numbers from word 13.</p> <p>Recovery: Use physical media to perform the installation.</p>

Operating system recovery

Use this procedure if an error occurred when you installed the OS/400 operating system:

1. If a problem occurs when you are replacing or installing the operating system, a reference code appears on the control panel display, or an error message appears on the console. Use the following tables to determine the cause of the problem and take the action indicated. Then continue with the next step in this list.
2. If you were using the automatic installation process, start the process again using the instructions in “Starting the automatic installation process again” on page 155.
3. Start the manual installation again using the following steps.

Attention: If you do this on a primary partition when secondary partitions are active, this will cause all partitions to IPL immediately. If you have active secondary partitions, power them off before you use this procedure.

- a. Load the first volume (B29xx_01) into the installation device for the alternate IPL. Prepare the device.
- b. Use the control panel to set the mode to **Manual** and select function **03**. Press Enter on the control panel.
- c. Return to the task that failed and start the task again at the step where the IPL or Install the System display appears on the console.
- d. After you respond to the Confirm Install of Operating System display, you should see the Select a Language Group display. Verify that the language feature that is displayed matches the language feature for the OS/400 installation media that you are using.

Operating system problems	
Symptom	Action
B900 3000 through B900 308F	The reference codes in this range are displayed by the installation of the operating system process. Review the information in Analyze server and system problems in the iSeries Information Center (Service, support, and troubleshooting > Get started with troubleshooting > Analyze server and system problems). Take the appropriate recovery action. Then start the installation process again.

Troubleshooting

Operating system problems	
Symptom	Action
B900 3100 through B900 37FF	The reference codes in this range are displayed by the start operating system process. Go to Analyze server and system problems in the iSeries Information Center (Service, support, and troubleshooting > Get started with troubleshooting > Analyze server and system problems). Take the appropriate recovery action.
Other reference codes not listed in this table.	If the reference code is not in the range of reference codes listed in this table, go to Analyze server and system problems in the iSeries Information Center (Service, support, and troubleshooting > Get started with troubleshooting > Analyze server and system problems).

The following table contains some of the error messages that could occur during the installation of the operating system.

Error messages	
Message	Description
CPA3DE6	<p>Cause: Software agreements were not found on the volume loaded in the alternate IPL device.</p> <p>Recovery: Read the instructions for the message that is displayed on the console. Perform the recovery action described in the message to correct the problem.</p>
CPFA0C6	<p>Cause: /QNetWare file system failed to mount.</p> <p>Recovery: If you are performing an OS/400 upgrade to V5R3, ignore this message. Option 25 (OS/400 - NetWare Enhanced Integration) of the operating system (5722-SS1) will be mounted later.</p>
CPZ2003 CPZ2004 CPZ2005 CPZ2010 CPZ2011	<p>Cause: The installation process received a tape or optical media error code. Recovery for Error Code Ex10 0019 or Ex10 001A:</p> <ol style="list-style-type: none"> Clean the media. <ul style="list-style-type: none"> If you are using tape, clean the tape head and tape path thoroughly. If you are using optical media, clean the media with a clean lint-free cloth. Gently wipe the disc from the center to the outside of the disc. Try the installation process again. <ul style="list-style-type: none"> If you were using the automatic installation process, go to "Starting the automatic installation process again" on page 155. If you were using the manual installation process, go to step 3 in "Licensed Internal Code recovery" on page 147 to start the installation process again. <p>If you receive another error message indicating a media error on the same installation media, contact your software provider to get another set of installation media to complete the installation process.</p> <p>Recovery for all other error codes: Contact your authorized service provider.</p>

Error messages	
Message	Description
CPZ2022	<p>Cause: The restore options read from the installation profile are not valid.</p> <p>Note: If you create distribution media and specify *NONE for the installation profile name, the media will contain an empty installation profile. These media cannot be used to perform an automatic installation.</p> <p>Recovery: Record the recovery information for the error message. Try to install the operating system again using the manual installation process. You can also try to use the automatic installation process with a different set of media. If the problem occurs again during an automatic installation process, contact your next level of service.</p>
CPZ2023	<p>Cause: The installation options read from the installation profile are not compatible with the current state of the system.</p> <p>The installation requested by the options read from the installation profile cannot be performed. For example, this condition can occur when an installation is requested that does not load program objects and that results in the QSYS library being damaged.</p> <p>Recovery: Try to install the operating system again using the manual installation process.</p>
CPZ20xx	<p>Cause: These termination messages are displayed by the installation of the operating system process. Print the display if possible; otherwise, copy all of the information.</p> <p>Recovery: Read the instructions for the messages that are displayed on the console. Perform the recovery action described in the message to correct the problem and then try the installation process again.</p> <p>Note: A short time after you press Enter, a B900 xxxx reference code is displayed. Analyze server and system problems in the iSeries Information Center (Service, support, and troubleshooting > Get started with troubleshooting > Analyze server and system problems) contains additional information.</p>

Licensed programs, PTFs, and secondary language recovery

Use this procedure if an error occurred when you installed a licensed program, PTF, or secondary language.

1. Type GO LICPGM on any command line.
2. On the Work with Licensed Programs menu, type 50 (Display log for messages). Press Enter.
3. The Display Install History display appears. Press Enter.
4. The Display History Log Contents display appears. Look at the messages to determine the installation status of the licensed programs and PTFs. The messages show what part of the licensed program installation function has failed. Areas where the failure could have occurred include the following:
 - Installing the IBM-supplied libraries
 - Installing the licensed programs

Troubleshooting

- Installing PTFs
- Installing a secondary language
- Initialization process

If a problem such as a power failure occurs during a process in the preceding list, you could see a message that the process has started. An example of such a message is Licensed program installation process started. However, the failed or completed status message might not be displayed.

5. There should be one or more messages that indicate which IBM-supplied library or licensed program failed. Be sure to look at all of the messages. Use F10 (Display all) to see all messages.
6. To see the online help information, move the cursor to the message and press the Help key. Look at the online help information for the error message to get the message identifier and more information about the cause and recovery for the failure. Go to the error messages table in this topic to review the list of possible messages that you could see.
7. A copy of the job log has been spooled to an output queue.

To locate and display the job log, enter one of the following Work with Spool File (WRKSPLF) commands:

- For automatic installation, type the following command and press Enter:
WRKSPLF SELECT(QLPAUTO) ASTLVL(*INTERMED)
- For manual installation, type the following command and press Enter:
WRKSPLF SELECT(QSECOFR) ASTLVL(*INTERMED)
- For the PTF process, type the following command and press Enter: WRKSPLF
SELECT(QSYS *ALL *ALL SCPF) ASTLVL(*INTERMED)

If the bottom of the display shows More..., page down (Roll up) until Bottom... appears. Select option 5 (5=Display) on the last entry.

Note: Ignore any error messages listed in the nnnnnn/QSYS/QLPINSTALL job log. These messages are not installation error messages.

Scan the job log for error messages. Determine the cause and recovery for each error message in the job log. Go to the error messages table in this topic for a list of possible messages that you might see. Be sure to scan the entire job log. There could be more than one failure. Scan the job log by using the message ID. Remember that the message ID is case-sensitive.

8. Select option 10 (Display installed licensed programs) on the Work with Licensed Programs display. The Installed Status column indicates which licensed programs and optional parts are installed. The Installed Status column also indicates whether each licensed program installed successfully and whether it is compatible with the installed operating system. Refer to "Installed status values" on page 197 for a description of the installed status values.

You can press the F11 key to see a view of the display that shows the Installed Release column. The version, release, and modification value appears for licensed programs that are either installed compatibly or are installed at a back level. Page down (Roll up) through all of the displays to see the status of your licensed programs.

Check to see if the licensed program that you are installing had a different language feature code than your primary language feature code. If it does, the licensed program either is flagged as *ERROR or the column is blank. The language objects for the licensed program are installed in a secondary language

- library. Obtain distribution media with the correct primary language feature code. Press the F3 key to return to the Work with Licensed Programs menu.
9. After you determine the cause of the error and complete the recommended recovery action, resume the installation process. If you were using automatic installation, go to “Starting the automatic installation process again” on page 155. If you were using the manual installation process, go to “Starting the manual installation process again” on page 156.

The following table contains some of the error messages with possible causes of the errors. Look at the messages on your server to determine the exact cause and recovery.

Error messages	
Message	Description
CPA3DD2 CPA3DD3	<p>Cause: The server could not identify the last volume loaded in the device.</p> <p>Recovery: Open the device door, verify that correct volume is loaded, and close the device door.</p>
CPA3DDD CPA3DDF	<p>Cause: The installation process is expecting more licensed programs to be loaded.</p> <p>Recovery: If you have more media that contains licensed programs, load the volume and type G to continue the installation process. If you do not have any more volumes that contain licensed programs, type X to indicate that there is no more media to load. When the installation process is completed, use option 50 of the LICPGM menu to verify messages in the installation history log.</p>
CPA3DE1	<p>Cause: The volume that is loaded does not contain licensed programs that are supported through the Work with Licensed Programs (LICPGM) menu.</p> <p>Recovery: Load the optical media that contains licensed programs.</p>
CPDB6DA	<p>Cause: During a manual installation, the software agreement for a licensed program was not accepted and cannot be installed.</p> <p>Recovery: Follow the instructions in “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115 to accept the software agreement and retry the installation.</p>
CPDB6DB	<p>Cause: During an automatic installation, the software agreement for a licensed program was not accepted and cannot be installed.</p> <p>Recovery: Follow the instructions in “Using the Work with Licensed Programs menu to install IBM licensed programs” on page 115 to accept the software agreement and retry the installation.</p>
CPD32B0 reason code 7 CPF327E reason code 3	<p>Cause: 5722SS1 option 1, Extended Base Support, failed to install.</p> <p>Recovery: Use the Reclaim Storage (RCLSTG) command and try to install option 1 again.</p>

Troubleshooting

Error messages	
Message	Description
CPD3713	<p>Cause: The licensed program is currently installed on your server and was not found on the distribution media.</p> <p>Recovery: Get another set of distribution media that contains the licensed program. Either install the licensed program again from “Installing additional licensed programs” on page 114 or delete the licensed program from your server if you no longer want it.</p>
CPD3D82 CPF3D8F	<p>Cause: These messages could be shown if you did not end all of the subsystems before you started the installation process.</p> <p>Recovery: End all subsystems and start installing the licensed programs again.</p>
CPF371C CPF3731	<p>Cause: Look at the messages previously listed in the job log to determine the failure.</p> <p>Recovery: Take the recommended recovery action.</p> <p>If you received one of these messages, the installation process ended before you completed installing the licensed programs.</p>
CPF371D CPF371E	<p>Cause: These messages could be shown if the wrong volume is loaded. The online information of the message can help determine the cause.</p> <p>Recovery: Load the correct volume and start the process again.</p>
CPF3D96	<p>Cause: Errors occurred during the restoring process for a licensed program.</p> <p>Recovery: Take the recommended recovery action explained in the online help information.</p> <p>If you received these messages, the installation continued with the other licensed programs if the problem was not too severe. However, problems with the tape or system storage level would have caused the installation to end.</p>
CPF3D81 CPF3D84 CPF3D8B CPF3D8C CPF3D90 CPF3D91	<p>Cause: Errors occurred when restoring a licensed program or PTFs.</p> <p>Recovery: Use the Display Job (DSPJOB) command. Enter DSPJOB nnnnnn/QLPINSTALL/QBCHINST or DSPJOB nnnnnn/QLPINSTALL/QLPINSTALL where nnnnnn is the job number of the job log in the message help of the error message. Select option 4 on the Display Job display to display spooled files. Select option 5 on the Display Job Spooled Files display to determine the cause of the failure. Correct the error and start the installation process again. Ignore error messages in the nnnnnn/QSYS/QLPINSTALL job log. These messages are not installation error messages.</p>
CPF3D82 CPF3D83	<p>Cause: There is not enough auxiliary storage to install the licensed programs that you selected.</p> <p>Recovery: Go to “Licensed program releases and sizes” on page 166 to determine the space requirements for each licensed program that you want to install. Obtain additional auxiliary storage and start the installation process again.</p>

Error messages	
Message	Description
CPF3D85 CPF3D86 CPF3D8E	<p>Cause: An object or PTF is not installed because it requires successful installation of a licensed program. That licensed program might not be installed or might be installed at the wrong release.</p> <p>Recovery: See the previous messages in the job log to determine if the licensed program is installed successfully. Correct any errors or install the required licensed program and start the installation process again.</p>
CPF3DD3	<p>Cause: The device description could not be found or could not be used.</p> <p>Recovery: Create a device description for the installation device (optical or tape). Use the CRTOPTDEV command to create a device description for the optical device that supports the optical media class. Use the CRTDEVTAP command to create a device description for the tape device. Then start the process again.</p>
CPI3D82 CPI3D84 CPI3D85	<p>Cause: A licensed program that is included on the distribution media was not currently installed on the server.</p> <p>Recovery: Use the online information of the message for recovery help. Use the topic "Installing additional licensed programs" on page 114 to install the licensed program.</p>
Media error messages	<p>Cause: A media error occurred during the installation process.</p> <p>Recovery: If you are using optical media, clean the disc, and then follow the recovery actions that are indicated for this message. If you are using tape, clean the tape head and tape path thoroughly. If you receive another error message that indicates a media error on the same tape, get another set of tapes to complete the installation.</p>

Starting the automatic installation process again

Use one of the following methods if you want to start the automatic installation process again after recovering from an error.

Methods for starting the automatic installation process again	
Method	Instructions
Method 1: Licensed Internal Code	<p>When to use: This method should be used if the Licensed Internal Code needs to be installed again. If you are sure the Licensed Internal Code has been successfully installed, you do not need to use this method. No message indicates that the Licensed Internal Code has been installed successfully; however, messages do indicate that the operating system has been installed successfully. If the operating system has been installed successfully, so has the Licensed Internal Code.</p> <p>How to use: To start an installation process again, use the instructions in "Upgrading or replacing software using automatic installation" on page 56.</p>

Methods for starting the automatic installation process again	
Method	Instructions
Method 2: Operating System	<p>When to use: If you are sure the Licensed Internal Code has been installed successfully, use Method 2 to install the operating system again. Method 2 is faster than using Method 1 because the Licensed Internal Code does not need to be installed again. No message indicates that the Licensed Internal Code has been installed successfully; however, messages do indicate that the operating system has been installed successfully. If the operating system has been installed successfully, so has the Licensed Internal Code.</p> <p>How to use:</p> <ol style="list-style-type: none"> 1. Use the control panel to set the mode selector to Manual. The function selected should be 03 (Start IPL). 2. Press the Enter button on the control panel. 3. Load the volume B29xx_01 in the installation device. 4. When the IPL or Install the System display is shown, set the mode selector on the control panel to Normal. 5. Select option 4 (Perform an automatic install of the operating system) on the IPL or Install the System display. 6. Continue with step 11 (begins with loading the next volume (B29xx_01) under "Replacing software using the automatic installation method" on page 57.
Method 3: Licensed Programs	<p>When to use: Use the Work with Licensed Programs display to install only the licensed programs that failed to install. Make sure the Licensed Internal Code and the operating system are successfully installed.</p> <p>How to use: Determine which products failed to install. Use option 11 (Install licensed programs) on the Work with Licensed Programs display. To install the licensed programs from a list, refer to "Installing additional licensed programs" on page 114.</p>

Starting the manual installation process again

Use one of these methods if you want to start the manual installation process again after you recover from an error while installing licensed programs, PTFs, or secondary languages.

Methods for starting the manual installation process again	
Method	Instructions
Method 1	<p>When to use: This method should be used if several licensed programs are not installed.</p> <p>How to use: To start an installation process again using method 1, use option 1 (Install all) on the Work with Licensed Programs display. Refer to "Manual installation Option 1. Install all" on page 201.</p>

Methods for starting the manual installation process again	
Method	Instructions
Method 2	<p>When to use: This method should be used if one or more licensed programs are not installed and you want to install only those licensed programs or optional parts that failed.</p> <p>How to use: To start the installation of only those licensed programs or optional parts that failed, use the instructions in "Installing additional licensed programs" on page 114. Complete all of the instructions in that part.</p>
Method 3	<p>When to use: This method can be used if only one or two licensed programs had PTFs that failed to install. Consider installing PTFs for only those licensed programs that failed.</p> <p>How to use: To install PTFs for selected licensed programs, use the GO PTF menu and select option 7 (Install a program temporary fix from a list).</p>
Method 4	<p>When to use: This method should be used if several licensed programs had PTFs that failed to install. Consider installing the entire cumulative PTF package again.</p> <p>How to use: To install the cumulative PTF package, use the instructions in the <i>iSeries System PTF Shipping Information Letter</i>.</p>

Initialize System (INZSYS) recovery

In a software upgrade, the installation is complete when the licensed program portion of the installation process is completed and the INZSYS process is successfully completed. The installation process must end before the INZSYS process is automatically started. This process is initiated during each IPL after you install the QUSRSYS library until the INZSYS process has successfully completed. The INZSYS process will not be initiated during the IPL if the system is in the restricted state. If the INZSYS process is initiated during the IPL, it runs in the SCPF system job.

Note: If you perform an IPL before installing a cumulative PTF package, make sure that the INZSYS process has completed before you start to install the PTF package. Using any PTF commands before the INZSYS process is completed causes the INZSYS to fail.

The completion time for INZSYS varies. Allow sufficient time for this process to complete.

When you select option 50 (Display log for messages) on the Work with Licensed Programs menu, you should see the message Initialize System (INZSYS) started. Later, you should see the message Initialize System (INZSYS) processing completed successfully (CPC37A9). If you do not see the completed message, or if the message Initialize System (INZSYS) failed appears, look at the job log to determine the problem. Use the information in the job log to correct the problem. Then start the conversion process again.

To start the conversion process yourself, you can either use a batch job or enter INZSYS on the command line. If you use a batch job, you can use your workstation while the process is running, but the server cannot be in a restricted state. Batch jobs do not run when the server is in a restricted state. If you enter

Troubleshooting

INZSYS from a command line, IBM recommends that the server be in a restricted state. Setting the server to a restricted state reduces the time that is needed for the INZSYS process to complete. Before you use the INZSYS command, set the mode selection to **Normal** and set the IPL type to **B** (or the IPL type that you use for everyday operation).

To set the server to restricted state, do the following:

1. Type CHGMSGQ QSYSOPR *BREAK SEV(60) and press Enter.
2. A message display could be shown. Press Enter. (Ignore the messages that are shown.)
3. Type the End Subsystem (ENDSBS) command: ENDSBS *ALL *IMMED.
The message System ended to restricted condition appears.
Press Enter to continue.

To start the conversion process again, do the following:

1. Type INZSYS and press Enter.
2. Use option 50 (Display log for messages) on the Work with Licensed Programs menu to make sure that the process is completed successfully.

Do not attempt to save your system until the INZSYS process has completed successfully.

Disk configuration warning and error messages


You see a disk configuration warning or an error report when your server detects errors or warning conditions in your disk configuration.

You might see this display immediately after the hardware upgrade procedure or while you are installing the operating system.

The action you take for each message depends on the upgrade method that you are using. The following table lists the messages that you might see on the display and the actions that you should take.

For each message, you can select option 5 (Display Detailed Report) to see more information about why the message occurred and what possible actions are available.

Attention: Are you using Option 1? When you are installing the Licensed Internal Code by using option 1 from the Install the Licensed Internal Code (LIC) menu, disk configuration warning messages might mean that the server will not be able to recover its ability to access the data on your disk units. **Important:** Do not ignore these messages or attempt to resolve them without consulting the table. An incorrect response will probably require you to reload your data.

Disk configuration warning messages	
Warning messages	Your action: Option 1 (Restore Licensed Internal Code)
Disk unit not formatted for optimal performance	Do the following: 1. Type a 5 (Display Detailed Report). 2. Write down the disk units that should be reformatted. 3. Press F12 to return to the warning report display. 4. Press F10 to accept the warning and continue. You cannot reformat the disk units during the upgrade procedure.
Unit possibly configured for PowerPC AS	Contact software support before you proceed.
Unit possibly configured for IMPI	Contact software support before you proceed.
Missing disk configuration	Contact hardware support before you proceed.
Unknown load source status	Contact hardware support before you proceed.
Load source failure	Contact hardware support before you proceed.
Restore load source	Contact software support before you proceed.
Missing disk units in the configuration	Contact hardware support before you proceed.
Restore in progress	View the online information and take the appropriate recovery action.
Device parity protected units in exposed mode	You have a failed unit in a parity set. You can ignore this message and continue the upgrade procedure. However, you should contact hardware support immediately after the upgrade procedure.
No alternatives available	Contact software support before you proceed.
New disk configuration	Contact software support before you proceed.
Incorrect Licensed Internal Code installed	Contact hardware support before you proceed. The load source unit and its mirrored pair might be configured incorrectly.
Change load source location	Contact hardware support before you proceed. Your load source unit might be configured incorrectly.
Bad load source configuration	Contact hardware support before you proceed. Your load source unit might be configured incorrectly.
Overflowed ASPs	Wait to correct the problem until after the upgrade process is completed. The book Backup and Recovery  describes how to reset an overflowed ASP.
Lower level of protection	Ignore during the installation procedure. However, you should analyze your mirrored configuration after the installation procedure.

Disk configuration warning messages	
Warning messages	Your action: Option 1 (Restore Licensed Internal Code)
Logical partition configuration error (only iSeries 8xx or earlier models)	<p>Do the following:</p> <ol style="list-style-type: none"> 1. Type 5 (Display Detailed Report). 2. Write down the disk units that contain the error. 3. Press F12 to return to the warning report display. 4. Press F10 to accept the warning and continue. <p>Refer to Troubleshoot logical partitions in the iSeries Information Center (Systems management > Logical partitions > Partitioning with iSeries Navigator > Troubleshoot logical partitions).</p>

Starting from a power-off condition

If your system unit power is off, perform the following steps to power on the system and begin a normal installation. When you complete this topic, you will be instructed to return to the appropriate step of your original installation procedures.

1. Use the control panel to set the mode and IPL type:
 - If you were directed here from “Upgrading or replacing software using automatic installation” on page 56, set the IPL type to **D** and the mode to **Normal**. On some models, this will appear as **DN**.
 - If you were directed here from “Upgrading or replacing software using manual installation” on page 64, set the IPL type to **D** and the mode to **Manual**. On some models, this will appear as **DM**
2. Press Enter on the control panel.
3. On your console, ensure that you have a connection to the server.
4. If your installation device has separate on and off switches, verify that the switch is in the On position.
5. Load the media and make the device ready. If you cannot load the media now, you will be able to in step 7.
6. Turn the power on for the server by pushing the power switch once.
7. If you could not load your media in the previous steps, load the first volume into the tape or optical device for the alternate IPL now.
8. You are ready to return to your original installation procedures.
 - If you are performing automatic installation, continue with step 4 on page 58 in the automatic installation procedures.
 - If you are performing a manual installation, continue with step 5 on page 66 in the manual installation procedures (replacing Licensed Internal Code).

Reference codes for software installation

This information gives a brief explanation of the common reference codes (also known as system reference codes or SRCs) that you might see while upgrading or replacing a release.

- “Common reference codes for software installation”
- “Installation recovery after using reference codes” on page 164

Common reference codes for software installation

The following table lists the most common reference codes. If you are looking at reference codes on a system with logical partitions, the reference code gives an

indication of the type of partition to which it pertains. For example, the reference code B1xx xxxx indicates a primary partition. The reference code B2xx xxxx indicates a secondary partition.

Table 10. Common reference codes

Symptom	Action
A1xx 19xx A12x 19xx (x is any character)	<p>These reference codes appear if the installation device for an alternate IPL is not ready. Check the following:</p> <ul style="list-style-type: none"> • Is the correct media volume loaded? • Is the device ready? • Is the device being used for a different purpose than the device was used for during the previous IPL? • Is the installation media loaded in the alternate IPL or alternate installation device allocated for that partition? <p>Any of these situations can cause these reference codes to appear. In the first two examples, ensure that the media volume is loaded correctly and that the device is ready. In the last example, you need to wait while the system finds the new installation device.</p> <p>Then perform the appropriate procedure under “Installation recovery after using reference codes” on page 164.</p>
A600 1103	<p>This reference code appears when Licensed Internal Code is damaged. Use the control panel or virtual control panel (Work with Partition Status display) to set the IPL type to D and to set the mode to Manual. Then use the instructions for “Upgrading or replacing software using manual installation” on page 64.</p>
A600 1104	<p>This reference code appears if the installation media is not readable. Either the media is dirty or damaged, or there is an error with the optical device. Clean the media or acquire a new set of media.</p> <p>Then perform the appropriate procedure under “Installation recovery after using reference codes” on page 164.</p>
B101 4500	<p>This reference code appears when an error is detected with the Integrated xSeries Server for iSeries.</p> <p>Make sure that you vary off the Integrated xSeries Server for iSeries before you perform the function that resulted in this reference code. If the reference code still occurs, try the installation again. If the same error occurs again, contact your authorized service provider.</p> <p>Note: Integrated xSeries Server for iSeries is the new name for Integrated PC Server (IPCS) or File Server Input/Output Processor (FSIOP).</p>
B1xx 4504 B1xx 1933	<p>This reference code appears when the system cannot locate the device used for the alternate IPL. Check that the installation media is loaded in correct device and, if necessary, make the device ready.</p> <p>Then perform the appropriate procedure under “Installation recovery after using reference codes” on page 164.</p>

Table 10. Common reference codes (continued)

Symptom	Action
B1xx 4505	<p>These reference codes appear if the installation media is dirty or if the wrong media was loaded. Verify that the correct media is loaded. If the problem still remains, clean the optical disc. If you are using tape, clean the tape head and tape path.</p> <p>Then perform the appropriate procedure under "Installation recovery after using reference codes" on page 164.</p>
B1xx 4507	<p>These reference codes appear if the tape device for the alternate IPL was not found or was not ready. Make sure the tape device is powered on and the correct tape is loaded and ready. To make tape devices ready, you might need to open and close the tape device door.</p> <p>Then perform the appropriate procedure under "Installation recovery after using reference codes" on page 164.</p>
B2pp 1310 (pp is the partition ID)	<p>No alternate IPL device IOP was selected. The IPL will attempt to continue, but there might not be enough information to find the correct alternate IPL load source. Configure an alternate IPL device IOP for the logical partition. Then, retry the partition IPL. If it continues to fail, contact your service provider.</p> <p>For iSeries 8xx and earlier models, refer to Manage logical partitions in the iSeries Information Center (Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions) for more information. For IBM @server^(R) 5xx models, see Managing OS/400 logical partitions in the IBM eServer Hardware Information Center (Partitioning the server > Partitioning for OS/400 > Managing OS/400 logical partitions).</p>
B2pp 1320 (pp is the partition ID)	<p>No default load source IOP was selected for a type A or type B IPL. The IPL will attempt to continue, but there might not be enough information to find the correct load source. Configure a load source IOP for the logical partition. Then retry the partition IPL. If it continues to fail, contact your service provider.</p> <p>For more information on iSeries 8xx and earlier models, refer to Manage logical partitions in the iSeries Information Center (Systems management > Logical partitions > Partitioning with iSeries Navigator > Manage logical partitions). For information on IBM eServer 5xx models, see Managing OS/400 logical partitions in the IBM eServer Hardware Information Center (Partitioning the server > Partitioning for OS/400 > Managing OS/400 logical partitions).</p>
B2pp 3110 (pp is the partition ID)	<p>The power-on operation for the logical partition failed. Scan the reference code history list of the logical partition for previous B2ppxxxx failure reference codes. Resolve each problem found, and then retry the partition IPL. If it continues to fail, contact your service provider.</p>

Table 10. Common reference codes (continued)

Symptom	Action
B2pp 3200 (pp is the partition ID)	<p>The logical partition failed to initialize a program load.</p> <ol style="list-style-type: none"> 1. If you performed a power-on operation from IPL type D, remove the installation media (optical or tape media), clean the device and clean the media if possible. Insert the media again and attempt to power on using IPL type D. 2. Verify that the device is addressed correctly. 3. Verify that the media is in the correct device. 4. Verify that the media in the device is compatible. 5. Verify that the IOP selected as the IPL resource is correct. 6. Retry the partition IPL.
B2xx xxxx	<p>All other reference codes: If you performed a D-mode IPL, clean the device and media, and then retry the same type of power-on operation. For more information, refer to the following topics:</p> <ul style="list-style-type: none"> • For iSeries 8xx and earlier models, see Logical partitions in the iSeries Information Center (Systems management > Logical partitions). • For IBM eServer 5xx models, see Partitioning for OS/400 in the IBM eServer Hardware Information Center (Partitioning the server > Partitioning for OS/400).
B608 1105	<p>This reference code occurs when you exit from the automatic installation because an alternate installation device that is attached to the system has one of the following problems:</p> <ul style="list-style-type: none"> • The device is enabled, but it is not ready because the tape is not loaded. • The device is not enabled as an alternate installation device. • The device itself has a problem. <p>To use the alternate installation device, do the following:</p> <ol style="list-style-type: none"> 1. Power off the system. 2. If necessary, fix the device. 3. Power on the system. 4. Verify that the alternate installation device is enabled as an alternate installation device. 5. Load the tape media in the alternate installation device and start the installation procedure again.
B900 3121	<p>This reference code occurs when an IPL is attempted after an installation failure. You need to reinstall some or all of the operating system. Start with the media volume containing the base operating system. (For optical media, this volume is labeled B29xx_01.)</p> <p>Then perform the appropriate procedure under “Installation recovery after using reference codes” on page 164.</p>
2644 3136	<p>This reference code appears if the tape device is assigned to another system or partition. Go to the other system or partition and vary off this tape device. Make sure the correct tape is loaded.</p> <p>Then perform the appropriate procedure under “Installation recovery after using reference codes” on page 164.</p>
Any other reference code	<p>Go to Chapter 10, “Troubleshooting software installation problems,” on page 143, and follow the instructions there.</p>

Installation recovery after using reference codes

After taking the corrective action for the reference code, perform one of the following procedures. Use the procedure that is appropriate for the installation process, either automatic or manual, that was in use when the reference code appeared.

If you used automatic installation:

1. Set the mode selector or toggle on the control panel to **Manual**.
2. Press the power switch to delayed off, press it again, and wait for the entire system to power off.
3. Set the mode selector or toggle on the control panel to **Normal**.
4. Press the power switch on and make the installation device ready. If the system attention light appears and the same reference code appears again, go to “Licensed Internal Code recovery” on page 147. Otherwise, continue with step 12 on page 60.

If you used manual installation:

1. Make sure that the media is loaded in the installation device for the alternate IPL.
2. Press the power switch to delayed off, press it again, and wait for the entire system to power off.
3. Press the power switch on and make the installation device ready. If the system attention light appears and the same reference code appears again, go to “Licensed Internal Code recovery” on page 147. Otherwise, continue with step 12 on page 67.

Chapter 11. Software reference

This topic contains a collection of supporting information about the concepts and tasks described in the Chapter 1, “Install, upgrade, or delete OS/400 and related software,” on page 1 topic.

“Licensed program releases and sizes” on page 166

Review many of the licensed programs that are available for this release and how much storage space they require.

“Estimates for software installation time” on page 171

Use this information to help you estimate the time it will take to install your software.

“Installation devices and media” on page 180

Find out about the devices and media used for upgrades or installations.

“OS/400 release interoperability” on page 188

An iSeries server interoperates with another iSeries server when you exchange data or when you save and restore objects. Review the supported combinations of OS/400 releases.

“Installation notes about the OS/400 release” on page 189

Review specific changes to the OS/400 release.

“Media labels and their contents” on page 189

Arrange your media for installation in the order that is listed in this table.

“Feature codes for national language version” on page 195

Locate the appropriate feature code for your primary or secondary language.

“Blank displays” on page 197

Understand what causes displays to be blank during an installation.

“System password” on page 197

Understand the basic concepts of the system password and how it relates to software installation.

“Installed status values” on page 197

Use these values to determine whether you can use a product or whether you need to upgrade a licensed program.

“Options on Prepare for Install menu” on page 199


Understand the different functions on the Prepare for Install menu.

“Options on Work with Licensed Programs menu” on page 201

Use this information to determine when and how you can use these options.

Licensed program releases and sizes

The following iSeries licensed programs are available this release and are compatible with the OS/400 operating system. To help you plan for installing your new release, use this information to find the release and current size of the licensed programs that are listed.

Licensed program release and size information for V5R1 and earlier releases is available in the Technical Studio  (http://www.as400.ibm.com/tstudio/tech_ref/lpsize/lpszdex.htm).

Product	Option	Version	Status	Storage (MB)	Description
5722	999	V5R3M0	Refreshed	1420.0	Licensed Internal Code
5722 SS1	Base (QGPL, QUSRSYS, QSYS)	V5R3M0	Refreshed	1566.0	Operating System/400 (actual size ranges from 1407 to 1566)
5722 SS1	Option 1	V5R3M0	Refreshed	18.6	OS/400 - Extended Base Support
5722 SS1	Option 2	V5R3M0	Refreshed	38.9	OS/400 - Online Information
5722 SS1	Option 3	V5R3M0	Refreshed	877.7	OS/400 - Extended Base Directory Support
5722 SS1	Option 5	V5R3M0	Refreshed	28.4	OS/400 - System/36 Environment
5722 SS1	Option 6	V5R3M0	Refreshed	13.4	OS/400 - System/38 Environment
5722 SS1	Option 7	V5R3M0	Refreshed	9.3	OS/400 - Example Tools Library
5722 SS1	Option 8	V5R3M0	Refreshed	26.7	OS/400 - AFP Compatibility Fonts
5722 SS1	Option 9	V5R3M0	Refreshed	93.1	OS/400 - *PRV CL Compiler Support
5722 SS1	Option 12	V5R3M0	Refreshed	20.6	OS/400 - Host Servers
5722 SS1	Option 13	V5R3M0	Refreshed	304.1	OS/400 - System Openness Includes
5722 SS1	Option 14	V5R3M0	Refreshed	16.3	OS/400 - GDDM
5722 SS1	Option 18	V5R3M0	Refreshed	7.0	OS/400 - Media and Storage Extensions
5722 SS1	Option 21	V5R3M0	Refreshed	115.1	OS/400 - Extended NLS Support
5722 SS1	Option 22	V5R3M0	Refreshed	3.7	OS/400 - ObjectConnect
5722 SS1	Option 23	V5R3M0	Refreshed	5.6	OS/400 - OptiConnect
5722 SS1	Option 25	V5R3M0	Refreshed	33.6	OS/400 - NetWare Enhanced Integration
5722 SS1	Option 26	V5R3M0	Refreshed	2.7	OS/400 - DB2 Symmetric Multiprocessing
5722 SS1	Option 27	V5R3M0	Refreshed	2.6	OS/400 - DB2 Multisystem
5722 SS1	Option 30	V5R3M0	Refreshed	28.6	OS/400 - Qshell
5722 SS1	Option 31	V5R3M0	Refreshed	9.8	OS/400 - Domain Name System

Software reference

Product	Option	Version	Status	Storage (MB)	Description
5722 SS1	Option 33	V5R3M0	Refreshed	207.6	OS/400 - Portable Application Solutions Environment
5722 SS1	Option 34	V5R3M0	Refreshed	105.5	OS/400 - Digital Certificate Manager
5722 SS1	Option 35	V5R3M0	Refreshed	23.0	OS/400 - CCA Cryptographic Service Provider
5722 SS1	Option 36	V5R3M0	Refreshed	1.6	OS/400 - PSF/400 1-45 IPM Printer Support
5722 SS1	Option 37	V5R3M0	Refreshed	1.6	OS/400 - PSF/400 1-100 IPM Printer Support
5722 SS1	Option 38	V5R3M0	Refreshed	1.6	OS/400 - PSF/400 Any Speed Printer Support
5722 SS1	Option 39	V5R3M0	Refreshed	266.3	OS/400 - International Components for Unicode
5722 SS1	Option 41	V5R3M0	Refreshed	1.7	OS/400 - HA Switchable Resources
5722 SS1	Option 42	V5R3M0	Refreshed	2.7	OS/400 - HA Journal Performance
5722 SS1	Option 43	V5R3M0	Refreshed	485.4	OS/400 - Additional Fonts
5722 AC3	Base	V5R3M0	Refreshed	91.1	IBM Cryptographic Access Provider 128-bit for iSeries
5722 AF1	Base	V5R3M0	Refreshed	19.7	IBM Advanced Function Printing™ Utilities for iSeries
5722 AP1	Base	V5R3M0	New	18.9	IBM Advanced DBCS Printer Support for iSeries
5722 AP1	Option 1	V5R3M0	New	2.7	Advanced DBCS Printer Support for iSeries - IPDS™
5722 BR1	Base	V5R3M0	Refreshed	269.6	IBM Backup Recovery and Media Services for iSeries
5722 BR1	Option 1	V5R3M0	Refreshed	94.7	BRMS - Network Feature
5722 BR1	BR1 option 2	V5R3M0	Refreshed	146.2	BRMS - Advanced Feature
5722 CE3	Base	V5R3M0	Refreshed	11.0	IBM iSeries Client Encryption (128-bit)
5722 CM1	Base	V5R3M0	Refreshed	14.6	IBM Communications Utilities for iSeries
5722 CR1	Base	V5R3M0	Refreshed	4.0	IBM Cryptographic Support for AS/400
5722 DB1	Base	V5R3M0	Refreshed	85.7	IBM System/38 Utilities for AS/400
5722 DE1	Base	V5R3M0	Refreshed	2.2	IBM DB2 Universal Database™ Extenders for iSeries V7.2
5722 DE1	Option 1	V5R3M0	Refreshed	27.7	Text Extender for iSeries
5722 DE1	Option 2	V5R3M0	Refreshed	41.8	XML Extender
5722 DE1	Option 3	V5R3M0	Refreshed	214.3	Text Search Engine

Software reference

Product	Option	Version	Status	Storage (MB)	Description
5722 DFH	Base	V5R3M0	Refreshed	95.2	IBM CICS® Transaction Server for iSeries
5722 DFH	Option 1	V5R3M0	Refreshed	12.8	CICS for iSeries - Sample Applications
5722 DG1	Base	V5R3M0	Refreshed	167.3	IBM HTTP Server for iSeries
5722 DG1	Option 1	V5R3M0	Refreshed	11.7	Triggered Cache Manager
5722 DP4	Base	V5R3M0	Refreshed	24.4	IBM DB2 DataPropagator™ for iSeries, V8.1
5722 DS1	Base	V5R3M0	Refreshed	8.2	IBM Business Graphics Utility for AS/400
5769 FNT	Base	V4R2M0	Ship level	2.0	IBM Advanced Function Printing Fonts for AS/400
5769 FNT	Option 1	V4R2M0	Ship level	8.3	AFP Fonts - Sonoran Serif
5769 FNT	Option 2	V4R2M0	Ship level	6.8	AFP Fonts - Sonoran Serif Headliner
5769 FNT	Option 3	V4R2M0	Ship level	8.1	AFP Fonts - Sonoran Sans Serif
5769 FNT	Option 4	V4R2M0	Ship level	6.7	AFP Fonts - Sonoran Sans Serif Headliner
5769 FNT	Option 5	V4R2M0	Ship level	6.4	AFP Fonts - Sonoran Sans Serif Condensed
5769 FNT	Option 6	V4R2M0	Ship level	5.4	AFP Fonts - Sonoran Sans Serif Expanded
5769 FNT	Option 7	V4R2M0	Ship level	6.1	AFP Fonts - Monotype Garamond
5769 FNT	Option 8	V4R2M0	Ship level	6.5	AFP Fonts - Century Schoolbook
5769 FNT	Option 9	V4R2M0	Ship level	2.6	AFP Fonts - Pi and Specials
5769 FNT	Option 10	V4R2M0	Ship level	6.1	AFP Fonts - ITC Souvenir
5769 FNT	Option 11	V4R2M0	Ship level	6.3	AFP Fonts - ITC Avant Garde Gothic
5769 FNT	Option 12	V4R2M0	Ship level	5.7	AFP Fonts - Math and Science
5769 FNT	Option 13	V4R2M0	Ship level	1.7	AFP Fonts - DATA1
5769 FNT	Option 14	V4R2M0	Ship level	2.4	AFP Fonts - APL2®
5769 FNT	Option 15	V4R2M0	Ship level	1.6	AFP Fonts - OCR A and OCR B
5769 FN1	Base	V4R2M0	Ship level	2.0	Advanced Function Printing DBCS Fonts for AS/400
5769 FN1	Option 1	V4R2M0	Ship level	100.2	AFP DBCS Fonts - Japanese
5769 FN1	Option 2	V4R2M0	Ship level	35.3	AFP DBCS Fonts - Korean
5769 FN1	Option 3	V4R2M0	Ship level	18.6	AFP DBCS Fonts - Traditional Chinese
5769 FN1	Option 4	V4R2M0	Ship level	12.4	AFP DBCS Fonts - Simplified Chinese
5769 FN1	Option 5	V4R2M0	Ship level	6.1	AFP DBCS Fonts - Thai

Product	Option	Version	Status	Storage (MB)	Description
5722 IP1	Base	V5R3M0	Refreshed	85.7	Infoprint Server for iSeries
5722 IP1	Option 1	V5R3M0	New	1.4	PS to AFP Transform
5722 IWE	Base	V5R1M0	Ship level	5.9	IBM WebSphere Application Server - Express, Version 5.0 for iSeries
5722 IWE	Option 2	V5R1M0	Ship level	720.6	IBM WebSphere Application Server - Express
5722 IWE	Option 4	V5R3M0	New		Embedded WebSphere Application Server - Express
5722 JC1	Base	V5R3M0	Refreshed	35.7	IBM Toolbox for Java
5722 JS1	Base	V5R3M0	Refreshed	100.9	IBM Advanced Job Scheduler for iSeries
5722 JV1	Base	V5R3M0	Refreshed	3.9	IBM Developer Kit for Java
5722 JV1	Option 5	V5R3M0	Refreshed	242.4	Java Developer Kit 1.3
5722 JV1	Option 6	V5R3M0	Refreshed	42.3	Java Developer Kit 1.4
5722 MG1	Base	V5R3M0	Refreshed	75.1	IBM Managed System Services for iSeries
5722 PD1	Base	V5R1M0	Ship level	79.6	IBM Application Program Driver for AS/400
5722 PT1	Base	V5R3M0	Refreshed	16.3	IBM Performance Tools for iSeries
5722 PT1	Option 1	V5R3M0	Refreshed	19.7	Performance Tools - Manager Feature
5722 PT1	Option 2	V5R3M0	Refreshed	3.9	Performance Tools - Agent Feature
5722 QU1	Base	V5R3M0	Refreshed	8.5	IBM Query for iSeries
5722 RD1	Base	V5R3M0	Refreshed	33.1	IBM Content Manager OnDemand for iSeries
5722 RD1	Option 1	V5R3M0	Refreshed	192.0	Content Manager OnDemand Spooled File Archive
5722 RD1	Option 2	V5R3M0	Refreshed	317.6	Content Manager OnDemand Object Archive
5722 RD1	Option 3	V5R3M0	Refreshed	317.0	Content Manager OnDemand Record Archive
5722 RD1	Option 4	V5R3M0	Refreshed	159.4	Content Manager OnDemand AnyStore
5722 RD1	Option 5	V5R3M0	Refreshed	163.2	Content Manager OnDemand Server
5722 RD1	Option 10	V5R3M0	Refreshed	337.8	Content Manager OnDemand Common Server
5722 RD1	Option 11	V5R3M0	Refreshed	22.1	Content Manager OnDemand Web Enablement Kit
5722 RD1	Option 12	V5R3M0	Refreshed	210.2	Content Manager OnDemand PDF Indexer
5722 SM1	Base	V5R3M0	Refreshed	22.7	IBM System Manager for iSeries

Software reference

Product	Option	Version	Status	Storage (MB)	Description
5722 ST1	Base	V5R3M0	Refreshed	24.6	IBM DB2 Query Manager and SQL Development Kit for iSeries
5722 TC1	Base	V5R3M0	Refreshed	57.9	IBM TCP/IP Connectivity Utilities for iSeries
5769 VG1	Base	V4R4M0	Ship level	7.8	IBM VisualAge® Generator Server for AS/400
5722 VI1	Base	V5R3M0	Refreshed	25.5	IBM Content Manager for iSeries
5722 VI1	Option 1	V5R3M0	Refreshed	85.0	Content Manager for iSeries
5722 VI1	Option 2	V5R3M0	Refreshed	46.5	Content Manager for iSeries
5722 VI1	Option 3	V5R3M0	New		Content Manager for iSeries Client for Windows
5722 WDS	Base	V5R3M0	Refreshed	38.1	IBM WebSphere Development Studio
5722 WDS	Option 21	V5R3M0	Refreshed	45.5	iSeries Tools - Application Development
5722 WDS	Option 31	V5R3M0	Refreshed	15.0	ILE RPG
5722 WDS	Option 32	V5R3M0	Refreshed	9.5	System/36 Compatible RPG II
5722 WDS	Option 33	V5R3M0	Refreshed	8.2	System/38 Compatible RPG III
5722 WDS	Option 34	V5R3M0	Refreshed	8.9	RPG/400
5722 WDS	Option 35	V5R3M0	Refreshed	20.8	ILE RPG *PRV Compiler
5722 WDS	Option 41	V5R3M0	Refreshed	28.4	ILE COBOL
5722 WDS	Option 42	V5R3M0	Refreshed	10.0	System/36 Compatible COBOL
5722 WDS	Option 43	V5R3M0	Refreshed	9.2	System/38 Compatible COBOL
5722 WDS	Option 44	V5R3M0	Refreshed	11.2	OPM COBOL
5722 WDS	Option 45	V5R3M0	Refreshed	43.5	ILE COBOL *PRV Compiler
5722 WDS	Option 51	V5R3M0	Refreshed	10.1	ILE C
5722 WDS	Option 52	V5R3M0	Refreshed	37.7	ILE C++
5722 WDS	Option 56	V5R3M0	New	1.7	IXLC for C/C++
5722 WDS	Option 60	V5R3M0	Refreshed	1.5	WebSphere Studio Dev Client - Server Support
5722 WE1	Base	V5R3M0	New		IBM Web Enablement for iSeries
5722 WSV	Base	V5R3M0	Refreshed	22.0	IBM iSeries Integration for Windows Server
5722 WSV	Option 2	V5R3M0	Refreshed	31.0	Integration for Windows 2000 and 2003
5722 XE1	Base	V5R3M0	Refreshed	188.2	IBM @server iSeries Access for Windows
5722 XH2	Base	V5R3M0	Refreshed	192.0	IBM @server iSeries Access for Web

Product	Option	Version	Status	Storage (MB)	Description
5722 XP1	Base	V5R3M0	Refreshed	2.6	IBM @server iSeries Access for Wireless
5722 XW1	Base	V5R3M0	Refreshed	2.2	IBM @server iSeries Access Family
5722 XW1	Option 1	V5R3M0	Refreshed	0.5	iSeries Access Enablement Support
1TME LCF	Base	V4R1M0	Ship level	5.7	Tivoli Management Agent

Estimates for software installation time

It is difficult to accurately estimate the amount of time needed to install a new release of software. Many variables combine to create a unique set of circumstances for each system. This topic helps you estimate the time that you need to install your new release.

“Minimizing software installation time” on page 38 can help you make the best use of the time you spend on software installation.

“Common methods of estimating installation time”

Understand the different ways to estimate installation time.

“Conditions that affect installation time” on page 172

Understand the major factors that affect installation performance.

“Installation processes” on page 172

The system determines the type of installation process it uses based on available system resources and the type of product being installed.

“Checklist: Estimating installation time” on page 173

Follow these directions to help you estimate the approximate installation time of this release.

Common methods of estimating installation time

The following list contains the most common methods of estimating your installation time for an upgrade.

- Base your estimate on the installation time of a previous release. If the system configuration and load remain similar, you can use the installation time of a previous release on this system *as the start* of your estimate. If you rely on only the installation time of the previous release, your estimate might not be accurate. This method is not accurate if many data conversions occur during the installation process. If you are skipping a release level, generally the time is longer. Be sure to add information for conversions that occur in the release you are skipping and for the new release.
- Base your estimate on the installation time for a similar system. If your enterprise has multiple systems, you can record the actual time to install the new release on one system. You can use this to estimate the time that is needed to install the new release on a system with a similar configuration and load. Of course, you cannot use this method until you complete the installation on the first system.
- Estimate time using a formula. You can use the information in the following sections to estimate how long it will take to install this release on your system.

Keep in mind that the number at which you arrive will vary from your actual installation time because of the variables that affect installation time.

- Combine one or more of the methods that are listed above.

Conditions that affect installation time

The amount of time it takes to install the licensed programs depends on your system configuration and the licensed programs you are installing. That is, the larger models with more system capacity have a shorter installation time than smaller models loading the same licensed programs. The major factors that affect installation performance are:

- Installation device
- Number and type of disk unit I/O processors
- Processing unit capacity
- Disk unit space available
- Main storage available in base pool
- Human interaction
- Licensed programs to be installed

Installation processes

The system determines the installation process based on available system resources and the type of product being installed.

A *single-process installation* is when licensed programs are installed one at a time (sequentially). A *multiprocess installation* is when the system starts multiple jobs to perform the installation of two or more licensed programs at the same time.

Licensed Internal Code and the base part of the operating system are always installed using single-process installation. Licensed programs (including libraries QGPL and QUSRSYS and optional parts of the operating system) can be installed using either single-process or multiprocess installation.

If you are installing only one licensed program, the system uses single-process installation. If you are installing more than one licensed program, multiprocess installation is used if system resources are available. If system resources are not available, single-process installation is used. A single-process installation is used when a system's main storage or auxiliary storage is limited and when a licensed program exceeds the requirements for multiprocess installation. For any set of licensed programs, if the system must use single-process installation, the installation takes longer.

Multiprocess installation

The operating system determines if your system configuration has enough system capacity to use multiprocess installation to install licensed programs. If your system has the required resources, the licensed programs are installed concurrently by doing the following tasks:

- Loading the licensed program installation files from the media to temporary save files.
- Using multiple batch jobs to concurrently install licensed programs from the save files. The save files are deleted during the installation process when they are no longer needed.

During installation, a status panel indicates the licensed programs that are currently being installed from save files. The display lists the licensed programs and the type of item being installed for each, as follows:

*PGM Program objects

*LNG Language objects

If your system does not have the required resources for a multiprocess installation, the licensed programs are installed sequentially from the installation media (single-process). In single-process installation, the status panel indicates the licensed program that is currently being installed from the media.

Checklist: Estimating installation time

The following information is provided to assist you in estimating the approximate installation time of this release on your system. Use the following checklist as a guide. The checklist refers you to other information or work sheets to obtain values.

The checklist assumes that you are not changing the primary language of your system. The estimate you arrive at by using this checklist is based on the assumption that your system must perform a single-process installation. If your system is able to use multiprocess installation, your time will be less.

The checklist and supporting work sheets do not include the amount of time that is spent on loading the next volumes, media errors, or recovery procedures. User data is not included. The time needed for INZSYS to complete is also not included.

Do the following to estimate your total installation time.

1. Estimate the amount of time you need to save your system before you install the new release. Time for saving the system depends on how much storage you have and what percentage of the storage you are using. Use the amount of time from the last backup of your system.
Time: _____
2. Estimate the amount of time to replace Licensed Internal Code. Allow 30 minutes for smaller servers. The average time for larger servers is about 15 minutes.
Time: _____
3. Use "Times for installing the operating system" on page 174 to estimate the amount of time to replace OS/400.
Time: _____
4. Use "Times for installing licensed programs" on page 174 to estimate this time. Be sure to include all the licensed programs and optional parts that you intend to install.
Time: _____
5. Add time for object conversions. Follow the steps in "Times for upgrade conversions" on page 179 to determine how much time you need to add.
Time (after the upgrade) for Backup Recovery and Media Services for iSeries Conversions (see "IBM Backup Recovery and Media Services for iSeries conversions" on page 179): _____
6. Consider the time required for your system to perform an IPL. If your system takes more than 20 minutes to perform an IPL, include the amount of time that exceeds 20 minutes. For example, if your system takes 45 minutes to perform an IPL, enter the difference of 25 minutes for the time ($45 - 20 = 25$).

Software reference

Time: _____

- Add time for saving your system after the installation. Be aware that data conversions can occur during the save operation that could increase the time needed for saving your system.

Time: _____

- Determine the amount of time required to install the cumulative PTF package. Use the timing information in the *iSeries System PTF Shipping Information Letter*.

Time: _____

- Add time for any extra clean-up work and to re-customize your system.

Time: _____

The total of these steps is your estimated time for installing your new release.

Estimated time: _____

If you have data protection mechanisms, add the value you obtained from the information in "Data protection mechanisms" on page 180): _____

Total estimated time: _____

Times for installing the operating system

Use the information in the following table to complete step 3 on page 173.

Table 11. Estimated Installation Time for OS/400, in Minutes

Advanced Systems and Servers		
Model	Processor	Time
170	2159	85
	2290	85
	All other processors	80
250	2295	85
	2296	80
270	All processors	80
@server ^(R) 5xx	All processors	80
7xx	All processors	80
8xx	All processors	80
SB2	2315	80

Note: These installation times are based on using optical installation media. If you install from tape (such as a distribution tape created by a central site), these numbers are not valid. The speed of the optical drive is 600 kilobytes per second, which is the same rate as the 6390 tape drive (8mm). The next closest tape speed is 300 kilobytes per second for the 6380 tape drive (1/4 inch).

Times for installing licensed programs

The information in this topic can be used to determine the estimated maximum value (in minutes) for installing your licensed programs. This table includes data that was available at the time of publication. Multiply the total calculated value of the licensed programs in the first table by the multiplication factor for your particular model and processor in the second table. Use this result to complete step 4 on page 173.

The estimated values are for individual process times for each licensed program to install. Expect some variation in the values. These values are not accurate if you install from tape, such as for distribution tapes created by a central site.

If you are viewing the following table online, use the information in Multiplication values for licensed program installation time to calculate the installation time for your licensed programs.

Notes:

1. Multiple storage columns are not shown because additional storage is no longer a factor that influences installation time. The values were created by using images that were preloaded into an image catalog.
2. A blank indicates that no value can be calculated.

Table 12. Licensed program time information

Product	Option	Description	Value for replacing licensed program	Value for adding licensed program
5722-999	—	Licensed Internal Code		
5722-SS1	Base	Operating System/400		
5722-SS1	Library	OS/400 - Library QGPL		
5722-SS1	Library	OS/400 - Library QUSRSYS		
5722-SS1	0	OS/400 - Per Processor Pricing Key		
5722-SS1	1	OS/400 - Extended Base Support	5.6	2.4
5722-SS1	2	OS/400 - Online Information	1.1	0.5
5722-SS1	3	OS/400 - Extended Base Directory Support	25.8	28.2
5722-SS1	5	OS/400 - System/36 Environment	5.7	1.7
5722-SS1	6	OS/400 - System/38 Environment	3.8	1.8
5722-SS1	7	OS/400 - Example Tools Library	0.9	0.7
5722-SS1	8	OS/400 - AFP Compatibility Fonts	3.0	2.4
5722-SS1	9	OS/400 - *PRV CL Compiler Support	26.2	9.7
5722-SS1	12	OS/400 - Host Servers	4.8	1.9
5722-SS1	13	OS/400 - System Openness Includes	14.2	11.4
5722-SS1	14	OS/400 - GDDM	3.4	1.1
5722-SS1	18	OS/400 - Media and Storage Extensions	0.7	0.5
5722-SS1	21	OS/400 - Extended NLS Support	6.7	4.7
5722-SS1	22	OS/400 - ObjectConnect	0.9	0.5
5722-SS1	23	OS/400 - OptiConnect	2.4	0.4
5722-SS1	25	OS/400 - NetWare Enhanced Integration	2.8	2.0
5722-SS1	26	OS/400 - DB2 Symmetric Multiprocessing	0.1	0.2
5722-SS1	27	OS/400 - DB2 Multisystem	0.2	0.2
5722-SS1	30	OS/400 - Qshell	3.2	1.6
5722-SS1	31	OS/400 - Domain Name System	1.8	0.9
5722-SS1	33	OS/400 - Portable Application Solutions Environment	20.9	9.7
5722-SS1	34	OS/400 - Digital Certificate Manager	6.7	2.8

Software reference

Table 12. Licensed program time information (continued)

Product	Option	Description	Value for replacing licensed program	Value for adding licensed program
5722-SS1	35	OS/400 - CCA Cryptographic Service Provider	5.7	1.5
5722-SS1	36	OS/400 - PSF/400 1-45 IPM Printer Support	0.4	0.4
5722-SS1	37	OS/400 - PSF/400 1-100 IPM Printer Support	0.3	0.3
5722-SS1	38	OS/400 - PSF/400 Any Speed Printer Support	0.3	0.3
5722-SS1	39	OS/400 - International Components for Unicode	9.2	5.9
5722-SS1	41	OS/400 - HA Switchable Resources	0.6	0.4
5722-SS1	42	OS/400 - HA Journal performance	0.3	0.3
5722-SS1	43	OS/400 - Additional Fonts	23.9	10.1
5722-AC3	Base	IBM Cryptographic Access Provider 128-bit for iSeries	4.6	3.2
5722-AF1	Base	IBM Advanced Function Printing Utilities for iSeries	5.0	1.7
5722-AP1	Base	IBM Advanced DBCS Printer Support for iSeries	3.3	0.8
5722-AP1	1	Advanced DBCS Printer Support for iSeries - IPDS	0.6	0.2
5722-BR1	Base	IBM Backup Recovery and Media Services for iSeries	34.4	9.6
5722-BR1	1	BRMS - Network Feature	0.4	0.2
5722-BR1	2	BRMS - Advanced Feature	0.1	0.1
5722-BZ1	Base	IBM Business Solutions	0.3	0.3
5722-CE3	Base	IBM iSeries Client Encryption (128-bit)	0.3	0.2
5722-CM1	Base	IBM Communications Utilities for iSeries	3.4	1.2
5722-CR1	Base	IBM Cryptographic Support for AS/400	0.4	0.2
5722-DB1	Base	IBM System/38 Utilities for AS/400	2.8	1.1
5722-DE1	Base	IBM DB2 Universal Database Extenders for iSeries V7.2	0.2	0.2
5722-DE1	1	Text Extender for iSeries	1.7	0.7
5722-DE1	2	XML Extender	2.2	1.4
5722-DE1	3	Text Search Engine	4.6	2.7
5722-DFH	Base	IBM CICS Transaction Server for iSeries	3.2	1.0
5722-DFH	1	CICS for iSeries - Sample Applications	0.5	0.2
5722-DG1	Base	IBM HTTP Server for iSeries	18.7	6.7
5722-DG1	1	Triggered Cache Manager	1.9	0.8
5722-DP4	Base	IBM DB2 DataPropagator for iSeries, V8.1	1.9	1.4
5722-DS1	Base	IBM Business Graphics Utility for AS/400	0.5	0.2
5769-FNT	Base	IBM Advanced Function Printing Fonts for AS/400	0.1	0.1
5769-FNT	1	AFP Fonts - Sonoran Serif	0.3	0.2
5769-FNT	2	AFP Fonts - Sonoran Serif Headliner	0.2	0.1
5769-FNT	3	AFP Fonts - Sonoran Sans Serif	0.3	0.2

Table 12. Licensed program time information (continued)

Product	Option	Description	Value for replacing licensed program	Value for adding licensed program
5769-FNT	4	AFP Fonts - Sonoran Sans Serif Headliner	0.2	0.1
5769-FNT	5	AFP Fonts - Sonoran Sans Serif Condensed	0.3	0.2
5769-FNT	6	AFP Fonts - Sonoran Sans Serif Expanded	0.2	0.2
5769-FNT	7	AFP Fonts - Monotype Garamond	0.2	0.2
5769-FNT	8	AFP Fonts - Century Schoolbook	0.2	0.2
5769-FNT	9	AFP Fonts - Pi and Specials	0.1	0.1
5769-FNT	10	AFP Fonts - ITC Souvenir	0.2	0.2
5769-FNT	11	AFP Fonts - ITC Avant Garde Gothic	0.2	0.2
5769-FNT	12	AFP Fonts - Math and Science	0.2	0.2
5769-FNT	13	AFP Fonts - DATA1	0.1	0.1
5769-FNT	14	AFP Fonts - APL2	0.1	0.1
5769-FNT	15	AFP Fonts - OCR A and OCR B	0.1	0.1
5769-FN1	Base	IBM Advanced Function Printing DBCS Fonts for AS/400	0.1	0.1
5769-FN1	1	AFP DBCS Fonts - Japanese	3.0	1.6
5769-FN1	2	AFP DBCS Fonts - Korean	1.3	0.7
5769-FN1	3	AFP DBCS Fonts - Traditional Chinese	0.6	0.4
5769-FN1	4	AFP DBCS Fonts - Simplified Chinese	0.5	0.3
5769-FN1	5	AFP DBCS Fonts - Thai	0.2	0.2
5722-IP1	Base	Infoprint Server for iSeries	4.2	2.3
5722-IP1	1	PS to AFP Transform	0.1	0.1
5722-IP1	2	PCL to AFP Transform		
5722-IWE	Base	IBM WebSphere Application Server - Express, Version 5.0 for iSeries	5.7	
5722-IWE	2	IBM WebSphere Application Server - Express	14.2	
5722-JC1	Base	IBM Toolbox for Java	3.9	2.1
5722-JS1	Base	IBM Advanced Job Scheduler for iSeries	14.9	4.1
5722-JV1	Base	IBM Developer Kit for Java	4.2	0.8
5722-JV1	5	Java Developer Kit 1.3	10.7	5.5
5722-JV1	6	Java Developer Kit 1.4	3.2	2.2
5722-MG1	Base	IBM Managed System Services for iSeries	1.8	1.1
5722-PD1	Base	IBM Application Program Driver for AS/400	2.0	1.6
5722-PT1	Base	IBM Performance Tools for iSeries	5.8	1.0
5722-PT1	1	Performance Tools - Manager Feature	2.6	1.0
5722-PT1	2	Performance Tools - Agent Feature	0.6	0.3
5722-QU1	Base	IBM Query for iSeries	1.5	0.6
5722-RD1	Base	IBM Content Manager OnDemand for iSeries	1.6	1.3
5722-RD1	1	Content Manager OnDemand Spooled File Archive	1.8	5.2

Software reference

Table 12. Licensed program time information (continued)

Product	Option	Description	Value for replacing licensed program	Value for adding licensed program
5722-RD1	2	Content Manager OnDemand Object Archive	0.4	0.3
5722-RD1	3	Content Manager OnDemand Record Archive	0.4	0.2
5722-RD1	4	Content Manager OnDemand AnyStore	0.2	0.1
5722-RD1	5	Content Manager OnDemand Server	0.3	0.2
5722-RD1	10	Content Manager OnDemand Common Server	1.6	1.0
5722-RD1	11	Content Manager OnDemand Web Enablement Kit	0.8	0.5
5722-RD1	12	Content Manager OnDemand PDF Indexer	1.3	1.2
5722-SM1	Base	IBM System Manager for iSeries	1.3	0.7
5722-ST1	Base	IBM DB2 Query Manager and SQL Development Kit for iSeries	3.9	0.8
5722-TC1	Base	IBM TCP/IP Connectivity Utilities for iSeries	9.1	2.5
5769-VG1	Base	IBM VisualAge Generator Server for AS/400	0.4	0.4
5722-VI1	Base	IBM Content Manager for iSeries	1.2	0.5
5722-VI1	1	Content Manager for iSeries	5.1	1.7
5722-VI1	2	Content Manager for iSeries	0.1	0.1
5722-VI1	4	Content Manager for iSeries Workflow Builder		
5722-WDS	Base	IBM WebSphere Studio Development Suite for iSeries	18.4	2.1
5722-WDS	21	iSeries Tools - Application Development	8.5	2.9
5722-WDS	31	ILE RPG	3.1	1.1
5722-WDS	32	System/36 Compatible RPG II	5.3	1.3
5722-WDS	33	System/38 Compatible RPG III	4.8	1.0
5722-WDS	34	RPG/400	4.9	1.0
5722-WDS	35	ILE RPG *PRV Compiler	2.0	0.7
5722-WDS	41	ILE COBOL	3.5	0.8
5722-WDS	42	System/36 Compatible COBOL	5.0	0.7
5722-WDS	43	System/38 Compatible COBOL	4.7	0.8
5722-WDS	44	OPM COBOL	5.4	0.8
5722-WDS	45	ILE COBOL *PRV Compiler	2.6	0.8
5722-WDS	51	ILE C	8.5	1.1
5722-WDS	52	ILE C++	6.8	1.1
5722-WDS	56	IXLC for C/C++	2.5	0.1
5722-WDS	60	WebSphere Studio Dev Client - Server Support	4.8	0.2
5722-WSV	Base	IBM iSeries Integration for Windows Server	3.9	1.3
5722-WSV	2	Integration for Windows 2000 and 2003	7.7	2.3
5722-XE1	Base	IBM @server iSeries Access for Windows	8.9	3.7
5722-XH2	Base	IBM @server iSeries Access for Web	12.9	7.7
5722-XP1	Base	IBM @server iSeries Access for Wireless	0.7	0.5

Table 12. Licensed program time information (continued)

Product	Option	Description	Value for replacing licensed program	Value for adding licensed program
5722-XW1	Base	IBM @server iSeries Access Family	0.7	0.2
5722-XW1	1	iSeries Access Enablement Support	0.4	0.2
1TME-LCF	Base	Tivoli Management Agent	1.0	1.3

Calculated multiplication value: _____


Multiply the total calculated multiplication value above by the multiplication factor for your processor in the following table to estimate the time for installing your licensed programs.

Table 13. Estimating licensed program installation time: multiplication factor

Model	Processor	Multiplication factor for licensed programs
170	2159	1.6
	2160	1.0
	2164	0.9
	2176	0.9
	2183	0.9
	2290	1.6
	2291	1.0
	2292	0.9
	2385	0.9
	2386	0.9
	2388	0.9
	250	2295
2296		1.0
270	All processors	0.9
@server ^(R) 5xx	All processors	0.9
7xx	All processors	0.9
8xx	All processors	0.9
SB2	2315	0.9

Times for upgrade conversions



The number and type of conversions that occur when you install the new release can have a significant effect on your installation time. Only the conversions that add to your installation time are discussed here.

More conversions occur if you are skipping a release level. You need to consider the time for conversions in both the release you are skipping and in the new release. To estimate the time that conversions will take during your installation, you might need to gather information about specific object types on your system. To review conversion information from a skipped release, see the software upgrade information in the **iSeries Information Center**  (<http://www.ibm.com/eserver/iseries/infocenter>) for that release.

IBM Backup Recovery and Media Services for iSeries conversions: If you are upgrading IBM Backup Recovery and Media Services for iSeries (BRMS), 5722-BR1,

Software reference

product initialization is required after a software upgrade before you can use the BRMS functions. BRMS product initialization was removed from the installation time to improve the time required to complete software upgrades that include BRMS.

The Memo to Users  in the iSeries Information Center has more information about BRMS product initialization and methods for determining the estimated product initialization time. The *Memo to Users* is also available from the IBM @server iSeries Support  Web site (www.ibm.com/eserver/series/support).

Data protection mechanisms

If your server uses mirroring or an implementation of a RAID-5 technique on the disk units in the system ASP, your installation time can be longer. This amount of time will vary depending on your configuration, but if the disk units are protected with RAID-5, the total installation time (for Licensed Internal Code, the OS/400 operating system, and licensed programs) will be approximately 15 percent longer. If the disk units are mirror protected, the total installation time will be approximately 10 percent longer. Mirroring and implementations of the RAID-5 techniques do not affect the duration of save operations.

Using the percents given, include a time estimate for your server in “Checklist: Estimating installation time” on page 173.

Installation devices and media

The following devices can be used to install the OS/400 release.

“Optical media”

Tips for using an optical device and optical media.

“Image catalog for a virtual optical device” on page 181

Image catalog requirements for a software upgrade.

“Tape or tape libraries” on page 181

Requirements for tape devices or tape libraries.

“Non-IBM tape device” on page 182

Recommendations for non-IBM tape device use.

“Alternate installation device” on page 182

Setup and disabling guidelines for an alternate installation device

“Types of software installation devices” on page 12 provides an overview of the devices available and their naming conventions.

Optical media

The optical device used with the optical media class is considered the alternate IPL device.

Keep optical media in its protective case when not in use. When handling optical media, do not touch the surface. If the media has dust or fingerprints on it, it can be cleaned with a lint free cloth (the tape cleaning cloth can be used). Gently wipe the media from the center to the outside of the disc.

When you install from optical media, it is important to know what each media volume contains so that you do not exit the installation process prematurely. The process of creating a master installation list will help you become familiar with what software is contained on each media volume.

The system must be powered on before you can load optical media in the media drawer. “Starting from a power-off condition” on page 160 describes how to start the system when power is off.

If you are using DVD, verify that you insert the media in the correct media drive.

Image catalog for a virtual optical device

You can use an image catalog to perform a software upgrade, install PTFs (fixes), or install single licensed programs that you receive on CD-ROM or optical media.

An *image catalog* is an object on the server that contains optical images. Each catalog is associated with one user-specified integrated file system directory. The system-recognized identifier for the object type is *IMGCLG.

When you use an image catalog, you preload all your media so that you do not need to handle the physical media when you perform the installation. You do this by copying the images from the physical media to a file in the integrated file system and then use these preloaded images to install. The topic Virtual optical storage in the iSeries Information Center (**Storage solutions > Optical storage > Virtual optical storage**) describes further the concepts and uses of virtual optical media.

Image catalog requirements:

- An image catalog upgrade works like a D-mode IPL without a console during the installation of Licensed Internal Code. Reference codes are used to display the status.
- Installations done by using image catalogs require a command line to initiate the installation.
- An installation cannot be performed if an independent auxiliary storage pool (ASP) is accessible. Image files cannot reside in an independent ASP.
- Virtual optical devices do not support the following:
 - Write operations (prior to V5R3)
 - The LODRUN command using multiple media.
 - Changing a primary language from secondary language media.
- The load-source disk unit must be at least a 4-GB unit.
- To perform an installation using image catalogs, you must have at least 1074 MB of free storage on the load-source disk unit. “Cleaning up disk storage space” on page 49 describes how to free up space in the load-source disk unit.
- “Determining storage space required” on page 47 describes how to calculate storage requirements for your server.

Tape or tape libraries

If you use tape for your installation, you need to determine which tape unit to use for the alternate IPL. The tape unit for the alternate IPL is either an internal or an external tape unit attached to a storage IOA on system bus 1. If you have only one

Software reference

tape unit, use it as the tape unit for the alternate IPL. If you do not know which tape unit to use, contact your marketing representative or authorized service provider.

To help prevent media errors, be sure to clean the heads on your alternate IPL tape drive before you begin the installation process. Refer to your tape drive reference guide if you need more information on how to clean the heads. If you receive a media error message during your installation process, see Chapter 10, “Troubleshooting software installation problems,” on page 143 for recovery information.

Sharing a tape device

If you have an alternate installation tape device that you are sharing, make sure other users do not assign or try to use the tape drive during the installation because the installation process might fail.

Setting up your tape library for installation

When you install a release using a tape library device, do not use the device in library mode or random mode. The 3494 tape library should use standalone mode. The 3490 and 35xx tape libraries should use either automatic, sequential, or manual mode. Refer to the operator’s guide for the media library device for information on setting up and using the correct mode.

Non-IBM tape device

If you are using a non-IBM tape device, read informational APAR I109685 for more details on installing a release. This informational APAR states that it is for V3R2, V3R6, and V3R7. The instructions, however, are also valid for this release.

If your tape device emulates an IBM tape device, you might experience problems during the installation process, and receive message CPF5401. If this occurs, contact your vendor to confirm whether your tape drive is compatible with V5R3.

Alternate installation device

If you use an alternate installation device, you need to ensure that the device is set up and enabled. You will need the following media:

- Media containing Licensed Internal Code that matches the level on your installation media. It is recommended that you use your IBM-supplied Licensed Internal Code media. Tape or DVD-RAM media can also be used.
- Tape or optical Installation media.

The following topics pertain to the setup and use of an alternate installation device.

- “Overview: Alternate installation device”
- “Setting up an alternate installation device” on page 183
- “Disabling an alternate installation device” on page 186
- “Verifying and selecting an alternate installation device during a manual installation” on page 187

Overview: Alternate installation device

You can perform installation and recovery procedures by using the primary installation device along with an alternate installation device that you define. The alternate installation device can be a tape device or an optical device. Some

servers, typically with faster devices attached, might see a performance improvement when using an alternate installation device.

If you use an alternate installation device, the system uses the primary installation device to load a small portion of the Licensed Internal Code during an IPL-type D and then continues the installation by using the media in the alternate installation device.

You can use the alternate installation device function for any installation or recovery that requires replacing Licensed Internal Code, the operating system, licensed programs, or data. Some models might require that you set up an alternate installation device and then use the alternate installation device to install the distribution media created by a central site or for recovery using a SAVSYS media volume.

Attention:

Tape devices attached by a Fibre Channel interface will need to be set up as alternate installation devices.

If you use an alternate installation device, you need to ensure that you set up the device and that you enable the device. You also need to have the CD-ROM, DVD-RAM, or tape media that contains the Licensed Internal Code and your save media.

Setting up an alternate installation device

Before you use an alternate installation device, you need to ensure that you define it on a bus other than system bus 1, and you must enable the device. You need to record and keep the logical address of the system bus and system card at which the alternate installation device is attached. If you have the device set up on different bus and you do not have this information available, you will not be able to complete installations or recoveries.

If you change the configuration of your system, you need to ensure that this information is correct before you start to use the alternate installation device.

Do the following to set the addresses and enable the alternate installation device:

Note: You need to know the password for Dedicated Service Tools to perform this procedure.

1. Place the optical media that contains the current release Licensed Internal Code into the optical device.
2. Use the control panel to set the mode to **Manual**. Then perform an IPL using the command: `PWRDWSYS OPTION(*IMMED) RESTART(*YES) IPLSRC(B)`.

Note: An alternative to this step is to use the control panel to select function 21. (Dedicated Service Tools). If you use this alternative, the next step is step 4 on page 184. You will not need to perform step 13 on page 186.

Attention logical partition users:

If you have a primary partition and are going to use this command on the primary partition, be sure to power off all secondary partitions before running the command.

If you are using the Hardware Management Console for eServer, refer to the Hardware Management Console topic in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).

3. When the IPL or Install the System display appears, select option 3 (Use Dedicated Service Tools (DST)) and press the Enter key.
4. The Dedicated Service Tools (DST) Sign On display appears.

```

Dedicated Service Tools (DST) Sign On
System: SYSTEMA
Type choices, press Enter.
DST user . . . . . QSECOFR
DST password . . . . .
    
```

Sign on using the QSECOFR user profile.

Note: Do not sign on with a profile other than QSECOFR.

5. The Use Dedicated Service Tools (DST) menu appears. From the Use Dedicated Service Tools (DST) menu, do the following:
 - a. Select option 5 (Work with DST environment).
 - b. Select option 2 (System devices) on the Work with DST Environment display.
 - c. Select option 5 (Alternate installation device) on the Work with System Devices display.
6. When the Select Media Type display appears, select 1 for tape or 2 for optical media. Press Enter.
7. From the Select Alternate Installation Device display, type a 5 (Display details) next to the resource you want and press the Enter key.

```

Select Alternate Installation Device
System: SYSTEMA
Additional devices may be available for use. Press F5 to see
if any additional devices have been detected.
Type option, press Enter.
1=Select 5=Display details

```

Option	Bus Number	Resource Name	Type	Model	Serial Number	Selected
-	1	OPT08	6330	002	00-11111	
-	3	TAP19	3570	B11	13-22222	*

```

F2=Deselect device  F3=Exit  F5=Refresh  F12=Cancel
    
```

8. The Display Device Details display appears.

Display Device Details				System: SYSTEMA
Resource Name	Type	Model	Serial Number	
TAP19	3570	B11	13-22222	
Physical location:				
Location text :				
Frame ID :				
Card slot :				
Logical address:				
SPD bus:				
System bus :				0003
System board :				0000
System card :				0002
Storage:				
I/O bus number :				0000
Controller :				0007
Device address :				0000
F3=Exit F12=Cancel				

You need to have a record of the addresses assigned to the alternate installation device selected for installing and recovering your system. Record the following information:

- Type/Model: _____
- System bus: _____
- System card: _____

Notes:

1. You might want to repeat this process to record the addresses for all alternate installation devices that appear in step 7 on page 184. You should store this information in a safe place, such as the location where your recovery information and recovery media are stored.
2. If more than one alternate installation device is defined, only one can be enabled.
3. You should ensure that only one device contains valid installation media. This prevents you from loading the wrong version of the Licensed Internal Code.

Press the Enter key.

9. The Select Alternate Installation Device display appears. Type 1 (Select) next to the resource you want and press the Enter key.
10. You should see the following message at the bottom of the display:
Alternate installation device selected
11. Press F3 (Exit) to return to the Use Dedicated Service Tools (DST) display.
12. Press F3 (Exit) again. The Exit Dedicated Service Tools (DST) display appears.

Exit Dedicated Service Tools

System: SYSTEMA

Select one of the following:

1. Exit Dedicated Service Tools (DST)
2. Resume Dedicated Service Tools

Type 1 (Exit Dedicated Service Tools (DST)) and press the Enter key.

13. The next display you see is the IPL or Install the System display. Type 1 (Perform an IPL) and press the Enter key to complete the procedure.

Disabling an alternate installation device

You might need to disable an alternate installation device for one of the following reasons:

- To continue with an installation using CD-ROM media.
 - To enable a different device as an alternate installation device.
 - To correct the logical address if hardware has been moved or changed.
1. Use the control panel to set the mode to **Manual**. Then perform an attended IPL using the command: `PWRDWSYS OPTION(*IMMED) RESTART(*YES) IPLSRC(B)`.

Note: An alternative to this step is to use the control panel to select function 21. (Dedicated Service Tools). If you use this alternative, skip steps 2 and 9 on page 187 below.

Attention logical partition users:

If you have a primary partition and secondary partitions and are going to use this command on the primary partition, be sure to power off all secondary partitions before running the command.

If you are using the Hardware Management Console for eServer, refer to the Hardware Management Console topic in the IBM eServer Hardware Information Center (**Managing your server > Hardware Management Console**).

2. When the IPL or Install the System display appears, select option 3 (Use Dedicated Service Tools (DST)) and press the Enter key.
3. The Dedicated Service Tools (DST) Sign On display appears. Sign on using the QSECOFR user profile.
4. The Use Dedicated Service Tools (DST) menu appears. From the Use Dedicated Service Tools (DST) menu, do the following:
 - a. Select option 5 (Work with DST environment).
 - b. Select option 2 (System devices) on the Work with DST Environment display.
 - c. Select option 5 (Alternate installation device) on the Work with System Devices display.
5. At the Select Alternate Installation Device display, press F2 (Deselect device).
6. You should see the following message at the bottom of the display:
Alternate installation device deselected
7. Press F3 (Exit) to return to the Use Dedicated Service Tools (DST) display.
8. Press F3 (Exit) again. The Exit Dedicated Service Tools (DST) display appears. Type 1 (Exit Dedicated Service Tools (DST)) and press the Enter key.

9. The next display you see is the IPL or Install the System display. Type 1 (Perform an IPL) and press the Enter key to complete the procedure.

Verifying and selecting an alternate installation device during a manual installation

1. The Install Licensed Internal Code display appears.

```

Install Licensed Internal Code
System: XXXX

Select one of the following:

1. Install Licensed Internal Code
2. Work with Dedicated Service Tools (DST)
3. Define alternate installation device

```

Type 3, and press Enter. This will verify the address of an alternate installation device attached to the system and determine whether it is enabled or disabled.

2. **Verifying and selecting alternate installation device:** The Select Alternate Installation Device Bus display appears.

```

Select Alternate Installation Device Bus
System: XXXX


Type Option, press Enter.
1=Select

Option   Bus Number   Selected
-        -           -
-        1           -
-        2           -
1        3           *
-        4           -
-        5           -
-        6           -
-        7           -
-        8           -
-        9           -
-        A           -
-        B           -
-        C           -
-        D           -

F2=Deselect Device  F3=Exit    F12=Cancel    More.....

```

- a. Verify that the selected device is on the correct system bus (the bus to which your device is attached). If you do not know the correct bus, you can try each bus number. Type 1 in the Options field next to the selected bus, and press Enter to view information about the device that is attached to the bus. This can take several minutes. If you see the message No alternate installation device configured, wait one minute and refresh the screen.
- b. When the Select Media Type display appears, select 1 for tape or 2 for optical media. Press Enter.
- c. The Select Alternate Installation Device display appears. Use this display to verify the resource name, type, model, and serial number for the device. The following display shows an example of a tape device.



- d. Type 1 to select the device and make any needed corrections to select, enable, or disable the device. Press Enter to confirm the changes.
 - e. The message Alternate installation device selected appears. Press F3 to return to the Install Licensed Internal Code display.
 - f. Type 1 and press Enter to install the Licensed Internal Code.
- End of verifying and selecting alternate installation device.**

OS/400 release interoperability

Interoperability is the ability of one system to exchange data or objects with another system. The exchange can be performed electronically or by physical media (such as tape). Either system can initiate the exchange.

An iSeries server interoperates with another iSeries server when it exchanges data or when it saves and restores objects.

If you have several iSeries servers in a network, they must be at compatible releases. This is necessary if objects and data are to be interchanged between systems. You can use option 10 (Display licensed programs) on the Work with Licensed Programs menu (type GO LICPGM) to see the installed release of your licensed programs.

The releases on servers must all be supported when data is exchanged

The source system (the system that sends the information) and the target system (the system that receives the information) must be within the supported releases.

For example, V5R1M0 Client Access Express supports functions on servers running OS/400 V4R4 or later. V5R3M0 iSeries Access for Windows supports functions on servers running OS/400 V5R1 or later.

Requirements for saving and restoring objects to be interoperable with previous releases

To be interoperable, objects must be saved by specifying either a specific release or *PRV for the value of the target release (TGTRLS) parameter.

You can save and restore licensed programs just like other objects as long as the release is compatible with the operating system release. “Licensed program releases and sizes” on page 166 contains more information about compatible releases of licensed programs.

For more information on supported combinations of OS/400 releases or saving objects to a system that is running a previous release, see the section on

release-to-release support in the Backup and Recovery  manual.

Installation notes about the OS/400 release

Note: The system must be in a restricted state to install the QGPL and QUSRSYS libraries, and to install Option 12 (Host Servers).

5722-SS1, OS/400 Option 1

This option installs automatically when you install the new release of OS/400. You cannot delete this option.

5722-SS1, OS/400 Option 3

This option installs automatically when you install the new release of OS/400. This option contains IFS directories. You cannot delete this option.

5722-SS1, OS/400 Option 4

Option 4 (OS/400 - S/36 and S/38 Migration) has been removed.

5722-SS1, OS/400 Option 11



Option 11 (OS/400 - S/36 Migration Assistant) has been removed.

5722-SS1, OS/400 Option 16

Option 16 (OS/400 - Ultimedia System Facilities) has been removed.

The Electronic Service Agent™, formerly 5798-RZG, is now part of the OS/400 operating system.

To find other information about what’s new or changed this release, see the Memo

to Users  in the information center. For more information on products or features that might not be supported in future releases of the OS/400 operating system or on future models, on Product Previews, and on Statements of Directions, see iSeries Upgrade Planning  (http://www.ibm.com/servers/eserver/iseres/support/planning/nav.html).

Media labels and their contents

Following is a list of the optical media you receive with your OS/400 order.

The licensed programs are identified as standard set products and keyed set products:

“Standard set products” on page 191 lists specific products contained in the standard set CD-ROMs.

“Keyed set products” on page 193 lists products contained in the priced licensed programs CD-ROMs.

Release identifier for V5R3: R03M00

Distribution media labels indicate the version, release, and modification level in a format that is different from what appears on displays during installation. The media labels show the version, V5, in the first line of the label. The release and modification level are shown in the format R0xM00.

Media type identifiers

Labels on the distribution media that are used for installation have unique identifiers. Media type identifiers are located on the center of the left side of the CD-ROM label. These identifiers help you determine when to use each media volume.

Note: With your V5R3 software order, you receive *Software Agreement PTFs for V5R1 and V5R2, SK3T-8163-00*. This media contains PTFs that you temporarily apply to be able to accept online software agreements for V5R3 licensed programs.

When you are ready to install your new software, arrange the media in this order:

1. I_BASE_01 Licensed Internal Code for OS/400
This language-independent Licensed Internal Code supports all national language features. The Licensed Internal Code is part of the standard set of media.
2. B29xx_01 Operating System/400
This standard set media contains the base part of the OS/400 operating system.
3. B29xx_02 OS/400 no-charge options
This standard set media contains IBM-supplied libraries QGPL and QUSRSYS and a no-charge optional part of OS/400.
4. B29MM_03 OS/400 no-charge options
This standard set media contains the no-charge option 3, OS/400 - Extended Base Directory Support.
5. B29MM_04 OS/400 no-charge options
This standard set media contains more of the no-charge option 3, OS/400 - Extended Base Directory Support.
6. D29xx_01 OS/400 no-charge options
This standard set media contains more of the no-charge optional parts of OS/400.
7. D29xx_02 OS/400 no-charge options
This standard set media contains more of the no-charge optional parts of OS/400.
8. D29xx_03 OS/400 no-charge options
This standard set media contains option 43 of the operating system, OS/400 - Additional Fonts.
9. D29xx_04 no-charge licensed programs
This standard set media contains some of the no-charge licensed programs.
10. D29xx_05 no-charge licensed programs
This standard set media contains some of the no-charge Java Developer Kit licensed programs.
11. L29xx_01 Priced licensed programs

This keyed set media contains keyed options of OS/400 and some of the keyed products and keyed product options.

12. L29xx_02 Priced licensed programs

This keyed set media contains the remainder of the keyed products and keyed product options.

13. F29xx_01 Single licensed programs

This media contains individual products that you ordered. Each piece of media is labeled in the same manner: F29xx_01. If you receive more than one media volume for a single licensed program, the additional volumes are labeled F29xx_02, F29xx_03, and so on. Refer to "Licensed program releases and sizes" on page 166 for the single products available this release.

14. N29xx_01 Secondary Language Media

This media contains only language objects for the indicated secondary language. For secondary language media, the value for 29xx is the feature code of the secondary language as used for installation. "Feature codes for national language version" on page 195 contains a listing of the specific national language feature codes.

15. SK3T-4091 iSeries Information Center

This media volume comes with all OS/400 orders. This package includes the iSeries Information Center and PDF versions of iSeries topics and manuals.

Notes:

1. Keep all of your distribution media. You might need them for recovery procedures.
2. Media identifiers that contain the string 29xx (where xx are numerals) indicate language-specific media. This string indicates the national language feature code for the primary language. For example, media labeled B2928_01 would be OS/400 with French as the primary language.
3. You might receive additional media volumes that do not conform to these descriptions. Examples include media that contain PRPQs or media for iSeries Access products that are installed on workstations. Also, IBM Business Partners might label the media differently.
4. Julian dates are shown in the form *yddd*. The *y* is the last digit of the year (0 through 9), and *ddd* is the day of the year (0 through 366). For example, the Julian date for 6 April 1998 would be shown as 8096 because 06 April is the 96th day of the year 1998.

Standard set products

The standard set comes with every software release order. It contains the hardware and software components to install on your server. This includes the Licensed Internal Code, OS/400, its no-charge options, and no-charge (bonus) licensed programs and features, such as online help messages.

I_BASE_01 standard set

Product	Description
5722999	Licensed Internal Code for OS/400

Software reference

B29xx_01 standard set

Product	Description
5722SS1	Operating System/400

B29xx_02 standard set

Product	Description
5722SS1	Operating System/400 (continued)
5722SS1	OS/400 - Library QGPL
5722SS1	OS/400 - Library QUSRSYS
5722SS1 option 1	OS/400 - Extended Base Support
5722SS1 option 2	OS/400 - Online Information

B29MM_03 standard sets

Product	Description
5722SS1 option 3	OS/400 - Extended Base Directory Support

B29MM_04 standard sets

Product	Description
5722SS1 option 3	OS/400 - Extended Base Directory Support (continued)

D29xx_01 standard set

Product	Description
5722SS1 option 3	OS/400 - Extended Base Directory Support (continued)
5722SS1 option 5	OS/400 - System/36 Environment
5722SS1 option 6	OS/400 - System/38 Environment
5722SS1 option 7	OS/400 - Example Tools Library
5722SS1 option 8	OS/400 - AFP Compatibility Fonts
5722SS1 option 9	OS/400 - *PRV CL Compiler Support
5722SS1 option 12	OS/400 - Host Servers
5722SS1 option 13	OS/400 - System Openness Includes
5722SS1 option 14	OS/400 - GDDM

D29xx_02 standard set

Product	Description
5722SS1 option 21	OS/400 - Extended NLS Support
5722SS1 option 22	OS/400 - ObjectConnect
5722SS1 option 25	OS/400 - NetWare Enhanced Integration
5722SS1 option 30	OS/400 - Qshell
5722SS1 option 31	OS/400 - Domain Name System

Product	Description
5722SS1 option 33	OS/400 - Portable Application Solutions Environment
5722SS1 option 34	OS/400 - Digital Certificate Manager
5722SS1 option 35	OS/400 - CCA Cryptographic Service Provider
5722SS1 option 39	OS/400 - International Components for Unicode

D29xx_03 standard set

Product	Description
5722SS1 option 43	OS/400 - Additional Fonts

D29xx_04 standard set

Product	Description
5722DG1 *BASE	IBM HTTP Server for iSeries
5722DG1 option 1	Triggered Cache Manager
5722JC1 *BASE	IBM Toolbox for Java
1TMELCF	Tivoli Management Agent
5722TC1 *BASE	IBM TCP/IP Connectivity Utilities for iSeries
5722WSV *BASE	IBM iSeries Integration for Windows Server
5722WSV option 2	Integration for Windows 2000 and 2003
5722XE1 *BASE	IBM @server iSeries Access for Windows
5722XP1 *BASE	IBM @server iSeries Access for Wireless

D29xx_05 standard set

Product	Description
5722JV1 *BASE	IBM Developer Kit for Java
5722JV1 option 5	Java Developer Kit 1.3
5722JV1 option 6	Java Developer Kit 1.4

Keyed set products

The keyed set comes with the standard set for every software or upgrade order. It contains keyed products and program options. Use the following information to verify the licensed programs that you ordered.

L29xx_01 keyed set

Product	Description
5722SS1 option 18	OS/400 - Media and Storage Extensions
5722SS1 option 36	OS/400 - PSF/400 1-45 IPM Printer Support
5722SS1 option 37	OS/400 - PSF/400 1-100 IPM Printer Support
5722SS1 option 38	OS/400 - PSF/400 Any Speed Printer Support
5722SS1 option 41	OS/400 - HA Switchable Resources

Software reference

Product	Description
5722SS1 option 42	OS/400 - HA Journal Performance
5722AF1 *BASE	IBM Advanced Function Printing Utilities for iSeries
5722BR1 *BASE	IBM Backup Recovery and Media Services for iSeries
5722BR1 option 1	BRMS - Network Feature
5722BR1 option 2	BRMS - Advanced Functions Feature
5722CM1 *BASE	IBM Communications Utilities for iSeries
5722DE1 *BASE	IBM DB2 Universal Database Extenders for iSeries V7.2
5722DE1 option 1	Text Extender for iSeries
5722DE1 option 2	XML Extender
5722DE1 option 3	Text Search Engine
5722DP4 *BASE	IBM DB2 DataPropagator for iSeries V8.1
5722JS1 *BASE	IBM Advanced Job Scheduler for iSeries
5722PT1 *BASE	IBM Performance Tools for iSeries
5722PT1 option 1	Performance Tools - Manager Feature
5722PT1 option 2	Performance Tools - Agent Feature
5722QU1 *BASE	IBM Query for iSeries
5722ST1 *BASE	IBM DB2 Query Manager and SQL Development Kit for iSeries
5722XH2 *BASE	IBM @server iSeries Access for Web
5722XW1 *BASE	IBM @server iSeries Access Family
5722XW1 option 1	iSeries Access Enablement Support

L29xx_02 keyed set

Product	Description
5722IP1 *BASE	Infoprint Server for iSeries
5722WDS *BASE	IBM WebSphere Studio Development Suite for iSeries
5722WDS option 21	iSeries Tools - Application Development
5722WDS option 31	Compiler - ILE RPG
5722WDS option 32	Compiler - System/36 Compatible RPG II
5722WDS option 33	Compiler - System/38 Compatible RPG III
5722WDS option 34	Compiler - RPG/400 [®]
5722WDS option 35	Compiler - ILE RPG *PRV
5722WDS option 41	Compiler - ILE COBOL
5722WDS option 42	Compiler - System/36 Compatible COBOL
5722WDS option 43	Compiler - System/38 Compatible COBOL
5722WDS option 44	Compiler - OPM COBOL
5722WDS option 45	Compiler - ILE COBOL *PRV
5722WDS option 51	Compiler - ILE C
5722WDS option 52	Compiler - ILE C++
5722WDS option 56	Compiler - IXLC for C/C++

Product	Description
5722WDS option 60	WebSphere Studio Dev Client - Server Support
5722AP1 *BASE (if media is in double-byte character set language)	IBM Advanced DBCS Printer Support for iSeries
5722AP1 option 1 (if media is in double-byte character set language)	Advanced DBCS Printer Support for iSeries - IPDS

Feature codes for national language version

Use this table to locate the appropriate feature code for your primary or secondary language.

Note: Labels on the installation media indicate the feature code for the primary language (29xx). When you install OS/400, the system prompts for the primary language in the form 29xx.

The secondary language feature code is only used when ordering secondary languages (56xx). When you install the secondary language, you select a feature code, in the form 29xx, from a list of national language feature code identifiers. For example, if you ordered French as a secondary language, the secondary language media volume would be labeled N2928, and you would select 2928 from the list of feature codes when you install the secondary language.

Primary language feature code	Secondary language feature code	National language
2902	5602	Estonian
2903	5603	Lithuanian
2904	5604	Latvian
2905	5605	Vietnamese
2906	5606	Lao
2909	5609	Belgian English
2911	5611	Slovenian
2912	5612	Croatian
2913	5613	Macedonian
2914	5614	Serbian Cyrillic
2922	5622	Portuguese
2923	5623	Dutch Netherlands
2924	5624	English
2925	5625	Finnish
2926	5626	Danish
2928	5628	French
2929	5629	German
2931	5631	Spanish
2932	5632	Italian

Software reference

Primary language feature code	Secondary language feature code	National language
2933	5633	Norwegian
2937	5637	Swedish
2938	5638	English Uppercase Support for Double-Byte Character Set (DBCS)
2939	5639	German Multinational Character Set
2940	5640	French Multinational Character Set
2942	5642	Italian Multinational Character Set
2950	5650	English Uppercase
2954	5654	Arabic
2956	5656	Turkish
2957	5657	Greek
2958	5658	Icelandic
2961	5661	Hebrew
2962	5662	Japanese Double-Byte Character Set (DBCS)
2963	5663	Belgian Dutch
2966	5666	Belgian French
2972	5672	Thai
2974	5674	Bulgarian
2975	5675	Czech
2976	5676	Hungarian
2978	5678	Polish
2979	5679	Russian
2980	5680	Brazilian Portuguese
2981	5681	Canadian French
2984	5684	English Uppercase and Lowercase Support for Double-Byte Character Set (DBCS)
2986	5686	Korean Double-Byte Character Set (DBCS)
2987	5687	Traditional Chinese Double-Byte Character Set (DBCS)
2989	5689	Simplified Chinese Double-Byte Character Set (DBCS) (PRC)
2992	5692	Romanian
2994	5694	Slovakian
2995	5695	Albanian

Primary language feature code	Secondary language feature code	National language
2996	5696	Portuguese Multinational Character Set
2998	5698	Farsi


Blank displays

During the installation process, you will see some blank displays. Some of these are predictable and the instructions give an approximate amount of time when there appears to be no installation activity. Other blank displays are less predictable because of unique situations on your system. If the processor light is blinking or reference codes are changing, the installation process is active. If the processor light goes out, the attention light turns on, and a reference code appears on the control panel, go to Chapter 10, "Troubleshooting software installation problems," on page 143 and follow the instructions.

System password

Support exists to detect processor model changes on all iSeries server models through the use of a 16-character system password. The system password identifies all model changes to help maintain the quality and integrity of the iSeries server. The system password also ensures the protection of IBM's intellectual property, including IBM Licensed Internal Code and licensed programs.

New servers from the factory come with the correct system password already installed. A new system password is required for each model change or for conditions that indicate probable change of ownership. If you do not have the system password at the first IPL, contact your marketing representative to place an iSeries system password RPQ (Request for Price Quotation) order. IBM manufacturing receives the RPQ order and sends the system password to you for installation. If the correct system password is not entered, you can select a system-password bypass period to allow you to obtain the correct system password from your marketing representative. If the correct password is not available and the bypass period expires, the system will not complete the next IPL unless the correct password is installed. While in bypass mode, the system uses operator messages to indicate the time that remains until the bypass period expires.

For more details on the system password, see Tips and Tools for Securing Your iSeries .

Installed status values

Here is a description of the installed status values you might see on the LICPGM displays. You can use these values to determine whether you can use a product or whether you need to upgrade a licensed program. If you do not see a value of *COMPATIBLE, you can check the other installed status values for how to proceed.

*COMPATIBLE

The product is installed. Its version, release, and modification is compatible with the installed level of the OS/400. You can use this program with the V5R3 OS/400 operating system.

***INSTALLED**

The product is installed, but might or might not be compatible with the installed OS/400.

Note: Licensed programs that are part of the single set will be listed on the display panel as *INSTALLED. You will need to verify that the release level of the licensed program is compatible with the release level of OS/400. For IBM products, either check the current release levels for licensed programs in the topic, "Licensed program releases and sizes" on page 166, or check with your software supplier before you use the licensed program.

***ERROR**

Either the product has not installed successfully or the product is only partially installed. For example, a language or a language object for the product is not installed. Use the Check Product Option (CHKPRDOPT) command to determine the cause of the failure. To determine the cause of a missing object, enter G0 LICPGM and select options 10 and 50.

Note: The product lists now show many products, such as Programming Request for Price Quotations (PRPQ), licensed program offerings (LPO), and non-IBM products. This *ERROR status might have existed prior to the upgrade of V5R3, but was not detected. Use the CHKPRDOPT to find out why the product shows an *ERROR, and contact your software provider if you need help correcting the problem.

***BACKLEVEL**

The product is installed. Its version, release, and modification is not compatible with the currently installed level of the OS/400. To correct this problem, install a current release of this product. And if you have secondary languages, install a new release of these languages as well, using LICPGM menu option 21.

Note: If you use a licensed program that is listed as *BACKLEVEL, you run the risk of having an information mix up between release levels, or some portions of the licensed program might not work properly. An installed status value of *COMPATIBLE is desired.

***BKLVL OPT**

The product is installed. Its version, release, and modification is not compatible with the currently installed level of the base product that is associated with the option. To correct this problem, install a current release of this option.

***BKLVLBASE**

The product is installed, but its associated base product is not compatible with this option. To correct this problem, install a current release of the base product.

Blank (on LICPGM menu, option 11)

If no value is shown, a blank in the installed status column means that the product is not installed.

***NOPRIMARY**

The product is installed, but the language for the product is not the same as the primary language of the OS/400. To correct this problem, install the primary language for the product by using the Restore Licensed Program (RSTLICPGM) command or from the LICPGM menu.

Note: If this product is an LPO, PRPQ or non-IBM product, it is possible that the licensed program (from the manufacturer) is not available in the primary language of the OS/400.

Options on Prepare for Install menu

This topic describes the Prepare for Install function. Highlights of this function include the following:

- Customizing an installation list. Preselecting licensed programs or options to be installed during the automatic installation process.
- Verifying the contents of the media before starting an installation.
- Determining additional storage requirements for the licensed programs that you plan to install.

This function appears as option 5 (Prepare for Install) on the Work with Licensed Programs menu. The Prepare for Install display appears when you select this option.

```

                                Prepare for Install
                                System:  XXXXXXXX

Type option, press Enter.
  1=Select

Opt   Description
-     Work with licensed programs for target release
-     Work with licensed programs to delete
-     List licensed programs not found on media
-     Display licensed programs for target release
-     Work with software agreements
-     Work with user profiles
-     Verify system objects
-     Estimate storage requirements for system ASP
-     Allocate additional space for LIC
-     Keep disk configuration

                                Bottom

F3=Exit  F9=Command line  F10=Display job log  F12=Cancel

```

For the instructions to use Option 5, Prepare for install, see “Required: Creating a custom list of software to install” on page 42.

With the **Work with licensed programs for target release** option, you can work with a list of the licensed programs for the target release. Use this option to verify the contents of the installation media and to create a customized list of licensed programs to install for the target release. The system can use the list you create to allow the installation processes that replace a release of software to also install the selected additional licensed programs. For more information, refer to “Verifying the contents of your software order” on page 28.

Note: This list does not include all products. Among those are programming request for price quotations (PRPQ), licensed program offerings (LPO), and licensed programs on the single set. If you want to install these products for the first time, use the G0 LICPGM menu, options 1 or 11.

With the **Work with licensed programs to delete** option, you can work with a list of installed licensed programs that should not remain on the system because either they are no longer supported or you chose not to replace them. This list also includes products for which no replacement was found on the distribution media. The display indicates the reason why a licensed program is included in this list, as

Software reference

well as provides options to save and delete any of the products listed. For more information, refer to “Cleaning up disk storage space” on page 49.

With the **List licensed programs not found on media** option, you can display a list of licensed programs that could replace existing products but that were not found on the optical distribution media. For more information on licensed program availability, refer to Chapter 11, “Software reference,” on page 165.

With the **Display licensed programs for target release** option, you can display the list of licensed programs that will be installed when you install the target release. For each licensed program in the list, you can display information such as the expected action during the installation process and whether a product option must be separately ordered. Use this option to verify your installation plans.

With the **Work with software agreements** option, you can review and accept software agreements prior to the installation of the target release. The agreements can be printed or displayed in different languages provided by the software provider. Any software agreement not accepted or specifically declined will result in the licensed program not being installed during the upgrade to the target release. If the Licensed Internal Code and Operating System/400 software agreements are not accepted, the upgrade to the target release is not allowed.

With the **Work with user profiles** option, you can work with a list of user profiles on the system and work with the objects owned by each user profile. Use this option to clean up user profiles that are no longer needed on the system before you install the target release. For more information, refer to “Cleaning up disk storage space” on page 49.

With the **Verify system objects** option, the system verifies that the system directory entries include the user profiles needed by the installation process. The system also checks database cross reference files for errors. If necessary, the QSECOFR and QLPINSTALL user profiles are added to the system distribution directory. For more information, refer to “Verifying user profiles and checking cross-reference files” on page 36.

With the **Estimate storage requirements for system ASP** option, you can determine whether additional storage is needed before you begin the installation process. This option helps you plan for growth in licensed programs that are listed on the Work with Licensed Programs for Target Release display. This option does not consider licensed programs that are not in the standard set or keyed set, Programming Request for Price Quotations (PRPQs), licensed program offerings (LPOs), or system conversion growth such as spooled files. The option also does not consider storage required for temporarily applied program temporary fixes (PTFs).

The **Allocate additional space for LIC** option is a required task before you upgrade to V5R3. The V5R3 Licensed Internal Code requires .42 GB more storage space than in previous releases. All models of the server require the additional reserved storage before V5R3 can be installed. Directions for doing this are included in “Required: Allocating additional space for Licensed Internal Code” on page 50.

The **Keep disk configuration** option appears only on V5R3 systems. Use this option to change your disk configuration before you upgrade or replace a release.

Options on Work with Licensed Programs menu


Use this information to determine when and how you can use these options. For each display, you can use the Help key for more information about the display.

The following topics pertain to the options on the Work with Licensed Programs menu:

- “Manual installation Option 1. Install all”
- “Automatic installation options” on page 202
- “Options for displaying, installing, deleting, and saving from a list” on page 202
- “Options for secondary languages” on page 207
- “Completion status” on page 208
- “Commands related to the Work with Licensed Programs menu” on page 209

Manual installation Option 1. Install all

Option 1 (Install all) on the Work with Licensed Programs menu enables you to install all of the licensed programs and optional parts of the licensed programs from distribution media. Secondary languages on distribution media can also be installed with this option.



The Manual Install display allows you to make choices for the prompts in the following list. Use the Help key for more information about each prompt.

1. Install option

This option determines what types of licensed programs and optional parts are installed from the distribution media. You can choose to install only new releases of products that already exist on your system, install all products, install only new products, or install new releases of products that exist on your system plus additionally selected products.

Notes:

1. The *Install option* does not apply to the QGPL and QUSRSYS libraries. QGPL and QUSRSYS libraries are always installed if they are found on the media. For all *Install option* choices, only new objects are installed in the QGPL and QUSRSYS libraries.
 2. To complete the installation successfully, the installation media must contain all renewed products that are currently installed on your system. The installation media might contain products whose version, release, and modification is earlier than that of the new operating system release. (The products did not renew at the same time as the operating system.)
- #### 2. Installation device

Software reference

The examples in this topic use OPT01 for the name of the installation device. For more information about the installation device naming convention, see “Types of software installation devices” on page 12.

3. Replace if current

By specifying *NO, the licensed programs that are currently installed and that are at the same release level on the installation media will not be replaced during an upgrade. You can change the *Replace if Current* parameter to *YES if you want to replace licensed programs that are already installed, including products installed at the same release level as on the installation media. By choosing *YES, you might have to reapply PTFs to some licensed programs that were replaced from the media.

4. Nonaccepted agreement

During the installation of licensed programs, if the software agreement has not been previously accepted, the nonaccepted agreement option determines if you will be prompted to accept or decline the software agreement, or if the installation will continue without installing the licensed program. A value of 1 indicates that you do not want to install the licensed program. A value of 2 indicates that you want to display the licensed program and accept the software agreement.

5. Automatic IPL

This option determines whether the system will automatically IPL when the installation process has completed successfully.

Attention: If you do this on a primary partition when secondary partitions are active, this will cause all partitions to do an IPL immediately. If you have active secondary partitions, power them off prior to using this procedure.

If you are using the Hardware Management Console for @server^(R), refer to the Hardware Management Console topic in the IBM eServer^(TM) Hardware Information Center (**Managing your server > Hardware Management Console**).

Automatic installation options

The Prepare for install option helps you to create an installation list and select the programs that you want to install during the automatic installation process. Prepare for install also helps you verify the contents of the installation media and determine the storage requirements, among other necessary tasks in preparation for automatic installation. “Options on Prepare for Install menu” on page 199 describes Option 5 (Prepare for Install) in more detail.

Option 5. Prepare for Install

“Required: Creating a custom list of software to install” on page 42 provides the instructions for using Option 5 (Prepare for Install).

Options for displaying, installing, deleting, and saving from a list

This topic contains information about displaying, installing, deleting, and saving licensed programs from a list.

- “Option 10. Display installed licensed programs” on page 203
- “Option 11. Install licensed programs” on page 203

- “Option 12. Delete licensed programs” on page 205
- “Option 13. Save licensed programs” on page 205

Option 10. Display installed licensed programs

After an installation process has completed, it is often necessary to determine if a licensed program is installed successfully on your system. To do this, select option 10 (Display installed licensed programs) on the Work with Licensed Programs menu. The Display Installed Licensed Programs display shows the licensed programs, optional parts, and IBM-supplied user libraries that are installed on your system.

The Installed Status column indicates whether or not the licensed program is successfully installed. Refer to “Installed status values” on page 197 for a description of the installed status values.

If a licensed program did not install successfully, use the recovery procedures in Chapter 10, “Troubleshooting software installation problems,” on page 143 to install the licensed program again.


You can use the F11 key to view the Installed Release column. This column shows the release and modification of each installed licensed program. The F11 key has a third view, also, that shows the product option number of each licensed program.

Option 11. Install licensed programs

Before you install any licensed programs, be sure to check the product documentation in the iSeries Information Center and also the documentation that comes with the product for any special instructions.

When you select option 11 (Install licensed programs) on the Work with Licensed Programs display, you see a list of licensed programs and optional parts of licensed programs. The listed items are the licensed programs and optional parts that were supported by the LICPGM installation processes at the time your currently installed operating system became available.

You can use this list to select licensed programs and optional parts to be installed on your system. You can also use this list to install a licensed program that did not successfully install during a previous installation process.



RV3D003-0

Software reference

To install one or more licensed programs from the list, type a 1 in the Option column next to the licensed programs and any optional parts that you want to install. For a list of the licensed programs that are on the media, refer to “Licensed program releases and sizes” on page 166.

A licensed program you want to install might not be listed on the Install Licensed Programs display. If a licensed program is not listed, it can be added to the list by entering information into the blank fields at the top of the list. After you press Enter, this product then appears on the list with the other products.

1. Type 1 in the Option column
2. Type the product identifier in the Licensed Program column
3. Type the product option value in the Product Option column
4. Press Enter

When you are typing the product option, the system accepts only the following three values: *BASE, option number, or *ALL.

- A value of *BASE installs only the base product of the associated product identifier.
- The product option number installs only the particular option of the associated product identifier. To be able to install options, you must install the base product (*BASE).
- A value of *ALL installs the base product and all options of the associated product identifier that are found on the media.

Keep in mind that licensed programs that you add will appear on the list with only the product identifier and will not give a descriptive name of the product.

The Confirm Install of Licensed Programs display shows which licensed programs you selected to install. If you do not need to make any changes, press Enter to confirm your choices.

Fill in the following choices on the Install Options display. Use the Help key for more information about each prompt on this display.

1. Installation Device
The examples in this topic use OPT01 for the name of the installation device. For more information about the installation device naming convention, see “Types of software installation devices” on page 12.
2. Objects to install
This option allows you to choose to install both programs and language objects, only programs, or only language objects.
3. Automatic IPL
This option determines if the system automatically IPLs after the installation process has completed successfully.

When the licensed programs are installed, the Work with Licensed Programs menu or the Sign On display appears again. To verify that all of the licensed programs are installed successfully, use option 50 (Display log for messages). (More information about that option is available in “Completion status” on page 208.) If an error occurs, you will see the message Work with licensed program function not complete, on the bottom of the Work with Licensed Programs display. Go to Chapter 10, “Troubleshooting software installation problems,” on page 143 to determine the problem.


If you install a licensed program or optional part again, you must also install the PTFs for that licensed program again.

Option 12. Delete licensed programs

Before you delete a licensed program, review “Considerations for deleting licensed programs” on page 141 and then return here.

Select option 12 on the Work with Licensed Programs menu to delete a licensed program or optional part of a licensed program that is installed on your system. When you select this option, the Delete Licensed Programs display appears. The list shows the licensed programs and optional parts that are installed on your system. Use this list to select licensed programs or optional parts to delete.

If you delete a (*BASE) licensed program that has optional parts, the system deletes all of the optional parts for that licensed program. If you delete only an optional part, the base program and other optional parts remain on your system. This option deletes all objects that are associated with the licensed program or optional part you select.




Type a 4 in the Option column next to the licensed program or optional part of a licensed program that you want to delete from your system.

The Confirm Delete of Licensed Programs display shows you which licensed programs or optional parts you selected to delete. Press Enter to delete the licensed programs or optional parts.

Option 13. Save licensed programs

Select option 13 on the Work with Licensed Programs menu to save one or more licensed programs for redistribution.

The Save Licensed Programs display lists the licensed programs and optional parts that are installed on your system. Use this list to select licensed programs or optional parts to save. Type a 1 in the option column on the Save Licensed Programs display next to the licensed programs that you want to save.



Fill in the information on the Save Options display by using the following information.

Use the Help key for more information for each of the prompts on the display.

1. Device

The examples in this topic use TAP01 for the name of the tape device. For more information about the tape device naming convention, see “Types of software installation devices” on page 12.

2. Sequence number

Use *Default, or enter your choice for the sequence number to be used for the save process.

3. End of media option

Tape: Determines the automatic positioning operation that is done on the tape volume when the save operation is completed. In the case of a multiple-volume save operation, this parameter applies to the last volume only. All other volumes rewind and unload if the tape reaches its end. You can specify these values:

- *REWIND: The tape automatically rewinds after the operation ends, but it does not unload the tape.
- *LEAVE: The tape does not rewind or unload after the operation ends. It remains at the current position on the tape drive.
- *UNLOAD: The tape automatically rewinds and unloads after the operation ends.

Optical: Specifies the operation that is automatically performed on the optical volume after the save operation ends. Optical devices only support the special value *UNLOAD. They ignore *REWIND and *LEAVE. Some optical devices will eject the volume after the operation ends.

Notes:

1. Licensed programs and optional parts that are shipped independently of an operating system release or modification are not displayed. Use the Save Licensed Program (SAVLICPGM) command to save independently shipped IBM licensed programs and optional parts.
2. This option should not be used for backup and recovery. It is only for redistribution. More information about redistribution is available in the Distribute software topic in the iSeries Information Center (**OS/400 and related software > Distribute software**). For information on saving your server, refer to the Backup up your server topic in the iSeries Information Center (**Systems management > Backup and recovery > Back up your server**).


Options for secondary languages

This topic contains information about displaying, installing, and deleting secondary languages on your system.

- “Option 20. Display secondary languages”
- “Option 21. Install secondary languages”
- “Option 22. Delete secondary languages” on page 208

Option 20. Display secondary languages

After an installation process has completed, it is often necessary to determine if a secondary language is installed successfully on your system. To do this, select option 20 on the Work with Licensed Programs menu. The Display Installed Secondary Languages display shows the primary and any secondary languages that are installed on your system.




Type 5 in the Option column next to a secondary language, and press Enter to see the licensed programs that are installed with the particular secondary language. This information is shown on the subsequent display, Display Installed Secondary Language Licensed Programs. By pressing the F11 key a few times, you will see this display change information. This display shows the secondary language library, product release, installed status value, or product option.

For a description of the installed status values, refer to “Installed status values” on page 197.

Option 21. Install secondary languages

Use option 21 to selectively install a secondary language for the licensed programs that are installed on your system.



Software reference

Type 1 by the language you want to install, and press Enter. Only one secondary language can be installed at a time. The Confirm Install of Secondary Language display shows the following:


- The language you selected to install
- The library where it will be installed
- The release level of the language

On the Install Option for Secondary Languages display, select your installation device and specify yes or no for the Replace if current parameter.

The examples in this topic use OPT01 for the name of the installation device. “Types of software installation devices” on page 12 contains more information about the installation device naming convention. By specifying *NO to the Replace if current parameter, the secondary languages that are currently installed and at the same release as on the installation media are not be replaced during an upgrade. You can change the Replace if Current parameter to *YES if you want to replace secondary languages that are already installed, including secondary languages installed at the same release as on the installation media.

Option 22. Delete secondary languages

Use option 22 to delete secondary languages you no longer want installed on your system.



On the Delete Secondary Languages display, type 4 to select the secondary language that you want to delete. Press Enter. Press Enter again at the confirmation display.


More information about secondary language libraries in user profiles is available in the OS/400 Globalization topic in the iSeries Information Center (**Programming > Globalization**).

Completion status

When you install licensed programs, a secondary language, or PTFs, make sure that the installation process has successfully completed to avoid problems when you begin using the system.

Option 50. Display log for messages

Selecting option 50 shows the Display Install History display. Press Enter to view the installation start and completion messages on the Display History Log Contents display. This option displays specific messages that are shown in the history log.



Each part of the installation process (such as licensed programs, PTFs, Initialize System (INZSYS)) should have a completion message. If you do not see the message on the display, wait a few minutes and select option 50 again. If you still do not see a completion message, use the recovery procedures in Chapter 10, “Troubleshooting software installation problems,” on page 143 to install any licensed programs or PTFs that were not successfully installed.

Commands related to the Work with Licensed Programs menu

Options 70, 71, and 72 display menus of additional commands you can use.

Option 70 shows the Save and Restore Commands display. This display shows a list of related command menus you can use.

Option 71 shows the Program Temporary Fix Commands display. You can use these commands to work with one or more individual PTFs. For ore information about fixes, see Use software fixes in the iSeries Information Center (**OS/400 and related software > Maintain and manage OS/400 and related software > Use software fixes**).

Option 72 shows the Licensed Commands display.

More information about the following commands is available in the iSeries Information Center: **Programming > CL**.



CPYPTFSAVF	Copy PTF to Save File
CRTPTF	Create Program Temporary Fix
CRTPTFPKG	Create PTF Package
HLDPTF	Hold Program Temporary Fix
ORDSPTPTF	Order Supported Product PTFs
RLSPTF	Release Program Temporary Fix
SNDPTF	Send Program Temporary Fix

Software reference


Chapter 12. Related information for software installation

Listed below are the iSeries manuals and IBM Redbooks™ (in PDF format), Web sites, and information center (*categories or*) topics that relate to the Install OS/400 and related software topic. You can view or print any of the PDFs.






Manuals

- **Memo to Users**  (about 50 pages)
This document provides information about software and hardware changes that could potentially affect your system operations.
- **Backup and Recovery**  (about 600 pages)
This document provides general information about backup and recovery options for the iSeries server. Topics include saving your system, restoring to different releases of OS/400, and selecting the right recovery strategy.

Redbooks

- **IBM @server iSeries System Handbook** 
This book provides a product overview of the iSeries server. It discusses the features, functions, and technical specifications for iSeries server models offered today, and identifies the software supported by the current product line. Use this Web page (<http://publib-b.boulder.ibm.com/cgi-bin/searchsite.cgi?query=iSeries+AND+handbook>) to search for the correct version .

Web sites

- **IBM @server iSeries Support** 
(<http://www.ibm.com/eserver/series/support>)
This Web site contains tools and resources such as preventive service planning (PSP) information and authorized problem analysis reports (APARs) that help you with your software installation.
- **iSeries Planning** 
(<http://www.ibm.com/servers/eserver/series/support/planning/>)
This web site provides links to a variety of planning tools and information.
- **iSeries Upgrade Planning** 
(<http://www.ibm.com/servers/eserver/series/support/planning/nav.html>)
This web site provides information on iSeries products or features that might not be supported in future releases of the OS/400 operating system or on future iSeries models, Product Previews, and Statements of Directions.
- **Integrated Technology Services (ITS)** 
(<http://www.ibm.com/services/its/us/inteapps.html>)
This Web site contains information on the services IBM has available to help you plan for an upgrade or migration of your server.
- **IBM Electronic Service Agent for iSeries** 
(<http://publib.boulder.ibm.com/isrvagt/sdsadoc.html>)
This Web site provides information on Electronic Service Agent, which is part of the OS/400 operating system. Electronic Service Agent provides a hardware problem reporting function that predicts and prevents hardware errors by early

Related information

detection of potential problems, downloads, fixes, and automatically calls IBM Service when necessary. Supplemental service information to aid in problem determination is sent and made available to IBM support centers for timely and proactive problem resolution.

Other information in the iSeries Information Center

- The **Backup and recovery** topic contains information on how to plan a backup and recovery strategy, how to set up disk protection for your data, how to back up your system, and how to control your system shutdown in the event of a failure. It also includes information about the Backup, Recovery, and Media Services plug-in to iSeries^(TM) Navigator.
- The **Basic system operations** topic contains topics on iSeries basic operations, OS/400 concepts, and analyzing and reporting system problems.
- The **Logical partitions** topic describes how you distribute resources within a single iSeries server to make it function as if it were two or more independent servers.
- The **Maintain and manage OS/400 and related software** topic indicates how you can manage and maintain fixes and licensed programs in your network.
- The **Distribute software** topic describes how you can distribute some or all of the programs on a system, including the operating system, to another system.

Saving PDF files

To save a PDF on your workstation for viewing or printing:

1. Right-click the PDF in your browser (right-click the link above).
2. Click **Save Target As...** if you are using Internet Explorer. Click **Save Link As...** if you are using Netscape Communicator.
3. Navigate to the directory in which you would like to save the PDF.
4. Click **Save**.

Downloading Adobe Acrobat Reader

You need Adobe Acrobat Reader to view or print these PDFs. You can download a copy from the Adobe Web site (www.adobe.com/products/acrobat/readstep.html)



Appendix. Notices

This information was developed for products and services offered in the U.S.A.

This document may contain references to Licensed Internal Code. Licensed Internal Code is Machine Code and is licensed to you under the terms of the IBM License Agreement for Machine Code.

IBM may not offer the products, services, or features discussed in this document in other countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
500 Columbus Avenue
Thornwood, NY 10594-1785
U.S.A.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation
Licensing
2-31 Roppongi 3-chome, Minato-ku
Tokyo 106, Japan

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law:

INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web

sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation
Software Interoperability Coordinator, Department 49XA
3605 Highway 52 N
Rochester, MN 55901
U.S.A.

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this information and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement, IBM License Agreement for Machine Code, or any equivalent agreement between us.

Any performance data contained herein was determined in a controlled environment. Therefore, the results obtained in other operating environments may vary significantly. Some measurements may have been made on development-level systems and there is no guarantee that these measurements will be the same on generally available systems. Furthermore, some measurements may have been estimated through extrapolation. Actual results may vary. Users of this document should verify the applicable data for their specific environment.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

COPYRIGHT LICENSE:

This information contains sample application programs in source language, which illustrate programming techniques on various operating platforms. You may copy, modify, and distribute these sample programs in any form without payment to IBM, for the purposes of developing, using, marketing or distributing application programs conforming to the application programming interface for the operating platform for which the sample programs are written. These examples have not

been thoroughly tested under all conditions. IBM, therefore, cannot guarantee or imply reliability, serviceability, or function of these programs.

If you are viewing this information softcopy, the photographs and color illustrations may not appear.

Trademarks

The following terms are trademarks of International Business Machines Corporation in the United States, other countries, or both:

Advanced Function Printing
Advanced 36
AFP
APL2
Application System/400
AS/400
AS/400e
CICS
DataPropagator
DB2
DB2 Universal Database
Domino
e(logo) server
eServer
Electronic Service Agent
GDDM
IBM
ibm.com
ImagePlus
IPDS
iSeries
Lotus
MQSeries
Netfinity
Operating System/400
OS/400
PowerPC
Print Services Facility
Redbooks
RPG/400
System/36
System/38
Tivoli
TME
VisualAge
VisualInfo
WebSphere
xSeries
400

Microsoft, Windows, and the Windows logo are trademarks of Microsoft Corporation in the United States, other countries, or both.

Java and all Java-based trademarks are trademarks of Sun Microsystems, Inc. in the United States, other countries, or both.

Other company, product, and service names may be trademarks or service marks of others.

Terms and conditions for downloading and printing publications

Permissions for the use of the publications you have selected for download are granted subject to the following terms and conditions and your indication of acceptance thereof.

Personal Use: You may reproduce these Publications for your personal, noncommercial use provided that all proprietary notices are preserved. You may not distribute, display or make derivative works of these Publications, or any portion thereof, without the express consent of IBM.

Commercial Use: You may reproduce, distribute and display these Publications solely within your enterprise provided that all proprietary notices are preserved. You may not make derivative works of these Publications, or reproduce, distribute or display these Publications or any portion thereof outside your enterprise, without the express consent of IBM.

Except as expressly granted in this permission, no other permissions, licenses or rights are granted, either express or implied, to the Publications or any information, data, software or other intellectual property contained therein.

IBM reserves the right to withdraw the permissions granted herein whenever, in its discretion, the use of the Publications is detrimental to its interest or, as determined by IBM, the above instructions are not being properly followed.

You may not download, export or re-export this information except in full compliance with all applicable laws and regulations, including all United States export laws and regulations. IBM MAKES NO GUARANTEE ABOUT THE CONTENT OF THESE PUBLICATIONS. THE PUBLICATIONS ARE PROVIDED "AS-IS" AND WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE

All material copyrighted by IBM Corporation.

By downloading or printing a publication from this site, you have indicated your agreement with these terms and conditions.

Code disclaimer information

This document contains programming examples.

IBM grants you a nonexclusive copyright license to use all programming code examples from which you can generate similar function tailored to your own specific needs.

All sample code is provided by IBM for illustrative purposes only. These examples have not been thoroughly tested under all conditions. IBM, therefore, cannot guarantee or imply reliability, serviceability, or function of these programs.

All programs contained herein are provided to you "AS IS" without any warranties of any kind. The implied warranties of non-infringement, merchantability and fitness for a particular purpose are expressly disclaimed.

Index

A

- alternate installation device
 - automatic installation 56
 - disabling 186
 - manual installation 64
 - verifying and selecting during manual installation 187
- automatic configuration 108, 113
- automatic installation 57

B

- blank display, response to 197

C

- checklist, readiness
 - new software installation 88
 - software upgrade or replacement 26
- command, CL
 - Delete Library (DLTLIB)
 - when not to use 141
 - Display Software Resources (DSPSFWRSC) 203
 - restore licensed program (RSTLICPGM) command
 - to install secondary languages 124
- completion status
 - display log for messages using option 50 208
- compressed objects and storage space
 - concepts 20
- concepts
 - software installation 9
- concepts for software installation
 - compressed objects and storage space 20
 - contents of software order 13
 - globalization
 - changing primary language 21
 - installing secondary language 21
 - overview 20
 - IBM-supplied object 19
 - media distribution set 15
 - mixed-release environment 17
 - object conversion 22
 - product documentation 16
 - releases supported, OS/400
 - upgrades 18
 - skipping release 16
 - software installation device 12
 - software installation process 9
 - software licensing documents 14
 - software upgrade or replacement 17
- configuration
 - automatic 108, 113
- contents of software order
 - concepts 13
 - verifying 28, 89

- CPA9E1B message 83, 127
- cross-reference file
 - checking before upgrade 36
- Cryptographic Access Provider
 - preparing to upgrade 55
- cumulative PTF packages
 - ordering 31, 91
- custom list
 - software for installing 42

D

- delete
 - licensed program
 - from list 205
- Delete Library (DLTLIB) command
 - when not to use 141
- deleting
 - licensed programs and optional parts
 - notes about 141
 - using option 12 141
 - using the DTLICPGM command 141
 - secondary languages
 - using option 22 208
- device configuration naming 108, 113
- disk configuration
 - choosing before upgrade 51
 - PTF (program temporary fix) 33
- display
 - blank 197
- Display Software Resources (DSPSFWRSC) command 203
- displaying
 - installed licensed programs using option 10 203
 - installed secondary languages using option 20 207
- DLTLIB (Delete Library) command
 - when not to use 141
- document
 - software installation 89
 - software upgrade or replacement 28
- DSPSFWRSC (Display Software Resources) command 203

E

- environment, mixed release
 - overview 17

F

- fastpath
 - installation, upgrade, or deletion tasks 7
- fixes (PTFs)
 - required for upgrades 31

G

- globalization
 - changing primary language 21
 - installing secondary language 21
 - preparing 42
 - software installation concepts 20
- GO LICPGM (Go Licensed Program) menu
 - completion status options
 - using option 50 208
 - licensed programs options
 - using option 10 203
 - using option 11 203
 - using option 12 205
 - using option 13 205
 - related commands
 - using option 70 209
 - using option 71 209
 - secondary languages options
 - using option 20 207
 - using option 21 207
 - using option 22 208

I

- IBM-supplied object
 - concepts 19
- image catalog
 - scenario for upgrade 53
- image catalog (virtual optical device)
 - automatic installation 57
 - licensed program installation 115
 - manual installation 65
- information resource
 - software installation 89
 - software upgrade or replacement 28
- install option
 - displaying, installing, deleting, and saving from list 202
- installation
 - licensed program
 - from list 204
- installation device
 - choosing 42
- installation method
 - choosing 42
- installation tasks
 - initial 90
- installation, new software
 - overview 87
- installing
 - licensed programs and optional parts
 - using option 11 203
 - secondary languages
 - using Work with Licensed Programs menu 121
 - secondary languages using option 21 207

- installing, software
 - new server with operating system 109
 - before you begin 110
- Integrated xSeries Server for iSeries
 - preparing to upgrade 55
- iSeries Access
 - user-created subdirectories 37

K

- keys, software license
 - verifying 30, 90

L

- license agreement
 - accepting 46
- license keys
 - verifying 30, 90
- Licensed Internal Code
 - space for 50
- licensed program
 - adding additional to installation list 45
 - deleting 49
 - from list 205
 - notes about 141
 - procedures for 141
 - using option 12 141
 - using the DLTLICPGM command 141
 - installation
 - from list 203
 - installing after changing primary language 135
 - preselecting 42
 - restoring
 - using option 11 203
 - using the RSTLICPGM command 203
 - saving
 - using option 13 206
 - using the SAVLICPGM command 206
- licensed program documentation
 - concepts 16
- LICPGM menu
 - using
 - to install secondary languages 121
- list, custom
 - software for installing 42
- load-source disk requirement 47, 91
- logical partition
 - automatic installation 57
 - licensed program installation 115
 - manual installation 65

M

- media distribution set
 - concepts 15
- message queue 78
 - working with 78
- migration 109, 113

- mixed-release environment
 - concepts 17

N

- national language version feature code
 - where used 103, 122

O

- object
 - concepts for software installation 19, 20, 22
- object conversion
 - concepts 22
- object, system
 - verifying integrity before upgrade 36
- operating system
 - installing software on new server 109
 - replacing when adding new release 72
- Operating System/400 (OS/400)
 - See* operating system
- Operations Console
 - automatic installation 51, 56, 91
 - installing Licensed Internal Code on a new partition 94
 - manual installation 64
- optical distribution media
 - verifying for new installation 90
 - verifying for software upgrade or replacement 29
- order, software
 - verifying 28, 89
- OS/400 (Operating System/400)
 - See* operating system
- OS/400 upgrade
 - nonsupported models 18
 - supported releases 18
- overview
 - new software installation 87
 - software installation 9
 - software upgrade or replacement 25

P

- performance data
 - collecting before upgrade 38
- preparing
 - software upgrade or replacement 25
- preventing problems
 - blank display 197
- preventive service planning information
 - new installations 91
 - upgrades 31
- primary language
 - changing
 - using secondary language media 132
 - installation concepts for changing 21
 - installing licensed programs after changing 135
 - what's new 4
- Print this topic 5

- product documentation
 - concepts 16
- product library
 - system ASP 37
- program temporary fix (PTF)
 - choose disk configuration 33
 - commands 209
 - identifying required 31
 - permanently applying 33
 - software agreement 32
- PTF (fixes)
 - required for upgrades 31
- PTF (program temporary fix)
 - choose disk configuration 33
 - commands 209
 - identifying required 31
 - permanently applying 33
 - software agreement 32
- R
- release, skipping
 - concepts 16
- releases supported, OS/400 upgrades 18
- replacing a release
 - using manual installation
 - replacing licensed programs 77
 - replacing operating system 72
 - verifying installation 80
- resource, information
 - software installation 89
 - software upgrade or replacement 28
- restore licensed program (RSTLICPGM)
 - command 124
- restoring
 - licensed programs and optional parts
 - using option 11 203
 - using the RSTLICPGM command 203
- RSTLICPGM (restore licensed program)
 - command 124

S

- saving
 - licensed programs and optional parts
 - using option 13 205, 206
 - using the SAVLICPGM command 206
- saving the server
 - before upgrade 55
- secondary language
 - installation concepts 21
 - using options on GO LICPGM menu 207
- security level 108, 112
- server preparation steps
 - upgrade or replacement 30
- skipping release
 - concepts 16
- software agreement
 - accepting 46
 - required PTF for 32
- software installation
 - concepts 9

- software installation (*continued*)
 - new server with operating system 109, 110
- software installation device
 - concepts 12
- software installation process
 - overview 9
- software installation time
 - ways to minimize 38
- software installation, new
 - checklist 88
 - overview 87
- software license keys
 - verifying 30, 90
- software licensing documents
 - concepts 14
- software upgrade or replacement
 - checklist 26
 - overview 17, 25
 - preparation steps 25
- storage space
 - cleaning up 49
 - determining for installation 91
 - determining for upgrade 47
 - image catalog 47
 - Licensed Internal Code 50
 - upgrades 46
- system object
 - verifying integrity before upgrade 36
- system password 197
- system value
 - changing before upgrade 34
 - recording and printing before upgrade 34
 - system time zone
 - creating data area 36
 - tasks before upgrade 33
- System/36 environment 109, 113

T

- time for installing software
 - ways to minimize 38
- two-phase commit integrity
 - ensuring before upgrade 37

U

- upgrade
 - supported release 18
- upgrade or replacement
 - server preparation steps 30
 - software
 - overview 25
 - preparation steps 25
- upgrade tasks
 - initial 41
- user profile
 - checking before upgrade 36
 - cleaning up 50
 - verifying before upgrade 36

V

- verify
 - installation using option 50 208

- virtual media
 - scenario for upgrade 53

W

- what's new for V5R3
 - console mode value 3
 - Licensed Internal Code storage requirements 3
 - primary languages 4
 - printed version of PDF 4
 - server firmware 3
 - software agreement acceptance 3
- Work with Licensed Programs menu
 - using
 - to install secondary languages 121

Readers' Comments — We'd Like to Hear from You

iSeries
Install, upgrade, or delete
OS/400 and related software
Version 5 Release 3

Publication No. SC41-5120-07

Overall, how satisfied are you with the information in this book?

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Overall satisfaction	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

How satisfied are you that the information in this book is:

	Very Satisfied	Satisfied	Neutral	Dissatisfied	Very Dissatisfied
Accurate	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Complete	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Easy to find	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Easy to understand	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Well organized	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
Applicable to your tasks	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

Please tell us how we can improve this book:

Thank you for your responses. May we contact you? Yes No

When you send comments to IBM, you grant IBM a nonexclusive right to use or distribute your comments in any way it believes appropriate without incurring any obligation to you.

Name

Address

Company or Organization

Phone No.



Fold and Tape

Please do not staple

Fold and Tape




NO POSTAGE
NECESSARY
IF MAILED IN THE
UNITED STATES

BUSINESS REPLY MAIL

FIRST-CLASS MAIL PERMIT NO. 40 ARMONK, NEW YORK

POSTAGE WILL BE PAID BY ADDRESSEE

IBM CORPORATION
ATTN DEPT 542 IDCLERK
3605 HWY 52 N
ROCHESTER MN 55901-7829



Fold and Tape

Please do not staple

Fold and Tape



Printed in USA

SC41-5120-07

